

1

2



ZigBee[®]
Alliance

3

4

5 **ZigBee Document 08-0006-05**

6 **ZigBee PRO/2007 Layer PICS and Stack**
7 **Profiles**

8

9 **Revision 05**

10

11 January 2013

12 **Sponsored by:**
13 ZigBee Alliance

14 **Accepted for release by:**
15 ZigBee Alliance Board of Directors.

16 **Abstract:**

17

18 **Keywords:**
19 ZigBee, ZigBee-PRO, Stack profile, Architecture.

20

Copyright © 1996-2013 by the ZigBee Alliance.
2400 Camino Ramon, Suite 375, San Ramon, CA 94583, USA
<http://www.zigbee.org>
All rights reserved.

Permission is granted to members of the ZigBee Alliance to reproduce this document for their own use or the use of other ZigBee Alliance members only, provided this notice is included. All other rights reserved. Duplication for sale, or for commercial or for-profit use is strictly prohibited without the prior written consent of the ZigBee Alliance.

1 Copyright © ZigBee Alliance, Inc. (2008-2013). All rights Reserved. This information within this document is the property of
2 the ZigBee Alliance and its use and disclosure are restricted.
3 Elements of ZigBee Alliance specifications may be subject to third party intellectual property rights, including without limitation,
4 patent, copyright or trademark rights (such a third party may or may not be a member of ZigBee). ZigBee is not responsible and
5 shall not be held responsible in any manner for identifying or failing to identify any or all such third party intellectual property
6 rights.
7 This document and the information contained herein are provided on an "AS IS" basis and ZigBee DISCLAIMS ALL
8 WARRANTIES EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO (A) ANY WARRANTY THAT THE USE OF THE
9 INFORMATION HEREIN WILL NOT INFRINGE ANY RIGHTS OF THIRD PARTIES (INCLUDING WITHOUT LIMITATION
10 ANY INTELLECTUAL PROPERTY RIGHTS INCLUDING PATENT, COPYRIGHT OR TRADEMARK RIGHTS) OR (B) ANY
11 IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, TITLE OR NON-
12 INFRINGEMENT. IN NO EVENT WILL ZIGBEE BE LIABLE FOR ANY LOSS OF PROFITS, LOSS OF BUSINESS, LOSS OF
13 USE OF DATA, INTERRUPTION OF BUSINESS, OR FOR ANY OTHER DIRECT, INDIRECT, SPECIAL OR EXEMPLARY,
14 INCIDENTAL, PUNITIVE OR CONSEQUENTIAL DAMAGES OF ANY KIND, IN CONTRACT OR IN TORT, IN
15 CONNECTION WITH THIS DOCUMENT OR THE INFORMATION CONTAINED HEREIN, EVEN IF ADVISED OF THE
16 POSSIBILITY OF SUCH LOSS OR DAMAGE. All Company, brand and product names may be trademarks that are the sole
17 property of their respective owners.
18 The above notice and this paragraph must be included on all copies of this document that are made.
19

20 ZigBee Alliance, Inc.
21 2400 Camino Ramon, Suite 375
22 San Ramon, CA 94583, USA
23

1 **Contact information**

2 Much of the information in this document is preliminary and subject to change. Members of the ZigBee
3 Working Group are encouraged to review and provide inputs for this proposal. For document status
4 updates, please contact:

5 Rob Alexander
6 Silicon Labs
7 25 Thomson Place
8 Boston, MA 02210
9 rob.alexander@silabs.com

10
11

12 You can also submit comments using the ZigBee Alliance reflector. Its web site address is:

13 www.zigbee.org

14 The information on this page should be removed when this document is accepted.

1 **Participants**

2 The following is a list of those who were members of the ZigBee Alliance Core Stack Working Group
3 leadership when this document was released:

4 **Don Sturek:** *Chair*

5 **Daniel Gavelle:** *Vice Chair*

6 **Tim Gilman:** *Secretary*

7

8
9 The editing team was composed of the following members:

10

11 **Rob Alexander:** Silicon Labs, Technical Editor ZigBee/ZigBee PRO

12 **Mads Westergreen** – Ubilogix, Technical Editor ZigBee/ZigBee PRO

13 **Joseph Reddy** – TI, Technical Editor ZigBee IP

14 **Robert Cragie** – Grid2Home, Technical Editor ZigBee IP

15 **Nicolas Cochard** – Schneider, Technical Editor Greenpower

16 **Bozena Erdmann** – Philips, Technical Editor Greenpower

17

18

19

1 **Table of Contents**

2 1 Introduction..... 1

3 1.1 Scope..... 1

4 1.2 Purpose..... 1

5 2 References 2

6 2.1 ZigBee Alliance documents 2

7 2.2 IEEE documents..... 2

8 3 Definitions..... 3

9 4 Acronyms and abbreviations 4

10 5 General description 5

11 6 Knob settings..... 6

12 6.1 Introduction 6

13 6.2 Network settings..... 6

14 6.3 Application settings..... 6

15 6.4 Security settings 7

16 7 Functional description 8

17 7.1 Device roles..... 8

18 7.2 ZigBee: Compatibility with Other Feature sets..... 8

19 7.3 ZigBee-PRO: Compatibility with Other Feature sets..... 8

20 7.4 Binding tables..... 9

21 7.5 Multicast mechanism and groups 9

22 7.6 Trust Center Policies and Security Settings 9

23 7.7 Battery powered devices 9

24 7.8 Mains powered devices 10

25 7.9 Persistent storage..... 10

26 7.10 Address Reuse..... 10

27 7.11 Duty cycle limitations and fragmentation 10

28 7.11.1 Vulnerability join..... 10

29 7.11.2 Pre-installation..... 10

30 7.12 Security 11

31 7.12.1 Security Modes within PRO Networks 11

32 8 Instructions for completing the PICS proforma 13

33 9 Identification of the implementation **Error! Bookmark not defined.**

34 10 Protocol implementation conformance statement (PICS) proforma..... 15

35 10.1 Abbreviations and special symbols 15

36 10.2 ZigBee device types 15

37 10.3 IEEE 802.15.4 PICS..... 16

38 10.3.1 FDT2 and FDT3 network join options..... 16

39 10.3.2 IEEE 802.15.4 PHY..... 17

40 10.3.3 IEEE 802.15.4 MAC..... 18

41 10.4 Network layer PICS 33

42 10.4.1 ZigBee network frame format..... 33

43 10.4.2 Major capabilities of the ZigBee network layer..... 33

44 10.5 Security PICS 54

45 10.5.1 ZigBee security roles 54

46 10.5.2 ZigBee trust center capabilities..... 55

47 10.5.3 Modes of operation 56

48 10.5.4 Security levels..... 56

1	10.5.5	NWK layer security	58
2	10.5.6	APS layer security	60
3	10.5.7	Application layer security	65
4	10.6	Application layer PICS	70
5	10.6.1	ZigBee security device types	70
6	10.6.2	ZigBee APS frame format	70
7	10.6.3	Major capabilities of the ZigBee application layer	71
8			

1

List of Tables

2	Table 1 – Document revision change history	viii
3	Table 2 – Network settings for this feature set.....	6
4	Table 3 – Application settings for this feature set	6
5	Table 4 – Security settings for this feature set.....	7
6		

1 **Change history**

2 Table 1 shows the change history for this specification.

3 **Table 1 – Document revision change history**

Revision	Description
00	Original version as a merge of 064321r08, 074855r04, 04319r01, 04300r08, 043171r04, 064147r07.
01	Snapshot version provided to Core Stack and Qualification Working Groups to validate format of the combined document
02	Major PICS update following many test events. Overhaul of the formatting.
03	Final updates during the June 2008 ZigBee members meeting in Atlanta.
04	Update for the ZigBee PRO R20 specification and Sub-ghz PICs items.
05	Address comments in document 12-0641-00 and CCBs 1039, 1279, 1623, 1624, 1629, 1633.

4

5

1 Introduction

2 To evaluate conformance of a particular implementation, it is necessary to have a statement of which
3 capabilities and options have been implemented for a given standard. Such a statement is called a
4 protocol implementation conformance statement (PICS).

5 1.1 Scope

6 This document provides the protocol implementation conformance statement (PICS) proforma for
7 ZigBee specification (05-3474r20) in compliance with the relevant requirements, and in accordance
8 with the relevant guidance, given in ISO/IEC 9646-7.

9 1.2 Purpose

10 The supplier of a protocol implementation claiming to conform to the ZigBee standard shall complete
11 the following PICS proforma and accompany it with the information necessary to identify fully both
12 the supplier and the implementation.

13
14 The protocol implementation conformance statement (PICS) of a protocol implementation is a
15 statement of which capabilities and options of the protocol have been implemented. The statement is in
16 the form of answers to a set of questions in the PICS proforma. The questions in a proforma consist of
17 a systematic list of protocol capabilities and options as well as their implementation requirements. The
18 implementation requirement indicates whether implementation of a capability is mandatory, optional,
19 or conditional depending on options selected. When a protocol implementer answers questions in a
20 PICS proforma, they would indicate whether an item is implemented or not, and provide explanations
21 if an item is not implemented.

2 References

The following standards and specifications contain provisions, which through reference in this document constitute provisions of this specification. All the standards and specifications listed are normative references. At the time of publication, the editions indicated were valid. All standards and specifications are subject to revision, and parties to agreements based on this specification are encouraged to investigate the possibility of applying the most recent editions of the standards and specifications indicated below.

2.1 ZigBee Alliance documents

- [R1] ZigBee document 05-3474r20, ZigBee specification release 20, ZigBee Core Stack Group
- [R2] ZigBee 04-0140r05, ZigBee Protocol Stack Settable Values (knobs) release 05, ZigBee Architecture Working Group
- [R3] ZigBee document 04-0319r01, ZigBee IEEE 802.15.4 PHY & MAC Layer Test Specification release r01
- [R4] ZigBee document 08-5195r02, ZigBee Trust Centre Best Practices, ZigBee Security Task Group.

2.2 IEEE documents

- [R5] IEEE Standards 802, Part 15.4: Wireless Medium Access Control (MAC) and Physical Layer (PHY) specifications for Low Rate Wireless Personal Area Networks (LR-WPANs), IEEE, April 2003.

1

3 Definitions

Feature set	A collection of parameter values and configuration settings, collectively and loosely referred to as “knobs” in [R2], that determine the specific performance of a ZigBee stack variant and govern interoperability between stacks provided by different vendors.
ZigBee coordinator	An IEEE 802.15.4-2003 PAN coordinator operating in a ZigBee network.
ZigBee end device	An IEEE 802.15.4-2003 RFD or FFD participating in a ZigBee network, which is neither the ZigBee coordinator nor a ZigBee router.
ZigBee router	An IEEE 802.15.4-2003 FFD participating in a ZigBee network, which is not the ZigBee coordinator but may act as an IEEE 802.15.4-2003 coordinator within its personal operating space, that is capable of routing messages between devices and supporting associations.

2

1 **4 Acronyms and abbreviations**

AODV	Ad-Hoc On-Demand Distance Vector
FFD	IEEE 802.15.4 Full Function Device
IEEE	Institute of Electrical and Electronic Engineers
PICS	Protocol Implementation Conformance Statement
RFD	IEEE 802.15.4 Reduced Function Device

2

5 General description

2 The sections in this document are:

- 3 • Knob settings – details of values to be used for parameters specified in the ZigBee
4 specification for tuning the operation of the ZigBee stack, including network, application and
5 security settings.
- 6 • Functional description – further operational restrictions to be applied to all devices in this
7 feature set where various approaches are otherwise supported by the ZigBee specification.
- 8 • Protocol implementation conformance statement (PICS) – a formal definition of functionality
9 to be implemented in these devices.

10 These requirements aim to allow a designer to make necessary assumptions about what settings,
11 features and safeguards will be in place in the networks in which a device will be deployed.

12 For clarity, settings applied to the ZigBee feature set will be marked with the string **ZigBee** and
13 settings applied to the ZigBee-PRO feature set will be marked with the string **ZigBee-PRO**.

6 Knob settings

6.1 Introduction

This section specifies values for parameters specified in the ZigBee specification for tuning the operation of the ZigBee and ZigBee-PRO stack. This section describes settings for both ZigBee and ZigBee-PRO feature sets applied to the ZigBee-2007 Specification ([R1])

6.2 Network settings

The network settings for the ZigBee and ZigBee-PRO feature sets are, for the most part, described in the restricted PICS captured in Section 10.4. Those setting not covered by the PICS are listed in Table 2.

Table 2 – Network settings for this feature set

Parameter Name	Setting		Comments
<i>nwkTransactionPersistenceTime</i>	0x01f4	ZigBee	Note that this value essentially “covers” the MAC attribute of the same name. Note also that, while [R1] implies that this quantity has meaning only in beacon-enabled networks, it may actually be used in beaconless networks as well and, in that case, is a multiplier for <i>aBaseSuperframeDuration</i> . The value here yields a persistence time of 7.68 seconds using the 2.4Ghz symbol rate from [R5] in a non-beaconed network.
		ZigBee-PRO	
<i>nwkReportConstantCost</i>	FALSE	ZigBee	The NWK layer in PRO shall always calculate routing cost on the basis of neighbor link cost and never report constant cost.
		ZigBee-PRO	

6.3 Application settings

The application settings for the ZigBee and ZigBee-PRO feature sets are, for the most part, described in the restricted PICS captured in Section 10.6. Those setting not covered by the PICS are listed in Table 3.

Table 3 – Application settings for this feature set

Parameter Name	Setting		Comments
Number of active endpoints per sleeping ZigBee end device (maximum)	-	ZigBee	As the responsibility to arrange for caching of service discovery information lies with the end device itself, this parameter is not restricted.
		ZigBee-PRO	

Parameter Name	Setting	Comments	
Config_NWK_Leave_removeChildren	FALSE	ZigBee	
		ZigBee-PRO	

1 6.4 Security settings

2 The security settings for the ZigBee and ZigBee-PRO feature sets are listed in Table 4.

3 **Table 4 – Security settings for this feature set**

Parameter Name	Setting	Comments	
apsSecurityTimeoutPeriod	$TxDuration^1 * (2 * NWK \text{ Maximum Depth}) + (AES \text{ Encrypt/Decrypt times})$	ZigBee	Where AES Encrypt/Decrypt times = 200ms, and Where NWK Maximum Depth is assumed to be 5, meaning every device in the network can be reached in not more than 10 hops, and Where TxDuration is assumed to be 1562.5 octetDurations (50 msec on 2.4GHz), meaning maximum duration of transmitting a packet by a hop, i.e. 700 milliseconds on 2.4 GHz. Note that this timeout assumes worst case AES engine speeds and is not indicative of expected performance for most devices.
		ZigBee-PRO	Where AES Encrypt/Decrypt times = 200ms, and Where NWK Maximum Depth is assumed to be 15, meaning every device in the network can be reached in not more than 30 hops, and Where TxDuration is assumed to be 1562.5 octetDurations (50 msec on 2.4GHz), meaning maximum duration of transmitting a packet by a hop, i.e. 1.7 seconds on 2.4 GHz. Note that this timeout assumes worst case AES engine speeds and is not indicative of expected performance for most devices.

4

¹ CCB 1623

7 Functional description

For the most part, the functioning of ZigBee and ZigBee-PRO with respect to the NWK layer, the APS layer and the ZDO is described in [R1]. However, the configuration details and operational requirements for devices operating under the ZigBee and ZigBee-PRO feature sets lead to some special functional considerations, which are detailed here.

7.1 Device roles

The basic roles performed by ZigBee devices in ZigBee and ZigBee-PRO networks are determined by their device type:

- The **ZigBee coordinator** initiates network formation, choosing the network channel, PAN ID and extended PAN ID in the process, and thereafter should act as a ZigBee router. It may also perform the roles of trust center and Network Channel Manager. With respect to binding, the ZigBee coordinator is expected to handle end device bind request on behalf of all end devices in the network but is not expected to be a global binding repository for the network.
- **ZigBee routers** are called upon to relay traffic on behalf of other devices in the network and, in particular, are required to act as routing agents on behalf of their end device children, which will typically not have the neighbor tables, routing tables, route discovery tables or broadcast transaction tables required to perform routing. Since end devices may sleep, ZigBee routers and ZigBee coordinators in their role of ZigBee routers may cache discovery information on behalf of their sleeping end-device children. A ZigBee router may perform the role of trust center and Network Channel Manager.
- **ZigBee end devices** are joined to and managed by ZigBee routers or the ZigBee coordinator. Because ZigBee-PRO networks are beaconless, there is no built-in synchronization mechanism between sleeping end devices and their router parents. End devices are free to set their own duty cycles within the broad polling limits defined by this feature set. End devices that wish to have their discovery information cached by their parent or some other device are responsible for using the discovery cache commands to achieve this.

Under the ZigBee and ZigBee-PRO feature sets, all devices are expected to manage their own binding tables if they use binding tables.

This section is valid for both the **ZigBee** and **ZigBee-PRO** feature sets.

7.2 ZigBee: Compatibility with Other Feature sets

Devices implementing the ZigBee feature set will advertise a feature set identifier of 1 in their beacon payloads as stated below in the additional restrictions for PICS item NLF4. In general, such devices will seek out and join networks in which the ZigBee coordinator and all ZigBee routers implement the ZigBee feature set and advertise this fact by placing a feature set identifier of 1 in their beacon payloads.

In order to provide compatibility with devices implemented according to the ZigBee-PRO feature set, ZigBee devices shall additionally be able to join networks which advertise a feature set identifier of 2 in their beacon payloads but the device must join the ZigBee-PRO networks as end devices and only those ZigBee-PRO networks employing standard network security.

This section is valid for the **ZigBee** feature set.

7.3 ZigBee-PRO: Compatibility with Other Feature sets

Devices implementing the ZigBee-PRO feature set will advertise a feature set identifier of 2 in their beacon payloads as stated below in the additional restrictions for PICS item NLF4. In general, such devices will seek out and join networks in which the ZigBee coordinator and all ZigBee routers implement the ZigBee-PRO feature set and advertise this fact by placing a feature set identifier of 2 in their beacon payloads.

- 1 In order to provide compatibility with devices implemented according to the ZigBee feature set,
2 ZigBee-PRO devices shall additionally be able to join networks which advertise a feature set identifier
3 of 1 in their beacon payloads but the device must join the ZigBee networks as end devices.
- 4 If a ZigBee PRO network is to allow ZigBee devices to join as end devices, it shall use the standard
5 network security. If high security is used, ZigBee devices will not be able to be authenticated on the
6 network.
- 7 This section is valid for the **ZigBee-PRO** feature set.

8 **7.4 Binding tables**

- 9 Binding tables, if used, shall be located on the source device. While binding is optional, devices that
10 choose to use binding tables should allocate enough binding table entries to handle their own
11 communications needs. This suggests that binding table size should be flexible enough that it can be
12 set, at least at compile time, with some awareness of the actual intended usage of the device.
- 13 This section is valid for both the **ZigBee** and **ZigBee-PRO** feature sets.

14 **7.5 Multicast mechanism and groups**

- 15 Support for APS level multicasts is mandatory to support compatibility with ZigBee devices. The
16 multicast groups are then established using the application level mechanisms. Support for routing of
17 network level multicasts is mandatory in the ZigBee-PRO feature set.
- 18 ZigBee devices do not support network level multicasts.

19 **7.6 Trust Center Policies and Security Settings**

- 20 A ZigBee PRO network shall have a trust center uniquely pointed to by each device in the network
21 through `apsTrustCenterAddress` within each network member device. It is beyond the scope of the
22 PRO Feature set to describe how this value is set or whether it is changed and the Trust Center
23 relocated to another device during operation. The only requirement of the PRO Feature set is that all
24 devices in the network point to the one unique Trust Center and that the device pointed to as the Trust
25 Center supplies the security services described by this document.
- 26 The trust center dictates the security parameters of the network, such as which network key type to use,
27 settings of the service permissions table, when, if at all, to allow devices to use unsecured association
28 to the network, and when, if at all, to allow an application master or link key to be set up between two
29 devices. For interoperability, there are two distinct security settings that can be used within the ZigBee
30 PRO feature set – a standard and a high security.
- 31 Networks can exist for periods without a trust center. There are some operations where it is necessary
32 for the trust center to be operational in the network. These include initial network setup, key changes,
33 and when joining and rejoining devices require updated keys.
- 34 A wide range of implementations are possible, depending on the requirements of the application. A
35 high security trust center may allow the user to install devices “out-of-band”, keep separate link keys
36 for different devices, optionally ignore `Mgmt_Permit_Joining_req` commands from other nodes, and
37 configure application trust policies between devices or groups of devices, etc. A standard security trust
38 center would not offer these advantages, but would not be required to carry the associated costs.

39 **7.7 Battery powered devices**

- 40 ZigBee-PRO networks may, of course, contain battery-powered devices. ZigBee routers are required to
41 have their receivers enabled whenever they are not transmitting.

1 As mentioned above, ZigBee-PRO networks are beaconless networks and, in the absence of an explicit
2 mechanism for synchronization and indirect transmission, sleeping devices must set their own duty
3 cycles and use polling, under ZDO control, if they expect to receive frames that are directed to them
4 when they are asleep. The feature set provides that parent devices, i.e. ZigBee routers and the ZigBee
5 coordinator, hold frames for 0x01F4 symbols² (7.68 seconds on 2.4 GHz) on behalf of sleeping end
6 devices and this is also, roughly speaking, the maximum polling rate prescribed here. Devices may
7 implement a polling interval longer than 0x01F4 symbols³, however the application will then have to
8 handle the potential loss of messages during longer sleep cycles.

9 **7.8 Mains powered devices**

10 It is assumed that for most ZigBee-PRO networks, the ZigBee coordinator and ZigBee routers will be
11 mains-powered and always on in order to properly perform their required roles with respect to the
12 operation of the network.

13 **7.9 Persistent storage**

14 The ZigBee-PRO feature set does not support devices without persistent storage. Devices have
15 information required to be saved between unintentional restarts and power failures. See [R1] sections
16 2.2.8.1 and 3.6.8 for details of persistent data in the application and NWK layers. Various security
17 material shall additionally be stored across power failures. All attributes in sections 4.3.3 and 4.4.10
18 shall be stored, except that it is not mandatory to store those values which can safely be recovered
19 using other stored information, or other methods.

20 **7.10 Address Reuse**

21 Re-use of previously assigned network short addresses in ZigBee-PRO devices is permitted subject to
22 execution of the address conflict procedure by the device on the re-used address.

23 **7.11 Duty cycle limitations and fragmentation**

24 No mandatory restrictions are defined for intermittent, low channel usage data, although developers are
25 encouraged to minimise bandwidth usage wherever possible.

26 Large acknowledged unicast transmissions should generally use the APS fragmentation mechanism,
27 where supported, as this handles retransmissions, duplicate rejection, flow control and congestion
28 control automatically. Use of the fragmentation mechanism is as specified in the application profile
29 documents.

30 **7.11.1 Vulnerability join**

31 Vulnerability join shall be optional for networked devices, but support for it shall be mandatory for
32 trust centers. The default for networks is permit joining is off. Permit joining is allowed for
33 established time periods based on application requirements and specific instructions based on the
34 system design.

35 Devices that join but do not successfully acquire and use the relevant security keys within the specified
36 security timeout period shall disassociate themselves from the network, and their short address may be
37 reused.

38 **7.11.2 Pre-installation**

39 Pre-installation is acceptable. Pre-installed devices are not exempt from the other requirements in this
40 document. For example, a device certified as a trust center for this feature set shall support
41 vulnerability installation of new devices, even if it is initially pre-installed.

² CCB 1624

³ CCB 1624

1 **7.12 Security**

2 This feature set is designed to allow the efficient deployment of low cost devices, while also supporting
3 the security requirements of highly sensitive applications. Installation and network maintenance
4 procedures and administration are defined with the goal of satisfying the requirements of a range of
5 applications within a single network infrastructure.

6 To achieve this, two security modes are specified: Standard mode and High Security mode. By default
7 all applications will use the network key for communications. However, where confidentiality from
8 other network nodes is required an application shall be permitted to use application link keys. Where
9 link keys are required by specific application profiles, commands not secured with a link key shall be
10 processed according to the rules established by the application profile.

11 The trust center plays a key role in determining the security settings in use in the network, and can
12 optionally be implemented to apply further restrictions on the network.

13 It is recommended that the trust center change the network key if it is discovered that any device has
14 been stolen or otherwise compromised, and in order to avoid deadlock if all frame counter records
15 become filled up. It is an application responsibility within the Trust Center to effect the change to the
16 network key. There is no expectation that the network key be changed when adding a new device.

17 All devices may implement a service permissions table, which they may use to determine which
18 devices are authorized to issue which commands. Unauthorized commands should not be carried out.

19 The trust center should be implemented to make appropriate choices about when to initiate an
20 application master/link key shared between two devices. Where restrictions between devices are
21 required it is the responsibility of the system installer/administrator to deploy a suitably intelligent trust
22 center and configure it to make relevant checks before initiating sharing of application link keys
23 between two devices. For example, it might facilitate policies based on certain times, certain
24 manufacturers or device types, or when the trust center is configured in a certain way, etc. By default a
25 simple trust center should always allow requests for link keys.

26 Devices may perform the relevant in or out of band authentication or key exchange before acquiring or
27 using a link key with a new target.

28 **7.12.1 Security Modes within PRO Networks**

29 The feature set shall use two security modes: Standard mode and High Security mode.

30 With the Standard mode, network keys and application link keys are permitted for all devices. The
31 network key type shall be the “standard” network key. It shall not be required that devices perform
32 entity authentication with their parent on joining nor shall it be required to perform entity
33 authentication between neighbors. If end devices wish to have a trust center link key, this should be
34 requested using the request key command. Note that it is optional for the trust center to support link
35 keys.

36 With the High Security mode, all three key types are permitted and shall be supported by all devices.
37 The network key type shall be the “high security” network key. It shall be required that devices shall
38 perform entity authentication with their parent on joining and it shall be required to perform entity
39 authentication between neighbors. Frames from devices not in the neighbor table shall not be accepted.

40 When a “standard” type network key is in use, devices shall be permitted to update the network key
41 when requested to do so by a command appropriately secured with the current network key. When a
42 “high security” type of network key is in use this shall not be permitted. Additionally, in “high
43 security”, new trust center link keys may be deployed by SKKE only, i.e.: they shall not be sent using
44 key transport.

45 Bit 6 of the capabilities field (security bit) shall be used to indicate whether or not a joining (or
46 rejoining) device supports High Security mode. It shall be set to 0 if the joining or rejoining device
47 does not support High Security mode (i.e. supports Standard mode), and shall be set to 1 if it does
48 support High Security mode. The trust center may optionally make use of this information as part of its
49 policy settings, for example when determining whether or not to allow the device onto the network, or
50 when determining whether to initiate SKKE with a new joiner or send a link key and/or network key in
51 the clear to the new device.

1 The above specifications are as currently described in the ZigBee specification. Standard mode and
2 High Security mode allow implementation of two different strengths of security depending on the
3 application requirements and the specification supports a device indicating its security capabilities as it
4 joins the network, thus giving the Trust Center the means to be able to accept or reject the device based
5 on its policy.

6

8 Instructions for completing the PICS proforma

- 1
- 2
- 3 *If a given implementation is claimed to conform to this standard, the actual PICS proforma to be filled in by a supplier shall be*
- 4 *technically equivalent to the text of the PICS proforma in this document, and shall preserve the numbering and naming and the*
- 5 *ordering of the PICS proforma.*
- 6
- 7 A PICS which conforms to this document shall be a conforming PICS proforma completed in
- 8 accordance with the instructions for completion given in this section.
- 9
- 10 The main part of the PICS is a fixed-format questionnaire, divided. Answers to the questionnaire are to
- 11 be provided in the rightmost column, either by simply marking an answer to indicate a restricted choice
- 12 (such as Yes or No), or by entering a value, set, or range of values.

1 **9 Identification of the implementation**

2 _____
3 **System under test (SUT) identification**
4 _____
5 SUT name: BitCloud_256RFR2
6 _____
7 _____
8 Software Version: 3.3
9 _____
10 Hardware Version: C
11 _____
12 Operating system (optional): _____
13 _____
14 _____
15 _____
16 **Specification Version Numbers at time of certification**
17 _____
18 ZigBee PRO Specification Revision: 20
19 _____
20 Approved Errata Text to the ZigBee PRO Specification (if any): _____
21 _____
22 ZigBee PRO Test Plan Revision: 6
23 _____
24 Approved Errata Text to the ZigBee PRO Test Plan (if any): _____
25 _____
26 **Product supplier Contact Information**
27 _____
28 Company Name: Atmel Corporation
29 _____
30 Contact Name: _____
31 _____
32 Address: 1600 Technology Drive , San Jose , CA 95110 , USA
33 _____
34 _____
35 _____
36 Telephone number: _____
37 _____
38 Facsimile number: _____
39 _____
40 Email address: _____
41 _____
42 Additional information: _____
43 _____
44 _____
45 _____
46 Signature [Handwritten Signature] _____
47 _____



10 Protocol implementation conformance statement (PICS) proforma

10.1 Abbreviations and special symbols

Notations for requirement status:

M Mandatory

O Optional

O.n Optional, but support of at least one of the group of options labeled O.n is required.

N/A Not applicable

X Prohibited

“item”: Conditional, status dependent upon the support marked for the “item”.

For example, if FDT1 and FDT2 are both marked “O.1” this indicates that the status is optional but at least one of the features described in FDT1 and FDT2 is required to be implemented, if this implementation is to follow the standard of which this PICS Proforma is a part.

10.2 ZigBee device types

Item number	Item description	Reference	ZigBee Status	Feature set Support	Additional Constraints	Platform Support	
FDT1	Is this device capable of acting as a ZigBee coordinator?	[R1]/Preface (Definitions)		ZigBee	O.1		Click here to enter text.
				ZigBee-PRO	O.1		Yes
FDT2	Is this device capable of acting as a ZigBee router?	[R1]/Preface (Definitions)		ZigBee	O.1		Click here to enter text.
				ZigBee-PRO	O.1		Yes
FDT3	Is this a ZigBee end device?	[R1]/Preface (Definitions)		ZigBee	O.1		Click here to enter text.
				ZigBee-PRO	O.1		Yes

11

1 **10.3 IEEE 802.15.4 PICS**2 **10.3.1 FDT2 and FDT3 network join options**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
JN1	The device joins a network by scanning and then associating (client)	[R5] 7.3.1.1	FDT1:X FDT2:O FDT3:O	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes
JN10	The device supports joining a network by associating (server)	[R5] 7.3.1.1	FDT1: O FDT2: O FDT3: N/A	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
JN2	The device joins a network by using an orphan scan (client)	[R5] 7.3.2.3	FDT1: N/A FDT2: O FDT3: O	ZigBee	FDT1: X FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: O FDT3: O		Yes
JN20	The device supports joining a network by using an orphan scan (server)	[R5] 7.3.2.3	FDT1: O FDT2: O FDT3: N/A	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes

3

1 **10.3.2 IEEE 802.15.4 PHY**2 **10.3.2.1 Radio frequency of operation**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
RF1	The device operates at a frequency of 868 MHz.	[R5] 6.1.1, 6.1.2, 6.6	O ³	ZigBee	O ³		Click here to enter text.
				ZigBee-PRO	O ³		No
RF2	The device operates at a frequency of 915 MHz.	[R5] 6.1.1, 6.1.2, 6.6	O ³	ZigBee	O ³		Click here to enter text.
				ZigBee-PRO	O ³		No
RF3	The device operates at a frequency of 2.4 GHz.	[R5] 6.1.1, 6.1.2, 6.5	O ³	ZigBee	O ³		Click here to enter text.
				ZigBee-PRO	O ³		Yes

3 O³: at least one option must be selected.

4

5 **10.3.2.2 Clear channel assessment**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
CCA1	Mode 1: Energy above threshold is supported.	[R5] 6.7.9	O ⁴	ZigBee	O ⁴		Click here to enter text.
				ZigBee-PRO	O ⁴		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
CCA2	Mode 2: Carrier sense only is supported.	[R5] 6.7.9	O ⁴	ZigBee	O ⁴		Click here to enter text.
				ZigBee-PRO	O ⁴		Yes
CCA3	Mode 3: Carrier sense with energy above threshold is supported.	[R5] 6.7.9	O ⁴	ZigBee	O ⁴		Click here to enter text.
				ZigBee-PRO	O ⁴		Yes

1 O⁴: at least one option must be selected.

2

3 10.3.3 IEEE 802.15.4 MAC

4 10.3.3.1 Channel access

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
CA1	A super-frame structure is supported.	[R5] 7.5.1.1	O	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
CA2	Un-slotted CSMA-CA is supported.	[R5] 7.5.1.1	M	ZigBee	M	All devices shall set their MIB values as follows: <i>macBeaconOrder</i> = 0x0f, <i>macSuperframeOrder</i> = 0x0f.	Click here to enter text.
				ZigBee-PRO	M	All devices shall set their MIB values as follows: <i>macBeaconOrder</i> = 0x0f, <i>macSuperframeOrder</i> = 0x0f.	Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
CA3	Slotted CSMA-CA is supported.	[R5] 7.5.1.1	CA1: M	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
CA4	Super-frame timing is supported.	[R5] 7.5.1.1	CA1: M	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No

1

2 **10.3.3.2 Guaranteed time slots**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
GTS1	Guaranteed time slots are supported (<i>server</i>).	[R5] 7.5.7	FDT1: O	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
GTS2	Guaranteed time slots are supported (<i>client</i>).	[R5] 7.5.7	FDT2: O FDT3: O	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
GTS3	<p>The client device has the ability to request a GTS. Operations include:</p> <ul style="list-style-type: none"> • Allocation requests • De-allocation requests • [MLME-GTS.request primitive] • [MLME-GTS.confirm primitive] • Transmission of the GTS request command. 	[R5] 7.1.7.1, 7.1.7.2, 7.3.3.1, 7.5.7.2, 7.5.7.4	GTS2: M	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
GTS4	<p>The server has the ability to process GTS requests. Operations include:</p> <ul style="list-style-type: none"> • Allocation requests • De-allocation requests • Re-allocation requests • [MLME-GTS.indication primitive] • Reception and processing of the GTS request command. 	[R5] 7.1.7.3, 7.3.3.1, 7.5.7.2, 7.5.7.4, 7.5.7.5	GTS1: M	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
GTS5	The server can manage the GTSs.	[R5] 7.5.7	GTS1: M	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
GTS6	The server can perform CAP maintenance.	[R5] 7.5.7.1	GTS1: M	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
GTS7	The device can transmit and/or receive data within a GTS.	[R5] 7.5.7.3	GTS1: M GTS2: M	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No

1

2 **10.3.3.3 Scanning**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
S1	The device can perform some form of channel scan. Operations include: <ul style="list-style-type: none"> Scanning mechanism [MLME-SCAN.request primitive] [MLME-SCAN.confirm primitive] 	[R5] 7.1.11.1, 7.1.11.2, 7.5.2.1	M	ZigBee	M	All devices shall be able to perform at least an active scan.	Click here to enter text.
				ZigBee-PRO	M	All devices shall be able to perform at least an active scan.	Yes
S2	The device can perform an energy detection scan.	[R5] 7.5.2.1.1	FDT1: M	ZigBee	FDT1: M FDT2: M FDT3: X	Network devices shall perform an energy detection scan on request from the next higher layer.	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X	The coordinator shall perform an energy detection scan on each available channel in the active channel mask before starting a network.	Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
S3	The device can perform an active scan. Operations include: <ul style="list-style-type: none"> • Transmission of the beacon request command. 	[R5] 7.3.2.4, 7.5.2.1.2	FDT1: M JN1: M	ZigBee	M	All devices shall perform an active scan on each available channel in the active channel mask.	Click here to enter text.
				ZigBee-PRO	M	All devices shall perform an active scan on each available channel in the active channel mask.	Yes
S4	The device can perform a passive scan.	[R5] 7.5.2.1.3	O	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
S5	The client can perform an orphan scan. Operations include: <ul style="list-style-type: none"> • Orphan device realignment. • Transmission of the orphan notify command. • Reception and processing of the coordinator realignment command. 	[R5] 7.3.2.3, 7.3.2.5, 7.5.2.1.4	JN2: M	ZigBee	JN2:M		Click here to enter text.
				ZigBee-PRO	JN2:M		Yes
S6	The server can perform orphan scan processing. Operations include: <ul style="list-style-type: none"> • [MLME-ORPHAN.indicate primitive] • [MLME-ORPHAN.response primitive] • Reception and processing of the orphan notify command. • Transmission of the coordinator realignment command. 	[R5] 7.1.8.1, 7.1.8.2, 7.3.2.3, 7.3.2.5, 7.5.2.1.4	FDT1: O FDT2: O	ZigBee	FDT1: M FDT2: M FDT3: X	Network rejoin is the preferred mechanism for devices to use, however, orphan scan may be used and the parent devices shall support orphan scan.	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X	Network rejoin is the preferred mechanism for devices to use, however, orphan scan may be used and the parent devices shall support orphan scan.	Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support	Additional Constraints	Platform Support
S7	The server can receive and process a beacon request command.	[R5] 7.3.2.4	S3 & FDT1: M	ZigBee	FDT1: M FDT2: M FDT3: X	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X	Yes

1

2 **10.3.3.4 PAN identifier conflict resolution**

Item number	Item description	Reference	ZigBee Status	Feature set Support	Additional Constraints	Platform Support
PICR1	PAN identifier conflict resolution is supported (<i>server</i>). Operations include: <ul style="list-style-type: none"> • Reception and processing of the PAN identifier conflict notification command. • Transmission of the coordinator realignment command. 	[R5] 7.3.2.2, 7.3.2.5, 7.5.2.2	FDT1: O	ZigBee	FDT1: X FDT2: X FDT3: X	Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: X	No
PICR2	PAN identifier conflict resolution is supported (<i>client</i>). Operations include: <ul style="list-style-type: none"> • Transmission of the PAN identifier conflict notification command. • Reception and processing of the coordinator realignment command. 	[R5] 7.3.2.2, 7.3.2.5, 7.5.2.2	FDT2: O FDT3: O	ZigBee	FDT1: X FDT2: X FDT3: X	Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: X	No

3

1 **10.3.3.5 PAN start**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
PS1	Starting a PAN is supported. Operations include: <ul style="list-style-type: none"> [MLME-START.request primitive] [MLME-START.confirm primitive] 	[R5] 7.1.14.1, 7.1.14.2, 7.5.2.3	FDT1: M FDT2: M FDT3: O	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes

2

3 **10.3.3.6 Association**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
A1	Association is supported (<i>server</i>).	[R5] 7.5.3.1	FDT1: O FDT2: O	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
A2	Association is supported (<i>client</i>).	[R5] 7.5.3.1	FDT2: O FDT3: O	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
A3	<p>The server can process association requests. Operations include:</p> <ul style="list-style-type: none"> • [MLME-ASSOCIATE.indicate primitive] • [MLME-ASSOCIATE.response primitive] • Reception and processing of the association request command. • Transmission of the association response command. 	[R5] 7.1.3.2, 7.1.3.3, 7.3.1.1, 7.3.1.2	A1: M	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
A4	<p>The client can perform association. Operations include:</p> <ul style="list-style-type: none"> • [MLME-ASSOCIATE.request primitive] • [MLME-ASSOCIATE.confirm primitive] • Transmission of the association request command. • Reception and processing of the association response command. 	[R5] 7.1.3.1, 7.1.3.4, 7.3.1.1, 7.3.1.2	A2: M	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes

1

1 **10.3.3.7 Disassociation**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
D1	The device can request a disassociation. Operations include: <ul style="list-style-type: none"> • [MLME-DISASSOCIATE.request primitive] • [MLME-DISASSOCIATE.confirm primitive] • Transmission of the disassociation notify command. 	[R5] 7.1.4.1, 7.1.4.3, 7.3.1.3	O	ZigBee	FDT1: X FDT2: X FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: X		No
D2	The client can react to a disassociation from the server. Operations include: <ul style="list-style-type: none"> • [MLME-DISASSOCIATE.indicate primitive] • Reception and processing of the disassociation notify command. 	[R5] 7.1.4.2, 7.3.1.3	O	ZigBee	FDT1: X FDT2: X FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: X		No
D3	The server can react to a disassociation from a client device. Operations include: <ul style="list-style-type: none"> • [MLME-DISASSOCIATE.indicate primitive] • Reception and processing of the disassociation notify command. 	[R5] 7.1.4.2, 7.3.1.3	O	ZigBee	FDT1: X FDT2: X FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: X		No

2

1 **10.3.3.8 Beacon synchronization**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
BS1	Beacon notification is supported. Operations include: <ul style="list-style-type: none"> [MLME-BEACON-NOTIFY.indication primitive] 	[R5] 7.1.5.1	O	ZigBee	FDT1: M FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: M		Yes
BS2	The client can synchronize to a beacon. Operations include: <ul style="list-style-type: none"> (Tracking only for beacon networks) [MLME-SYNC.request primitive] [MLME-SYNC-LOSS.indication primitive] 	[R5] 7.1.15.1, 7.1.15.2, 7.5.4	O	ZigBee	FDT1: X FDT2: X FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: X		No

2

3 **10.3.3.9 Transmission**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
T1	Frame transmission is supported. Operations include: <ul style="list-style-type: none"> Frame construction [MCPS-DATA.request primitive] [MCPS-DATA.confirm primitive] Transmission of data frames. 	[R5] 7.1.1.1, 7.1.1.2, 7.2.1, 7.2.2.2, 7.5.6.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
T2	Implicit (command frame) transmission confirmation is supported. Operations include: <ul style="list-style-type: none"> [MLME-COMM-STATUS.indication primitive] 	[R5] 7.1.12.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

1

2 **10.3.3.10 Reception**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
R1	Frame reception is supported. Operations include: <ul style="list-style-type: none"> Data frame deconstruction [MCPS-DATA.indication primitive] Reception of data frames. 	[R5] 7.1.1.3, 7.2.1, 7.2.2.2	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
R2	Receiver control is supported. Operations include: <ul style="list-style-type: none"> [MLME-RX-ENABLE.request primitive] [MLME-RX-ENABLE.confirm primitive] 	[R5] 7.1.10.1, 7.1.10.2	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes
R3	Filtering and rejection is supported.	[R5] 7.5.6.2	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
R4	Promiscuous mode is supported.	[R5] 7.5.6.6	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		No

1

2 **10.3.3.11 Transaction handling**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
TH1	Transaction handling is supported (<i>server</i>).	[R5] 7.5.5	FDT1: O FDT2: O	ZigBee	FDT1: M FDT2: M FDT3: X	The server shall be able to handle at least one transaction.	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X	The server shall be able to handle at least one transaction.	Yes
TH2	Transaction handling is supported (<i>client</i>).	[R5] 7.5.5	FDT2: O FDT3: O	ZigBee	FDT1: X FDT2: X FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: M		Yes
TH3	The server can manage transactions to its devices. Operations include: <ul style="list-style-type: none"> Transaction queuing Reception and processing of the data request command. 	[R5] 7.5.5, 7.1.1.4, 7.1.1.5, 7.3.2.1	TH1: M	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
TH30	The server can manage transaction purging operations: <ul style="list-style-type: none"> [MCPS-PURGE.request primitive] [MCPS-PURGE.confirm primitive] 	[R5] 7.1.1.4, 7.1.1.5, 7.3.2.1	TH1: M	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes
TH4	The client can extract data from the coordinator following an indication of data in a beacon.	[R5] 7.5.6.3	TH2: O ⁵	ZigBee	FDT1: X FDT2: X FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: X		No
TH5	The client can poll for data. Operations include: <ul style="list-style-type: none"> [MLME-POLL.request primitive] [MLME-POLL.confirm primitive] Transmission of the data request command. 	[R5] 7.1.16.1, 7.1.16.2, 7.3.2.1	TH2: O ⁵	ZigBee	FDT1: X FDT2: X FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: M		Yes

1 O⁵: At least one of these options must be supported.

2 10.3.3.12 Acknowledgement service

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AS1	The acknowledgement service is supported.	[R5] 7.5.6.4	O	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AS2	The device can transmit, receive and process acknowledgement frames.	[R5] 7.2.2.3	AS1: M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
AS3	Deprecated	[R5] 7.5.6.4.2, 7.5.6.5	AS1: M	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
AS4	Retransmissions are supported.	[R5] 7.5.6.5	AS1: M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

1

2 **10.3.3.13 MIB management**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
MM1	MIB management is supported. Operations include: <ul style="list-style-type: none"> MIB attribute storage 	[R5] 7.4.2	O	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
MM2	The device supports the reading of MIB attributes. Operations include: <ul style="list-style-type: none"> [MLME-GET.request primitive] [MLME-GET.confirm primitive] 	[R5] 7.1.6.1, 7.1.6.2, 7.4.2	MM1: O	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
MM3	The device supports the writing of MIB attributes. Operations include: <ul style="list-style-type: none"> • MIB attribute verification • [MLME-SET.request primitive] • [MLME-SET.confirm primitive] 	[R5] 7.1.13.1, 7.1.13.2, 7.4.2	MM1: O	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

1

2 **10.3.3.14 MAC security**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
MS1	The device supports ACL mode. Operations include: <ul style="list-style-type: none"> • ACL storage • ACL mode usage 	[R5] 7.4.2, 7.5.8.1, 7.5.8.3	O	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
MS2	The device supports secured mode.	[R5] 7.5.8.4	O	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No

3

4

1 **10.3.3.15 Device reset**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
DR1	The device is able to reset. Operations include: <ul style="list-style-type: none"> [MLME-RESET.request primitive] [MLME-RESET.confirm primitive] 	[R5] 7.1.9.1, 7.1.9.2	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes

2

3 **10.4 Network layer PICS**4 **10.4.1 ZigBee network frame format**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
GFF1	Does the device support the general ZigBee network frame format?	[R1]/3.3.1		ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

5

6 **10.4.2 Major capabilities of the ZigBee network layer**

7 Tables in the following sub-clauses detail the capabilities of NWK layer for ZigBee devices.

8 **10.4.2.1 Network layer functions**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NLF1	Does the network layer support transmission of data by the next higher layer?	[R1]/3.2.1.1, 3.2.1.2, 3.6.2.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NLF2	Does the network layer support reception of data by the next higher layer?	[R1]/3.2.1.3, 3.6.2.2	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NLF3	Does the network layer support discovery of existing ZigBee networks?	[R1]/3.2.2.1, 3.2.2.2	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NLF4	Does the network layer support formation of ZigBee networks?	[R1]/3.2.2.3, 3.2.2.4, 3.6.1.1	FDT1:M, FDT2:X, FDT3:X	ZigBee	FDT1: M FDT2: X FDT3: X	Devices using the ZigBee feature set shall set: Feature set = 1 <i>nwkProtocolVersion</i> = 2 and shall advertise these values in their beacon payload in response to MAC beacon requests. Devices using the ZigBee feature set shall also set: <i>nwkSecurityLevel</i> = 5	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: X FDT3: X	Devices using the ZigBee-PRO feature set shall set: Feature set = 2 <i>nwkProtocolVersion</i> = 2 and shall advertise these values in their beacon payload in response to MAC beacon requests. Devices using the ZigBee-PRO feature set shall also set: <i>nwkSecurityLevel</i> = 5	Yes
NLF5	Can the network layer permit other devices to join the network of which it is a part (and also deny such permission)?	[R1]/3.2.2.5, 3.2.2.6, 3.6.1.2	FDT1:M, FDT2:M, FDT3:X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NLF6	Can the device start as a router?	[R1]/3.2.2.7, 3.2.2.8	FDT1:X, FDT2:M, FDT3:X	ZigBee	FDT1: X FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: X		Yes
NLF60	Can the network layer perform energy detection scans at the request of the next higher layer?	[R1]/3.2.2.9, 3.2.2.10	M	ZigBee	FDT1: M FDT2: M FDT3: X	NLME-ED-SCAN is mandatory for the coordinator and optional for all routers on a ZigBee network.	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X	NLME-ED-SCAN is mandatory for the coordinator and all routers on a PRO network.	Yes
NLF7	Can the device request membership in a ZigBee network?	[R1]/3.2.2.11, 3.2.2.13, 3.6.1.4	FDT1: N/A FDT2: M FDT3: M	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes
NLF70	Can the device request to join or rejoin a network using the orphaning procedure?	[R1]/3.2.2.14, 3.2.2.15, 3.6.1.4.3.1	FDT1: N/A FDT2: O FDT3: O	ZigBee	FDT1: X FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: O FDT3: O		Yes
NLF71	Can the device request to join / rejoin a network using the rejoin command frame and associated procedure?	[R1]/3.2.2.11, 3.2.2.13, 3.6.1.4.2.1	FDT1: N/A FDT2: O FDT3: O	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NLF72	Can the network layer be directed by the next higher layer to change the operating channel of the network of which it is currently a part?	[R1]/3.2.2.11, 3.2.2.13	O	ZigBee	M	The network layer can be directed by the next higher layer to change the operating channel of the network of which it is currently part.	Click here to enter text.
				ZigBee-PRO	M		Yes
NLF8	Can the device respond to requests to join the network of which it is a part?	[R1]/3.6.1.4.1.2, 3.6.1.4.2.2	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NLF81	Does the network layer of a device inform the next higher layer when a second device has joined or rejoined its network as a child?	[R1]/3.2.2.12	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NLF9	Does the network layer employ the Distributed Address Mechanism to generate a unique network address to assign to a joining device?	[R1]/3.6.1.6	FDT1: O FDT2: O FDT3: N/A	ZigBee	FDT1: M FDT2: M FDT3: X	The ZigBee feature set always employs the distributed addressing scheme with: nwkMaxDepth = 5 nwkMaxChildren = 20 nwkMaxRouters = 6	Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: X		Yes
NLF90	Does the network layer employ the Stochastic Addressing Scheme to	[R1]/3.6.1.7	FDT1: O FDT2: O FDT3: N/A	ZigBee	FDT1: X FDT2: X FDT3: X		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	generate a unique network address to assign to a joining or rejoining device?			ZigBee-PRO	FDT1: M FDT2: M FDT3: X	The ZigBee-PRO feature set employs stochastic address allocation. The follow parameter values are defined: <i>nwkAddrAlloc</i> = 2 <i>nwkUseTreeRouting</i> = FALSE <i>nwkMaxDepth</i> = 15 Note that <i>nwkMaxDepth</i> above is only used to compute timeouts and shall not limit the actual network radius, as this feature set does not use tree-based addressing. The parameter <i>nwkMaxChildren</i> is not restricted in this feature set.	Yes
NLF100	Does the network layer employ the Higher Layer Address Assignment Mechanism to generate a unique network address to assign to a joining device?	Deprecated	X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
NLF10	Can the next higher layer request that a particular device be "pre-joined" to it using the DIRECT-JOIN procedure?	[R1]/3.2.2.14, 3.2.2.15, 3.6.1.4.3	FDT1: O FDT2: O FDT3: X	ZigBee	X	This service is useful for testing and may be allowed as a part of test procedures at the option of the stack developer.	Click here to enter text.
				ZigBee-PRO	X	This service is useful for testing and may be allowed as a part of test procedures at the option of the stack developer.	Yes
NLF11	Can the device make a request to leave the network?	[R1]/3.2.2.16, 3.2.2.18, 3.6.1.10.1	O	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NLF12	Can the device make a request that one of its child devices leave the network?	[R1]/3.2.2.16, 3.2.2.18, 3.6.1.10.2	FDT1: O FDT2: O FDT3: N/A	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NLF13	Can the network layer process network leave commands from child devices?	[R1]/3.6.1.10.3	FDT1: M FDT2: M FDT3: N/A	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NLF130	Can the network layer process network leave commands from parent devices?	[R1]/3.6.1.10.3	FDT1: N/A FDT2: M FDT3: M	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes
NLF131	Does the network layer inform the next higher layer if the device itself has left the network?	[R1]/3.2.2.17	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NLF14	Does the device support changing of the ZigBee coordinator configuration in an operating network?	[R1]/3.2.2.3, 3.2.2.4, 3.6.1.11	FDT1: O FDT2: X FDT3: X	ZigBee	FDT1: M FDT2: X FDT3: X	The ZigBee coordinator shall change the logical channel and PAN ID when directed to by the Network Channel Manager.	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: X FDT3: X		Yes
NLF15	Does the device support changing of the ZigBee router configuration in	[R1]/3.2.2.7, 3.2.2.8	FDT1: X FDT2: O FDT3: X	ZigBee	FDT1: X FDT2: M FDT3: X	The ZigBee router shall change the logical channel and PAN ID	Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	an operating network?			ZigBee-PRO	FDT1: X FDT2: M FDT3: X	when directed to by the Network Channel Manager.	Yes
NLF16	Does the network layer support reset?	[R1]/3.2.2.19, 3.2.2.20, 3.6.1.12	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NLF17	Does the network layer allow the next higher layer to synchronize with or extract data from the device's ZigBee coordinator or router?	[R1]/3.2.2.22, 3.2.2.23	FDT1: X FDT2: O FDT3: M	ZigBee	FDT1: X FDT2: X FDT3: M	Recommended polling rates for end devices using this feature set: Maximum: once per 7.5s Minimum: once per hour Note that these values represent the (rather loose) recommended boundaries on polling rate for normal operation only. Additionally, the polling rate established to meet this requirement shall have a maximum value less than <i>nwkTransactionPersistenceTime</i> to ensure that child devices can poll frequently enough to retrieve messages prior to expiration in the indirect message queue of their parent. The polling rate established here also does not consider APS acknowledgement timeout (which is much shorter than <i>nwkTransaction-PersistenceTime</i>). If APS acknowledged messages are directed to sleeping end devices, then the polling rate of those destination devices may be adjusted to occur more frequently than the APS acknowledgement timeout.	Click here to enter text.
							ZigBee-PRO
NLF18	Does the network layer report a loss of synchronization with the device's ZigBee router or	[R1]/3.2.2.23	FDT1: X FDT2: O FDT3: M	ZigBee	X		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	ZigBee coordinator to the next higher layer?			ZigBee-PRO	X		No
NLF19	Does the network layer offer the next higher layer the ability to retrieve network information base (NIB) attributes?	[R1]/3.2.2.26, 3.2.2.27	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NLF20	Does the network layer offer the next higher layer the ability to set network information base (NIB) attributes?	[R1]/3.2.2.28, 3.2.2.29	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NLF110	Does the network layer support network status reporting to the next higher layer?	[R1]/3.2.2.30	M	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NLF111	Does the network layer support Route Discovery?	[R1]/3.2.2.31, 3.2.2.32, 3.6.3.5	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NLF112	Does the network layer support Route Discovery requests with DstAddrMode of 0x00 in support of Many-to-One discovery?	[R1]/3.2.2.31, 3.2.2.32, 3.6.3.5	FDT1: O FDT2: O FDT3: X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X	Initiation of a Many-to-One route discovery is optional, and should be used in cases where there are relatively few concentrators in the network. Application developers should weigh the trade-offs between Many-to-One discovery and unicast discovery before deploying.	Yes
NLF113	Does the network layer support Route Discovery requests with DstAddrMode of 0x01 in support of Multicast Group Discovery?	[R1]/3.2.2.31, 3.2.2.32, 3.6.3.5, 3.6.6	FDT1: O FDT2: O FDT3: X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X	Initiation of route discovery commands where DstAddrMode is 0x01 (Multicast Group Discovery) is optional.	Yes
NLF114	Does the network layer support Route Discovery requests with DstAddrMode of 0x02 in support of the discovery of Unicast routes?	[R1]/3.2.2.31, 3.2.2.32, 3.6.3.5	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: O FDT2: O FDT3: X	Initiation of route discovery commands where DstAddrMode is 0x02 (Unicast) is optional.	Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X	ZigBee coordinators and ZigBee routers shall support reception and correct handling of unicast discovery commands.	Yes
NLF115	Does the network layer employ tree routing?	3.6.3.3	O	ZigBee	M	Devices using the ZigBee stack profile must set: <i>nwkUseTreeRouting</i> = TRUE	Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
				ZigBee-PRO	X	Devices using the ZigBee-PRO stack profile shall set: <i>nwkUseTreeRouting</i> = FALSE	Yes
NLF21	Does the network layer calculate routing cost based on probability of reception?	3.6.3.1	O	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NLF22	Does the network layer maintain a routing table and route discovery table?	[R1]/3.6.3.2	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X	ZigBee coordinators and ZigBee routers shall maintain a routing table and a route discovery table as follows: Routing table (minimum): 8 entries Route discovery table (minimum): 4 entries	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X	ZigBee coordinators and ZigBee routers shall maintain a routing table and a route discovery table as follows: Routing table (minimum): 10 entries An aging algorithm is recommended but is beyond the scope of this specification. Route discovery table entries (minimum): 4 entries The Route discovery table entries shall be managed as described in [R1] sub-clause 3.6.3.6.	Yes
NLF220	Does the network layer maintain a route record table?	[R1]/3.5.2, 3.6.3.2	FDT1: O FDT2: O FDT3: X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NLF221	Does the network layer maintain a multicast group ID table?	[R1]/3.6.6.1	FDT1:O, FDT2:O, FDT3:X	ZigBee	X	ZigBee coordinators and ZigBee routers that use this stack profile shall set <i>nwkUseMulticast</i> to FALSE.	Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X		Yes
NLF23	Does the network layer reserve routing capacity for route repair operations? (Note: This capability has been removed from the ZigBee specification as of r08).	None	X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
NLF24	Does the device implement beacon collision-avoidance measures?	[R1]/3.6.4	O	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
NLF25	Does the network layer support router re-enumeration as a route repair method? (Note: This capability has been removed from the ZigBee specification as of r10).	None	X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
NLF26	Does the network layer assume that links are symmetrical and establish forward and reverse routes at the same time?	[R1]/3.5.2, 3.6.3.5.2	O	ZigBee	X	Devices using the ZigBee stack profile must set: <i>nwkSymLink</i> = FALSE	Click here to enter text.
				ZigBee-PRO	M	Devices using the ZigBee-PRO stack profile shall set: <i>nwkSymLink</i> = TRUE	Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NLF27	Does the network layer maintain a neighbor table or tables in order to store information about nearby devices?	[R1]/3.6.1.5	M	ZigBee	M	ZigBee coordinators and ZigBee routers shall maintain a neighbor table or tables as follows: ZigBee coordinator (minimum): 24 entries ZigBee router (minimum): 25 entries ZigBee end device (minimum): 1 entry	Click here to enter text.
				ZigBee-PRO	M	ZigBee coordinators and ZigBee routers shall maintain a neighbor table or tables as follows: ZigBee coordinator (minimum): (Number of child end devices accepted) plus 16 ZigBee router (minimum): (Number of child end devices accepted) plus 16 ZigBee end device: 1 (Note: End Device shall only support only a single neighbor table entry and that entry shall be for their parent) Where (Number of child end devices accepted) is the maximum number of end device children that a particular router or coordinator in the network is configured to accept.	Yes
NLF28	Does the network layer buffer frames pending route discovery or route repair operations?	[R1]/3.6.3.5.1	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes
NLF29	Does the network layer buffer data frames on behalf of end device that	[R1]/3.6.5	FDT1:M FDT2:M FDT3:X	ZigBee	FDT1: M FDT2: M FDT3: X	ZigBee router and coordinator devices shall set: Number of frames	Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	are its children?			ZigBee-PRO	FDT1: M FDT2: M FDT3: X	buffered on behalf of sleeping end devices (minimum): 1 Note that this means 1 frame TOTAL not 1 frame for each end device. In other words, it is up to the implementer to put in some buffering but routers should not be overburdened with, possibly unnecessary, buffering.	Yes
NLF30	Is the device capable of participating in a beacon-oriented network?	[R1]/Preface Definitions and Network Topology sections	O	ZigBee	X	On invocation of the NLME-NETWORK-FORMATION.request or NLME-START-ROUTER.request primitives, devices shall employ:	Click here to enter text.
				ZigBee-PRO	X	BeaconOrder = 0x0f SuperframeOrder = 0x0f	No
NLF31	Does the network layer support the detection of address conflicts?	[R1]/3.6.1.9	O	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X	Address conflict detection is mandatory for this stack profile (nwkUniqueAddr = FALSE). The coordinator and all routers shall implement the Address Conflict procedure.	Yes
NLF32	Does the network layer support resolving address conflicts?	[R1]/3.6.1.9.3	FDT1: O FDT2: O FDT3: X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X	Address conflict resolution is mandatory for this stack profile (nwkUniqueAddr = FALSE). The coordinator and all routers shall implement the Address Conflict procedure.	Yes
NLF33	Does the network layer support the detection of PAN ID conflicts?	[R1]/3.6.1.13	O	ZigBee	FDT1:M FDT2:M FDT3:X	PAN ID conflict resolution is mandatory for the coordinator and routers. Notification of a PAN ID conflict via the	Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
				ZigBee-PRO	FDT1:M FDT2:M FDT3:X	NWK Status command frame directed to the nwkManagerAddr is mandatory for all routers and the coordinator. The nwkManagerAddr is required to process all NWK Status command frames directed to it by the coordinator and routers.	Yes
NLF34	Does the device support resolving PAN ID conflicts?	[R1]/3.6.1.13	O	ZigBee	FDT1: M FDT2: M FDT3: X	PAN ID conflict resolution is mandatory for the coordinator and routers. Notification of a PAN ID conflict via the NWK Status command frame directed to the nwkManagerAddr is mandatory for all routers and the coordinator. The nwkManagerAddr is required to process all NWK Status command frames directed to it by the coordinator and routers.	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes

1

2 **10.4.2.2 Network layer frames**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NDF1	Does the device support the origination of network data frames?	[R1]/3.3.2.1, 3.6.2.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NDF2	Does the device support the receipt of network data frames?	[R1]/3.3.2.1, 3.6.2.2	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NDF3	Does the device support the relaying of unicast network data	[R1]/3.3.2.1, 3.6.3.3	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	frames?			ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes

1

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NDF4	Does the device support relaying of broadcast network data frames?	[R1]/3.3.2.1, 3.6.5	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X	Devices using the ZigBee stack profile must set: Broadcast Transaction Table size: 9 (minimum) <i>nwkBroadcastDeliveryTime</i> = 0x44AA2 ⁴ Octet durations (9 seconds on 2.4 GHz) <i>nwkPassiveAckTimeout</i> = 0x3D09 ⁵ Octet durations ⁶ (500 ms on 2.4 GHz) maximum <i>nwkMaxBroadcastRetries</i> = 2	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X	Devices using the ZigBee-PRO stack profile shall set: Broadcast Transaction Table size: 9 (minimum) <i>nwkBroadcastDeliveryTime</i> = 0x44AA2 ⁷ Octet durations (9 seconds on 2.4 GHz) <i>nwkPassiveAckTimeout</i> = 0x3D09 ⁸ Octet Durations ⁹ (500 ms on 2.4 GHz) maximum <i>nwkMaxBroadcastRetries</i> = 2 Application designers should take care to use multicast and broadcast sparingly due to the limitations of the broadcast bandwidth of a network.	Yes
NDF100	Does the device support relaying of multicast network data frames?	[R2]/3.3.2.1, 3.6.6	FDT1: O FDT2: O FDT3: X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X	The coordinator and all routers in a PRO network shall be able to relay member mode multicast network data frames.	Yes
NDF101	Does the device support the relaying of source routed network	[R2]/3.3.2.1, 3.6.3.3.2	FDT1:O, FDT2:O, FDT3:X	ZigBee	X		Click here to enter text.

⁴ CCB 1629⁵ CCB 1633⁶ CCB 1633⁷ CCB 1629⁸ CCB 1633⁹ CCB 1633

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	data frames?			ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes

1 10.4.2.3 Network command frames

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NCF1	Does the device support the origination of route request command frames?	[R1]/3.4.1, 3.6.3.5.1	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF2	Does the device support the receipt of route request command frames?	[R1]/3.4.1, 3.6.3.5.2	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF3	Does the device support the relaying of route request command frames?	[R1]/3.4.1, 3.6.3.5.2	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF4	Does the device support the origination of route reply command frames?	[R1]/3.4.2, 3.6.3.5.2	FDT1:M, FDT2:M, FDT3:X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF5	Does the device support the receipt of route reply command frames?	[R1]/3.4.2, 3.6.3.5.3	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF6	Does the device support the relaying of route reply command frames?	[R1]/3.4.2, 3.6.3.5.3	FDT1:M, FDT2:M, FDT3:X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF7	Does the device support the transmission of network status command frames?	[R1]/3.4.3, 3.6.1.9.3, 3.6.3.3, 3.6.3.7.1	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF8	Does the device support the receipt of network status command frames?	[R1]/3.4.3, 3.6.1.9.3, 3.6.3.7.1	M	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF9	Does the device support the relaying of network command frames? In particular, does it support the relaying of those command frames, specifically network status, network report and network update, which require relaying but for which there are no special per-hop processing requirements?	[R1]/3.4.3, 3.4.9, 3.4.10	FDT1:M, FDT2:M, FDT3:X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NCF100	Does the device support the origination of leave command frames?	[R1]/3.4.4, 3.6.1.10	FDT1:O, FDT2:O, FDT3:O	ZigBee	FDT1: M FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: M		Yes
NCF101	Does the device support the receipt of leave command frames?	[R1]/3.4.4, 3.6.1.10	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NCF103	Does the device support the origination of route record command frames?	[R1]/3.4.5, 3.6.3.5.4	FDT1: O FDT2: O FDT3: X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF104	Does the device support the receipt of route record command frames?	[R1]/3.4.5, 3.6.3.5.4	FDT1: O FDT2: O FDT3: X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF105	Does the device support the relaying of route record command frames?	[R1]/3.4.5, 3.6.3.5.4	FDT1: O FDT2: O FDT3: X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NCF106	Does the device support the transmission of rejoin request command frames?	[R1]/3.4.6, 3.7.1.3.2.1	FDT1:X FDT2:M FDT3:M	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes
NCF107	Does the device support the reception of rejoin request command frames?	[R1]/3.4.6, 3.7.1.3.2.2	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF108	Does the device support the transmission of rejoin response command frames?	[R1]/3.4.7, 3.7.1.3.2.2	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF109	Does the device support the reception of rejoin response command frames?	[R1]/3.4.7, 3.7.1.3.2.1	FDT1: X FDT2: M FDT3: M	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NCF110	Does the device support the generation of a network report command frame.	[R1]/3.4.9, 3.6.1.13.1	O	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes
NCF111	Does the device support the reception of a network report command frame	[R1]/3.4.9, 3.6.1.13.2	O	ZigBee	FDT1: O FDT2: O FDT3: X	While this feature is optional, one device in the network must be designated as the network manager and for that device this feature is mandatory.	Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X		Yes
NCF112	Does the device support the generation of a network update command frame.	[R1]/3.4.10, 3.6.1.13.2	O	ZigBee	FDT1: O FDT2: O FDT3: X	While this feature is optional, one device in the network must be designated as the network manager and for that device this feature is mandatory.	Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X		Yes
NCF113	Does the device support the reception of a network update command frame	[R1]/3.4.10, 3.6.1.13.3	O	ZigBee	FDT1: M FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: M		Yes
NCF114	Does the device support the generation of a link status command frame.	[R1]/3.4.8, 3.6.3.4.1	FDT1: O FDT2: O FDT3: X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NCF115	Does the device support the reception of a link status command frame.	[R1]/3.4.8, 3.6.1.5, 3.6.3.4.2	FDT1: O FDT2: O FDT3: X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
NCF116 ¹⁰	Does the device support ignoring the NWK leave command?	[R1]/3.5.2, 3.6.1.10.3	FDT1: O FDT2: O FDT3: X	ZigBee-PRO	FDT1: O FDT2: O FDT3: X		Yes

1 10.5 Security PICS

2 10.5.1 ZigBee security roles

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
SR1	Is this device capable of acting in the role of a trust center?	[R1]/1.4, 4.6.2	FDT1: M FDT2: O FDT3: X	ZigBee	FDT1: M FDT2: O FDT3: X	Upon initial network formation, the coordinator must at least temporarily serve as the trust center. After formation, at least one of the routers or the coordinator must be capable of acting in the role of the trust center. It is an application responsibility to transition the trust center from the coordinator to another router device pointed to by <code>apsTrustCenterAddress</code> within all devices in the network if desired. For the device whose address is <code>apsTrustCenterAddress</code> , it is mandatory to act in the role of the trust center. All devices in the network shall maintain a single consistent definition of <code>apsTrustCenterAddress</code> . It is possible, under application control, to change <code>apsTrustCenterAddress</code> during later network operation,	Click here to enter text.

¹⁰ CCB 1279

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
				ZigBee-PRO	FDT1: M FDT2: O FDT3: X	however, it is the application's responsibility to ensure that all devices in the network are notified of the change.	Yes

1
2
3

10.5.2 ZigBee trust center capabilities

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
TCC1	Is this device capable of acting as a ZigBee trust center in high security mode?	[R1]/1.4.1.2, 4.6.2.1	SR1:O.2	ZigBee	X		Click here to enter text.
				ZigBee-PRO	SR1: O.2	Every PRO network shall have a Trust Center either running in Standard or High Security mode The device designated as the Trust Center shall be declared a concentrator in a PRO network and a Many to One route shall be created to the Trust Center. At least one of TCC1 or TCC2 must be supported if the device supports SR1.	No
TCC2	Is this device capable of acting as a ZigBee trust center in standard mode?	[R1]/1.4.1.2, 4.6.2.2	SR1:O.2	ZigBee	M		Click here to enter text.
				ZigBee-PRO	SR1: O.2	Every PRO network shall have a Trust Center either running in Standard or High Security mode The device designated as the Trust Center shall be declared a concentrator in a PRO network and a Many to One route shall be created to the Trust Center. At least one of TCC1 or TCC2 must be supported if the device supports SR1.	Yes

4
5

1 **10.5.3 Modes of operation**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
MOO1	Is this device capable of operating in a network secured with a trust center running in high security mode?	[R1]/1.4.1.2, 4.6.2.1	O.3	ZigBee	X		Click here to enter text.
				ZigBee-PRO	O.3	A PRO device shall join a PRO network either running in Standard or High Security mode. At least one of MOO1 or MOO2 must be supported.	No
MOO2	Is this device capable of operating in a network secured with a trust center running in standard mode?	[R1]/1.4.1.2,	O.3	ZigBee	M		Click here to enter text.
				ZigBee-PRO	O.3	A PRO device shall join a PRO network either running in Standard or High Security mode. At least one of MOO1 or MOO2 must be supported.	Yes

2

3 **10.5.4 Security levels**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
SL1	Is this device capable of supporting security level 0x01?	[R1]/4.5.1.1.1	O.4	ZigBee	X	The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05.	Click here to enter text.
				ZigBee-PRO	X		No
SL2	Is this device capable of supporting security level 0x02?	[R1]/4.5.1.1.1	O.4	ZigBee	X	The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05.	Click here to enter text.
				ZigBee-PRO	X		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
SL3	Is this device capable of supporting security level 0x03?	[R1]/4.5.1.1.1	O.4	ZigBee	X	The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05.	Click here to enter text.
				ZigBee-PRO	X		No
SL4	Is this device capable of supporting security level 0x04?	[R1]/4.5.1.1.1	O.4	ZigBee	X	The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05.	Click here to enter text.
				ZigBee-PRO	X		No
SL5	Is this device capable of supporting security level 0x05?	[R1]/4.5.1.1.1	O.4	ZigBee	M	The device shall apply security to outgoing frames or accept secured incoming frames using only level 0x05 (i.e., ENC-MIC-32)	Click here to enter text.
				ZigBee-PRO	M		Yes
SL6	Is this device capable of supporting security level 0x06?	[R1]/4.5.1.1.1	O.4	ZigBee	X	The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05.	Click here to enter text.
				ZigBee-PRO	X		No
SL7	Is this device capable of supporting security level 0x07?	[R1]/4.5.1.1.1	O.4	ZigBee	X	The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05.	Click here to enter text.
				ZigBee-PRO	X		No

1

2

1 **10.5.5 NWK layer security**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NLS1	Does the device support the security processing of NWK layer outgoing frames?	[R1]/4.3.1.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NLS2	Does the device support the security processing of NWK layer incoming frames?	[R1]/4.3.1.2	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NLS3	Does the device support the ZigBee secured NWK layer frame format?	[R1]/4.3.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
NLS4	Does the device support the ability to manage at least one network key and corresponding outgoing frame counter?	[R1]/4.2.1.3, 4.3.3	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NLS5	Does the device support the ability to manage two network keys and corresponding outgoing frame counter?	[R1]/4.2.1.3, 4.3.1, 4.3.3	O	ZigBee	M	All devices shall maintain at least 2 NWK keys with the frame counters consistent with the security mode of the network (Standard or High). A NWK key of all zero's shall be treated as reserved. Due to the fact that a NWK key of all zero's was used as a "dummy key" and employed in the trust center exchange where pre-configured keys are used, a NWK key of all zero's is indistinguishable from transport of a dummy key.	Click here to enter text.
				ZigBee-PRO	M		Yes
NLS7	Does the device support at least one frame counter for incoming NWK layer frames for each potential source of incoming frames (e.g., a coordinator or router should support the same number of counters per network key as the maximum number of neighbor table entries and an end device should support one counter per network key)?	[R1]/4.2.1.3, 4.3.1, 4.3.3	O	ZigBee	M	Devices using this stack profile in Standard Security and High Security mode shall store a single frame counter per neighbor table entry associated with the current NWK Key.	Click here to enter text.
				ZigBee-PRO	M		Yes
NLS8	Does the device support a setting to indicate that all incoming NWK frames must be checked for freshness (i.e., <i>nwkAllFresh</i>).	[R1]/4.4.1.2, 4.6.2.1, 4.6.2.2	MOO1: M MOO2: O	ZigBee	MOO1: M MOO2: O	See also the trust centre policies document [R4].	Click here to enter text.
				ZigBee-PRO	MOO1: M MOO2: O		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
NLS9	Does the device support the ability to secure all incoming and outgoing NWK frames (i.e., the <i>nwkSecureAllFrames</i> attribute of the NIB)?	[R1]/4.2.3, 4.6	O	ZigBee	M	Devices using the ZigBee and ZigBee-PRO feature sets shall set: nwkSecureAllFrames = TRUE	Click here to enter text.
				ZigBee-PRO	M		Yes
NLS10	Does the device support the ability to reject frames from neighbors which have not been properly authenticated?	[R1]/4.2.3, 4.6	O	ZigBee	MOO1: M MOO2: O	Coordinator and Router devices employing ZigBee and ZigBee PRO Standard Mode security shall not reject frames from neighbors which have not been properly authenticated. Coordinator and Router devices employing ZigBee PRO High Security shall reject frames from neighbors which have not been properly authenticated.	Click here to enter text.
				ZigBee-PRO	MOO1: M MOO2: O		No

1

2 **10.5.6 APS layer security**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ASLS1	Does the device support the security processing of APS layer outgoing frames?	[R1]/4.4.1.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
ASLS2	Does the device support the security processing of APS layer incoming frames?	[R1]/4.4.1.2	M	ZigBee	M		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
				ZigBee-PRO	M		Yes
ASLS3	Does the device support the ZigBee secured APS layer frame format?	[R1]/4.4.7.3	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
ASLS4	Does the device support the ability to manage trust center master keys?	[R1]/4.4.3, 4.4.10, 4.6.3	O	ZigBee	MOO1: M MOO2: O	In ZigBee and ZigBee PRO Standard Mode security, trust center master keys are optional for all devices. In ZigBee PRO High Security, trust center master keys mandatory for all devices.	Click here to enter text.
				ZigBee-PRO	MOO1: M MOO2: O		No
ASLS5	Does the device support the ability to manage application master keys?	[R1]/4.2.3.5, 4.4.3, 4.4.6, 4.4.10, 4.6.3.5	O	ZigBee	O	In ZigBee and ZigBee PRO Standard and ZigBee PRO High security modes, application master keys are optional for all devices.	Click here to enter text.
				ZigBee-PRO	O		No
ASLS6	Does the device support the ability to manage application data keys and corresponding security material (e.g., the incoming and outgoing frame counters)?	[R1]/4.2.1.3, 4.4.1, 4.4.10	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes
ASLS7	Does the device support network key incoming frame counters for incoming APS layer frames secured with the network key?	[R1]/4.4.1.2, 4.3.3	O	ZigBee	X	ZigBee and ZigBee PRO Standard-Mode or ZigBee-PRO High Mode security use nwkSecure-AllFrames=TRUE, the APS security header is not employed when the network key is used for incoming APS layer frames.	Click here to enter text.
				ZigBee-PRO	X		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ASLS8	Does the device support establish-key service using the Symmetric-Key Key Establishment (SKKE) protocol?	[R1]/4.2.3.1, 4.4.2, 4.4.9.1	O	ZigBee	MOO1: M MOO2: O	In ZigBee and ZigBee PRO Standard Mode security, SKKE is optional for all devices. In ZigBee PRO High Security, SKKE is mandatory for all devices.	Click here to enter text.
				ZigBee-PRO	MOO1: M MOO2: O		No
ASLS9	Does the device support the origination of transport-key commands?	[R1]/4.2.3.2, 4.4.3, 4.4.9.2	SR1: M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ASLS10	Does the device support the receipt of transport-key commands?	[R1]/4.2.3.2, 4.4.3, 4.4.9.2	O	ZigBee	M	A newly joined device in ZigBee or ZigBee PRO Standard and ZigBee PRO High Security shall be capable of receiving the NWK key from the trust center via transport-key commands.	Click here to enter text.
				ZigBee-PRO	M		Yes
ASLS11	Does the device support the origination of update-device commands?	[R1]/4.2.3.3, 4.4.4, 4.4.9.3	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
ASLS12	Does the device support the receipt of update-device commands?	[R1]/4.2.3.3, 4.4.4, 4.4.9.3	SR1:M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ASLS13	Does the device support the origination of remove-device commands?	[R1]/4.2.3.4, 4.4.5, 4.4.9.4	SR1:M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ASLS14	Does the device support the receipt of remove-device commands?	[R1]/4.2.3.4, 4.4.5, 4.4.9.4	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X	The trust center shall be able to ask a ZigBee router or the ZigBee coordinator to request that a child device leave the network.	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
ASLS15	Does the device support the origination of request-key commands?	[R1]/4.2.3.5, 4.4.6, 4.4.9.5	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes
ASLS16	Does the device support the receipt of request-key commands?	[R1]/4.2.3.5, 4.4.6, 4.4.9.5	SR1:M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ASLS17	Does the device support origination of switch-key commands?	[R1]/4.2.3.6, 4.4.7, 4.4.9.6	SR1:M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ASLS18	Does the device support receipt of switch-key commands?	[R1]/4.2.3.6, 4.4.7, 4.4.9.6	O	ZigBee	M		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
				ZigBee-PRO	M		Yes
ASLS19	Does the device support origination of tunnel commands?	[R1]/4.4.3.1, 4.4.9.8	SR1:M	ZigBee	MOO1: M MOO2: O	In ZigBee and ZigBee PRO Standard security, the ability to originate tunnel commands from the Trust Center is optional unless using link keys. In ZigBee PRO High Security, it is mandatory.	Click here to enter text.
				ZigBee-PRO	MOO1: M MOO2: O		Yes
ASLS20	Does the device support receipt of tunnel commands?	[R1]/4.4.3.1, 4.4.9.8	O	ZigBee	MOO2: FDT1: O FDT2: O FDT3: X	In ZigBee and ZigBee PRO Standard and High security, the ability for the coordinator and all routers to receive tunnel commands is mandatory.	Click here to enter text.
				ZigBee-PRO	MOO1: FDT1: M FDT2: M FDT3: X MOO2: FDT1: O FDT2: O FDT3: X		Yes
ASLS21	Does the device support the authentication service using the entity authentication protocol?	[R1]/4.2.3.7, 4.4.8, 4.4.9.7	O	ZigBee	MOO2: FDT1: O FDT2: O FDT3: X	In ZigBee and ZigBee PRO Standard security, the ability to support the authentication service using the entity authentication protocol is optional. In ZigBee PRO High Security, it is mandatory.	Click here to enter text.
				ZigBee-PRO	MOO1: FDT1: M FDT2: M FDT3: X MOO2: FDT1: O FDT2: O FDT3: X		No

1 **10.5.7 Application layer security**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ALS1	Is this device capable of learning and maintaining knowledge of its trust center using the <i>apsTrustCenterAddress</i> attribute in the AIB?	[R1]/4.4.10, 4.6.1	O	ZigBee	O	Trust Center must initially reside on the ZigBee coordinator but may, under application control, move to any router on the PAN as long as all devices in the PAN have their <i>apsTrustCenterAddress</i> attribute updated appropriately by the application.	Click here to enter text.
				ZigBee-PRO	M		Yes
ALS2	Is this device capable of following the “joining a secure network procedure” in the role of a router?	[R1]/4.6.3.1	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
ALS3	Is this device capable of following the “joining a secure network procedure” in the role of a joining device?	[R1]/4.6.3.1	O	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes
ALS4	Is this device capable of following the “authentication procedure” in the role of a trust center?	[R1]/4.6.3.2, 4.6.3.2.1	TCC1: O TCC2: O	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ALS5	Is this device capable of following the “authentication procedure” in the	[R1]/4.6.3.2, 4.6.3.2.1	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	role of a router?			ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
ALS6	Is this device capable of following the “authentication procedure” in the role of a joining device with a preconfigured network key?	[R1]/4.6.3.2, 4.6.3.2.3.1	O	ZigBee	O	For devices implementing ZigBee and ZigBee PRO Standard Security, following the “authentication procedure” in the role of joining device with a pre-configured network key is optional. For devices implementing ZigBee PRO High Security, it is prohibited.	Click here to enter text.
				ZigBee-PRO	O		Yes
ALS7	Is this device capable of following the “authentication procedure” in the role of a joining device with a preconfigured trust center link key?	[R1]/4.6.3.2, 4.6.3.2.3.2	O	ZigBee	O	For devices implementing ZigBee and ZigBee PRO Standard Security, following the “authentication procedure” in the role of joining device with a pre-configured trust center link key is optional. For devices implementing ZigBee PRO High Security, it is mandatory unless the ZigBee PRO High Security Trust Center policy permits in the clear delivery of the master key.	Click here to enter text.
				ZigBee-PRO	O		Yes
ALS8	Is this device capable of following the “authentication procedure” in the	[R1]/4.6.3.2, 4.6.3.2.3.3	O	ZigBee	O	For devices implementing ZigBee and ZigBee PRO Standard Security, following the	Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	role of a joining device without preconfigured network or trust center link keys?			ZigBee-PRO	O	“authentication procedure” in the role of joining device without a pre-configured trust center link key is optional and supported by default due to the requirement to permit ZigBee Residential Security Mode devices onto PRO Standard Security networks as end devices. For devices implementing ZigBee PRO High Security, it is optional and supported only if the ZigBee PRO High Security Trust Center policy permits in the clear delivery of the master key.	Yes
ALS9	Is this device capable of following the “network key update procedure” in the role of a trust center?	[R1]/4.6.3.4, 4.6.3.4.1	TCC1: O TCC2: O	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ALS10	Is this device capable of following the “network key update procedure” in the role of a network device?	[R1]/4.6.3.4, 4.6.3.4.2	O	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes
ALS11	Is this device capable of following the “network key recovery procedure” in the role of a trust center?		TCC1:O. 1 TCC2:O. 1	ZigBee	X	This item was deprecated.	Click here to enter text.
				ZigBee-PRO	X		No
ALS12	Is this device capable of following the “network key recovery procedure” in the role of a network device?		O	ZigBee	X	This item was deprecated.	Click here to enter text.
				ZigBee-PRO	X		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ALS13	Is this device capable of following the “end-to-end application key establishment procedure” in the role of a trust center?	[R1]/4.6.3.5, 4.6.3.5.2	TCC1: O TCC2: O	ZigBee	SR1: O	For ZigBee and ZigBee PRO Standard Security, it is optional for the trust center to perform the “end-to-end application key establishment” procedure. For ZigBee PRO High Security, it is mandatory.	Click here to enter text.
				ZigBee-PRO	SR1: O		No
ALS14	Is this device capable of following the “end-to-end application key establishment procedure” in the role of a device receiving a master key for use with the SKKE protocol?	[R1]/4.6.3.5, 4.6.3.5.1, 4.6.3.5.1.2	O	ZigBee	O	For ZigBee and ZigBee PRO Standard Security and ZigBee PRO High Security, it is optional for the network devices to perform the “end-to-end application key establishment” procedure.	Click here to enter text.
				ZigBee-PRO	O		No
ALS15	Is this device capable of following the “end-to-end application key establishment procedure” in the role of a device directly receiving a link key?	[R1]/4.6.3.5, 4.6.3.5.1, 4.6.3.5.1.1	O	ZigBee	O	For ZigBee and ZigBee PRO Standard Security and ZigBee PRO High Security, it is optional for the network devices to perform the “end-to-end application key establishment” procedure.	Click here to enter text.
				ZigBee-PRO	O		No
ALS16	Is this device capable of following the “network leave procedure” in the role of a trust center?	[R1]/4.6.3.6, 4.6.3.6.1	TCC1: O TCC2: O	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ALS17	Is this device capable of following the “network leave procedure” in the role of a router?	[R1]/4.6.3.6, 4.6.3.6.2	FDT1:O, FDT2:O, FDT3:X	ZigBee	FDT1: X FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: X		Yes
ALS18	Is this device capable of following the “network leave procedure” in the role of a leaving device?	[R1]/4.6.3.6, 4.6.3.6.3	O	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ALS19	Is this device capable of following the “intra-PAN portability procedure” in the role of a parent?	[R1]/4.6.3.3, 4.6.3.3.1	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
ALS20	Is this device capable of following the “intra-PAN portability procedure” in the role of an end device?	[R1]/4.6.3.3, 4.6.3.3.2	O	ZigBee	FDT1: X FDT2: X FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: M		Yes
ALS21	Is this device capable of following the “command tunneling procedure” in the role of a trust center device?	[R1]/4.6.3.8, 4.6.3.8.1	TCC1: O TCC2: O	ZigBee	SR1: O	For ZigBee PRO High Security, the command tunneling procedure in the role of a trust center device is mandatory. For ZigBee and ZigBee PRO Standard Security, it is optional.	Click here to enter text.
				ZigBee-PRO	SR1: O		Yes
ALS22	Is this device capable of following the “command tunneling procedure” in the role of a router?	[R1]/4.6.3.8, 4.6.3.8.2	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: O FDT2: O FDT3: X	For ZigBee PRO High Security, the command tunneling procedure in the role of a router device is mandatory. For ZigBee and ZigBee PRO Standard Security, it is optional.	Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X		Yes
ALS23	Does the device support the permissions configuration table?	[R1]/4.2.3.8, 4.6.3.8	O	ZigBee	O	The Permissions Configuration Table is optional for all devices.	Click here to enter text.
				ZigBee-PRO	O		No

1 **10.6 Application layer PICS**2 **10.6.1 ZigBee security device types**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
SDT1	Is this device capable of acting as a ZigBee Trust Center?	[R1]/4.2.4, 4.6.2	O.2	ZigBee	FDT1: M FDT2: O FDT3: X	This item was deprecated in favor of SR1.	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: O FDT3: X		Yes
SDT2	Is this device capable of joining a secure ZigBee network only as a device?	[R1]/4.6.3	O.2	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes

3

4 **10.6.2 ZigBee APS frame format**

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AFF1	Does the device support the general ZigBee APS frame format?	[R1]/2.2.5.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
AFF2	Does the device support the ZigBee APS data frame format?	[R1]/2.2.5.2.1	M	ZigBee	M		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
				ZigBee-PRO	M		Yes
AFF3	Does the device support the ZigBee APS command frame format?	[R1]/2.2.5.2.2, 2.2.6	O	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
AFF4	Does the device support the ZigBee APS acknowledgement frame format?	[R1]/2.2.5.2.3	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

1

2 10.6.3 Major capabilities of the ZigBee application layer

3 *Tables in the following subclauses detail the capabilities of the APL layer for ZigBee devices.*

4 10.6.3.1 Application layer functions

5 10.6.3.1.1 Application Support Sub-layer functions

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ALF1	Does the application support sub-layer support transmission of data by the next higher layer?	[R1]/2.2.4.1.1, 2.2.4.1.2	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
ALF200	Does the device support transmission of outgoing APS frames within	[R1]/2.2.4.1.1	O	ZigBee	X	This must be handled by the application.	Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	APSD with the DstAddrMode set to 0x00 (indirect)			ZigBee-PRO	X		Yes
ALF201	Does the device support transmission of outgoing APS frames within APSDE with the DstAddrMode set to 0x01 (group addressed)	[R1]/2.2.4.1.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
ALF202	Does the device support transmission of outgoing APS frames within APSDE with the DstAddrMode set to 0x02 (unicast using NWK address and Destination Endpoint)	[R1]/2.2.4.1.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
ALF203	Does the device support transmission of outgoing APS frames within APSDE with the DstAddrMode set to 0x03 (unicast using IEEE address and Destination Endpoint)	[R1]/2.2.4.1.1	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes
ALF2	Does the application support sub-layer support reception of data by the next higher layer at the endpoint supplied by the incoming packet?	[R1]/2.2.4.1.3	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
ALF300	Does the device support reception of incoming APS frames within APSDE with the DstAddrMode set to 0x00 (indirect)	[R1]/2.2.4.1.3	O	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ALF301	Does the device support reception of incoming APS frames within APSDE with the DstAddrMode set to 0x01 (group addressed)	[R1]/2.2.4.1.3	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
ALF302	Does the device support reception of incoming APS frames within APSDE with the DstAddrMode set to 0x02 (unicast using NWK address and Destination Endpoint)	[R1]/2.2.4.1.3	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
ALF3	Does the application support sub-layer support BIND and UNBIND requests and confirms?	[R1]/2.2.4.3.1, 2.2.4.3.2, 2.2.4.3.3, 2.2.4.3.4	O	ZigBee	O	Binding support is optional for all devices, except that: <ul style="list-style-type: none"> Source binding only is supported (coordinator based binding is disallowed) All devices shall minimally respond with NOT_IMPLEMENTED The ZigBee Coordinator shall implement the mechanism for matching end device bind requests (AZD24; FDT1: M).	Click here to enter text.
				ZigBee-PRO	O		Yes
ALF4	Does the device's application support sub-layer offer the next higher layer the ability to get application information base (AIB) attributes.	[R1]/2.2.4.4.1, 2.2.4.4.2	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
ALF5	Does the device's application support sub-layer offer the next higher layer the	[R1]/2.2.4.4.3, 2.2.4.4.4	M	ZigBee	M		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	ability to set application information base (AIB) attributes.			ZigBee-PRO	M		Yes
ALF100	Does the application support sub-layer support ADD GROUP requests and confirms?	[R1]/2.2.4.5.1, 2.2.4.5.2	M	ZigBee	O	If supported, the group table in the APS shall contain a minimum of 16 group addresses.	Click here to enter text.
				ZigBee-PRO	O		Yes
ALF101	Does the application support sub-layer support REMOVE GROUP requests and confirms?	[R1]/2.2.4.5.3, 2.2.4.5.4	M	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes
ALF102	Does the application support sub-layer support REMOVE ALL GROUPS requests and confirms?	[R1]/2.2.4.5.5, 2.2.4.5.6	M	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes

1

2 10.6.3.1.2 Application layer frames

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ADF1	Does the device support the origination of application data frames.	[R1]/2.2.5.1, 2.2.5.2.1, 2.2.8.4.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ADF2	Does the device support the receipt of application data frames.	[R1]/2.2.5.1 2.2.5.2.1, 2.2.8.3.2, 2.2.8.3.3	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
ADF3	Does the device support the origination of application data frames with the auxiliary APS security header?	[R1]/ 2.2.5.1, 2.2.5.2.1, 2.2.8.4.1, 4.4.1.1	O	ZigBee	O	Use of the auxiliary APS security header is optional for all devices. The application profiles shall determine requirements for use of the auxiliary APS security header.	Click here to enter text.
				ZigBee-PRO	O		Yes
ADF4	Does the device support the receipt of application data frames with the auxiliary APS security header?	[R1]/ 2.2.5.1 2.2.5.2.1, 2.2.8.3.2, 2.2.8.3.3, 4.4.1.2	O	ZigBee	O	Use of the auxiliary APS security header is optional for all devices. The application profiles shall determine requirements for use of the auxiliary APS security header.	Click here to enter text.
				ZigBee-PRO	O		Yes
ADF5	Does the device support the origination of application data frames with the extended APS fragmentation/re-assembly header?	[R1]/ 2.2.5.1, 2.2.5.2.1, 2.2.8.4.1, 2.2.5.1.8, 2.2.8.4.5.1	O	ZigBee	O	Use of the extended APS fragmentation/re-assembly header is optional, but in all cases the parameters shall be set by agreement within specific application profiles. Devices using the ZigBee and ZigBee-PRO feature sets shall set: <i>Config_Max_ZDO-Payload = 0</i> (i.e. for compatibility with the earlier ZigBee feature set, ZDO messages shall not be fragmented)	Click here to enter text.
				ZigBee-PRO	O		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ADF6	Does the device support the receipt of application data frames with the extended APS fragmentation/re-assembly header?	[R1]/ 2.2.5.1 2.2.5.2.1, 2.2.8.3.2, 2.2.8.3.3, 2.2.5.1.8, 2.2.8.4.5.2	O	ZigBee	O	Use of the extended APS fragmentation/re-assembly header is optional, but in all cases the parameters shall be set by agreement within specific application profiles. Devices using the ZigBee and ZigBee-PRO feature sets shall set: <i>Config_Max_ZDO-Payload = 0</i> (i.e. for compatibility with the earlier ZigBee feature set, ZDO messages shall not be fragmented)	Click here to enter text.
				ZigBee-PRO	O		Yes

1 10.6.3.1.3 Application layer command frames

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ACF500	Does the device support the origination of command frames with the auxiliary APS security header?	[R1]/ 2.2.5.1, 2.2.5.2.2, 2.2.6, 4.4.1.1	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes
ACF501	Does the device support the receipt of command frames with the auxiliary APS security header?	[R1]/ 2.2.5.1 2.2.5.2.1, 2.2.6, 2.2.8.3.3, 4.4.1.2	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ACF1	Does the device support the origination of application command frames from the Trust Center.	[R1]/4.4.9, 4.6.2, 4.6.3.2, 4.6.3.3, 4.6.3.4, 4.6.3.5, 4.6.3.6, 4.6.3.7	SDT1: M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ACF100	Does the device support the origination of Key Establishment application command frames from the Trust Center?	[R1]/4.4.9.1	SDT1:M	ZigBee	SR1: O	In ZigBee and ZigBee PRO Standard Security Mode, it is optional to originate Key Establishment command frames from the Trust Center. In ZigBee PRO High Security, it is mandatory.	Click here to enter text.
				ZigBee-PRO	SR1: O		No
ACF101	Does the device support the origination of Transport Key application command frames from the Trust Center?	[R1]/4.4.9.2	SDT1:M	ZigBee	SR1: M	In ZigBee and ZigBee PRO Standard Security Mode, it is mandatory to originate Transport Key command frames from the Trust Center for Key Type 1 (Network Key Standard Mode). In ZigBee PRO High Security Mode, it is mandatory to originate Transport Key command frames from the Trust Center for Key Type 0 (Trust Center Master Key) and Key Type 5 (Network Key High Security Mode). It is optional in either ZigBee and ZigBee PRO Standard Security or High Security to originate Transport Key command frames for Key Types 4 (Trust Center Link Key), Key Type 2 (Application Master Key) and Key Type 3 (Application Link Key).	Click here to enter text.
				ZigBee-PRO	SR1: M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ACF102	Does the device support the origination of Remove Device application command frames from the Trust Center?	[R1]/4.4.9.4	SDT1:M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ACF103	Does the device support the origination of Switch Key application command frames from the Trust Center?	[R1]/4.4.9.6	SDT1:M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ACF104	Does the device support the origination of entity authentication application command frames?	[R1]/4.4.9.7	SDT1:M	ZigBee	SR1: O		Click here to enter text.
				ZigBee-PRO	MOO2: O MOO1: M		No
ACF2	Does the device support the receipt of application command frames at the Trust Center	[R1]/4.4.9, 4.6.2, 4.6.3.2, 4.6.3.3, 4.6.3.4, 4.6.3.5, 4.6.3.6, 4.6.3.7	SDT1:M	ZigBee	SR1: M	Mandatory for the trust centre and optional for other devices.	Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ACF200	Does the device support the receipt of Key Establishment application command frames at the Trust Center?	[R1]/4.4.9.1	SDT1:M	ZigBee	SR1: O	In ZigBee and ZigBee PRO Standard Security Mode, it is optional to receive Key Establishment command frames from the Trust Center. In ZigBee PRO High Security, it is mandatory.	Click here to enter text.
				ZigBee-PRO	SR1: O		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ACF201	Does the device support the receipt of Transport Key application command frames at the Trust Center?	[R1]/4.4.9.2	SDT1:M	ZigBee	SR1: M	In ZigBee and ZigBee PRO Standard Security Mode, it is mandatory to receive Transport Key command frames from the Trust Center for Key Type 1 (Network Key Standard Mode). In ZigBee PRO High Security Mode, it is mandatory to receive Transport Key command frames from the Trust Center for Key Type 0 (Trust Center Master Key) and Key Type 5 (Network Key High Security Mode). It is optional in ZigBee and ZigBee PRO Standard Security to receive Transport Key command frames for Key Types 4 (Trust Center Link Key), Key Type 2 (Application Master Key) and Key Type 3 (Application Link Key). It is prohibited in ZigBee PRO High Security to receive Transport Key command frames for Key Types 4 (Trust Center Link Key) and optional to receive Transport Key command frames for Key Type 2 (Application Master Key) and Key Type 3 (Application Link Key).	Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ACF202	Does the device support the receipt of Update Device application command frames at the Trust Center?	[R1]/4.4.9.3	SDT1:M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ACF203	Does the device support the receipt of Request Key application command frames at the Trust Center?	[R1]/4.4.9.5	SDT1:M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ACF204	Does the device support the receipt of entity authentication application command frames?	[R1]/4.4.9.7	SDT1:M	ZigBee	X		Click here to enter text.
				ZigBee-PRO	MOO1: M MOO2: O		No
ACF3	Does the device support the origination of application command frames from a non-Trust Center device.	[R1]/4.4.9, 4.6.3	SDT2:M	ZigBee	FDT1: X FDT2: M FDT3: O	In ZigBee and ZigBee PRO Standard Security, non Trust Center devices may optionally originate application command frames. In ZigBee PRO High Security, all non Trust Center routers and the coordinator shall originate application command frames and end devices may originate application command frames.	Click here to enter text.
				ZigBee-PRO	MOO1: FDT1: X FDT2: M FDT3: M MOO2: FDT1: X FDT2: M FDT3: O		Yes
ACF300	Does the device support the origination of Key Establishment application command frames from a non-Trust Center device?	[R1]/4.4.9.1, 4.6.3.5	SDT2:M	ZigBee	O	In ZigBee and ZigBee PRO Standard Security, it is optional for all devices to support origination of Key Establishment command frames from a non Trust Center device. In ZigBee PRO High Security, it is mandatory for all devices to support origination of Key Establishment command frames from a non Trust Center device.	Click here to enter text.
				ZigBee-PRO	O		No
ACF301	Does the device support the origination of Transport Key application command frames from a non-Trust Center device?	[R1]/4.4.9.2	SDT2:M	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		No
ACF302	Does the device support the origination of Update Device application command frames from a non-Trust Center device?	[R1]/4.4.9.3, 4.6.3.4	SDT2:M	ZigBee	FDT1: M FDT2: M FDT3: O	Assumes it is legal to have the Trust Center on a non-ZigBee Coordinator device for the ZigBee feature set via ZigBee-2007	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: O		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ACF303	Does the device support the origination of Request Key application command frames from a non-Trust Center device?	[R1]/4.4.9.5	SDT2:M	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes
ACF304	Does the device support the origination of Authenticate application command frames from a non-Trust Center device?	[R1]/4.4.9.7, 4.6.3.2	SDT2:M	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		No
ACF4	Does the device support the receipt of application command frames from a non-Trust Center device.	[R1]/4.4.9, 4.6.3	SDT1:M, SDT2:M	ZigBee	SR1: FDT1: M FDT2: M FDT3: O	In all ZigBee and ZigBee PRO security modes, the Trust Center shall receive application command frames from non Trust Center devices. In ZigBee and ZigBee PRO Standard Security, all non Trust Center routers and the coordinator shall receive application command frames. In ZigBee PRO High Security, all non Trust Center devices shall receive application command frames.	Click here to enter text.
				ZigBee-PRO	SR1: FDT1: M FDT2: M FDT3: O		Yes
ACF400	Does the device support the receipt of Key Establishment application command frames from a non-Trust Center device?	[R1]/4.4.9.1, 4.6.3.5	SDT1:M, SDT2:M	ZigBee	O	For all devices in ZigBee PRO Standard Security, receipt of Key Establishment application command frames from a non Trust Center device is optional. In ZigBee PRO High Security, receipt of Key Establishment application command frames from non Trust Center devices is mandatory in all devices.	Click here to enter text.
				ZigBee-PRO	O		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
ACF401	Does the device support the receipt of Transport Key application command frames from a non-Trust Center device?	[R1]/4.4.9.2	SDT1:M, SDT2:M	ZigBee	SR1: M SDT2: M		Click here to enter text.
				ZigBee-PRO	SR1: M SDT2: M		Yes
ACF402	Does the device support the receipt of Update Device application command frames from a non-Trust Center device?	[R1]/4.4.9.3, 4.6.3.4	SDT1:M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ACF403	Does the device support the receipt of Request Key application command frames from a non-Trust Center device?	[R1]/4.4.9.5	SDT1:M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
ACF404	Does the device support the receipt of entity authenticate application command frames from a non-Trust Center device?	[R1]/4.4.9.7, 4.6.3.2	SDT1:M SDT2:M	ZigBee	O	Need a comment that this feature is optional in ZigBee and ZigBee PRO Standard Security and mandatory for all devices in ZigBee PRO High Security.	Click here to enter text.
				ZigBee-PRO	O		No
ACF405 ¹¹	Does the device support the receipt of a Transport Key message APS encrypted with the default TC link key?	[R1]/4.2.1.3	FDT1: X FDT2: M FDT3: M	ZigBee	X		Click here to enter text.
				ZigBee-PRO	SDT1:X SDT2:M		Yes

¹¹ CCB 1039

1

ACF406 ¹²	Does the device support the transmission of a Transport Key message APS encrypted with the default TC link key?	[R1]/4.2.1.3	FDT1:M FDT2:X FDT3:X	ZigBee	X		Click here to enter text.
				ZigBee-PRO	SDT1:M SDT2:X		Yes

2

10.6.3.1.4 Application acknowledgement frames

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AFR1	Does the device support the origination of application acknowledgement frames.	[R1]/2.2.8.3.1, 2.2.8.3.3	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
AFR2	Does the device support the receipt of application acknowledgement frames?	[R1]/2.2.8.3.2, 2.2.8.3.3	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

3

10.6.3.1.5 ZigBee Device Objects functions

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD700	Does the device support the permissions configuration table?	[R1]/4.6.3.8	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		No

¹² CCB 1039

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD701	Does the device support the ModifyPermissionsCapabilityTable element of the permissions configuration table?	[R1]/4.6.3.8	AZD700: O	ZigBee	AZD700: O		Click here to enter text.
				ZigBee-PRO	AZD700: O		No
AZD702	Does the device support the NetworkSettings element of the permissions configuration table?	[R1]/4.6.3.8	AZD700: O	ZigBee	AZD700: O		Click here to enter text.
				ZigBee-PRO	AZD700: O		No
AZD703	Does the device support the Application-Settings element of the permissions configuration table?	[R1]/4.6.3.8	AZD700: O	ZigBee	AZD700: O		Click here to enter text.
				ZigBee-PRO	AZD700: O		No
AZD704	Does the device support the SecuritySettings element of the permissions configuration table?	[R1]/4.6.3.8	AZD700: O	ZigBee	AZD700: O		Click here to enter text.
				ZigBee-PRO	AZD700: O		No
AZD705	Does the device support the Application-Commands element of the permissions configuration table?	[R1]/4.6.3.8	AZD700: O	ZigBee	AZD700: O		Click here to enter text.
				ZigBee-PRO	AZD700: O		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD706	Does the device support the SKKEWith-MasterKey element of the permissions configuration table?	[R1]/4.6.3.8	AZD700: O	ZigBee	AZD700: O		Click here to enter text.
				ZigBee-PRO	AZD700: O		No
AZD707	Does the device support the NWK rejoin procedure?	[R1]/3.6.1.4.2	M	ZigBee	M	Support of the rejoin mechanism for recovering from a missed network update (of any kind) is mandatory ([R1] Section 2.5.5.5.4). The length of time between hearing from its parent, or from the ZigBee coordinator, beyond which a ZigBee router shall initiate steps to rejoin the "fragment" of the network which has the ZigBee coordinator in it, is left up to the application designer.	Click here to enter text.
				ZigBee-PRO	M		Yes
AZD600	Does the device act as a Binding Table Cache?	[R1]/2.5.5.5.3	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: O FDT2: O FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X		No
AZD601	Does the device perform the Intra-PAN portability parent procedure?	[R1]/2.5.5.5.4	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
AZD602	Does the device perform the Intra-PAN portability child procedure?	[R1]/2.5.5.5.4	FDT1: X FDT2: X FDT3: M	ZigBee	FDT1: X FDT2: X FDT3: M		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
				ZigBee-PRO	FDT1: X FDT2: X FDT3: M		Yes
AZD603	Does the device support the Configuration Parameters, Startup Procedures and Additional Configuration Parameters?	[R1]/2.5.5.5.6.1, 2.5.5.5.6.2, 2.5.5.5.6.3	O	ZigBee	O	For the ChannelMask parameter, in the 2.4 Ghz band, channel 26 shall either not be used or else a special provision for limited transmission power shall be imposed to permit U.S. FCC operations.	Click here to enter text.
				ZigBee-PRO	M		Yes
AZD1	Does the device support the mandatory Device and Service Discovery Object?	[R1]/2.5.5.6.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
AZD2	Does the device support the mandatory attributes of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
AZD3	Does the device support the optional attributes of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes
AZD4	Does the device support the optional NWK address client service of the	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
	Device and Service Discovery Object?			ZigBee-PRO	AZD3: O		Yes
AZD5	Does the device support the optional IEEE address client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		Yes
AZD6	Does the device support the optional Node Descriptor client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		Yes
AZD7	Does the device support the optional Power Descriptor client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		Yes
AZD8	Does the device support the optional Simple Descriptor client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		Yes
AZD9	Does the device support the optional Active Endpoint client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD10	Does the device support the optional Match Descriptor client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		Yes
AZD11	Does the device support the optional Complex Descriptor client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No
AZD12	Does the device support the optional Complex Descriptor server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No
AZD13	Does the device support the optional User Descriptor client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		Yes
AZD14	Does the device support the optional User Descriptor server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD17	Does the device support the mandatory Device Announce client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD1: M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
AZD18	Does the device support the Device Announce server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD1: M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
AZD100	Does the device support the optional System Server Discovery client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		Yes
AZD101	Does the device support the optional System Server Discovery server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
AZD102	Does the device support the optional Discovery Cache client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD103	Does the device support the optional Discovery Cache server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: FDT1: O FDT2: O FDT3: X		Click here to enter text.
				ZigBee-PRO	AZD3: FDT1: O FDT2: O FDT3: X		No
AZD104	Does the device support the optional Discovery Store client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No
AZD105	Does the device support the optional Discovery Store server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD103: M	ZigBee	AZD103: M		Click here to enter text.
				ZigBee-PRO	AZD103: M		No
AZD106	Does the device support the optional Node Descriptor Store client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No
AZD107	Does the device support the optional Node Descriptor Store server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD103: M	ZigBee	AZD103: M		Click here to enter text.
				ZigBee-PRO	AZD103: M		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD108	Does the device support the optional Power Descriptor Store client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No
AZD109	Does the device support the optional Power Descriptor Store server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD103: M	ZigBee	AZD103: M		Click here to enter text.
				ZigBee-PRO	AZD103: M		No
AZD110	Does the device support the optional Active Endpoint Store client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No
AZD111	Does the device support the optional Active Endpoint Store server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD103: M	ZigBee	AZD103: M		Click here to enter text.
				ZigBee-PRO	AZD103: M		No
AZD112	Does the device support the optional Simple Descriptor Store client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD113	Does the device support the optional Simple Descriptor Store server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD103: M	ZigBee	AZD103: M		Click here to enter text.
				ZigBee-PRO	AZD103: M		No
AZD114	Does the device support the optional Remove Node Cache client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No
AZD115	Does the device support the optional Remove Node Cache server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD103: M	ZigBee	AZD103: M		Click here to enter text.
				ZigBee-PRO	AZD103: M		No
AZD116	Does the device support the optional Find Node Cache client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No
AZD117	Does the device support the optional Find Node Cache server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD103: M	ZigBee	AZD103: M		Click here to enter text.
				ZigBee-PRO	AZD103: M		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD650	Does the device support the optional Extended Simple Descriptor client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No
AZD651	Does the device support the optional Extended Simple Descriptor server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD103: M	ZigBee	AZD103: M		Click here to enter text.
				ZigBee-PRO	AZD103: M		No
AZD652	Does the device support the optional Extended Active Endpoint client service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD3: O	ZigBee	AZD3: O		Click here to enter text.
				ZigBee-PRO	AZD3: O		No
AZD653	Does the device support the optional Extended Active Endpoint server service of the Device and Service Discovery Object?	[R1]/2.5.5.6.1	AZD103: M	ZigBee	AZD103: M		Click here to enter text.
				ZigBee-PRO	AZD103: M		No
AZD19	Does the device support the optional Security Manager Object?	[R1]/2.5.5.7.1	O	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD20	Does the device support the mandatory attributes of the Security Manager Object with the device in a Trust Center role?	[R1]/2.5.5.7.1	AZD19: SDT1: M	ZigBee	SR1: M		Click here to enter text.
				ZigBee-PRO	SR1: M		Yes
AZD21	Does the device support the mandatory attributes of the Security Manager Object with the device in a non-Trust Center role?	[R1]/2.5.5.7.1	AZD19: SDT2: M	ZigBee	SDT2: M		Click here to enter text.
				ZigBee-PRO	SDT2: M		Yes
AZD22	Does the device support the optional Binding Manager Object?	[R1]/2.5.5.8.1	O	ZigBee	FDT1: M FDT2: O FDT3: O	End_Device_Bind_req server processing in the coordinator is required. The ZigBee coordinator must process end device bind requests and supply Bind_req commands to the source of matched clusters in the paired end device bind requests.	Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: O FDT3: O		Yes
AZD23	Does the device support the optional End Device Bind client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.1	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		Yes
AZD24	Does the device support the optional End Device Bind server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.1	AZD22: FDT1: M FDT2: X FDT3: X	ZigBee	AZD22: FDT1: M FDT2: X FDT3: X		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: M FDT2: X FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD25	Does the device support the optional Bind client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.2	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		Yes
AZD26	Does the device support the optional Bind server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.2	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		Yes
AZD27	Does the device support the optional Unbind client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.3	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		Yes
AZD28	Does the device support the optional Unbind server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.3	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		Yes
AZD200	Does the device support the optional Bind Register client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.4	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD201	Does the device support the optional Bind Register server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.4	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD202	Does the device support the optional Replace Device client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.5	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD203	Does the device support the optional Replace Device server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.5	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD204	Does the device support the optional Store Backup Bind Entry client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.6	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD205	Does the device support the optional Store Backup Bind Entry server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.6	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD206	Does the device support the optional Remove Backup Bind Entry client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.7	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD207	Does the device support the optional Remove Backup Bind Entry server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.7	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD208	Does the device support the optional Backup Bind Table client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.8	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD209	Does the device support the optional Backup Bind Table server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.8	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD210	Does the device support the optional Recover Bind Table client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.9	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD211	Does the device support the optional Recover Bind Table server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.9	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD212	Does the device support the optional Backup Source Bind client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.1 0	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD213	Does the device support the optional Backup Source Bind server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.1 0	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD214	Does the device support the optional Recover Source Bind client service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.3.2.1 1	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No
AZD215	Does the device support the optional Recover Source Bind server service of the Binding Manager Object?	[R1]/2.5.5.8.1 [R1]/2.4.4.2.1 1	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD29	Does the device support the optional APSME BIND and UNBIND service of the Binding Manager Object?	[R1]/2.5.5.8.1	AZD22: FDT1: O FDT2: O FDT3: O	ZigBee	AZD22: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD22: FDT1: O FDT2: O FDT3: O		Yes
AZD30	Does the device support the mandatory NLME GET, SET and NETWORK DISCOVERY services of the Network Manager Object?	[R1]/2.5.5.9.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
AZD31	Does the device support the optional NLME NETWORK FORMATION service of the Network Manager Object?	[R1]/2.5.5.9.1	FDT1: M FDT2: X FDT3: X	ZigBee	FDT1: M FDT2: X FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: X FDT3: X		Yes
AZD32	Does the device support the optional NLME JOIN service of the Network Manager Object?	[R1]/2.5.5.9.1	FDT1: X FDT2: M FDT3: M	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes
AZD300	Does the device support the optional NLME START ROUTER service of the Network Manager Object?	[R1]/2.5.5.9.1	FDT1: X FDT2: M FDT3: X	ZigBee	FDT1: X FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD33	Does the device support the mandatory NLME LEAVE service of the Network Manager Object?	[R1]/2.5.5.9.1	FDT1: X FDT2: M FDT3: M	ZigBee	FDT1: X FDT2: M FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: M FDT3: M		Yes
AZD301	Does the device support the optional NLME PERMIT JOINING service of the Network Manager Object?	[R1]/2.5.5.9.1	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
AZD34	Does the device support the optional NLME RESET service of the Network Manager Object?	[R1]/2.5.5.9.1	FDT1: O FDT2: O FDT3: O	ZigBee	FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: O		Yes
AZD35	Does the device support the optional NLME SYNC service of the Network Manager Object?	[R1]/2.5.5.9.1	FDT1: O FDT2: O FDT3: O	ZigBee	FDT1: X FDT2: X FDT3: M	See clause 8.4.2.1 in this document, Network layer functions, Item number NLF17.	Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: M		Yes
AZD302	Does the device support the mandatory NLME NWK_STATUS service of the Network Manager Object?	[R1]/2.5.5.9.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD303	Does the device support the optional NLME ROUTE DISCOVERY service of the Network Manager Object?	[R1]/2.5.5.9.1	FDT1: O FDT2: O FDT3: O	ZigBee	FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: O		Yes
AZD36	Does the device support the optional Node Manager Object?	[R1]/2.5.5.10.1	FDT1: O FDT2: O FDT3: O	ZigBee	FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: O		Yes
AZD37	Does the device support the optional Node Manager NWK Discovery client service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		Yes
AZD38	Does the device support the optional Node Manager NWK Discovery server service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: M FDT2: M FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: M FDT2: M FDT3: O		Yes
AZD39	Does the device support the optional Node Manager LQI client service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD40	Does the device support the optional Node Manager LQI server service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: M FDT2: M FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: M FDT2: M FDT3: O		Yes
AZD41	Does the device support the optional Node Manager RTG client service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		No
AZD42	Does the device support the optional Node Manager RTG server service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: M FDT2: M FDT3: O		No
AZD43	Does the device support the optional Node Manager Bind client service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		Yes
AZD44	Does the device support the optional Node Manager Bind server service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD45	Does the device support the optional Node Manager Leave client service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		Yes
AZD46	Does the device support the optional Node Manager Leave server service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: M FDT2: M FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: M FDT2: M FDT3: O		Yes
AZD47	Does the device support the optional Node Manager Direct Join client service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		Yes
AZD48	Does the device support the optional Node Manager Direct Join server service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	X		Click here to enter text.
				ZigBee-PRO	X		No
AZD400	Does the device support the optional Node Manager Permit Joining client service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: M FDT2: M FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD401	Does the device support the optional Node Manager Discovery Cache client service?	[R1]/2.5.5.10.1	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		No
AZD402	Does the device support the optional Node Manager Discovery Cache server service?	[R1]/2.5.5.10.2	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		No
AZD800	Does the device support the optional Node Manager NWK update client service?	[R1]/2.4.3.3.9	AZD36: FDT1: O FDT2: O FDT3: X	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O	The ability to send the Mgmt_NWK_Update_req command in order to request the target to perform an energy scan is mandatory for the Network Channel Manager, and optional for all non Network Channel Manager routers and the coordinator.	Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		Yes
AZD801	Does the device support the optional Node Manager NWK update server service?	[R1]/2.4.4.3.9	AZD36: FDT1: O FDT2: O FDT3: O	ZigBee	AZD36: FDT1: O FDT2: O FDT3: O	The ability for a non Network Channel Manager to receive and process the Mgmt_NWK_Update_req command is mandatory for the network manager and all routers and optional for end devices.	Click here to enter text.
				ZigBee-PRO	AZD36: FDT1: O FDT2: O FDT3: O		Yes
AZD49	Does the device support the mandatory Configuration Attributes?	[R1]/2.5.6	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD50	Does the device support the optional Complex Descriptor configuration attribute?	[R1]/2.5.6	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		No
AZD51	Does the device support the optional User Descriptor configuration attribute?	[R1]/2.5.6	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		No
AZD52	Does the device support the optional Max Bind configuration attribute?	[R1]/2.5.6	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		No
AZD53	Does the device support the optional Master Key configuration attribute?	[R1]/2.5.6	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		No
AZD54	Does the device support the optional End Device Bind Timeout configuration attribute?	[R1]/2.5.6	FDT1: M FDT2: X FDT3: X	ZigBee	FDT1: M FDT2: X FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: X FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD55	Does the device support the optional Permit Join Duration configuration attribute?	[R1]/2.5.6	FDT1: M FDT2: M FDT3: X	ZigBee	FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: M FDT2: M FDT3: X		Yes
AZD56	Does the device support the optional NWK Security Level configuration attribute?	[R1]/2.5.6	AZD19: O	ZigBee	AZD19: O		Click here to enter text.
				ZigBee-PRO	AZD19: O		No
AZD57	Does the device support the optional NWK Secure All Frames configuration attribute?	[R1]/2.5.6	AZD19: O	ZigBee	AZD19: O		Click here to enter text.
				ZigBee-PRO	AZD19: O		Yes
AZD500	Does the device support the optional NWK Leave Remove Children configuration attribute?	[R1]/2.5.6	AZD19: FDT1: M FDT2: M FDT3: X	ZigBee	AZD19: FDT1: M FDT2: M FDT3: X		Click here to enter text.
				ZigBee-PRO	AZD19: FDT1: M FDT2: M FDT3: X		Yes
AZD501	Does the device support the optional NWK Broadcast Delivery configuration attribute?	[R1]/2.5.6	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: O FDT2: O FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD502	Does the device support the optional NWK Transaction Persistence Time configuration attribute?	[R1]/2.5.6	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: O FDT2: O FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X		No
AZD503	Does the device support the optional NWK Indirect Poll Rate configuration attribute?	[R1]/2.5.6	FDT1: X FDT2: X FDT3: M	ZigBee	FDT1: X FDT2: X FDT3: M		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: X FDT3: M		Yes
AZD504	Does the device support the optional Max Associations configuration attribute?	[R1]/2.5.6	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: O FDT2: O FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X		No
AZD505	Does the device support the optional NWK Direct Join Addresses configuration attribute?	[R1]/2.5.6	FDT1: O FDT2: O FDT3: X	ZigBee	FDT1: O FDT2: O FDT3: X		Click here to enter text.
				ZigBee-PRO	FDT1: O FDT2: O FDT3: X		No
AZD506	Does the device support the optional Parent Link Retry Threshold configuration attribute?	[R1]/2.5.6	FDT1: X FDT2: O FDT3: O	ZigBee	FDT1: X FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: O FDT3: O		No

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AZD507	Does the device support the optional Orphan Rejoin Interval configuration attribute?	[R1]/2.5.6	FDT1: X FDT2: O FDT3: O	ZigBee	FDT1: X FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: O FDT3: O		No
AZD508	Does the device support the optional Max Orphan Rejoin Interval configuration attribute?	[R1]/2.5.6	FDT1: X FDT2: O FDT3: O	ZigBee	FDT1: X FDT2: O FDT3: O		Click here to enter text.
				ZigBee-PRO	FDT1: X FDT2: O FDT3: O		No

1 10.6.3.1.6 ZigBee Application Framework functions

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AAF2	Does the device support the mandatory ZigBee Descriptor structures?	[R1]/2.3.2	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes
AAF3	Does the device support the optional ZigBee Complex Descriptor structure?	[R1]/2.3.2	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		No
AAF4	Does the device support the optional ZigBee User Descriptor structure?	[R1]/2.3.2	O	ZigBee	O		Click here to enter text.
				ZigBee-PRO	O		Yes

Item number	Item description	Reference	ZigBee Status	Feature set Support		Additional Constraints	Platform Support
AAF5	Does the device support the transmission of descriptors?	[R1]/2.3.2.1	M	ZigBee	M		Click here to enter text.
				ZigBee-PRO	M		Yes

1