



ZigBee[®]

Control your world

ZigBee Cluster Library Identify Cluster (0x0003) Test Specification Version 1.0

ZigBee Document 15-0304-05

April 18th, 2016

Sponsored by: ZigBee Alliance

Accepted by This document has been accepted for release by the ZigBee Alliance Board of Directors

Abstract This document describes the certification tests for devices which implement the ZCL Identify cluster.

Keywords ZCL, Identify, cluster

Copyright © ZigBee Alliance, Inc. (1996-2016). All rights reserved.

508 Second Street, Suite 206 Davis, CA 95616 - USA

<http://www.zigbee.org>

Permission is granted to members of the ZigBee Alliance to reproduce this document for their own use or the use of other ZigBee Alliance members only, provided this notice is included. All other rights reserved. Duplication for sale, or for commercial or for-profit use is strictly prohibited without the prior written consent of the ZigBee Alliance.

1

2

This page is intentionally blank

3 **Notice of use and disclosure**

4 Copyright © ZigBee Alliance, Inc. (1996-2016). All rights Reserved. This
5 information within this document is the property of the ZigBee Alliance and its use
6 and disclosure are restricted.

7 Elements of ZigBee Alliance specifications may be subject to third party intellectual
8 property rights, including without limitation, patent, copyright or trademark rights
9 (such a third party may or may not be a member of ZigBee). ZigBee is not responsible
10 and shall not be held responsible in any manner for identifying or failing to identify
11 any or all such third party intellectual property rights.

12 No right to use any ZigBee name, logo or trademark is conferred herein. Use of any
13 ZigBee name, logo or trademark requires membership in the ZigBee Alliance and
14 compliance with the ZigBee Logo and Trademark Policy and related ZigBee policies.

15 This document and the information contained herein are provided on an “AS IS” basis
16 and ZigBee DISCLAIMS ALL WARRANTIES EXPRESS OR IMPLIED,
17 INCLUDING BUT NOT LIMITED TO (A) ANY WARRANTY THAT THE USE
18 OF THE INFORMATION HEREIN WILL NOT INFRINGE ANY RIGHTS OF
19 THIRD PARTIES (INCLUDING WITHOUT LIMITATION ANY
20 INTELLECTUAL PROPERTY RIGHTS INCLUDING PATENT, COPYRIGHT OR
21 TRADEMARK RIGHTS) OR (B) ANY IMPLIED WARRANTIES OF
22 MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, TITLE OR
23 NONINFRINGEMENT. IN NO EVENT WILL ZIGBEE BE LIABLE FOR ANY
24 LOSS OF PROFITS, LOSS OF BUSINESS, LOSS OF USE OF DATA,
25 INTERRUPTION OF BUSINESS, OR FOR ANY OTHER DIRECT, INDIRECT,
26 SPECIAL OR EXEMPLARY, INCIDENTAL, PUNITIVE OR CONSEQUENTIAL
27 DAMAGES OF ANY KIND, IN CONTRACT OR IN TORT, IN CONNECTION
28 WITH THIS DOCUMENT OR THE INFORMATION CONTAINED HEREIN,
29 EVEN IF ADVISED OF THE POSSIBILITY OF SUCH LOSS OR DAMAGE. All
30 Company, brand and product names may be trademarks that are the sole property of
31 their respective owners.

32 The above notice and this paragraph must be included on all copies of this document
33 that are made.

34

35

36

37

This page is intentionally blank

38

Revision history

Revision	Date	Details	Editor
00	April, 2015	Created from ZHA and ZLL test specifications.	Phil Jamieson
01	August 12 th , 2015	Resolved comments received since the Hull test event in June 2015.	Phil Jamieson
02	September 28 th , 2015	Added the new mandatory global attribute.	Phil Jamieson
03	October 30 th , 2015	Addressed comments from GTE #3 and the v0.9 ballot.	Phil Jamieson
04	March 1 st , 2016	Addressed comments from the ZigBee 3.0 SVEs.	Phil Jamieson
05	April 18 th , 2016	Changed status to "approved" and version to 1.0.	Phil Jamieson

39

40

41

42

This page is intentionally blank

43

44	Table of Contents	
45	1	Introduction.....9
46	1.1	Conformance levels..... 9
47	2	References..... 10
48	2.1	ZigBee Alliance documents 10
49	2.2	IETF documents 10
50	3	PICS 11
51	3.1	Usage 11
52	3.2	Server..... 11
53	3.2.1	Attributes..... 11
54	3.2.2	Commands received..... 11
55	3.2.3	Commands generated..... 11
56	3.3	Client 12
57	3.3.1	Attributes..... 12
58	3.3.2	Commands received..... 12
59	3.3.3	Commands generated..... 12
60	4	Test specification 13
61	4.1	Introduction 13
62	4.1.1	Test case overview 13
63	4.1.2	Testing tolerances 13
64	4.1.3	Client DUTs 13
65	4.1.4	Test steps manipulating attributes..... 13
66	4.2	Generic test cases 14
67	4.2.1	I-TC-01G: Global attributes..... 14
68	4.3	Server test cases..... 18
69	4.3.1	I-TC-01S: Attributes with server as DUT..... 18
70	4.3.2	I-TC-02S: Primary functionality with server as DUT 21
71	4.3.3	I-TC-03S: Secondary functionality with server as DUT 25
72	4.4	Client test cases 29
73	4.4.1	I-TC-01C: Functionality with client as DUT..... 29
74	5	Annex A: PICS to test case cross reference..... 32
75	5.1	Server..... 32
76	5.2	Client 32
77		
78		
79		

80

81

This page is intentionally blank

82 **1 Introduction**

83 This document contains the PICS, test specification and PICS/test case cross reference for the
84 ZCL *identify* cluster.

85 **1.1 Conformance levels**

86 The key words "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT",
87 "RECOMMENDED" and "MAY" in this document are to be interpreted as described in [R5].

88

89 **2 References**

90 **2.1 ZigBee Alliance documents**

- 91 [R1] ZigBee Cluster Library Specification, ZigBee Alliance document 07-5123.
- 92 [R2] ZCL General Test Specification, ZigBee Alliance document 15-0xxx.
- 93 [R3] ZCL On/Off Cluster Test Specification, ZigBee Alliance document 15-0310.
- 94 [R4] ZCL Identify Cluster XML PICS, ZigBee Alliance document 15-0xxx.

95 **2.2 IETF documents**

- 96 [R5] S. Bradner, Key words for use in RFCs to Indicate Requirement Levels, IETF RFC 2119,
97 March 1997.
- 98

99 3 PICS

100 All references are for the ZigBee Cluster Library specification [R1] unless otherwise indicated.
 101 An XML version of these PICS is also available in [R4].
 102

103 3.1 Usage

Item number	Feature	Reference	Status	Support
I.S	Does the device implement the <i>identify</i> cluster as a server?	3.5.2	O	Yes
I.C	Does the device implement the <i>identify</i> cluster as a client?	3.5.3	O	Yes

104

105 3.2 Server

106 3.2.1 Attributes

Item number	Feature	Reference	Status	Support
I.S.A0000	Does the device implement the <i>IdentifyTime</i> attribute?	Table 3.28, 3.5.2.2.1	I.S: M	Yes
I.S.Afffd	Does the device implement the <i>ClusterRevision</i> global attribute?	Table 2-1, 2.3.5.1.1	I.S: M	Yes

107

108 3.2.2 Commands received

Item number	Feature	Reference	Status	Support
I.S.C00.Rsp	Does the device implement receiving the <i>Identify</i> command?	Table 3.29, 3.5.2.3.1	I.S: M	Yes
I.S.C01.Rsp	Does the device implement receiving the <i>Identify query</i> command?	Table 3.29, 3.5.2.3.2	I.S: M	Yes
I.S.C40.Rsp	Does the device implement receiving the <i>Trigger effect</i> command?	Table 3.29, 3.5.2.3.3	I.S: O	Yes

109

110 3.2.3 Commands generated

Item number	Feature	Reference	Status	Support
I.S.C00.Tx	Does the device implement sending the <i>Identify query response</i> command?	Table 3.32, 3.5.2.4.1	I.S: M	Yes

111

112 **3.3 Client**113 **3.3.1 Attributes**

Item number	Feature	Reference	Status	Support
I.C.Afffd	Does the device implement the <i>ClusterRevision</i> global attribute?	Table 2-1, 2.3.5.1.1	I.C: M	Yes

114

115 **3.3.2 Commands received**

Item number	Feature	Reference	Status	Support
I.C.C00.Rsp	Does the device implement receiving the <i>Identify query response</i> command?	Table 3.32, 3.5.2.4.1	I.C: M	No

116

117 **3.3.3 Commands generated**

Item number	Feature	Reference	Status	Support
I.C.C00.Tx	Does the device implement sending the <i>Identify</i> command?	Table 3.29, 3.5.2.3.1	I.C: O	No
I.C.C01.Tx	Does the device implement sending the <i>Identify query</i> command?	Table 3.29, 3.5.2.3.2	I.C: O	No
I.C.C40.Tx	Does the device implement sending the <i>Trigger effect</i> command?	Table 3.29, 3.5.2.3.3	I.C: O	No

118

119 4 Test specification

120 4.1 Introduction

121 4.1.1 Test case overview

122 The following test cases are available for the *identify* cluster:

Test ID	Description	Reference
Global tests		
I-TC-01G	Global attributes	4.2.1
Server side tests		
I-TC-01S	Attributes with server as DUT	4.3.1
I-TC-02S	Primary functionality with server as DUT	4.3.2
I-TC-03S	Secondary functionality with server as DUT	4.3.3
Client side tests		
I-TC-01C	Functionality with client as DUT	4.4.1

123

124 4.1.2 Testing tolerances

125 In test cases where a change in an attribute value is tested over time, it is permitted for the
 126 devices involved in the test to be within a tolerance of $\pm 15\%$ of the expected value. As such,
 127 these test cases indicate that the attribute value must be approximately equal to an expected
 128 value, to which the $\pm 15\%$ tolerance should then be applied. All other attribute values presented
 129 are expected to be exact.

130 4.1.3 Client DUTs

131 For client test cases only test steps that pertain to commands that are supported on the DUT are
 132 required to be executed. All commands in this cluster for which support is indicated in the
 133 PICS shall be exercised, using valid, application achievable values.

134 Note that for the client attribute test case, it is permissible for the client not to be able to
 135 execute any of the test steps.

136 The client SHALL ensure that an application link, e.g. a binding link, exists between itself and
 137 the test harness. This should be configured before starting the test.

138 4.1.4 Test steps manipulating attributes

139 In test case steps that require more than one attribute to be manipulated (e.g. read), the tester
 140 may decide whether it is appropriate or practical to send a single attribute manipulation
 141 command, containing multiple attributes, or multiple attribute manipulation commands, each
 142 containing a single attribute. The test case is designed to verify the behavior of the device
 143 supporting the attribute rather than verifying the attribute manipulation command in question.

144

145 4.2 Generic test cases

146 4.2.1 I-TC-01G: Global attributes

147 This test case verifies the behavior of the global attributes of the *identify* cluster client and
148 server.

149 In this test, the PICS notation *I.S.Agm* and *I.C.Agm* represents the list of global attributes that
150 are specified as being mandatory for either the server or client, respectively. Similarly, the
151 PICS notation *I.S.Ago* and *I.C.Ago* represents the list of global attributes that are specified as
152 being optional for either the server or client, respectively.

153 4.2.1.1 Scope

154 General:

- 155 • *Read attributes* command (0x00)
- 156 • *Read attributes response* command (0x01)
- 157 • *Write attributes* command (0x02)
- 158 • *Write attributes response* command (0x04)

159 *Identify* cluster (0x0003):

- 160 • All global attributes

161 PICS:

- 162 • I.S, I.C
- 163 • I.S.Agm, I.C.Agm, I.S.Ago, I.C.Ago

164 4.2.1.2 Required devices

Designation	Symbol	Description
DUT		Device under test implementing: <ul style="list-style-type: none"> • The <i>identify</i> cluster server or client.
TH		Test harness implementing: <ul style="list-style-type: none"> • The <i>identify</i> cluster client or server, i.e. the opposite cluster instantiation as implemented on the DUT.


165

166 4.2.1.3 Initial conditions

Item	Initial Conditions
1	A packet sniffer shall be observing the communication over the air interface.
2	All devices are factory new and powered off until used.

167

168 **4.2.1.4 Test preparation**



169

I-TC-01G: Global attributes		
Item	Preparation Step	Observation
P2	Power on TH and DUT.	TH and DUT are powered on.
P3	Ensure TH and DUT are on the same ZigBee network.	Observe appropriate communication between TH, DUT and any other relevant node on the ZigBee network.

--- End of test case I-TC-01G preparation ---

170

171 **4.2.1.5 Test procedure**

I-TC-01G: Global attributes			
Item	PICS	Test Harness Step	DUT pass Verification
1	I.S.Agm, I.C.Agm	TH unicasts a <i>ZCL read attributes</i> command frame to DUT to read each mandatory global attribute of this cluster one at a time.	DUT unicasts a <i>ZCL read attributes response</i> command frame to TH containing each requested attribute. The data type in each command must match the value listed in the specification(s). The data value in each command for the attribute must fall within the valid range described in the specification(s).
2a	I.S.Agm, I.C.Agm	TH unicasts a <i>ZCL write attributes</i> command frame to DUT to write the respective default value to each mandatory global attribute of this cluster one at a time.	DUT unicasts a <i>ZCL write attributes response</i> command frame to TH for each attribute. If the access control of DUT is set to READ, the DUT response will indicate that the attribute write command was not a SUCCESS. If the access control of DUT is set to READ/WRITE, the DUT response will indicate that the write command was a SUCCESS.
2b	I.S.Agm, I.C.Agm	TH unicasts a <i>ZCL read attributes</i> command frame to DUT to read back each attribute written in step 2a.	DUT unicasts a <i>ZCL read attributes response</i> command frame to TH containing the requested attribute. If the <i>Status</i> field of the <i>write attributes response</i> command frame was equal to SUCCESS, the updated value is read back. If the <i>Status</i> field of the <i>write attributes response</i> command frame was not equal to SUCCESS the value is not updated when read back.

Continued...

I-TC-01G: Global attributes			
Item	PICS	Test Harness Step	DUT pass Verification
3	I.S.Ago, I.C.Ago	TH unicasts a ZCL <i>read attributes</i> command frame to DUT to read each optional global attribute of this cluster one at a time.	DUT unicasts a ZCL <i>read attributes response</i> command frame to TH containing each attribute. If the DUT implements the attribute, the <i>Status</i> field will be equal to SUCCESS and the command will contain the requested attribute. If the DUT does not implement the attribute, the <i>Status</i> field will not be equal to SUCCESS. The data type in each command must match the value listed in the specification(s). The data value in each command for the attribute must fall within the valid range described in the specification(s).
4a	I.S.Ago, I.C.Ago	TH unicasts a ZCL <i>write attributes</i> command frame to DUT to write the respective default value to each optional global attribute of this cluster one at a time.	DUT unicasts a ZCL <i>write attributes response</i> command frame to TH for each attribute. If the attribute is not implemented or the access control of DUT is set to READ, the DUT response will indicate that the attribute write command was not a SUCCESS. If the attribute is implemented and the access control of DUT is set to READ/WRITE, the DUT response will indicate that the write command was a SUCCESS.
4b	I.S.Ago, I.C.Ago	TH unicasts a ZCL <i>read attributes</i> command frame to DUT to read back each attribute written in step 4a.	DUT unicasts a ZCL <i>read attributes response</i> command frame to TH containing the requested attribute. If the <i>Status</i> field of the <i>write attributes response</i> command frame was equal to SUCCESS, the updated value is read back. If the <i>Status</i> field of the <i>write attributes response</i> command frame was not equal to SUCCESS the value is not updated when read back.

--- End of test case I-TC-01G ---

173 4.3 Server test cases

174 4.3.1 I-TC-01S: Attributes with server as DUT

175 This test case verifies the behavior of the non-global attributes of the *identify* cluster server.

176 In this test, the PICS notation *I.S.Am* represents the list of non-global attributes that are
177 specified as being mandatory.

178 4.3.1.1 Scope

179 General:

- 180 • *Read attributes* command (0x00)
- 181 • *Read attributes response* command (0x01)
- 182 • *Write attributes* command (0x02)
- 183 • *Write attributes response* command (0x04)

184 *Identify* cluster (0x0003):

- 185 • All non-global attributes

186 PICS:

- 187 • I.S,
- 188 • I.S.Am

189 4.3.1.2 Required devices

Designation	Symbol	Description
TH CLIENT		Test harness client implementing: <ul style="list-style-type: none"> • The <i>identify</i> cluster client.
DUT SERVER		Device under test server: <ul style="list-style-type: none"> • The <i>identify</i> cluster server.

190


191 4.3.1.3 Initial conditions

Item	Initial Conditions
1	A packet sniffer shall be observing the communication over the air interface.
2	All devices are factory new and powered off until used.

192

193

194 **4.3.1.4 Test preparation**



195

I-TC-01S: Attributes with server as DUT		
Item	Preparation Step	Observation
P2	Power on TH CLIENT and DUT SERVER.	TH CLIENT and DUT SERVER are powered on.
P3	Ensure TH CLIENT and DUT SERVER are on the same ZigBee network.	Observe appropriate communication between TH CLIENT, DUT SERVER and any other relevant node on the ZigBee network.

--- End of test case I-TC-01C preparation ---

196

197 **4.3.1.5 Test procedure**

I-TC-01S: Attributes with server as DUT			
Item	PICS	Test Harness Step	DUT pass Verification
1	I.S.Am	TH CLIENT unicasts a ZCL <i>read attributes</i> command frame to DUT SERVER to read each mandatory attribute of this cluster one at a time.	DUT SERVER unicasts a ZCL <i>read attributes response</i> command frame to TH CLIENT containing each requested attribute. The data type in each command must match the value listed in the specification(s). The data value in each command for the attribute must fall within the valid range described in the specification(s).
2a	I.S.Am	TH CLIENT unicasts a ZCL <i>write attributes</i> command frame to DUT SERVER to write the respective default value to each mandatory attribute of this cluster one at a time.	DUT SERVER unicasts a ZCL <i>write attributes response</i> command frame to TH CLIENT for each attribute. If the access control of DUT SERVER is set to READ, the DUT SERVER response will indicate that the attribute write command was not a SUCCESS. If the access control of DUT SERVER is set to READ/WRITE, the DUT SERVER response will indicate that the write command was a SUCCESS.
2b	I.S.Am	TH CLIENT unicasts a ZCL <i>read attributes</i> command frame to DUT SERVER to read back each attribute written in step 2a.	DUT SERVER unicasts a ZCL <i>read attributes response</i> command frame to TH CLIENT containing the requested attribute. If the <i>Status</i> field of the <i>write attributes response</i> command frame was equal to SUCCESS, the updated value is read back. If the <i>Status</i> field of the <i>write attributes response</i> command frame was not equal to SUCCESS the value is not updated when read back.

--- End of test case I-TC-01S ---

198

199

200 **4.3.2 I-TC-02S: Primary functionality with server as DUT**

201 This test verifies the primary functionality of the *identify* cluster.

202 **4.3.2.1 Scope**

203 General:

- 204 • *Read attributes* command (0x00)
- 205 • *Read attributes response* command (0x01)
- 206 • *Write attributes no response* command (0x05)
- 207 • *Default response* command (0x0b)

208 *Identify* cluster (0x0003):

- 209 • *IdentifyTime* attribute (0x0000)
- 210 • *Identify* command (0x00)
- 211 • *Identify query* command (0x01)
- 212 • *Identify query response* command (0x00)

213 PICS:

- 214 • I.S
- 215 • I.S.A0000
- 216 • I.S.C00.Rsp, I.S.C01.Rsp
- 217 • I.S.C00.Tx

218 **4.3.2.2 Required devices**

Designation	Symbol	Description
TH CLIENT		Test harness client implementing: <ul style="list-style-type: none"> • The <i>identify</i> cluster client.
DUT SERVER		Device under test server implementing: <ul style="list-style-type: none"> • The <i>identify</i> cluster server.

219


220 **4.3.2.3 Initial conditions**

Item	Initial Conditions
1	A packet sniffer shall be observing the communication over the air interface.
2	All devices are factory new and powered off until used.

221

222

223 **4.3.2.4 Test preparation**



224

I-TC-02S: Primary functionality with server as DUT		
Item	Preparation Step	Observation
P2	Power on TH CLIENT and DUT SERVER.	TH CLIENT and DUT SERVER are powered on.
P3	Ensure TH CLIENT and DUT SERVER are on the same ZigBee network.	Observe appropriate communication between TH CLIENT, DUT SERVER and any other relevant node on the ZigBee network.

--- End of test case I-TC-02S preparation ---

225

226

4.3.2.5 Test procedure

I-TC-02S: Primary functionality with server as DUT			
Item	PICS	Test Harness Step	DUT Pass Verification
1a	I.S.C00.Rsp	TH CLIENT unicasts a ZCL <i>identify</i> command frame to DUT SERVER, with the <i>identify time</i> field set to 0x003c (60s).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER begins to identify itself.
1b	I.S.A0000	TH CLIENT immediately unicasts a ZCL <i>read attributes</i> command frame to DUT SERVER to read the <i>IdentifyTime</i> attribute.	DUT SERVER unicasts a ZCL <i>read attributes response</i> command frame to TH CLIENT. <i>IdentifyTime</i> attribute has a value approximately equal to 0x003c.
1c	I.S.A0000	After 3s, TH CLIENT unicasts a ZCL <i>read attributes</i> command frame to DUT SERVER to read the <i>IdentifyTime</i> attribute.	DUT SERVER unicasts a ZCL <i>read attributes response</i> command frame to TH CLIENT. <i>IdentifyTime</i> attribute has a value approximately equal to 0x0039.
2	I.S.C01.Rsp, I.S.C00.Tx	TH CLIENT unicasts a ZCL <i>identify query</i> command to DUT SERVER.	DUT SERVER unicasts a ZCL <i>identify query response</i> command frame to TH CLIENT with the <i>Timeout</i> field set to a value in the range 0x0000 – 0x0039.
3a	I.S.C00.Rsp	TH CLIENT unicasts a ZCL <i>identify</i> command frame to DUT SERVER, with the <i>identify time</i> field set to 0x0000 (stop identifying).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER stops identifying itself.
3b	I.S.A0000	TH CLIENT unicasts a ZCL <i>read attributes</i> command frame to DUT SERVER to read the <i>IdentifyTime</i> attribute.	DUT SERVER unicasts a ZCL <i>read attributes response</i> command frame to TH CLIENT. <i>IdentifyTime</i> attribute has the value 0x0000.

Continued...

I-TC-02S: Primary functionality with server as DUT			
Item	PICS	Test Harness Step	DUT Pass Verification
4	I.S.C01.Rsp, I.S.C00.Tx	TH CLIENT unicasts a ZCL <i>identify query</i> command to DUT SERVER.	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER does not respond with an <i>identify query response</i> command frame.
5a	I.S.A0000	TH CLIENT unicasts a ZCL <i>write attributes no response</i> command to DUT SERVER to write the <i>IdentifyTime</i> attribute to 0x000a (10s).	DUT SERVER sends no response. DUT SERVER begins to identify itself.
5b	I.S.A0000	After 5s, TH CLIENT unicasts a ZCL <i>read attributes</i> command frame to DUT SERVER to read the <i>IdentifyTime</i> attribute.	DUT SERVER unicasts a ZCL <i>read attributes response</i> command frame to TH CLIENT. <i>IdentifyTime</i> attribute has a value approximately equal to 0x0005.

--- End of test case I-TC-02S ---

228
229

230 **4.3.3 I-TC-03S: Secondary functionality with server as DUT**

231 This test verifies the secondary functionality of the *identify* cluster.

232 **4.3.3.1 Scope**

233 General:

- 234
 - *Default response* command (0x0b)

235 *Identify* cluster (0x0008):

- 236
 - *Trigger effect* command (0x40)

237 PICS:

- 238
 - I.S
 - I.S.C40.Rsp

240 **4.3.3.2 Required devices**

Designation	Symbol	Description
TH CLIENT		Test harness client implementing: <ul style="list-style-type: none">• The <i>identify</i> cluster client.
DUT SERVER		Device under test server implementing: <ul style="list-style-type: none">• The <i>identify</i> cluster server.

241


242 **4.3.3.3 Initial conditions**

Item	Initial Conditions
1	A packet sniffer shall be observing the communication over the air interface.
2	All devices are factory new and powered off until used.

243

244

245 **4.3.3.4 Test preparation**



246

I-TC-03S: Secondary functionality with server as DUT		
Item	Preparation Step	Observation
P2	Power on TH CLIENT and DUT SERVER.	TH CLIENT and DUT SERVER are powered on.
P3	Ensure TH CLIENT and DUT SERVER are on the same ZigBee network.	Observe appropriate communication between TH CLIENT, DUT SERVER and any other relevant node on the ZigBee network.

--- End of test case I-TC-03S preparation ---

247

248

249 **4.3.3.5 Test procedure**

I-TC-03S: Secondary functionality with server as DUT			
Item	PICS	Test Harness Step	DUT Pass Verification
1a	I.S.C40.Rsp	TH CLIENT unicasts a ZCL <i>trigger effect</i> command frame to DUT SERVER with the <i>effect identifier</i> field set to 0x00 (blink) and the <i>effect variant</i> field set to 0x00 (default).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER executes a blink effect.
1b	I.S.C40.Rsp	TH CLIENT unicasts a ZCL <i>trigger effect</i> command frame to DUT SERVER with the <i>effect identifier</i> field set to 0x01 (breathe) and the <i>effect variant</i> field set to 0x00 (default).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER executes a breathe effect.
1c	I.S.C40.Rsp	TH CLIENT unicasts a ZCL <i>trigger effect</i> command frame to DUT SERVER with the <i>effect identifier</i> field set to 0x02 (okay) and the <i>effect variant</i> field set to 0x00 (default).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER executes an okay effect.
1d	I.S.C40.Rsp	TH CLIENT unicasts a ZCL <i>trigger effect</i> command frame to DUT SERVER with the <i>effect identifier</i> field set to 0x0b (channel change) and the <i>effect variant</i> field set to 0x00 (default).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER executes a channel change effect.
1e	I.S.C40.Rsp	TH CLIENT unicasts a ZCL <i>trigger effect</i> command frame to DUT SERVER with the <i>effect identifier</i> field set to 0x01 (breathe) and the <i>effect variant</i> field set to 0x00 (default).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER executes a breathe effect.

Continued...

I-TC-03S: Secondary functionality with server as DUT			
Item	PICS	Test Harness Step	DUT Pass Verification
1f	I.S.C40.Rsp	TH CLIENT unicasts a ZCL <i>trigger effect</i> command frame to DUT SERVER with the <i>effect identifier</i> field set to 0xfe (finish effect) and the <i>effect variant</i> field set to 0x00 (default).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER stops the breathe effect after the current effect sequence.
1g	I.S.C40.Rsp	TH CLIENT unicasts a ZCL <i>trigger effect</i> command frame to DUT SERVER with the <i>effect identifier</i> field set to 0x01 (breathe) and the <i>effect variant</i> field set to 0x00 (default).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER executes a breathe effect.
1h	I.S.C40.Rsp	TH CLIENT unicasts a ZCL <i>trigger effect</i> command frame to DUT SERVER with the <i>effect identifier</i> field set to 0xff (stop effect) and the <i>effect variant</i> field set to 0x00 (default).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER stops the breathe effect as soon as possible.
2a	I.S.C40.Rsp	TH CLIENT unicasts a ZCL <i>trigger effect</i> command frame to DUT SERVER with the <i>effect identifier</i> field set to 0x00 (blink) and the <i>effect variant</i> field set to 0x42 (unknown).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER executes a blink effect.
2b	I.S.C40.Rsp	TH CLIENT unicasts a ZCL <i>trigger effect</i> command frame to DUT SERVER with the <i>effect identifier</i> field set to 0xff (stop effect) and the <i>effect variant</i> field set to 0x00 (default).	If requested, DUT SERVER unicasts a ZCL <i>default response</i> command frame to TH CLIENT with the <i>status</i> field equal to 0x00 (SUCCESS). DUT SERVER stops any effect that may be still running as soon as possible.

--- End of test case I-TC-03S ---

250

251

252 4.4 Client test cases

253 4.4.1 I-TC-01C: Functionality with client as DUT

254 This case test verifies the functionality of the *identify* cluster client.

255 The DUT client SHALL be on the same network as a suitable server, provided by the user, and
 256 this device SHALL be used by the client to exercise its functionality. The test case uses the
 257 test harness to prompt the user, based on the declared PICS, to exercise the functionality of the
 258 *basic* cluster client and to verify the results. A sniffer tool SHALL be used to log the exercised
 259 functionality and to determine its validity.

260 In this test case, the PICS notation I.C.CdTx represents the list of commands that are declared
 261 as being transmitted by the DUT.

262 4.4.1.1 Scope

263 *Identify* cluster (0x0003):

- 264 • *Identify* command (0x00)
- 265 • *Identify query* command (0x01)
- 266 • *Trigger effect* command (0x40)

267 PICS:

- 268 • I.C
- 269 • I.C.C00.Tx, I.C.C01.Tx, I.C.C40.Tx

270 4.4.1.2 Required devices

Designation	Symbol	Description
DUT CLIENT		Device under test client implementing: <ul style="list-style-type: none"> • The <i>identify</i> cluster client.
SERVER		Suitable server device implementing: <ul style="list-style-type: none"> • The <i>identify</i> cluster server.

271

272 4.4.1.3 Initial conditions


Item	Initial Conditions
1	A packet sniffer shall be observing the communication over the air interface.
2	All devices are factory new and powered off until used.

273

274

275

276 **4.4.1.4 Test preparation**



277

I-TC-01C: Functionality with client as DUT		
Item	Preparation Step	Observation
P1	Power on the DUT CLIENT device and the SERVER device.	DUT CLIENT and SERVER are powered on.
P2	Ensure the DUT CLIENT device and the SERVER device are on the same ZigBee network.	Observe appropriate communication between DUT CLIENT, SERVER and any other relevant node on the ZigBee network.

--- End of test case I-TC-01C preparation ---

278

279

280 **4.4.1.5 Test procedure**

I-TC-01C: Functionality with client as DUT			
Item	PICS	Test Harness Step	DUT Pass Verification
1	-	Test harness prompts the user with a list of commands, based on the declared PICS, which the DUT CLIENT indicates it can transmit.	None.
2	I.C.Cd.Tx	None.	DUT CLIENT transmits correctly formed commands in any order and with application achievable values. This is verified using the sniffer log.
3	-	Prompt the user to verify that the cluster commands listed in step 1 were transmitted during step 2.	During step 2, DUT CLIENT has transmitted every command listed by the test harness in step 1.
4	-	Prompt the user to verify that the cluster commands not listed in step 1 were not transmitted during step 2.	During step 2, DUT CLIENT has not transmitted any commands from this cluster that were not listed by the test harness in step 1.

--- End of test case I-TC-01C ---

281
282
283

284 5 Annex A: PICS to test case cross reference

285 5.1 Server

PICS	Test case			
	I-TC-01G	I-TC-01S	I-TC-02S	I-TC-03S
I.S	X	X	X	X
I.S.A0000		X	X	
I.S.Afffd	X			
I.S.C00.Rsp			X	
I.S.C01.Rsp			X	
I.S.C40.Rsp				X
I.S.C00.Tx			X	

286

287 5.2 Client

PICS	Test case	
	I-TC-01G	I-TC-01C
I.C	X	X
I.C.Afffd	X	
I.C.C00.Rsp		X
I.C.C00.Tx		X
I.C.C01.Tx		X
I.C.C40.Tx		X

288

289

290