

1

2

# zigbee alliance

3

4

5 **zigbee Document 08-0006-07**

6 **zigbee PRO Layer PICS and Stack Profiles**  
7 **Revision 06**

8

9 April 2017

10 **Sponsored by:**  
11 zigbee alliance

12 **Accepted for release by:**  
13 ZigBee Alliance Board of Directors.

14 **Abstract:**  
15

16 **Keywords:**  
17 zigbee, zigbee-PRO, Stack profile, Architecture.

18

## 19 **Notice of use and disclosure**

20 Copyright © zigbee alliance (2005-2017). All rights reserved. This information within  
21 this document is the property of the zigbee alliance and its use and disclosure are  
22 restricted.

23 Elements of zigbee alliance specifications may be subject to third party intellectual  
24 property rights, including without limitation, patent, copyright or trademark rights  
25 (such a third party may or may not be a member of zigbee). zigbee is not responsible  
26 and shall not be held responsible in any manner for identifying or failing to identify  
27 any or all such third party intellectual property rights.

28 No right to use any zigbee name, logo or trademark is conferred herein. Use of any  
29 zigbee name, logo or trademark requires membership in the zigbee alliance and  
30 compliance with the zigbee Logo and Trademark Policy and related zigbee policies.

31 This document and the information contained herein are provided on an “AS IS” basis  
32 and zigbee DISCLAIMS ALL WARRANTIES EXPRESS OR IMPLIED,  
33 INCLUDING BUT NOT LIMITED TO (A) ANY WARRANTY THAT THE USE  
34 OF THE INFORMATION HEREIN WILL NOT INFRINGE ANY RIGHTS OF  
35 THIRD PARTIES (INCLUDING WITHOUT LIMITATION ANY  
36 INTELLECTUAL PROPERTY RIGHTS INCLUDING PATENT, COPYRIGHT OR  
37 TRADEMARK RIGHTS) OR (B) ANY IMPLIED WARRANTIES OF  
38 MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, TITLE OR  
39 NONINFRINGEMENT. IN NO EVENT WILL ZIGBEE BE LIABLE FOR ANY  
40 LOSS OF PROFITS, LOSS OF BUSINESS, LOSS OF USE OF DATA,  
41 INTERRUPTION OF BUSINESS, OR FOR ANY OTHER DIRECT, INDIRECT,  
42 SPECIAL OR EXEMPLARY, INCIDENTAL, PUNITIVE OR CONSEQUENTIAL  
43 DAMAGES OF ANY KIND, IN CONTRACT OR IN TORT, IN CONNECTION  
44 WITH THIS DOCUMENT OR THE INFORMATION CONTAINED HEREIN,  
45 EVEN IF ADVISED OF THE POSSIBILITY OF SUCH LOSS OR DAMAGE. All  
46 company, brand, and product names may be trademarks that are the sole property of  
47 their respective owners.

48 The above notice and this paragraph must be included on all copies of this document  
49 that are made.

## 50 **Contact information**

51 Much of the information in this document is preliminary and subject to change. Members of the ZigBee  
52 Working Group are encouraged to review and provide inputs for this proposal. For document status  
53 updates, please contact:

54 Michael Cowan  
55 639 Davis Drive  
56 Morrisville, NC, USA 27560  
57 [michael.cowan@sensus.com](mailto:michael.cowan@sensus.com)  
58 Desk Phone: 919-317-6320  
59 Lab Phone: 919-317-6184

60  
61  
62 You can also submit comments using the ZigBee Alliance reflector. Its web site address is:

63 [www.zigbee.org](http://www.zigbee.org)

64 The information on this page should be removed when this document is accepted.

## 65 Participants

66 The following is a list of those who were members of the ZigBee Alliance PRO Core Stack Working  
67 Group leadership when this document was released:

68 **Robert Alexander:** *Chair*

69 **Arasch Honarbacht:** *Vice Chair*

70 **Tim Gillman:** *Secretary*

71

72

73 The editing team was composed of the following members:

74

75 Colin Faulkner: EDMI, Ltd, Technical Editor ZigBee PRO Core Specification

76 Ian Winterburn: Landis&Gyr, Technical Editor ZigBee PRO Energy Specification

77 Michael Cowan: Sensus Technical Editor ZigBee PRO Energy Test Spec and PICS

78

79

80 Additionally, the following individuals contributed to the PICS document:

81 Robert Alexander Silicon Laboratories, Inc.

82 Arasch Honarbacht ubisys technologies GmbH

83 Chris Brandson Exegin

## Table of Contents

|     |        |   |    |
|-----|--------|---|----|
| 85  | 1      | Introduction .....  | 1  |
| 86  | 1.1    | Scope .....   | 1  |
| 87  | 1.2    | Purpose .....   | 1  |
| 88  | 2      | References .....  | 2  |
| 89  | 2.1    | ZigBee Alliance documents .....                                     | 2  |
| 90  | 2.2    | IEEE documents .....  | 2  |
| 91  | 2.3    | ETSI documents .....  | 2  |
| 92  | 3      | Definitions .....   | 3  |
| 93  | 4      | Acronyms and abbreviations .....                                    | 4  |
| 94  | 5      | General description .....   | 5  |
| 95  | 6      | Knob settings .....   | 6  |
| 96  | 6.1    | Introduction .....  | 6  |
| 97  | 6.2    | Network settings .....  | 6  |
| 98  | 6.3    | Application settings .....  | 6  |
| 99  | 6.4    | Security settings .....   | 7  |
| 100 | 7      | Functional description .....  | 8  |
| 101 | 7.1    | Device roles .....  | 8  |
| 102 | 7.2    | ZigBee: Compatibility with Other Feature sets .....                 | 8  |
| 103 | 7.3    | ZigBee-PRO: Feature set .....                                       | 9  |
| 104 | 7.4    | Binding tables .....  | 9  |
| 105 | 7.5    | Multicast mechanism and groups .....                                | 9  |
| 106 | 7.6    | Trust Center Policies and Security Settings .....                   | 9  |
| 107 | 7.7    | Battery powered devices .....                                       | 9  |
| 108 | 7.8    | Mains powered devices .....   | 10 |
| 109 | 7.9    | Persistent storage .....  | 10 |
| 110 | 7.10   | Address Reuse .....   | 10 |
| 111 | 7.11   | Duty cycle limitations and fragmentation .....                      | 10 |
| 112 | 7.11.1 | Vulnerability join .....  | 10 |
| 113 | 7.11.2 | Pre-installation .....  | 11 |
| 114 | 7.12   | Security .....  | 11 |
| 115 | 7.12.1 | Security Modes within PRO Networks .....                            | 11 |
| 116 | 8      | Instructions for completing the PICS proforma .....                 | 13 |
| 117 | 9      | Identification of the implementation .....                          | 14 |
| 118 | 10     | Protocol implementation conformance statement (PICS) proforma ..... | 15 |
| 119 | 10.1   | Abbreviations and special symbols .....                             | 15 |
| 120 | 10.2   | ZigBee device types .....   | 15 |
| 121 | 10.3   | IEEE 802.15.4 PICS .....  | 16 |
| 122 | 10.3.1 | FDT2 and FDT3 network join options .....                            | 16 |
| 123 | 10.3.2 | IEEE 802.15.4 PHY .....   | 17 |
| 124 | 10.3.3 | IEEE 802.15.4 MAC .....   | 18 |
| 125 | 10.4   | Network layer PICS .....  | 32 |
| 126 | 10.4.1 | ZigBee network frame format .....                                   | 32 |
| 127 | 10.4.2 | Major capabilities of the ZigBee network layer .....                | 33 |
| 128 | 10.5   | Security PICS .....   | 55 |
| 129 | 10.5.1 | ZigBee security roles .....   | 55 |
| 130 | 10.5.2 | ZigBee trust center capabilities .....                              | 56 |
| 131 | 10.5.3 | Modes of operation .....  | 57 |
| 132 | 10.5.4 | Security levels .....   | 57 |

|     |        |  |    |
|-----|--------|--|----|
| 133 | 10.5.5 | NWK layer security .....                                 | 59 |
| 134 | 10.5.6 | APS layer security.....                                  | 61 |
| 135 | 10.5.7 | Application layer security .....                         | 66 |
| 136 | 10.6   | Application layer PICS.....                              | 71 |
| 137 | 10.6.1 | ZigBee security device types .....                       | 71 |
| 138 | 10.6.2 | ZigBee APS frame format.....                             | 71 |
| 139 | 10.6.3 | Major capabilities of the ZigBee application layer ..... | 72 |
| 140 |        |  |    |

141

**List of Tables**

142 Table 1 – Document revision change history ..... viii  
143 Table 2 – Network settings for this feature set.....6  
144 Table 3 – Application settings for this feature set.....6  
145 Table 4 – Security settings for this feature set .....7  
146

147 **Change history**

148 Table 1 shows the change history for this specification.

149 **Table 1 – Document revision change history**

| Revision | Description   |
|----------|---|
| 00       | Original version based on 08-0006-05 snap shoot in Dec 2014.  |
| 01       | Baseline original -00 document to ZigBee Document 08-0006-05 (R21 rev 1.0 equivalent document with all changes accepted) ZigBee PRO/2007 Layer PICS and Stack Profiles then added in R22 changes based on R22 Combined Document (Specification) dated Oct 8, 2015 10:37 AM.   |
| 02       | Addressed All rev 0.7 comments and updated document for rev 0.7 re-ballot   |
| 03       | Addressed All rev 0.7 re-ballot comments and updated document for rev 0.7 release   |
| 04       | Address deferred rev 0.7 comments – comment 303 (Chris Brandson) fix section numbers references in PICS to match rev 0.9 PRO CORE Specification section numbers. Add update fixes for CCBs:<br>CCB 2091 – NLF27 - Number of Entries in End Device Neighbor Table increase to 5 per specification section 3.6.1.4.2.1<br>CCB 2137 – Modify NLF4 slightly to note that this is for forming *centralized* networks. and AZD31 - Add a separate PICs item for forming *distributed* networks = AZD299 added. Same text for NLF4 except it would be mandatory for both FDT1 and FDT2.<br>CCB 2144 – NDF106 – replace orphan notification and keep alive methods with end device timeout keep alive methods.<br>CCB 2178 – Trust center must be collocated with ZC (short address 0x0000) throughout network life – SR1.<br>CCB 2239 – Update NDF108 and NDF109 both conditional on NDF105<br>CCB 2240 – if support GP need to support list of items in PICS defined in CCB |
| 05       | Added Oct 17 2016 rev 0.9 comments from KAVI and release for reballot comments  |
| 06       | No rev 0.9 re-ballot comments in KAVI, updated for Rev 1.0 release plans.   |

150

151

## 152 **1 Introduction**

153 To evaluate conformance of a particular implementation, it is necessary to have a statement of which  
154 capabilities and options have been implemented for a given standard. Such a statement is called a  
155 protocol implementation conformance statement (PICS).

### 156 **1.1 Scope**

157 This document provides the protocol implementation conformance statement (PICS) proforma for  
158 ZigBee R22 Draft specification (05-3474-22) in compliance with the relevant requirements, and in  
159 accordance with the relevant guidance, given in ISO/IEC 9646-7. The specification adds multiband  
160 functionality support which required changes to PHY/MAC and network layers. In addition ZigBee  
161 2007 was been deprecated by the ZigBee Alliance therefore all ZigBee 2007 stack protocol  
162 implementation conformance statement (PICS) have been removed from this document. Starting with  
163 R22 and later, only ZigBee PRO stack will be supported per ZigBee 3.0 inter-operability marketing  
164 decision.

165

### 166 **1.2 Purpose**

167 The supplier of a protocol implementation claiming to conform to the ZigBee standard shall complete  
168 the following PICS proforma and accompany it with the information necessary to identify fully both  
169 the supplier and the implementation.

170

171 The protocol implementation conformance statement (PICS) of a protocol implementation is a  
172 statement of which capabilities and options of the protocol have been implemented. The statement is in  
173 the form of answers to a set of questions in the PICS proforma. The questions in a proforma consist of  
174 a systematic list of protocol capabilities and options as well as their implementation requirements. The  
175 implementation requirement indicates whether implementation of a capability is mandatory, optional,  
176 or conditional depending on options selected. When a protocol implementer answers questions in a  
177 PICS proforma, they would indicate whether an item is implemented or not, and provide explanations  
178 if an item is not implemented.

## 179 2 References

180 The following standards and specifications contain provisions, which through reference in this  
181 document constitute provisions of this specification. All the standards and specifications listed are  
182 normative references. At the time of publication, the editions indicated were valid. All standards and  
183 specifications are subject to revision, and parties to agreements based on this specification are  
184 encouraged to investigate the possibility of applying the most recent editions of the standards and  
185 specifications indicated below.

### 186 2.1 ZigBee Alliance documents

- 187 [R1] ZigBee document 05-3474r22, ZigBee draft specification release 22, ZigBee Core Stack  
188 Group
- 189 [R2] ZigBee 04-0140r05, ZigBee Protocol Stack Settable Values (knobs) release 05, ZigBee  
190 Architecture Working Group
- 191 [R3] ZigBee document 04-0319r01, ZigBee IEEE 802.15.4 PHY & MAC Layer Test Specification  
192 release r01
- 193 [R4] ZigBee document 08-5195r02, ZigBee Trust Centre Best Practices, ZigBee Security Task  
194 Group.
- 195 [R5] CEPT/ERC/REC 70-03: "Relating to the use of Short Range Devices (SRD)". (13-0390-02).  
196 Version after Public Consultation CEPT SRDMG#60 13th December 2013.
- 197 [R6] EN 300 220-1 "Electromagnetic compatibility and Radio spectrum Matters (ERM); Short  
198 Range Devices (SRD); Radio equipment to be used in the 25 MHz to 1 000 MHz frequency  
199 range with power levels ranging up to 500 mW; Part 1: Technical characteristics and test  
200 methods" version 2.4.1 (13-391-00)
- 201 [R7] ZigBee 09-5499r26 Green Power Specification
- 202 [R8] ZigBee 14-0563-16 PRO Green Power Feature specification

### 204 2.2 IEEE documents

- 205 [R9] IEEE 802.15.4:2011 "IEEE Standard for Local and metropolitan area networks Part 15.4:  
206 Low-Rate Wireless Personal Area Networks (LR-WPANs)"
- 207 [R10] IEEE 802.15.4:2015 "IEEE Standard for Local and metropolitan area networks Part 15.4:  
208 Low-Rate Wireless Personal Area Networks (LR-WPANs)"
- 209 [R11] IEEE Standards Style Manual, published and distributed in May 2000 and last revised in  
210 2012. Available from  
211 <https://development.standards.ieee.org/myproject/Public/mytools/draft/styleman.pdf>

### 212 2.3 ETSI documents

- 213 [R12] ETSI TR 102 887-1 "Electromagnetic compatibility and Radio spectrum Matters (ERM); Short  
214 Range Devices; Smart Metering Wireless Access Protocol; Part 1: PHY layer" (13-0425-00)

215

216

### 3 Definitions

|  |   |
|--|---|
| <b>Feature set</b>                           | A collection of parameter values and configuration settings, collectively and loosely referred to as “knobs” in [R2], that determine the specific performance of a ZigBee stack variant and govern interoperability between stacks provided by different vendors.   |
| <b>ZigBee 2.4 GHz Coordinator</b>            | An IEEE 802.15.4-2011 PAN coordinator operating in a ZigBee 2.4 GHz network.  |
| <b>ZigBee 2.4 GHz End Device</b>             | An IEEE 802.15.4-2011 RFD participating in a ZigBee 2.4 GHz network, which is neither the ZigBee coordinator nor a ZigBee router.   |
| <b>ZigBee 2.4 GHz Router</b>                 | An IEEE 802.15.4-2011 FFD participating in a ZigBee 2.4 GHz network, which is not the ZigBee coordinator but may act as an IEEE 802.15.4-2003 coordinator within its personal operating space, that is capable of routing messages between devices and supporting associations  |
| <b>ZigBee Sub-GHz Router</b>                 | An IEEE 802.15.4-2015 FFD participating in a ZigBee Sub- GHz network, which is not the ZigBee coordinator but may act as an IEEE 802.15.4-2011 coordinator within its personal operating space, that is capable of routing messages between devices and supporting associations. ZigBee Sub-GHz Router (ZSR) is supported in R22 with power control on end device to routers and end devices to coordinators links. No power control for router to router, and router to coordinator links and devices should transmit at maximum power of + 14 dBm |
| <b>ZigBee Multi-MAC Selection Router</b>     | An IEEE 802.15.4-2015 FFD participating in a ZigBee Sub-GHz <b>or</b> 2.4 GHz network but <b>not</b> in both bands. Power control only on Sub-GHz interface and not on the 2.4 GHz interface. Router in Sub-GHz mode in R22 will support power control on end device to routers and end devices to coordinators links. No power control for router to router, and router to coordinator links and devices should transmit at maximum power of + 14 dBm  |
| <b>ZigBee Multi-MAC Switch Router</b>        | An IEEE 802.15.4-2015 FFD participating in a ZigBee Sub-GHz <b>and</b> 2.4 GHz network. In R22 only allows a single ZigBee Multi-MAC Switch Router in the network integrated into the ZigBee Multi-MAC Switch Coordinator   |
| <b>ZigBee Multi-MAC Switch Coordinator</b>   | An IEEE 802.15.4-2015 PAN coordinator operating in a ZigBee 2.4 GHz network <b>and</b> in Sub-GHz band.   |
| <b>ZigBee Multi-MAC Selection End Device</b> | An IEEE 802.15.4-2015 RFD participating in a ZigBee 2.4 GHz network <b>or</b> the Sub-GHz network which is neither the ZigBee coordinator nor a ZigBee router.  |
| <b>ZigBee Sub-GHz End Device</b>             | An IEEE 802.15.4-2015 RFD participating in a ZigBee Sub-GHz network which is neither the ZigBee coordinator nor a ZigBee router.  |

## 218 **4 Acronyms and abbreviations**

|      |  |
|------|--|
| AODV | Ad-Hoc On-Demand Distance Vector                 |
| FFD  | IEEE 802.15.4 Full Function Device               |
| IEEE | Institute of Electrical and Electronic Engineers |
| PICS | Protocol Implementation Conformance Statement    |
| RFD  | IEEE 802.15.4 Reduced Function Device            |

219

## 5 General description

220  
221 The sections in this document are:

- 222 • Knob settings – details of values to be used for parameters specified in the ZigBee  
223 specification for tuning the operation of the ZigBee stack, including network, application and  
224 security settings.
- 225 • Functional description – further operational restrictions to be applied to all devices in this  
226 feature set where various approaches are otherwise supported by the ZigBee specification.
- 227 • Protocol implementation conformance statement (PICS) – a formal definition of functionality  
228 to be implemented in these devices.

229 These requirements aim to allow a designer to make necessary assumptions about what settings,  
230 features and safeguards will be in place in the networks in which a device will be deployed.

231 For clarity, settings applied to the ZigBee PRO Multi-MAC (PRO MM) feature set will be marked with  
232 the string **ZigBee PRO MM** and settings applied to the ZigBee-PRO feature set will be marked with  
233 the string **ZigBee-PRO**. Parameters that are unique to Multi-Band (MB or sub GHz interface) will be  
234 called out in PRO MM PRO MM PICS cells including unique timing. If timing and functionality the  
235 same as ZigBee PRO and **ZigBee PRO MM** the cells will be merged to flag timing, behavior, etc.. are  
236 the same on Sub GHz interface and 2.4 GHz interface as part of rev 0.9 release.

237 R22 stack depreciated ZigBee 2007 stack functionality therefore starting in R22 ZigBee 2007  
238 functionality can be removed from the R22 stack.

239 R22 sub GHz interface channel and channel spacing is targeted for Great Britain deployment and  
240 European country deployment.

241 Green Power is only certifiable on 2.4 GHz interface.

242 Functionality not supported by Great Britain will be called out in the PICS, for example sub GHz  
243 routers will not be supported.

244 Channel Change Manager is a function of the Multi-MAC (MM) Coordinator. Channel change is  
245 driven by head end systems which is out of scope of this document. MM and 2.4 GHz devices SHALL  
246 detect a channel change via a keep alive method or other methods and properly form network on new  
247 Sub-GHz channel and/or on new 2.4 GHz channel. Channel change can occur on Sub-GHz network or  
248 2.4 GHz network or both networks. The reason for channel change is outside the scope of this  
249 document.

## 250 6 Knob settings

### 251 6.1 Introduction

252 This section specifies values for parameters specified in the ZigBee specification for tuning the  
 253 operation of the **ZigBee PRO MM** and ZigBee-PRO stack. This section describes settings for both  
 254 **ZigBee PRO MM** and ZigBee-PRO feature sets applied to the ZigBee R22 Specification ([R1])

### 255 6.2 Network settings

256 The network settings for the ZigBee PRO and **ZigBee PRO MM** feature sets are, for the most part,  
 257 described in the restricted PICS captured in Section 10.4. Those setting not covered by the PICS are  
 258 listed in Table 2.

259 **Table 2 – Network settings for this feature set**

| Parameter Name                       | Setting |                  | Comments   |
|--------------------------------------|---------|------------------|--|
| <i>nwkTransactionPersistenceTime</i> | 0x01f4  | ZigBee<br>PRO MM | Note that this value essentially “covers” the MAC attribute of the same name.  |
|                                      |         | ZigBee-<br>PRO   | Note also that, while [R1] implies that this quantity has meaning only in beacon-enabled networks, it may actually be used in beaconless networks as well and, in that case, is a multiplier for <i>aBaseSuperframeDuration</i> . The value here yields a persistence time of 7.68 seconds using the 2.4Ghz symbol rate from [R9] in a non-beaconed network. |
| <i>nwkReportConstantCost</i>         | FALSE   | ZigBee<br>PRO MM | The NWK layer in PRO shall always calculate routing cost on the basis of neighbor link cost and never report constant cost.  |
|                                      |         | ZigBee-<br>PRO   |  |

### 260 6.3 Application settings

261 The application settings for the ZigBee and ZigBee-PRO feature sets are, for the most part, described  
 262 in the restricted PICS captured in Section 10.6. Those setting not covered by the PICS are listed in  
 263 Table 3.

264 **Table 3 – Application settings for this feature set**

| Parameter Name  | Setting |                  | Comments   |
|---|---------|------------------|--|
| Number of active endpoints per sleeping ZigBee end device (maximum) | -       | ZigBee<br>PRO MM | As the responsibility to arrange for caching of service discovery information lies with the end device itself, this parameter is not restricted. |
|   |         | ZigBee-<br>PRO   |  |

| Parameter Name                  | Setting | Comments         |  |
|---------------------------------|---------|------------------|--|
| Config_NWK_Leave_removeChildren | FALSE   | ZigBee<br>PRO MM |  |
|                                 |         | ZigBee-<br>PRO   |  |

## 265 6.4 Security settings

266 The security settings for the ZigBee and ZigBee-PRO feature sets are listed in Table 4.

267 **Table 4 – Security settings for this feature set**

| Parameter Name           | Setting  | Comments         |  |
|--------------------------|--|------------------|--|
| apsSecurityTimeoutPeriod | $TxDuration^1 * (2 * NWK \text{ Maximum Depth}) + (AES \text{ Encrypt/Decrypt times})$ | ZigBee<br>PRO MM | <p>Where AES Encrypt/Decrypt times = 200ms, and</p> <p>Where NWK Maximum Depth is assumed to be 5, meaning every device in the network can be reached in not more than 10 hops, and</p> <p>Where TxDuration is assumed to be 1562.5 octetDurations (50 msec on 2.4GHz), meaning maximum duration of transmitting a packet by a hop,</p> <p>i.e. 700 milliseconds on 2.4 GHz. Note that this timeout assumes worst case AES engine speeds and is not indicative of expected performance for most devices.</p> |
|                          |  | ZigBee-<br>PRO   | <p>Where AES Encrypt/Decrypt times = 200ms, and</p> <p>Where NWK Maximum Depth is assumed to be 15, meaning every device in the network can be reached in not more than 30 hops, and</p> <p>Where TxDuration is assumed to be 1562.5 octetDurations (50 msec on 2.4GHz), meaning maximum duration of transmitting a packet by a hop,</p> <p>i.e. 1.7 seconds on 2.4 GHz. Note that this timeout assumes worst case AES engine speeds and is not indicative of expected performance for most devices.</p>     |

268

<sup>1</sup> CCB 1623

## 269 7 Functional description

270 For the most part, the functioning of ZigBee **PRO MM** and ZigBee-PRO with respect to the NWK  
271 layer, the APS layer and the ZDO is described in [R1]. However, the configuration details and  
272 operational requirements for devices operating under the ZigBee **PRO MM** and ZigBee-PRO feature  
273 sets lead to some special functional considerations, which are detailed here.

### 274 7.1 Device roles

275 The basic roles performed by ZigBee devices in ZigBee **PRO MM** and ZigBee-PRO networks are  
276 determined by their device type:

- 277 • The **ZigBee PRO and PRO MM coordinator** initiates network formation, choosing the  
278 network channel, PAN ID and extended PAN ID in the process, and thereafter should act as a  
279 ZigBee router. It may also perform the roles of trust center and Network Channel Manager.  
280 With respect to binding, the ZigBee coordinator is expected to handle end device bind request  
281 on behalf of all end devices in the network but is not expected to be a global binding  
282 repository for the network.
- 283 • **All ZigBee routers** are called upon to relay traffic on behalf of other devices in the network  
284 and, in particular, are required to act as routing agents on behalf of their end device children,  
285 which will typically not have the neighbor tables, routing tables, route discovery tables or  
286 broadcast transaction tables required to perform routing. Since end devices may sleep, ZigBee  
287 routers and ZigBee coordinators in their role of ZigBee routers may cache discovery  
288 information on behalf of their sleeping end-device children. A ZigBee router may perform the  
289 role of trust center and Network Channel Manager.
- 290 • **All ZigBee end devices** are joined to and managed by ZigBee routers or the ZigBee  
291 coordinator. Because ZigBee-PRO networks are beaconless, there is no built-in  
292 synchronization mechanism between sleeping end devices and their router parents. End  
293 devices are free to set their own duty cycles within the broad polling limits defined by this  
294 feature set. End devices that wish to have their discovery information cached by their parent  
295 or some other device are responsible for using the discovery cache commands to achieve this.

296 Under the ZigBee and ZigBee-PRO feature sets, all devices are expected to manage their own binding  
297 tables if they use binding tables.

298 This section is valid for both the **ZigBee PRO MM** and **ZigBee PRO** feature sets. In R22 release only  
299 one ZigBee MB coordinator is supported per HAN network and no ZigBee MB or sub GHz routers are  
300 supported to simplify deployment for GB market.

301

### 302 7.2 ZigBee: Compatibility with Other Feature sets

303 Devices implementing the ZigBee feature set will advertise a feature set identifier of 1 in their beacon  
304 payloads as stated below in the additional restrictions for PICS item NLF4. In general, such devices  
305 will seek out and join networks in which the ZigBee coordinator (Centralized network) and all ZigBee  
306 routers implement the ZigBee feature set and advertise this fact by placing a feature set identifier of 1  
307 in their beacon payloads.

308 In ZigBee 3.0 ZigBee End Devices (eg. Light, etc..) and ZigBee Router Devices (eg Light switch, etc..) can form multiple distributed networks without a ZigBee coordinator in the network using distributed security. (CCB 2178)

311 In order to provide compatibility with devices implemented according to the ZigBee-PRO feature set,  
312 ZigBee devices shall additionally be able to join networks which advertise a feature set identifier of 2  
313 in their beacon payloads but the device must join the ZigBee-PRO networks as end devices and only  
314 those ZigBee-PRO networks employing standard network security.

315 This section is valid for the **ZigBee PRO MM and ZigBee PRO** feature set.

### 316 **7.3 ZigBee-PRO: Feature set**

### 317 **7.4 Binding tables**

318 Binding tables, if used, shall be located on the source device. While binding is optional, devices that  
319 choose to use binding tables should allocate enough binding table entries to handle their own  
320 communications needs. This suggests that binding table size should be flexible enough that it can be  
321 set, at least at compile time, with some awareness of the actual intended usage of the device.

322 This section is valid for both the **ZigBee PRO MM** and **ZigBee-PRO** feature sets.

### 323 **7.5 Multicast mechanism and groups**

324 Support for APS level multicasts is mandatory to support compatibility with ZigBee devices. The  
325 multicast groups are then established using the application level mechanisms. Support for routing of  
326 network level multicasts is mandatory in the ZigBee-PRO feature set.

327 ZigBee devices do not support network level multicasts.

### 328 **7.6 Trust Center Policies and Security Settings**

329 A ZigBee PRO network shall have a trust center uniquely pointed to by each device in the network  
330 through `apsTrustCenterAddress` within each network member device. It is beyond the scope of the  
331 PRO Feature set to describe how this value is set or whether it is changed and the Trust Center  
332 relocated to another device during operation. The only requirement of the PRO Feature set is that all  
333 devices in the network point to the one unique Trust Center and that the device pointed to as the Trust  
334 Center supplies the security services described by this document.

335 The trust center dictates the security parameters of the network, such as which network key type to use,  
336 settings of the service permissions table, when, if at all, to allow devices to use unsecured association  
337 to the network, and when, if at all, to allow an application master or link key to be set up between two  
338 devices. For interoperability, there are two distinct security settings that can be used within the ZigBee  
339 PRO feature set – a standard and a high security.

340 Networks can exist for periods without a trust center. There are some operations where it is necessary  
341 for the trust center to be operational in the network. These include initial network setup, key changes,  
342 and when joining and rejoining devices require updated keys.

343 A wide range of implementations are possible, depending on the requirements of the application. A  
344 high security trust center may allow the user to install devices “out-of-band”, keep separate link keys  
345 for different devices, optionally ignore `Mgmt_Permit_Joining_req` commands from other nodes, and  
346 configure application trust policies between devices or groups of devices, etc. A standard security trust  
347 center would not offer these advantages, but would not be required to carry the associated costs.

### 348 **7.7 Battery powered devices**

349 ZigBee-PRO networks may, of course, contain battery-powered devices. ZigBee routers are required to  
350 have their receivers enabled whenever they are not transmitting.

351 As mentioned above, ZigBee-PRO networks are beaconless networks and, in the absence of an explicit  
352 mechanism for synchronization and indirect transmission, sleeping devices must set their own duty  
353 cycles and use polling, under ZDO control, if they expect to receive frames that are directed to them  
354 when they are asleep. The feature set provides that parent devices, i.e. ZigBee routers and the ZigBee  
355 coordinator, hold frames for 0x01F4 symbols<sup>2</sup> (7.68 seconds on 2.4 GHz) on behalf of sleeping end  
356 devices and this is also, roughly speaking, the maximum polling rate prescribed here. Devices may  
357 implement a polling interval longer than 0x01F4 symbols<sup>3</sup>, however the application will then have to  
358 handle the potential loss of messages during longer sleep cycles.

## 359 **7.8 Mains powered devices**

360 It is assumed that for most ZigBee-PRO networks, the ZigBee coordinator and ZigBee routers will be  
361 mains-powered and always on in order to properly perform their required roles with respect to the  
362 operation of the network.

## 363 **7.9 Persistent storage**

364 The ZigBee-PRO feature set does not support devices without persistent storage. Devices have  
365 information required to be saved between unintentional restarts and power failures. See [R1] sections  
366 2.2.8.1 and 3.6.8 for details of persistent data in the application and NWK layers. Various security  
367 material shall additionally be stored across power failures. All attributes in sections 4.3.3 and 4.4.10  
368 shall be stored, except that it is not mandatory to store those values which can safely be recovered  
369 using other stored information, or other methods.

## 370 **7.10 Address Reuse**

371 Re-use of previously assigned network short addresses in ZigBee-PRO devices is permitted subject to  
372 execution of the address conflict procedure by the device on the re-used address.

## 373 **7.11 Duty cycle limitations and fragmentation**

374 No mandatory restrictions on 2.4 GHz are defined for intermittent, low channel usage data, although  
375 developers are encouraged to minimise bandwidth usage wherever possible.

376 Large acknowledged unicast transmissions should generally use the APS fragmentation mechanism,  
377 where supported, as this handles retransmissions, duplicate rejection, flow control and congestion  
378 control automatically. Use of the fragmentation mechanism is as specified in the application profile  
379 documents.

380 Sub GHz UK deployment limits Regulatory Duty Cycle to 2.5% when CSMA LBT is used.

### 381 **7.11.1 Vulnerability join**

382 Vulnerability join shall be optional for networked devices, but support for it shall be mandatory for  
383 trust centers. The default for networks is permit joining is off. Permit joining is allowed for  
384 established time periods based on application requirements and specific instructions based on the  
385 system design.

386 Devices that join but do not successfully acquire and use the relevant security keys within the specified  
387 security timeout period shall disassociate themselves from the network, and their short address may be  
388 reused.

---

<sup>2</sup> CCB 1624

<sup>3</sup> CCB 1624

### 389 **7.11.2 Pre-installation**

390 Pre-installation is acceptable. Pre-installed devices are not exempt from the other requirements in this  
391 document. For example, a device certified as a trust center for this feature set shall support  
392 vulnerability installation of new devices, even if it is initially pre-installed.

## 393 **7.12 Security**

394 This feature set is designed to allow the efficient deployment of low cost devices, while also supporting  
395 the security requirements of highly sensitive applications. Installation and network maintenance  
396 procedures and administration are defined with the goal of satisfying the requirements of a range of  
397 applications within a single network infrastructure.

398 To achieve this, two security modes are specified: Standard mode and High Security mode. By default  
399 all applications will use the network key for communications. However, where confidentiality from  
400 other network nodes is required an application shall be permitted to use application link keys. Where  
401 link keys are required by specific application profiles, commands not secured with a link key shall be  
402 processed according to the rules established by the application profile.

403 The trust center plays a key role in determining the security settings in use in the network, and can  
404 optionally be implemented to apply further restrictions on the network.

405 It is recommended that the trust center change the network key if it is discovered that any device has  
406 been stolen or otherwise compromised, and in order to avoid deadlock if all frame counter records  
407 become filled up. It is an application responsibility within the Trust Center to effect the change to the  
408 network key. There is no expectation that the network key be changed when adding a new device.

409 All devices may implement a service permissions table, which they may use to determine which  
410 devices are authorized to issue which commands. Unauthorized commands should not be carried out.

411 The trust center should be implemented to make appropriate choices about when to initiate an  
412 application master/link key shared between two devices. Where restrictions between devices are  
413 required it is the responsibility of the system installer/administrator to deploy a suitably intelligent trust  
414 center and configure it to make relevant checks before initiating sharing of application link keys  
415 between two devices. For example, it might facilitate policies based on certain times, certain  
416 manufacturers or device types, or when the trust center is configured in a certain way, etc. By default a  
417 simple trust center should always allow requests for link keys.

418 Devices may perform the relevant in or out of band authentication or key exchange before acquiring or  
419 using a link key with a new target.

### 420 **7.12.1 Security Modes within PRO Networks**

421 The feature set shall use two security modes: Standard mode and High Security mode.

422 With the Standard mode, network keys and application link keys are permitted for all devices. The  
423 network key type shall be the “standard” network key. It shall not be required that devices perform  
424 entity authentication with their parent on joining nor shall it be required to perform entity  
425 authentication between neighbors. If end devices wish to have a trust center link key, this should be  
426 requested using the request key command. Note that it is optional for the trust center to support link  
427 keys.

428 With the High Security mode, all three key types are permitted and shall be supported by all devices.  
429 The network key type shall be the “high security” network key. It shall be required that devices shall  
430 perform entity authentication with their parent on joining and it shall be required to perform entity  
431 authentication between neighbors. Frames from devices not in the neighbour table shall not be  
432 accepted.

433 When a “standard” type network key is in use, devices shall be permitted to update the network key  
434 when requested to do so by a command appropriately secured with the current network key. When a  
435 “high security” type of network key is in use this shall not be permitted. Additionally, in “high  
436 security”, new trust center link keys may be deployed by SKKE only, i.e.: they shall not be sent using  
437 key transport.

438 Bit 6 of the capabilities field (security bit) shall be used to indicate whether or not a joining (or re-  
439 joining) device supports High Security mode. It shall be set to 0 if the joining or re-joining device does  
440 not support High Security mode (i.e. supports Standard mode), and shall be set to 1 if it does support  
441 High Security mode. The trust center may optionally make use of this information as part of its policy  
442 settings, for example when determining whether or not to allow the device onto the network, or when  
443 determining whether to initiate SKKE with a new joiner or send a link key and/or network key in the  
444 clear to the new device.

445 The above specifications are as currently described in the ZigBee specification. Standard mode and  
446 High Security mode allow implementation of two different strengths of security depending on the  
447 application requirements and the specification supports a device indicating its security capabilities as it  
448 joins the network, thus giving the Trust Center the means to be able to accept or reject the device based  
449 on its policy.

450

## 8 Instructions for completing the PICS proforma

451

452

453

454

455

456

*If a given implementation is claimed to conform to this standard, the actual PICS proforma to be filled in by a supplier shall be technically equivalent to the text of the PICS proforma in this document, and shall preserve the numbering and naming and the ordering of the PICS proforma.*

457

458

459

A PICS which conforms to this document shall be a conforming PICS proforma completed in accordance with the instructions for completion given in this section.

460

461

462

The main part of the PICS is a fixed-format questionnaire, divided. Answers to the questionnaire are to be provided in the rightmost column, either by simply marking an answer to indicate a restricted choice (such as Yes or No), or by entering a value, set, or range of values.

## 9 Identification of the implementation

463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508

### System under test (SUT) identification

SUT name: **EmberZnet 6.7.7**

Software Version: **EmberZnet 6.7.7**

Hardware Version: **EFR32MG21x (Series 2) Family**

Operating system (optional): \_\_\_\_\_

### Specification Version Numbers at time of certification

ZigBee PRO Specification Revision: **R22**

Approved Errata Text to the ZigBee PRO Specification (if any): \_\_\_\_\_

ZigBee PRO Test Plan Revision: \_\_\_\_\_

Approved Errata Text to the ZigBee PRO Test Plan (if any): \_\_\_\_\_

### Product supplier Contact Information

Company Name: **Silicon Laboratories**

Contact Name: **John Loukota**

Address: **400 West Cesar Chavez Austin, TX 78701**

Telephone number: **617-951-1226**

Facsimile number: \_\_\_\_\_

Email address: \_\_\_\_\_ [john.loukota@silabs.com](mailto:john.loukota@silabs.com) \_\_\_\_\_

Additional information: \_\_\_\_\_

Signature **John M Loukota**

## 509 10 Protocol implementation conformance statement (PICS) 510 proforma

### 511 10.1 Abbreviations and special symbols

512 *Notations for requirement status:*

M Mandatory

O Optional

O.n Optional, but support of at least one of the group of options labeled O.n is required.

N/A Not applicable

X Prohibited

513

514 *“item”*: Conditional, status dependent upon the support marked for the “item”.

515 For example, if FDT1 and FDT2 are both marked “O.1” this indicates that the status is optional but at  
516 least one of the features described in FDT1 and FDT2 is required to be implemented, if this  
517 implementation is to follow the standard of which this PICS Proforma is a part.

518 In below table if a Multi-MAC (MM) device list bands supports, if supported concurrently with 2.4  
519 GHz, and maximum Power level supported in each band.

### 520 10.2 ZigBee device types

| Item number | Item description  | Reference                  | ZigBee Status | Feature set Support | Additional Constraints | Platform Support |
|-------------|---|----------------------------|---------------|---------------------|------------------------|------------------|
| FDT1        | Is this device capable of acting as a ZigBee coordinator?   | [R1]/Preface (Definitions) |               | ZigBee PRO MM       | O.1                    | No               |
|             |   |                            |               | ZigBee-PRO          | O.1                    | Yes              |
| FDT2        | Is this device capable of acting as a ZigBee router?<br><br>Note: Great Britain not supporting sub GHz router in R22 but can be deployed in other European markets. | [R1]/Preface (Definitions) |               | ZigBee PRO MM       | O.1                    | No               |
|             |   |                            |               | ZigBee-PRO          | O.1                    | Yes              |
| FDT3        | Is this a ZigBee end device?  | [R1]/Preface (Definitions) |               | ZigBee PRO MM       | O.1                    | No               |
|             |   |                            |               | ZigBee-PRO          | O.1                    | Yes              |

521

522 **10.3 IEEE 802.15.4 PICS**523 **10.3.1 FDT2 and FDT3 network join options**

| Item number | Item description   | Reference    | ZigBee Status                   | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|--|--------------|---------------------------------|---------------------|-------------------------------|------------------------|------------------|
| JN1         | The device joins a network by scanning and then associating (client)   | [R9] 7.3.1.1 | FDT1:X<br>FDT2:O<br>FDT3:O      | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |                        | Yes              |
|             |  |              |                                 | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |                        | Yes              |
| JN10        | The device supports joining a network by associating (server)          | [R9] 7.3.1.1 | FDT1: O<br>FDT2: O<br>FDT3: N/A | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |              |                                 | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| JN2         | The device joins a network by using an orphan scan (client)            | [R9] 7.3.2.3 | FDT1: N/A<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |  |              |                                 | ZigBee-PRO          | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes              |
| JN20        | The device supports joining a network by using an orphan scan (server) | [R9] 7.3.2.3 | FDT1: O<br>FDT2: O<br>FDT3: N/A | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |              |                                 | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |

524

525 **10.3.2 IEEE 802.15.4 PHY**526 **10.3.2.1 Radio frequency of operation**

| Item number | Item description   | Reference              | ZigBee Status  | Feature set Support |                | Additional Constraints | Platform Support |
|-------------|--|------------------------|----------------|---------------------|----------------|------------------------|------------------|
| RF1         | The device operates at Sub GHz GB/OFCOM – Page 28 to 31 and defined channels | [R9] 6.1.1, 6.1.2, 6.6 | O <sup>3</sup> | ZigBee PRO MM       | O <sup>3</sup> |                        | Yes              |
|             |  |                        |                | ZigBee-PRO          | O <sup>3</sup> |                        | No               |
| RF2         | The device operates at a frequency of 2.4 GHz.                               | [R9] 6.1.1, 6.1.2, 6.5 | O <sup>3</sup> | ZigBee PRO MM       | O <sup>3</sup> |                        | Yes              |
|             |  |                        |                | ZigBee-PRO          | O <sup>3</sup> |                        | Yes              |

527 O<sup>3</sup>: at least one option must be selected.

528

529 **10.3.2.2 Clear channel assessment**

| Item number | Item description                             | Reference  | ZigBee Status  | Feature set Support |                | Additional Constraints | Platform Support |
|-------------|--|------------|----------------|---------------------|----------------|------------------------|------------------|
| CCA1        | Mode 1: Energy above threshold is supported. | [R9] 6.7.9 | O <sup>4</sup> | ZigBee PRO MM       | O <sup>4</sup> |                        | Yes              |
|             |  |            |                | ZigBee-PRO          | O <sup>4</sup> |                        | Yes              |
| CCA2        | Mode 2: Carrier sense only is supported.     | [R9] 6.7.9 | O <sup>4</sup> | ZigBee PRO MM       | O <sup>4</sup> |                        | No               |
|             |  |            |                | ZigBee-PRO          | O <sup>4</sup> |                        | No               |

| Item number | Item description  | Reference  | ZigBee Status  | Feature set Support |                | Additional Constraints | Platform Support |
|-------------|---|------------|----------------|---------------------|----------------|------------------------|------------------|
| CCA3        | Mode 3: Carrier sense with energy above threshold is supported. | [R9] 6.7.9 | O <sup>4</sup> | ZigBee PRO MM       | O <sup>4</sup> |                        | No               |
|             |   |            |                | ZigBee-PRO          | O <sup>4</sup> |                        | No               |

530 O<sup>4</sup>: at least one option must be selected.  
531

### 532 10.3.3 IEEE 802.15.4 MAC

#### 533 10.3.3.1 Channel access

| Item number | Item description                      | Reference    | ZigBee Status | Feature set Support |   | Additional Constraints   | Platform Support   |
|-------------|---------------------------------------|--------------|---------------|---------------------|---|--|--|
| CA1         | A super-frame structure is supported. | [R9] 7.5.1.1 | O             | ZigBee PRO MM       | X |  | No   |
|             |                                       |              |               | ZigBee-PRO          | X |  | No   |
| CA2         | Un-slotted CSMA-CA is supported.      | [R9] 7.5.1.1 | M             | ZigBee PRO MM       | M | All devices shall set their MIB values as follows:<br><i>macBeaconOrder</i> = 0x0f,<br><i>macSuperframeOrder</i> = 0x0f. | Yes  |
|             |                                       |              |               | ZigBee-PRO          | M |  | All devices shall set their MIB values as follows:<br><i>macBeaconOrder</i> = 0x0f,<br><i>macSuperframeOrder</i> = 0x0f. |
| CA3         | Slotted CSMA-CA is supported.         | [R9] 7.5.1.1 | CA1: M        | ZigBee PRO MM       | X |  | No   |
|             |                                       |              |               | ZigBee-PRO          | X |  | No   |

| Item number | Item description                 | Reference    | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|----------------------------------|--------------|---------------|---------------------|---|------------------------|------------------|
| CA4         | Super-frame timing is supported. | [R9] 7.5.1.1 | CA1: M        | ZigBee PRO MM       | X |                        | No               |
|             |                                  |              |               | ZigBee-PRO          | X |                        | No               |

534

535 **10.3.3.2 Guaranteed time slots**

| Item number | Item description  | Reference  | ZigBee Status      | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|--|--------------------|---------------------|---|------------------------|------------------|
| GTS1        | Guaranteed time slots are supported ( <i>server</i> ).  | [R9] 7.5.7   | FDT1: O            | ZigBee PRO MM       | X |                        | No               |
|             |   |  |                    | ZigBee-PRO          | X |                        | No               |
| GTS2        | Guaranteed time slots are supported ( <i>client</i> ).  | [R9] 7.5.7   | FDT2: O<br>FDT3: O | ZigBee PRO MM       | X |                        | No               |
|             |   |  |                    | ZigBee-PRO          | X |                        | No               |
| GTS3        | The client device has the ability to request a GTS. Operations include: <ul style="list-style-type: none"> <li>• Allocation requests</li> <li>• De-allocation requests</li> <li>• [MLME-GTS.request primitive]</li> <li>• [MLME-GTS.confirm primitive]</li> <li>• Transmission of the GTS request command.</li> </ul> | [R9] 7.1.7.1,<br>7.1.7.2,<br>7.3.3.1,<br>7.5.7.2,<br>7.5.7.4 | GTS2: M            | ZigBee PRO MM       | X |                        | No               |
|             |   |  |                    | ZigBee-PRO          | X |                        | No               |

| Item number | Item description   | Reference  | ZigBee Status      | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|--|--|--------------------|---------------------|---|------------------------|------------------|
| GTS4        | The server has the ability to process GTS requests. Operations include: <ul style="list-style-type: none"> <li>• Allocation requests</li> <li>• De-allocation requests</li> <li>• Re-allocation requests</li> <li>• [MLME-GTS.indication primitive]</li> <li>• Reception and processing of the GTS request command.</li> </ul> | [R9] 7.1.7.3, 7.3.3.1, 7.5.7.2, 7.5.7.4, 7.5.7.5 | GTS1: M            | ZigBee PRO MM       | X |                        | No               |
|             |  |  |                    | ZigBee-PRO          | X |                        | No               |
| GTS5        | The server can manage the GTSs.  | [R9] 7.5.7                                       | GTS1: M            | ZigBee PRO MM       | X |                        | No               |
|             |  |  |                    | ZigBee-PRO          | X |                        | No               |
| GTS6        | The server can perform CAP maintenance.  | [R9] 7.5.7.1                                     | GTS1: M            | ZigBee PRO MM       | X |                        | No               |
|             |  |  |                    | ZigBee-PRO          | X |                        | No               |
| GTS7        | The device can transmit and/or receive data within a GTS.  | [R9] 7.5.7.3                                     | GTS1: M<br>GTS2: M | ZigBee PRO MM       | X |                        | No               |
|             |  |  |                    | ZigBee-PRO          | X |                        | No               |

537 **10.3.3.3 Scanning**

| Item number | Item description   | Reference                        | ZigBee Status     | Feature set Support |                               | Additional Constraints   | Platform Support |
|-------------|--|----------------------------------|-------------------|---------------------|-------------------------------|--|------------------|
| S1          | The device can perform some form of channel scan. Operations include: <ul style="list-style-type: none"> <li>Scanning mechanism</li> <li>[MLME-SCAN.request primitive]</li> <li>[MLME-SCAN.confirm primitive]</li> </ul> | [R9] 7.1.11.1, 7.1.11.2, 7.5.2.1 | M                 | ZigBee PRO MM       | M                             | All devices shall be able to perform at least an active scan.  | Yes              |
|             |  |                                  |                   | ZigBee-PRO          | M                             | All devices shall be able to perform at least an active scan.  | Yes              |
| S2          | The device can perform an energy detection scan.   | [R9] 7.5.2.1.1                   | FDT1: M           | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X | Network devices shall perform an energy detection scan on request from the next higher layer.  | No               |
|             |  |                                  |                   | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | The coordinator shall perform an energy detection scan on each available channel in the active channel mask before starting a network. | Yes              |
| S3          | The device can perform an active scan. Operations include: <ul style="list-style-type: none"> <li>Transmission of the beacon request command.</li> </ul>   | [R9] 7.3.2.4, 7.5.2.1.2          | FDT1: M<br>JN1: M | ZigBee PRO MM       | M                             | All devices shall perform an active scan on each available channel in the active channel mask.   | Yes              |
|             |  |                                  |                   | ZigBee-PRO          | M                             | All devices shall perform an active scan on each available channel in the active channel mask.   | Yes              |
| S4          | The device can perform a passive scan.   | [R9] 7.5.2.1.3                   | O                 | ZigBee PRO MM       | X                             |  | Yes              |
|             |  |                                  |                   | ZigBee-PRO          | X                             |  | Yes              |

| Item number | Item description   | Reference  | ZigBee Status      | Feature set Support |                               | Additional Constraints   | Platform Support |
|-------------|--|--|--------------------|---------------------|-------------------------------|--|------------------|
| S5          | <p>The client can perform an orphan scan. Operations include:</p> <ul style="list-style-type: none"> <li>Orphan device realignment.</li> <li>Transmission of the orphan notify command.</li> <li>Reception and processing of the coordinator realignment command.</li> </ul>   | [R9] 7.3.2.3, 7.3.2.5, 7.5.2.1.4                   | JN2: M             | ZigBee PRO MM       | JN2:M                         |  | Yes              |
|             |  |  |                    | ZigBee-PRO          | JN2:M                         |  | Yes              |
| S6          | <p>The server can perform orphan scan processing. Operations include:</p> <ul style="list-style-type: none"> <li>[MLME-ORPHAN.indicate primitive]</li> <li>[MLME-ORPHAN.response primitive]</li> <li>Reception and processing of the orphan notify command.</li> <li>Transmission of the coordinator realignment command.</li> </ul> | [R9] 7.1.8.1, 7.1.8.2, 7.3.2.3, 7.3.2.5, 7.5.2.1.4 | FDT1: O<br>FDT2: O | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X | Network rejoin is the preferred mechanism for devices to use, however, orphan scan may be used and the parent devices shall support orphan scan. | No               |
|             |  |  |                    | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | Network rejoin is the preferred mechanism for devices to use, however, orphan scan may be used and the parent devices shall support orphan scan. | Yes              |
| S7          | The server can receive and process a beacon request command.   | [R9] 7.3.2.4                                       | S3 &<br>FDT1: M    | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |  | No               |
|             |  |  |                    | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |  | Yes              |

539 **10.3.3.4 PAN identifier conflict resolution**

| Item number | Item description   | Reference                      | ZigBee Status      | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|--|--------------------------------|--------------------|---------------------|-------------------------------|------------------------|------------------|
| PICR1       | PAN identifier conflict resolution is supported ( <i>server</i> ). Operations include: <ul style="list-style-type: none"> <li>Reception and processing of the PAN identifier conflict notification command.</li> <li>Transmission of the coordinator realignment command.</li> </ul> | [R9] 7.3.2.2, 7.3.2.5, 7.5.2.2 | FDT1: O            | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: X |                        | No               |
|             |  |                                |                    | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: X |                        | Yes              |
| PICR2       | PAN identifier conflict resolution is supported ( <i>client</i> ). Operations include: <ul style="list-style-type: none"> <li>Transmission of the PAN identifier conflict notification command.</li> <li>Reception and processing of the coordinator realignment command.</li> </ul> | [R9] 7.3.2.2, 7.3.2.5, 7.5.2.2 | FDT2: O<br>FDT3: O | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: X |                        | No               |
|             |  |                                |                    | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: X |                        | Yes              |

540

541 **10.3.3.5 PAN start**

| Item number | Item description  | Reference                        | ZigBee Status                 | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|---|----------------------------------|-------------------------------|---------------------|-------------------------------|------------------------|------------------|
| PS1         | Starting a PAN is supported. Operations include: <ul style="list-style-type: none"> <li>[MLME-START.request primitive]</li> <li>[MLME-START.confirm primitive]</li> </ul> | [R9] 7.1.14.1, 7.1.14.2, 7.5.2.3 | FDT1: M<br>FDT2: M<br>FDT3: O | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |   |                                  |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |

542

543 **10.3.3.6 Association**

| Item number | Item description   | Reference                               | ZigBee Status      | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|--|---|--------------------|---------------------|-------------------------------|------------------------|------------------|
| A1          | Association is supported ( <i>server</i> ).  | [R9] 7.5.3.1                            | FDT1: O<br>FDT2: O | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |   |                    | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| A2          | Association is supported ( <i>client</i> ).  | [R9] 7.5.3.1                            | FDT2: O<br>FDT3: O | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |                        | Yes              |
|             |  |   |                    | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |                        | Yes              |
| A3          | The server can process association requests. Operations include: <ul style="list-style-type: none"> <li>• [MLME-ASSOCIATE.indicate primitive]</li> <li>• [MLME-ASSOCIATE.response primitive]</li> <li>• Reception and processing of the association request command.</li> <li>• Transmission of the association response command.</li> </ul> | [R9] 7.1.3.2, 7.1.3.3, 7.3.1.1, 7.3.1.2 | A1: M              | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |   |                    | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |

| Item number | Item description  | Reference                               | ZigBee Status | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|---|---|---------------|---------------------|-------------------------------|------------------------|------------------|
| A4          | The client can perform association. Operations include: <ul style="list-style-type: none"> <li>• [MLME-ASSOCIATE.request primitive]</li> <li>• [MLME-ASSOCIATE.confirm primitive]</li> <li>• Transmission of the association request command.</li> <li>• Reception and processing of the association response command.</li> </ul> | [R9] 7.1.3.1, 7.1.3.4, 7.3.1.1, 7.3.1.2 | A2: M         | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |                        | Yes              |
|             |   |   |               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |                        | Yes              |

544

545 **10.3.3.7 Disassociation**

| Item number | Item description  | Reference                      | ZigBee Status | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|---|--------------------------------|---------------|---------------------|-------------------------------|------------------------|------------------|
| D1          | The device can request a disassociation. Operations include: <ul style="list-style-type: none"> <li>• [MLME-DISASSOCIATE.request primitive]</li> <li>• [MLME-DISASSOCIATE.confirm primitive]</li> <li>• Transmission of the disassociation notify command.</li> </ul> | [R9] 7.1.4.1, 7.1.4.3, 7.3.1.3 | O             | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: X |                        | No               |
|             |   |                                |               | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: X |                        | No               |

| Item number | Item description  | Reference             | ZigBee Status | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|---|-----------------------|---------------|---------------------|-------------------------------|------------------------|------------------|
| D2          | The client can react to a disassociation from the server. Operations include: <ul style="list-style-type: none"> <li>[MLME-DISASSOCIATE.indicate primitive]</li> <li>Reception and processing of the disassociation notify command.</li> </ul>      | [R9] 7.1.4.2, 7.3.1.3 | O             | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: X |                        | No               |
|             |   |                       |               | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: X |                        | No               |
| D3          | The server can react to a disassociation from a client device. Operations include: <ul style="list-style-type: none"> <li>[MLME-DISASSOCIATE.indicate primitive]</li> <li>Reception and processing of the disassociation notify command.</li> </ul> | [R9] 7.1.4.2, 7.3.1.3 | O             | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: X |                        | No               |
|             |   |                       |               | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: X |                        | No               |

546

547 **10.3.3.8 Beacon synchronization**

| Item number | Item description  | Reference    | ZigBee Status | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|---|--------------|---------------|---------------------|-------------------------------|------------------------|------------------|
| BS1         | Beacon notification is supported. Operations include: <ul style="list-style-type: none"> <li>[MLME-BEACON-NOTIFY.indication primitive]</li> </ul> | [R9] 7.1.5.1 | O             | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: M |                        | Yes              |
|             |   |              |               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: M |                        | Yes              |

| Item number | Item description  | Reference                      | ZigBee Status | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|---|--------------------------------|---------------|---------------------|-------------------------------|------------------------|------------------|
| BS2         | The client can synchronize to a beacon. Operations include: <ul style="list-style-type: none"> <li>(Tracking only for beacon networks)</li> <li>[MLME-SYNC.request primitive]</li> <li>[MLME-SYNC-LOSS.indication primitive]</li> </ul> | [R9] 7.1.15.1, 7.1.15.2, 7.5.4 | O             | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: X |                        | No               |
|             |   |                                |               | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: X |                        | No               |

548

549 **10.3.3.9 Transmission**

| Item number | Item description  | Reference                                      | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|--|---------------|---------------------|---|------------------------|------------------|
| T1          | Frame transmission is supported. Operations include: <ul style="list-style-type: none"> <li>Frame construction</li> <li>[MCPS-DATA.request primitive]</li> <li>[MCPS-DATA.confirm primitive]</li> <li>Transmission of data frames.</li> </ul> | [R9] 7.1.1.1, 7.1.1.2, 7.2.1, 7.2.2.2, 7.5.6.1 | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |   |  |               | ZigBee-PRO          | M |                        | Yes              |
| T2          | Implicit (command frame) transmission confirmation is supported. Operations include: <ul style="list-style-type: none"> <li>[MLME-COMM-STATUS.indication primitive]</li> </ul>  | [R9] 7.1.12.1                                  | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |   |  |               | ZigBee-PRO          | M |                        | Yes              |

550

551 **10.3.3.10 Reception**

| Item number | Item description  | Reference                    | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|------------------------------|---------------|---------------------|---|------------------------|------------------|
| R1          | Frame reception is supported.<br>Operations include: <ul style="list-style-type: none"> <li>• Data frame deconstruction</li> <li>• [MCPS-DATA.indication primitive]</li> <li>• Reception of data frames.</li> </ul> | [R9] 7.1.1.3, 7.2.1, 7.2.2.2 | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |   |                              |               | ZigBee-PRO          | M |                        | Yes              |
| R2          | Receiver control is supported.<br>Operations include: <ul style="list-style-type: none"> <li>• [MLME-RX-ENABLE.request primitive]</li> <li>• [MLME-RX-ENABLE.confirm primitive]</li> </ul>                          | [R9] 7.1.10.1, 7.1.10.2      | O             | ZigBee PRO MM       | O |                        | No               |
|             |   |                              |               | ZigBee-PRO          | O |                        | No               |
| R3          | Filtering and rejection is supported.   | [R9] 7.5.6.2                 | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |   |                              |               | ZigBee-PRO          | M |                        | Yes              |
| R4          | Promiscuous mode is supported.  | [R9] 7.5.6.6                 | O             | ZigBee PRO MM       | O |                        | No               |
|             |   |                              |               | ZigBee-PRO          | O |                        | No               |

552

553 **10.3.3.11 Transaction handling**

| Item number | Item description  | Reference                             | ZigBee Status       | Feature set Support |                               | Additional Constraints                                       | Platform Support |
|-------------|---|---------------------------------------|---------------------|---------------------|-------------------------------|--|------------------|
| TH1         | Transaction handling is supported ( <i>server</i> ).  | [R9] 7.5.5                            | FDT1: O<br>FDT2: O  | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X | The server shall be able to handle at least one transaction. | No               |
|             |   |                                       |                     | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | The server shall be able to handle at least one transaction. | Yes              |
| TH2         | Transaction handling is supported ( <i>client</i> ).  | [R9] 7.5.5                            | FDT2: O<br>FDT3: O  | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: M |  | Yes              |
|             |   |                                       |                     | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: M |  | Yes              |
| TH3         | The server can manage transactions to its devices. Operations include: <ul style="list-style-type: none"> <li>Transaction queuing</li> <li>Reception and processing of the data request command.</li> </ul> | [R9] 7.5.5, 7.1.1.4, 7.1.1.5, 7.3.2.1 | TH1: M              | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |  | No               |
|             |   |                                       |                     | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |  | Yes              |
| TH30        | The server can manage transaction purging operations: <ul style="list-style-type: none"> <li>[MCPS-PURGE.request primitive]</li> <li>[MCPS-PURGE.confirm primitive]</li> </ul>                              | [R9] 7.1.1.4, 7.1.1.5, 7.3.2.1        | TH1: M              | ZigBee PRO MM       | O                             |  | No               |
|             |   |                                       |                     | ZigBee-PRO          | O                             |  | No               |
| TH4         | The client can extract data from the coordinator following an indication of data in a beacon.   | [R9] 7.5.6.3                          | TH2: O <sup>5</sup> | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: X |  | No               |
|             |   |                                       |                     | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: X |  | No               |

| Item number | Item description  | Reference                        | ZigBee Status       | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|---|----------------------------------|---------------------|---------------------|-------------------------------|------------------------|------------------|
| TH5         | The client can poll for data. Operations include: <ul style="list-style-type: none"> <li>[MLME-POLL.request primitive]</li> <li>[MLME-POLL.confirm primitive]</li> <li>Transmission of the data request command.</li> </ul> | [R9] 7.1.16.1, 7.1.16.2, 7.3.2.1 | TH2: O <sup>5</sup> | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: M |                        | Yes              |
|             |   |                                  |                     | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: M |                        | Yes              |

554 O<sup>5</sup>: At least one of these options must be supported.

### 555 10.3.3.12 Acknowledgement service

| Item number | Item description   | Reference               | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support          |
|-------------|--|-------------------------|---------------|---------------------|---|------------------------|---------------------------|
| AS1         | The acknowledgement service is supported.                            | [R9] 7.5.6.4            | O             | ZigBee PRO MM       | M |                        | Yes                       |
|             |  |                         |               | ZigBee-PRO          | M |                        | Yes                       |
| AS2         | The device can transmit, receive and process acknowledgement frames. | [R9] 7.2.2.3            | AS1: M        | ZigBee PRO MM       | M |                        | Yes                       |
|             |  |                         |               | ZigBee-PRO          | M |                        | Yes                       |
| AS3         | Deprecated   | [R9] 7.5.6.4.2, 7.5.6.5 | AS1: M        | ZigBee PRO MM       | X |                        | Click here to enter text. |
|             |  |                         |               | ZigBee-PRO          | X |                        | Click here to enter text. |

| Item number | Item description               | Reference    | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|--------------------------------|--------------|---------------|---------------------|---|------------------------|------------------|
| AS4         | Retransmissions are supported. | [R9] 7.5.6.5 | AS1: M        | ZigBee PRO MM       | M |                        | Yes              |
|             |                                |              |               | ZigBee-PRO          | M |                        | Yes              |

556

557 **10.3.3.13 MIB management**

| Item number | Item description  | Reference                      | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|--------------------------------|---------------|---------------------|---|------------------------|------------------|
| MM1         | MIB management is supported. Operations include: <ul style="list-style-type: none"> <li>MIB attribute storage</li> </ul>  | [R9] 7.4.2                     | O             | ZigBee PRO MM       | M |                        | Yes              |
|             |   |                                |               | ZigBee-PRO          | M |                        | Yes              |
| MM2         | The device supports the reading of MIB attributes. Operations include: <ul style="list-style-type: none"> <li>[MLME-GET.request primitive]</li> <li>[MLME-GET.confirm primitive]</li> </ul>                                     | [R9] 7.1.6.1, 7.1.6.2, 7.4.2   | MM1: O        | ZigBee PRO MM       | M |                        | Yes              |
|             |   |                                |               | ZigBee-PRO          | M |                        | Yes              |
| MM3         | The device supports the writing of MIB attributes. Operations include: <ul style="list-style-type: none"> <li>MIB attribute verification</li> <li>[MLME-SET.request primitive]</li> <li>[MLME-SET.confirm primitive]</li> </ul> | [R9] 7.1.13.1, 7.1.13.2, 7.4.2 | MM1: O        | ZigBee PRO MM       | M |                        | Yes              |
|             |   |                                |               | ZigBee-PRO          | M |                        | Yes              |

558

559 **10.3.3.14 MAC security**

| Item number | Item description  | Reference                    | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|------------------------------|---------------|---------------------|---|------------------------|------------------|
| MS1         | The device supports ACL mode. Operations include: <ul style="list-style-type: none"> <li>• ACL storage</li> <li>• ACL mode usage</li> </ul> | [R9] 7.4.2, 7.5.8.1, 7.5.8.3 | O             | ZigBee PRO MM       | X |                        | No               |
|             |   |                              |               | ZigBee-PRO          | X |                        | No               |
| MS2         | The device supports secured mode.   | [R9] 7.5.8.4                 | O             | ZigBee PRO MM       | X |                        | No               |
|             |   |                              |               | ZigBee-PRO          | X |                        | No               |

560

561

562 **10.3.3.15 Device reset**

| Item number | Item description  | Reference             | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|-----------------------|---------------|---------------------|---|------------------------|------------------|
| DR1         | The device is able to reset. Operations include: <ul style="list-style-type: none"> <li>• [MLME-RESET.request primitive]</li> <li>• [MLME-RESET.confirm primitive]</li> </ul> | [R9] 7.1.9.1, 7.1.9.2 | O             | ZigBee PRO MM       | O |                        | No               |
|             |   |                       |               | ZigBee-PRO          | O |                        | No               |

563

564 **10.4 Network layer PICS**565 **10.4.1 ZigBee network frame format**

| Item number | Item description   | Reference  | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|--|------------|---------------|---------------------|---|------------------------|------------------|
| GFF1        | Does the device support the general ZigBee network frame | [R1]/3.3.1 |               | ZigBee PRO MM       | M |                        | Yes              |

| Item number | Item description | Reference | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|------------------|-----------|---------------|---------------------|---|------------------------|------------------|
|             | format?          |           |               | ZigBee-PRO          | M |                        | Yes              |

566

567 **10.4.2 Major capabilities of the ZigBee network layer**

568 Tables in the following sub-clauses detail the capabilities of NWK layer for ZigBee devices.

569 **10.4.2.1 Network layer functions**

| Item number | Item description  | Reference                      | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|--------------------------------|---------------|---------------------|---|------------------------|------------------|
| NLF1        | Does the network layer support transmission of data by the next higher layer? | [R1]/3.2.1.1, 3.2.1.2, 3.6.2.1 | M             | ZigBee-PRO MM       | M |                        | Yes              |
|             |   |                                |               | ZigBee-PRO          | M |                        | Yes              |
| NLF2        | Does the network layer support reception of data by the next higher layer?    | [R1]/3.2.1.3, 3.6.2.2          | M             | ZigBee-PRO MM       | M |                        | Yes              |
|             |   |                                |               | ZigBee-PRO          | M |                        | Yes              |
| NLF3        | Does the network layer support discovery of existing ZigBee networks?         | [R1]/3.2.2.1, 3.2.2.2          | M             | ZigBee-PRO MM       | M |                        | Yes              |
|             |   |                                |               | ZigBee-PRO          | M |                        | Yes              |

| Item number | Item description  | Reference                            | ZigBee Status                | Feature set Support        |                               | Additional Constraints   | Platform Support |
|-------------|---|--------------------------------------|------------------------------|----------------------------|-------------------------------|--|------------------|
| NLF4        | Does the network layer support formation of Distributed ZigBee networks?<br>(CCB 2137)                                | [R1]/3.2.2.5,                        | O                            | ZigBee PRO MM / ZigBee PRO | FDT1: X<br>FDT2: M<br>FDT3: M | Devices using the ZigBee feature set shall set:<br><br>Feature set = 1<br><i>nwkProtocolVersion</i> = 2<br><br>and shall advertise these values in their beacon payload in response to MAC beacon requests.<br><br>Devices using the ZigBee feature set shall also set:<br><br><i>nwkSecurityLevel</i> = 1         | No               |
|             | Does the network layer support formation of Centralized ZigBee networks?  | [R1]/3.2.2.5,                        | O                            | ZigBee PRO MM / ZigBee PRO | FDT1: M<br>FDT2: M<br>FDT3: X | Devices using the ZigBee-PRO feature set shall set:<br><br>Feature set = 2<br><i>nwkProtocolVersion</i> = 2<br><br>and shall advertise these values in their beacon payload in response to MAC beacon requests.<br><br>Devices using the ZigBee-PRO feature set shall also set:<br><br><i>nwkSecurityLevel</i> = 5 | Yes              |
| NLF5        | Can the network layer permit other devices to join the network of which it is a part (and also deny such permission)? | [R1]/3.2.2.5,<br>3.2.2.6,<br>3.6.1.2 | FDT1:M,<br>FDT2:M,<br>FDT3:X | ZigBee PRO MM              | FDT1: M<br>FDT2: M<br>FDT3: X |  | No               |
|             |   |                                      |                              | ZigBee-PRO                 | FDT1: M<br>FDT2: M<br>FDT3: X |  | Yes              |
| NLF6        | Can the device start as a router?   | [R1]/3.2.2.7,<br>3.2.2.8             | FDT1:X,<br>FDT2:M,<br>FDT3:X | ZigBee PRO MM              | FDT1: X<br>FDT2: M<br>FDT3: X |  | No               |
|             |   |                                      |                              | ZigBee-PRO                 | FDT1: X<br>FDT2: M<br>FDT3: X |  | Yes              |
| NLF60       | Can the network layer perform energy detection scans at the request of the next                                       | [R1]/3.2.2.9,<br>3.2.2.10            | M                            | ZigBee PRO MM              | FDT1: M<br>FDT2: M<br>FDT3: X | NLME-ED-SCAN is mandatory for the coordinator and optional for all routers on a ZigBee network.  | No               |

| Item number | Item description   | Reference                            | ZigBee Status                   | Feature set Support |                               | Additional Constraints   | Platform Support |
|-------------|--|--------------------------------------|---------------------------------|---------------------|-------------------------------|--|------------------|
|             | higher layer?  |                                      |                                 | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | NLME-ED-SCAN is mandatory for the coordinator and all routers on a PRO network.  | Yes              |
| NLF7        | Can the device request membership in a ZigBee network?   | [R1]/3.2.2.11, 3.2.2.13, 3.6.1.4     | FDT1: N/A<br>FDT2: M<br>FDT3: M | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes              |
|             |  |                                      |                                 | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes              |
| NLF70       | Can the device request to join or rejoin a network using the end device timeout or MAC_PHY polling procedure? (CCB 2144)                   | [R1]/3.2.2.14, 3.2.2.15, 3.6.1.4.3.1 | FDT1: N/A<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | FDT1: X<br>FDT2: O<br>FDT3: O |  | Yes              |
|             |  |                                      |                                 | ZigBee-PRO          | FDT1: X<br>FDT2: O<br>FDT3: O |  | Yes              |
| NLF71       | Can the device request to join / rejoin a network using the rejoin command frame and associated procedure?                                 | [R1]/3.2.2.11, 3.2.2.13, 3.6.1.4.2.1 | FDT1: N/A<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes              |
|             |  |                                      |                                 | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes              |
| NLF72       | Can the network layer be directed by the next higher layer to change the operating channel of the network of which it is currently a part? | [R1]/3.2.2.11, 3.2.2.13              | O                               | ZigBee PRO MM       | M                             | The network layer can be directed by the next higher layer to change the operating channel of the network of which it is currently part. | Yes              |
|             |  |                                      |                                 | ZigBee-PRO          | M                             |  | Yes              |
| NLF8        | Can the device respond to requests to join the network of which it is a part?  | [R1]/3.6.1.4.1.2, 3.6.1.4.2.2        | FDT1: M<br>FDT2: M<br>FDT3: X   | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |  | No               |
|             |  |                                      |                                 | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |  | Yes              |

| Item number | Item description  | Reference     | ZigBee Status                   | Feature set Support |                               | Additional Constraints  | Platform Support          |
|-------------|---|---------------|---------------------------------|---------------------|-------------------------------|---|---------------------------|
| NLF81       | Does the network layer of a device inform the next higher layer when a second device has joined or rejoined its network as a child?             | [R1]/3.2.2.12 | FDT1: M<br>FDT2: M<br>FDT3: X   | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |   | No                        |
|             |   |               |                                 | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |   | Yes                       |
| NLF9        | Does the network layer employ the Distributed Address Mechanism to generate a unique network address to assign to a joining device?             | [R1]/3.6.1.6  | FDT1: O<br>FDT2: O<br>FDT3: N/A | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X | The ZigBee feature set always employs the distributed addressing scheme with:<br><br><i>nwkMaxDepth</i> = 5<br><i>nwkMaxChildren</i> = 20<br><i>nwkMaxRouters</i> = 6   | No                        |
|             |   |               |                                 | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: X |   | No                        |
| NLF90       | Does the network layer employ the Stochastic Addressing Scheme to generate a unique network address to assign to a joining or rejoining device? | [R1]/3.6.1.7  | FDT1: O<br>FDT2: O<br>FDT3: N/A | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: X |   | No                        |
|             |   |               |                                 | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | The ZigBee-PRO feature set employs stochastic address allocation.<br><br>The follow parameter values are defined:<br><br><i>nwkAddrAlloc</i> = 2<br><i>nwkUseTreeRouting</i> = FALSE<br><i>nwkMaxDepth</i> = 15<br><br>Note that <i>nwkMaxDepth</i> above is only used to compute timeouts and shall not limit the actual network radius, as this feature set does not use tree-based addressing.<br><br>The parameter <i>nwkMaxChildren</i> is not restricted in this feature set. | Yes                       |
| NLF100      | Does the network layer employ the Higher Layer Address Assignment   | Deprecated    | X                               | ZigBee PRO MM       | X                             |   | Click here to enter text. |

| Item number | Item description  | Reference                           | ZigBee Status                   | Feature set Support |                               | Additional Constraints   | Platform Support          |
|-------------|---|-------------------------------------|---------------------------------|---------------------|-------------------------------|--|---------------------------|
|             | Mechanism to generate a unique network address to assign to a joining device?                                     |                                     |                                 | ZigBee-PRO          | X                             |  | Click here to enter text. |
| NLF10       | Can the next higher layer request that a particular device be "pre-joined" to it using the DIRECT-JOIN procedure? | [R1]/3.2.2.14, 3.2.2.15, 3.6.1.4.3  | FDT1: O<br>FDT2: O<br>FDT3: X   | ZigBee-PRO MM       | X                             | This service is useful for testing and may be allowed as a part of test procedures at the option of the stack developer. | No                        |
|             |   |                                     |                                 | ZigBee-PRO          | X                             | This service is useful for testing and may be allowed as a part of test procedures at the option of the stack developer. | No                        |
| NLF11       | Can the device make a request to leave the network?   | [R1]/3.2.2.16, 3.2.2.18, 3.6.1.10.1 | O                               | ZigBee-PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes                       |
|             |   |                                     |                                 | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes                       |
| NLF12       | Can the device make a request that one of its child devices leave the network?                                    | [R1]/3.2.2.16, 3.2.2.18, 3.6.1.10.2 | FDT1: O<br>FDT2: O<br>FDT3: N/A | ZigBee-PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |  | No                        |
|             |   |                                     |                                 | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |  | Yes                       |
| NLF13       | Can the network layer process network leave commands from child devices?  | [R1]/3.6.1.10.3                     | FDT1: M<br>FDT2: M<br>FDT3: N/A | ZigBee-PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |  | No                        |
|             |   |                                     |                                 | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |  | Yes                       |

| Item number | Item description  | Reference                         | ZigBee Status                   | Feature set Support |                               | Additional Constraints  | Platform Support |
|-------------|---|-----------------------------------|---------------------------------|---------------------|-------------------------------|---|------------------|
| NLF130      | Can the network layer process network leave commands from parent devices?                         | [R1]/3.6.1.10.3                   | FDT1: N/A<br>FDT2: M<br>FDT3: M | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |   | Yes              |
|             |   |                                   |                                 | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |   | Yes              |
| NLF131      | Does the network layer inform the next higher layer if the device itself has left the network?    | [R1]/3.2.2.17                     | M                               | ZigBee PRO MM       | M                             |   | Yes              |
|             |   |                                   |                                 | ZigBee-PRO          | M                             |   | Yes              |
| NLF14       | Does the device support changing of the ZigBee coordinator configuration in an operating network? | [R1]/3.2.2.3, 3.2.2.4, 3.6.1.11   | FDT1: O<br>FDT2: X<br>FDT3: X   | ZigBee PRO MM       | FDT1: M<br>FDT2: X<br>FDT3: X | The ZigBee coordinator shall change the logical channel and PAN ID when directed to by the Network Channel Manager. | No               |
|             |   |                                   |                                 | ZigBee-PRO          | FDT1: M<br>FDT2: X<br>FDT3: X |   | Yes              |
| NLF15       | Does the device support changing of the ZigBee router configuration in an operating network?      | [R1]/3.2.2.7, 3.2.2.8             | FDT1: X<br>FDT2: O<br>FDT3: X   | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: X | The ZigBee router shall change the logical channel and PAN ID when directed to by the Network Channel Manager.      | No               |
|             |   |                                   |                                 | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: X |   | Yes              |
| NLF16       | Does the network layer support reset?   | [R1]/3.2.2.19, 3.2.2.20, 3.6.1.12 | M                               | ZigBee PRO MM       | M                             |   | Yes              |
|             |   |                                   |                                 | ZigBee-PRO          | M                             |   | Yes              |

| Item number | Item description  | Reference               | ZigBee Status                 | Feature set Support |                               | Additional Constraints   | Platform Support |
|-------------|---|-------------------------|-------------------------------|---------------------|-------------------------------|--|------------------|
| NLF17       | Does the network layer allow the next higher layer to synchronize with or extract data from the device's ZigBee coordinator or router?  | [R1]/3.2.2.22, 3.2.2.23 | FDT1: X<br>FDT2: O<br>FDT3: M | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: M | <p>Recommended polling rates for end devices using this feature set:</p> <p>Maximum: once per 7.5s<br/>Minimum: once per hour</p> <p>Note that these values represent the (rather loose) recommended boundaries on polling rate for normal operation only.</p> <p>Additionally, the polling rate established to meet this requirement shall have a maximum value less than <i>nwkTransactionPersistenceTime</i> to ensure that child devices can poll frequently enough to retrieve messages prior to expiration in the indirect message queue of their parent.</p> <p>The polling rate established here also does not consider APS acknowledgement timeout (which is much shorter than <i>nwkTransaction-PersistenceTime</i>). If APS acknowledged messages are directed to sleeping end devices, then the polling rate of those destination devices may be adjusted to occur more frequently than the APS acknowledgement timeout.</p> | Yes              |
|             |   |                         |                               | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: M |  | Yes              |
| NLF18       | Does the network layer report a loss of synchronization with the device's ZigBee router or ZigBee coordinator to the next higher layer? | [R1]/3.2.2.23           | FDT1: X<br>FDT2: O<br>FDT3: M | ZigBee PRO MM       | X                             |  | No               |
|             |   |                         |                               | ZigBee-PRO          | X                             |  | No               |
| NLF19       | Does the network layer offer the next higher layer the ability to retrieve network information base (NIB) attributes?                   | [R1]/3.2.2.26, 3.2.2.27 | M                             | ZigBee PRO MM       | M                             |  | Yes              |

| Item number | Item description  | Reference                        | ZigBee Status                 | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|---|----------------------------------|-------------------------------|---------------------|-------------------------------|------------------------|------------------|
|             |   |                                  |                               | ZigBee-PRO          | M                             |                        | Yes              |
| NLF20       | Does the network layer offer the next higher layer the ability to set network information base (NIB) attributes?      | [R1]/3.2.2.28, 3.2.2.29          | M                             | ZigBee PRO MM       | M                             |                        | Yes              |
|             |   |                                  |                               | ZigBee-PRO          | M                             |                        | Yes              |
| NLF110      | Does the network layer support network status reporting to the next higher layer?                                     | [R1]/3.2.2.30                    | M                             | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |   |                                  |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NLF111      | Does the network layer support Route Discovery?   | [R1]/3.2.2.31, 3.2.2.32, 3.6.3.5 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |   |                                  |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NLF112      | Does the network layer support Route Discovery requests with DstAddrMode of 0x00 in support of Many-to-One discovery? | [R1]/3.2.2.31, 3.2.2.32, 3.6.3.5 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | X                             |                        | No               |

| Item number | Item description  | Reference                               | ZigBee Status                 | Feature set Support |                               | Additional Constraints   | Platform Support |
|-------------|---|---|-------------------------------|---------------------|-------------------------------|--|------------------|
|             |   |   |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: X | Initiation of a Many-to-One route discovery is optional, and should be used in cases where there are relatively few concentrators in the network. Application developers should weigh the trade-offs between Many-to-One discovery and unicast discovery before deploying. | Yes              |
| NLF113      | Does the network layer support Route Discovery requests with DstAddrMode of 0x01 in support of Multicast Group Discovery?       | [R1]/3.2.2.31, 3.2.2.32, 3.6.3.5, 3.6.6 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | X                             |  | No               |
|             |   |   |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: X | Initiation of route discovery commands where DstAddrMode is 0x01 (Multicast Group Discovery) is optional.  | Yes              |
| NLF114      | Does the network layer support Route Discovery requests with DstAddrMode of 0x02 in support of the discovery of Unicast routes? | [R1]/3.2.2.31, 3.2.2.32, 3.6.3.5        | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | FDT1: O<br>FDT2: O<br>FDT3: X | Initiation of route discovery commands where DstAddrMode is 0x02 (Unicast) is optional.  | No               |
|             |   |   |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee coordinators and ZigBee routers shall support reception and correct handling of unicast discovery commands.   | Yes              |
| NLF115      | Does the network layer employ tree routing?   | 3.6.3.3                                 | O                             | ZigBee PRO MM       | M                             | Devices using the ZigBee stack profile must set:<br><i>nwkUseTreeRouting</i> = TRUE  | Yes              |
|             |   |   |                               | ZigBee-PRO          | X                             | Devices using the ZigBee-PRO stack profile shall set:<br><i>nwkUseTreeRouting</i> = FALSE  | No               |
| NLF21       | Does the network layer calculate routing cost based on probability of   | 3.6.3.1                                 | O                             | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |  | No               |

| Item number | Item description   | Reference           | ZigBee Status                 | Feature set Support |                               | Additional Constraints  | Platform Support |
|-------------|--|---------------------|-------------------------------|---------------------|-------------------------------|---|------------------|
|             | reception?   |                     |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |   | Yes              |
| NLF22       | Does the network layer maintain a routing table and route discovery table? | [R1]/3.6.3.2        | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee coordinators and ZigBee routers shall maintain a routing table and a route discovery table as follows:<br><br>Routing table (minimum): 8 entries<br><br>Route discovery table (minimum): 4 entries   | No               |
|             |  |                     |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee coordinators and ZigBee routers shall maintain a routing table and a route discovery table as follows:<br><br>Routing table (minimum): 10 entries<br><br>An aging algorithm is recommended but is beyond the scope of this specification.<br><br>Route discovery table entries (minimum): 4 entries<br><br>The Route discovery table entries shall be managed as described in [R1] sub-clause 3.6.3.6. | Yes              |
| NLF220      | Does the network layer maintain a route record table?                      | [R1]/3.5.2, 3.6.3.2 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | X                             |   | No               |
|             |  |                     |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: X |   | Yes              |
| NLF221      | Does the network layer maintain a multicast group ID table?                | [R1]/3.6.6.1        | FDT1:O,<br>FDT2:O,<br>FDT3:X  | ZigBee PRO MM       | X                             | ZigBee coordinators and ZigBee routers that use this stack profile shall set <i>nwkUseMulticast</i> to FALSE.   | No               |
|             |  |                     |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: X |   | Yes              |

| Item number | Item description  | Reference             | ZigBee Status | Feature set Support |   | Additional Constraints  | Platform Support |
|-------------|---|-----------------------|---------------|---------------------|---|---|------------------|
| NLF23       | Does the network layer reserve routing capacity for route repair operations?<br><br>(Note: This capability has been removed from the ZigBee specification as of r08).   | None                  | X             | ZigBee PRO MM       | X |   | No               |
|             |   |                       |               | ZigBee-PRO          | X |   | No               |
| NLF24       | Does the device implement beacon collision-avoidance measures?  | [R1]/3.6.4            | O             | ZigBee PRO MM       | X |   | No               |
|             |   |                       |               | ZigBee-PRO          | X |   | No               |
| NLF25       | Does the network layer support router re-enumeration as a route repair method?<br><br>(Note: This capability has been removed from the ZigBee specification as of r10). | None                  | X             | ZigBee PRO MM       | X |   | No               |
|             |   |                       |               | ZigBee-PRO          | X |   | No               |
| NLF26       | Does the network layer assume that links are symmetrical and establish forward and reverse routes at the same time?   | [R1]/3.5.2, 3.6.3.5.2 | O             | ZigBee PRO MM       | X | Devices using the ZigBee stack profile must set:<br><i>nwkSymLink</i> = FALSE   | No               |
|             |   |                       |               | ZigBee-PRO          | M | Devices using the ZigBee-PRO stack profile shall set:<br><i>nwkSymLink</i> = TRUE   | Yes              |
| NLF27       | Does the network layer maintain a neighbor table or tables in order to store information about nearby devices?  | [R1]/3.6.1.5          | M             | ZigBee PRO MM       | M | ZigBee coordinators and ZigBee routers shall maintain a neighbor table or tables as follows:<br><br>ZigBee coordinator (minimum): 24 entries<br><br>ZigBee router (minimum): 25 entries<br><br>ZigBee end device (minimum): 1 entry | Yes              |

| Item number | Item description   | Reference                                     | ZigBee Status              | Feature set Support |                               | Additional Constraints   | Platform Support |
|-------------|--|---|----------------------------|---------------------|-------------------------------|--|------------------|
|             |  |   |                            | ZigBee-PRO          | M                             | <p>ZigBee coordinators and ZigBee routers shall maintain a neighbor table or tables as follows:</p> <p>ZigBee coordinator (minimum): (Number of child end devices accepted) plus 16</p> <p>ZigBee router (minimum): (Number of child end devices accepted) plus 16</p> <p>ZigBee end device: 1<br/>(Note: End Device shall support a minimum of 5 neighbor table entries and that entry shall be for their parent) (CCB 2091)</p> <p>Where (Number of child end devices accepted) is the minimum number of end device children that a particular router or coordinator in the network is configured to accept.</p> | Yes              |
| NLF28       | Does the network layer buffer frames pending route discovery or route repair operations? | [R1]/3.6.3.5.1                                | O                          | ZigBee-PRO MM       | O                             |  | Yes              |
|             |  |   |                            | ZigBee-PRO          | O                             |  | Yes              |
| NLF29       | Does the network layer buffer data frames on behalf of end device that are its children? | [R1]/3.6.5                                    | FDT1:M<br>FDT2:M<br>FDT3:X | ZigBee-PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee router and coordinator devices shall set:<br><br>Number of frames buffered on behalf of sleeping end devices (minimum): 1   | No               |
|             |  |   |                            | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | Note that this means 1 frame TOTAL not 1 frame for each end device. In other words, it is up to the implementer to put in some buffering but routers should not be overburdened with, possibly unnecessary, buffering.   | Yes              |
| NLF30       | Is the device capable of participating in a beacon-oriented                              | [R1]/Preface Definitions and Network Topology | O                          | ZigBee-PRO MM       | X                             | On invocation of the NLME-NETWORK-FORMATION.request or NLME-START-ROUTER.request   | No               |

| Item number | Item description   | Reference      | ZigBee Status                 | Feature set Support |                               | Additional Constraints  | Platform Support |
|-------------|--|----------------|-------------------------------|---------------------|-------------------------------|---|------------------|
|             | network?   | sections       |                               | ZigBee-PRO          | X                             | primitives, devices shall employ:<br>BeaconOrder = 0x0f<br>SuperframeOrder = 0x0f   | No               |
| NLF31       | Does the network layer support the detection of address conflicts? | [R1]/3.6.1.9   | O                             | ZigBee-PRO MM       | X                             |   | No               |
|             |  |                |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | Address conflict detection is mandatory for this stack profile (nwkUniqueAddr = FALSE). The coordinator and all routers shall implement the Address Conflict procedure.   | Yes              |
| NLF32       | Does the network layer support resolving address conflicts?        | [R1]/3.6.1.9.3 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee-PRO MM       | X                             |   | No               |
|             |  |                |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | Address conflict resolution is mandatory for this stack profile (nwkUniqueAddr = FALSE). The coordinator and all routers shall implement the Address Conflict procedure.  | Yes              |
| NLF33       | Does the network layer support the detection of PAN ID conflicts?  | [R1]/3.6.1.13  | O                             | ZigBee-PRO MM       | FDT1:M<br>FDT2:M<br>FDT3:X    | PAN ID conflict resolution is mandatory for the coordinator and routers. Notification of a PAN ID conflict via the NWK Status command frame directed to the nwkManagerAddr is mandatory for all routers and the coordinator. The nwkManagerAddr is required to process all NWK Status command frames directed to it by the coordinator and routers. | No               |
|             |  |                |                               | ZigBee-PRO          | FDT1:M<br>FDT2:M<br>FDT3:X    |   | Yes              |
| NLF34       | Does the device support resolving PAN ID conflicts?                | [R1]/3.6.1.13  | O                             | ZigBee-PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X | PAN ID conflict resolution is mandatory for the coordinator and routers. Notification of a PAN ID conflict via the  | No               |

| Item number | Item description | Reference | ZigBee Status | Feature set Support |                               | Additional Constraints   | Platform Support |
|-------------|------------------|-----------|---------------|---------------------|-------------------------------|--|------------------|
|             |                  |           |               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | NWK Status command frame directed to the nwkManagerAddr is mandatory for all routers and the coordinator. The nwkManagerAddr is required to process all NWK Status command frames directed to it by the coordinator and routers. | Yes              |

570

571 **10.4.2.2 Network layer frames**

| Item number | Item description   | Reference             | ZigBee Status                 | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|--|-----------------------|-------------------------------|---------------------|-------------------------------|------------------------|------------------|
| NDF1        | Does the device support the origination of network data frames?      | [R1]/3.3.2.1, 3.6.2.1 | M                             | ZigBee PRO MM       | M                             |                        | Yes              |
|             |  |                       |                               | ZigBee-PRO          | M                             |                        | Yes              |
| NDF2        | Does the device support the receipt of network data frames?          | [R1]/3.3.2.1, 3.6.2.2 | M                             | ZigBee PRO MM       | M                             |                        | Yes              |
|             |  |                       |                               | ZigBee-PRO          | M                             |                        | Yes              |
| NDF3        | Does the device support the relaying of unicast network data frames? | [R1]/3.3.2.1, 3.6.3.3 | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |                       |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |

572

| Item number | Item description   | Reference               | ZigBee Status                 | Feature set Support |                               | Additional Constraints   | Platform Support |
|-------------|--|-------------------------|-------------------------------|---------------------|-------------------------------|--|------------------|
| NDF4        | Does the device support relaying of broadcast network data frames? | [R1]/3.3.2.1, 3.6.5     | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X | Devices using the ZigBee stack profile must set:<br><br>Broadcast Transaction Table size: 9 (minimum)<br><br><i>nwkBroadcastDeliveryTime</i> = 0x44AA <sup>4</sup> Octet durations (9 seconds on 2.4 GHz)<br><i>nwkPassiveAckTimeout</i> = 0x3D09 <sup>5</sup> Octet durations <sup>6</sup> (500 ms on 2.4 GHz) maximum<br><i>nwkMaxBroadcastRetries</i> = 2   | No               |
|             |  |                         |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | Devices using the ZigBee-PRO stack profile shall set:<br><br>Broadcast Transaction Table size: 9 (minimum)<br><br><i>nwkBroadcastDeliveryTime</i> = 0x44AA <sup>7</sup> Octet durations (9 seconds on 2.4 GHz)<br><i>nwkPassiveAckTimeout</i> = 0x3D09 <sup>8</sup> Octet Durations <sup>9</sup> (500 ms on 2.4 GHz) maximum<br><i>nwkMaxBroadcastRetries</i> = 2<br><br>Application designers should take care to use multicast and broadcast sparingly due to the limitations of the broadcast bandwidth of a network. | Yes              |
| NDF100      | Does the device support relaying of multicast network data frames? | [R2]/3.3.2.1, 3.6.6     | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | X                             |  | No               |
|             |  |                         |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X | The coordinator and all routers in a PRO network shall be able to relay member mode multicast network data frames.   | Yes              |
| NDF101      | Does the device support the relaying of source routed network      | [R2]/3.3.2.1, 3.6.3.3.2 | FDT1:O,<br>FDT2:O,<br>FDT3:X  | ZigBee PRO MM       | X                             |  | No               |

<sup>4</sup> CCB 1629<sup>5</sup> CCB 1633<sup>6</sup> CCB 1633<sup>7</sup> CCB 1629<sup>8</sup> CCB 1633<sup>9</sup> CCB 1633

| Item number | Item description   | Reference       | ZigBee Status | Feature set Support                                     | Additional Constraints   | Platform Support |
|-------------|--|-----------------|---------------|---|--|------------------|
|             | data frames?   |                 |               | ZigBee-PRO<br>FDT1: M<br>FDT2: M<br>FDT3: X             |  | Yes              |
| NDF102      | Does the device support conditionally setting the End Device Initiator bit of the NWK frame control?             | [R1]/3.3.1.1.9  |               | ZigBee-PRO<br>FDT1: X<br>FDT2: X<br>FDT3: M             |  | Yes              |
| NDF103      | Does the device support processing NWK data frames with the End Device Initiator bit set?                        | [R1]/3.6.2.2    |               | ZigBee-PRO<br>FDT1: M<br>FDT2: M<br>FDT3: X             |  | Yes              |
| NDF104      | Does the device support aging out children that have not sent a keepalive within the configured timeout?         | [R1]/3.6.10     |               | ZigBee-PRO<br>FDT1: M<br>FDT2: M<br>FDT3: X             |  | Yes              |
| NDF105      | Does the device support reception of a MAC Data poll as an End Device Keepalive?                                 | [R1]/3.6.10.4   | O             | ZigBee-PRO<br>FDT1: O<br>FDT2: O<br>FDT3: M             | It is permissible to not have support for this if NDF106 is supported.   | Yes              |
| NDF106      | Does the device support reception of an end device timeout keep alive? (CCB 2144)                                | [R1]/3.6.10.5   | M             | ZigBee-PRO<br>FDT1: MFDT2: M<br>FDT3: M                 | It is permissible to not have support for this if NDF105 is supported.   | Yes              |
| NDF107      | Does the device support persistence of the end device configuration for end devices?                             | [R1]/3.6.10.8   |               | ZigBee-PRO<br>FDT1: M<br>FDT2: M<br>FDT3: X             |  | Yes              |
| NDF108      | Does the device support sending a NWK leave message to an end device that is NOT in its neighbor table?          | [R1]/3.6.10.4.1 | M             | ZigBee-PRO / ZigBee MB<br>FDT1: M<br>FDT2: M<br>FDT3: X | It is permissible to not have support for this if NDF109 is supported<br>NDF105 must be supported to support NDF108 (CCB 2239).  | Yes              |
| NDF109      | Does the device support sending a ZDO_Mgmt_Leave_Req message to an end device that is NOT in its neighbor table? | [R1]/3.6.10.4.1 |               | ZigBee-PRO / ZigBee MB<br>FDT1: M<br>FDT2: M<br>FDT3: X | It is permissible to not have support for this if NDF108 is supported.<br>NDF105 must be supported to support NDF109 (CCB 2239). | Yes              |

| Item number | Item description   | Reference                | ZigBee Status | Feature set Support       |                               | Additional Constraints   | Platform Support |
|-------------|--|--------------------------|---------------|---------------------------|-------------------------------|--|------------------|
| NDF110      | Does the end device support timing itself when it does not send a keepalive to its router parent within its timeout?                 | [R1]/3.6.10.7            |               | ZigBee-PRO /<br>ZigBee MB | FDT1: X<br>FDT2: X<br>FDT3: O |  | Yes              |
| F-GP1       | Does the device support the Green Power Feature?<br>(CCB 2240)   | [R1]/2.1.2               | O             | ZigBee-PRO /<br>ZigBee MB | FDT1: O<br>FDT2: O<br>FDT3: O | Refer to Refer to [R7] and [R8] for additional details<br><br>The Green Power cluster if implemented shall use endpoint 242. | Yes              |
| NDF201      | Does the device support reception of ZigBee NWK frames with non-incremental sequence number in the NWK header Sequence Number field? | [R1]/4.3.1.1,<br>4.3.1.2 | M             | ZigBee-PRO /<br>ZigBee MB | FDT1: X<br>FDT2: X<br>FDT3: O | Included use of GP.<br><br>Unconditionally mandatory for R22 CORE stack and later for all devices (CCB 2240)                 | Yes              |

573

### 10.4.2.3 Network command frames

| Item number | Item description   | Reference                | ZigBee Status                 | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|--|--------------------------|-------------------------------|---------------------|-------------------------------|------------------------|------------------|
| NCF1        | Does the device support the origination of route request command frames? | [R1]/3.4.1,<br>3.6.3.5.1 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee<br>PRO MM    | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |                          |                               | ZigBee-<br>PRO      | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF2        | Does the device support the receipt of route request command frames?     | [R1]/3.4.1,<br>3.6.3.5.2 | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee<br>PRO MM    | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |                          |                               | ZigBee-<br>PRO      | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF3        | Does the device support the relaying of route request command            | [R1]/3.4.1,<br>3.6.3.5.2 | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee<br>PRO MM    | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |

| Item number | Item description   | Reference                                 | ZigBee Status                 | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|--|---|-------------------------------|---------------------|-------------------------------|------------------------|------------------|
|             | frames?  |   |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF4        | Does the device support the origination of route reply command frames?     | [R1]/3.4.2, 3.6.3.5.2                     | FDT1:M,<br>FDT2:M,<br>FDT3:X  | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |   |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF5        | Does the device support the receipt of route reply command frames?         | [R1]/3.4.2, 3.6.3.5.3                     | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |   |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF6        | Does the device support the relaying of route reply command frames?        | [R1]/3.4.2, 3.6.3.5.3                     | FDT1:M,<br>FDT2:M,<br>FDT3:X  | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |   |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF7        | Does the device support the transmission of network status command frames? | [R1]/3.4.3, 3.6.1.9.3, 3.6.3.3, 3.6.3.7.1 | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |   |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF8        | Does the device support the receipt of network status command frames?      | [R1]/3.4.3, 3.6.1.9.3, 3.6.3.7.1          | M                             | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |

| Item number | Item description  | Reference                 | ZigBee Status                 | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|---|---------------------------|-------------------------------|---------------------|-------------------------------|------------------------|------------------|
|             |   |                           |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF9        | Does the device support the relaying of network command frames? In particular, does it support the relaying of those command frames, specifically network status, network report and network update, which require relaying but for which there are no special per-hop processing requirements? | [R1]/3.4.3, 3.4.9, 3.4.10 | FDT1:M,<br>FDT2:M,<br>FDT3:X  | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |   |                           |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF100      | Does the device support the origination of leave command frames?  | [R1]/3.4.4, 3.6.1.10      | FDT1:O,<br>FDT2:O,<br>FDT3:O  | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: M |                        | Yes              |
|             |   |                           |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: M |                        | Yes              |
| NCF101      | Does the device support the receipt of leave command frames?  | [R1]/3.4.4, 3.6.1.10      | M                             | ZigBee PRO MM       | M                             |                        | Yes              |
|             |   |                           |                               | ZigBee-PRO          | M                             |                        | Yes              |
| NCF103      | Does the device support the origination of route record command frames?   | [R1]/3.4.5, 3.6.3.5.4     | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | X                             |                        | No               |
|             |   |                           |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |

| Item number | Item description   | Reference               | ZigBee Status                 | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|--|-------------------------|-------------------------------|---------------------|-------------------------------|------------------------|------------------|
| NCF104      | Does the device support the receipt of route record command frames?        | [R1]/3.4.5, 3.6.3.5.4   | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | X                             |                        | No               |
|             |  |                         |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF105      | Does the device support the relaying of route record command frames?       | [R1]/3.4.5, 3.6.3.5.4   | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | X                             |                        | No               |
|             |  |                         |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF106      | Does the device support the transmission of rejoin request command frames? | [R1]/3.4.6, 3.7.1.3.2.1 | FDT1:X<br>FDT2:M<br>FDT3:M    | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |                        | Yes              |
|             |  |                         |                               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |                        | Yes              |
| NCF107      | Does the device support the reception of rejoin request command frames?    | [R1]/3.4.6, 3.7.1.3.2.2 | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
|             |  |                         |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF108      | Does the device support the transmission of rejoin response                | [R1]/3.4.7, 3.7.1.3.2.2 | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |

| Item number | Item description  | Reference               | ZigBee Status                 | Feature set Support |                               | Additional Constraints   | Platform Support |
|-------------|---|-------------------------|-------------------------------|---------------------|-------------------------------|--|------------------|
|             | command frames?   |                         |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |  | Yes              |
| NCF109      | Does the device support the reception of rejoin response command frames?  | [R1]/3.4.7, 3.7.1.3.2.1 | FDT1: X<br>FDT2: M<br>FDT3: M | ZigBee-PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes              |
|             |   |                         |                               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes              |
| NCF110      | Does the device support the generation of a network report command frame. | [R1]/3.4.9, 3.6.1.13.1  | O                             | ZigBee-PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes              |
|             |   |                         |                               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes              |
| NCF111      | Does the device support the reception of a network report command frame   | [R1]/3.4.9, 3.6.1.13.2  | O                             | ZigBee-PRO MM       | FDT1: O<br>FDT2: O<br>FDT3: X | While this feature is optional, one device in the network must be designated as the network manager and for that device this feature is mandatory. | No               |
|             |   |                         |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: X |  | Yes              |
| NCF112      | Does the device support the generation of a network update command frame. | [R1]/3.4.10, 3.6.1.13.2 | O                             | ZigBee-PRO MM       | FDT1: O<br>FDT2: O<br>FDT3: X | While this feature is optional, one device in the network must be designated as the network manager and for that device this feature is mandatory. | No               |
|             |   |                         |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: X |  | Yes              |
| NCF113      | Does the device support the reception of a network update                 | [R1]/3.4.10, 3.6.1.13.3 | O                             | ZigBee-PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: M |  | Yes              |

| Item number          | Item description   | Reference                      | ZigBee Status                 | Feature set Support |                               | Additional Constraints | Platform Support |
|----------------------|--|--------------------------------|-------------------------------|---------------------|-------------------------------|------------------------|------------------|
|                      | command frame  |                                |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: M |                        | Yes              |
| NCF114               | Does the device support the generation of a link status command frame. | [R1]/3.4.8, 3.6.3.4.1          | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee-PRO MM       | X                             |                        | No               |
|                      |  |                                |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF115               | Does the device support the reception of a link status command frame.  | [R1]/3.4.8, 3.6.1.5, 3.6.3.4.2 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee-PRO MM       | X                             |                        | No               |
|                      |  |                                |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
| NCF116 <sup>10</sup> | Does the device support ignoring the NWK leave command?                | [R1]/3.5.2, 3.6.1.10.3         | FDT1:O<br>FDT2: O<br>FDT3:X   | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: X |                        | Yes              |

---

<sup>10</sup> CCB 1279

574 **10.5 Security PICS**575 **10.5.1 ZigBee security roles**

| Item number | Item description  | Reference       | ZigBee Status                 | Feature set Support |                               | Additional Constraints   | Platform Support |
|-------------|---|-----------------|-------------------------------|---------------------|-------------------------------|--|------------------|
| SR1         | Is this device capable of acting in the role of a trust center? | [R1]/1.4, 4.6.2 | FDT1: M<br>FDT2: O<br>FDT3: X | ZigBee<br>PRO<br>MM | FDT1: M<br>FDT2: O<br>FDT3: X | Upon initial network formation, the coordinator must at least temporarily serve as the trust center. After formation, at least one of the routers or the coordinator must be capable of acting in the role of the trust center. It is an application responsibility to transition the trust center from the coordinator to another router device pointed to by apsTrustCenterAddress within all devices in the network if desired. For the device whose address is apsTrustCenterAddress, it is mandatory to act in the role of the trust center. All devices in the network shall maintain a single consistent definition of apsTrustCenterAddress. It is possible, under application control, to change apsTrustCenterAddress during later network operation, however, it is the application's responsibility to ensure that all devices in the network are notified of the change.<br><br>Trust center must be collocated with ZC (short address 0x0000) throughout network life (CCB 2178) | No               |
|             |   |                 |                               |                     |                               |  | ZigBee-<br>PRO   |

576

577

578 **10.5.2 ZigBee trust center capabilities**

| Item number | Item description   | Reference             | ZigBee Status | Feature set Support |          | Additional Constraints  | Platform Support          |
|-------------|--|-----------------------|---------------|---------------------|----------|---|---------------------------|
| TCC1        | Is this device capable of acting as a ZigBee trust center in high security mode? | [R1]/1.4.1.2, 4.6.2.1 | SR1:O.2       | ZigBee PRO MM       | X        |   | Click here to enter text. |
|             |  |                       |               | ZigBee-PRO          | SR1: O.2 | <p>Every PRO network shall have a Trust Center either running in Standard or High Security mode</p> <p>The device designated as the Trust Center shall be declared a concentrator in a PRO network and a Many to One route shall be created to the Trust Center.</p> <p>At least one of TCC1 or TCC2 must be supported if the device supports SR1.</p> <p>Trust center must be collocated with ZC (short address 0x0000) throughout network life (CCB 2178)</p> | Click here to enter text. |
| TCC2        | Is this device capable of acting as a ZigBee trust center in standard mode?      | [R1]/1.4.1.2, 4.6.2.2 | SR1:O.2       | ZigBee PRO MM       | M        |   | No                        |
|             |  |                       |               | ZigBee-PRO          | SR1: O.2 | <p>Every PRO network shall have a Trust Center either running in Standard or High Security mode</p> <p>The device designated as the Trust Center shall be declared a concentrator in a PRO network and a Many to One route shall be created to the Trust Center.</p> <p>At least one of TCC1 or TCC2 must be supported if the device supports SR1.</p> <p>Trust center must be collocated with ZC (short address 0x0000) throughout network life (CCB 2178)</p> | Yes                       |

579

580

581 **10.5.3 Modes of operation**

| Item number | Item description  | Reference             | ZigBee Status | Feature set Support |     | Additional Constraints   | Platform Support          |
|-------------|---|-----------------------|---------------|---------------------|-----|--|---------------------------|
| MOO1        | Is this device capable of operating in a network secured with a trust center running in high security mode? | [R1]/1.4.1.2, 4.6.2.1 | O.3           | ZigBee PRO MM       | X   |  | Click here to enter text. |
|             |   |                       |               | ZigBee-PRO          | O.3 | A PRO device shall join a PRO network either running in Standard or High Security mode.<br>At least one of MOO1 or MOO2 must be supported. | Click here to enter text. |
| MOO2        | Is this device capable of operating in a network secured with a trust center running in standard mode?      | [R1]/1.4.1.2,         | O.3           | ZigBee PRO MM       | M   |  | Yes                       |
|             |   |                       |               | ZigBee-PRO          | O.3 | A PRO device shall join a PRO network either running in Standard or High Security mode.<br>At least one of MOO1 or MOO2 must be supported. | Yes                       |

582

583 **10.5.4 Security levels**

| Item number | Item description  | Reference      | ZigBee Status | Feature set Support |   | Additional Constraints  | Platform Support          |
|-------------|---|----------------|---------------|---------------------|---|---|---------------------------|
| SL1         | Is this device capable of supporting security level 0x01? | [R1]/4.5.1.1.1 | O.4           | ZigBee PRO MM       | X | The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05. | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | X |   | Click here to enter text. |
| SL2         | Is this device capable of supporting security level 0x02? | [R1]/4.5.1.1.1 | O.4           | ZigBee PRO MM       | X | The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05. | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | X |   | Click here to enter text. |

| Item number | Item description  | Reference      | ZigBee Status | Feature set Support |   | Additional Constraints  | Platform Support          |
|-------------|---|----------------|---------------|---------------------|---|---|---------------------------|
| SL3         | Is this device capable of supporting security level 0x03? | [R1]/4.5.1.1.1 | O.4           | ZigBee PRO MM       | X | The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05. | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | X |   | Click here to enter text. |
| SL4         | Is this device capable of supporting security level 0x04? | [R1]/4.5.1.1.1 | O.4           | ZigBee PRO MM       | X | The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05. | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | X |   | Click here to enter text. |
| SL5         | Is this device capable of supporting security level 0x05? | [R1]/4.5.1.1.1 | O.4           | ZigBee PRO MM       | M | The device shall apply security to outgoing frames or accept secured incoming frames using only level 0x05 (i.e., ENC-MIC-32)   | Yes                       |
|             |   |                |               | ZigBee-PRO          | M |   | Yes                       |
| SL6         | Is this device capable of supporting security level 0x06? | [R1]/4.5.1.1.1 | O.4           | ZigBee PRO MM       | X | The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05. | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | X |   | Click here to enter text. |
| SL7         | Is this device capable of supporting security level 0x07? | [R1]/4.5.1.1.1 | O.4           | ZigBee PRO MM       | X | The device shall not apply security to outgoing frames or accept secured incoming frames using any level other than level 0x05. | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | X |   | Click here to enter text. |

584

585

586 **10.5.5 NWK layer security**

| Item number | Item description   | Reference           | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|--|---------------------|---------------|---------------------|---|------------------------|------------------|
| NLS1        | Does the device support the security processing of NWK layer outgoing frames?                                    | [R1]/4.3.1.1        | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |  |                     |               | ZigBee-PRO          | M |                        | Yes              |
| NLS2        | Does the device support the security processing of NWK layer incoming frames?                                    | [R1]/4.3.1.2        | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |  |                     |               | ZigBee-PRO          | M |                        | Yes              |
| NLS3        | Does the device support the ZigBee secured NWK layer frame format?   | [R1]/4.3.1          | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |  |                     |               | ZigBee-PRO          | M |                        | Yes              |
| NLS4        | Does the device support the ability to manage at least one network key and corresponding outgoing frame counter? | [R1]/4.2.1.3, 4.3.3 | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |  |                     |               | ZigBee-PRO          | M |                        | Yes              |

| Item number | Item description   | Reference                      | ZigBee Status      | Feature set Support |                    | Additional Constraints  | Platform Support |
|-------------|--|--------------------------------|--------------------|---------------------|--------------------|---|------------------|
| NLS5        | Does the device support the ability to manage two network keys and corresponding outgoing frame counter?   | [R1]/4.2.1.3, 4.3.1, 4.3.3     | O                  | ZigBee PRO MM       | M                  | All devices shall maintain at least 2 NWK keys with the frame counters consistent with the security mode of the network (Standard or High).<br><br>A NWK key of all zero's shall be treated as reserved. Due to the fact that a NWK key of all zero's was used as a "dummy key" and employed in the trust center exchange where pre-configured keys are used, a NWK key of all zero's is indistinguishable from transport of a dummy key. | Yes              |
|             |  |                                |                    | ZigBee-PRO          | M                  |   | Yes              |
| NLS7        | Does the device support at least one frame counter for incoming NWK layer frames for each potential source of incoming frames (e.g., a coordinator or router should support the same number of counters per network key as the maximum number of neighbor table entries and an end device should support one counter per network key)? | [R1]/4.2.1.3, 4.3.1, 4.3.3     | O                  | ZigBee PRO MM       | M                  | Devices using this stack profile in Standard Security and High Security mode shall store a single frame counter per neighbor table entry associated with the current NWK Key.   | Yes              |
|             |  |                                |                    | ZigBee-PRO          | M                  |   | Yes              |
| NLS8        | Does the device support a setting to indicate that all incoming NWK frames must be checked for freshness (i.e., <i>mwkAllFresh</i> )?  | [R1]/4.4.1.2, 4.6.2.1, 4.6.2.2 | MOO1: M<br>MOO2: O | ZigBee PRO MM       | MOO1: M<br>MOO2: O | See also the trust centre policies document [R4].   | Yes              |
|             |  |                                |                    | ZigBee-PRO          | MOO1: M<br>MOO2: O |   | Yes              |

| Item number | Item description   | Reference       | ZigBee Status | Feature set Support |                    | Additional Constraints   | Platform Support          |
|-------------|--|-----------------|---------------|---------------------|--------------------|--|---------------------------|
| NLS9        | Does the device support the ability to secure all incoming and outgoing NWK frames (i.e., the <i>nwkSecureAllFrames</i> attribute of the NIB)? | [R1]/4.2.3, 4.6 | O             | ZigBee PRO MM       | M                  | Devices using the ZigBee and ZigBee-PRO feature sets shall set:<br><br><i>nwkSecureAllFrames</i> = TRUE  | Yes                       |
|             |  |                 |               | ZigBee-PRO          | M                  |  | Yes                       |
| NLS10       | Does the device support the ability to reject frames from neighbors which have not been properly authenticated?                                | [R1]/4.2.3, 4.6 | O             | ZigBee PRO MM       | MOO1: M<br>MOO2: O | Coordinator and Router devices employing ZigBee and ZigBee PRO Standard Mode security shall not reject frames from neighbors which have not been properly authenticated.<br>Coordinator and Router devices employing ZigBee PRO High Security shall reject frames from neighbors which have not been properly authenticated. | Click here to enter text. |
|             |  |                 |               | ZigBee-PRO          | MOO1: M<br>MOO2: O |  | Click here to enter text. |

587

588 **10.5.6 APS layer security**

| Item number | Item description  | Reference    | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|--------------|---------------|---------------------|---|------------------------|------------------|
| ASLS1       | Does the device support the security processing of APS layer outgoing frames? | [R1]/4.4.1.1 | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |   |              |               | ZigBee-PRO          | M |                        | Yes              |
| ASLS2       | Does the device support the security processing of APS layer incoming frames? | [R1]/4.4.1.2 | M             | ZigBee PRO MM       | M |                        | Yes              |

| Item number | Item description  | Reference                                   | ZigBee Status | Feature set Support |                    | Additional Constraints   | Platform Support          |
|-------------|---|---|---------------|---------------------|--------------------|--|---------------------------|
|             |   |   |               | ZigBee-PRO          | M                  |  | Yes                       |
| ASLS3       | Does the device support the ZigBee secured APS layer frame format?  | [R1]/4.4.7.3                                | M             | ZigBee PRO MM       | M                  |  | Yes                       |
|             |   |   |               | ZigBee-PRO          | M                  |  | Yes                       |
| ASLS4       | Does the device support the ability to manage trust center master keys?   | [R1]/4.4.3, 4.4.10, 4.6.3                   | O             | ZigBee PRO MM       | MOO1: M<br>MOO2: O | In ZigBee and ZigBee PRO Standard Mode security, trust center master keys are optional for all devices. In ZigBee PRO High Security, trust center master keys mandatory for all devices.               | Click here to enter text. |
|             |   |   |               | ZigBee-PRO          | MOO1: M<br>MOO2: O |  | Click here to enter text. |
| ASLS5       | Does the device support the ability to manage application master keys?  | [R1]/4.2.3.5, 4.4.3, 4.4.6, 4.4.10, 4.6.3.5 | O             | ZigBee PRO MM       | O                  | In ZigBee and ZigBee PRO Standard and ZigBee PRO High security modes, application master keys are optional for all devices.  | Click here to enter text. |
|             |   |   |               | ZigBee-PRO          | O                  |  | Click here to enter text. |
| ASLS6       | Does the device support the ability to manage application data keys and corresponding security material (e.g., the incoming and outgoing frame counters)? | [R1]/4.2.1.3, 4.4.1, 4.4.10                 | O             | ZigBee PRO MM       | O                  |  | Yes                       |
|             |   |   |               | ZigBee-PRO          | O                  |  | Yes                       |
| ASLS7       | Does the device support network key incoming frame counters for incoming APS layer frames secured with the network key?                                   | [R1]/4.4.1.2, 4.3.3                         | O             | ZigBee PRO MM       | X                  | ZigBee and ZigBee PRO Standard Mode or ZigBee-PRO High Mode security use nwkSecure-AllFrames=TRUE, the APS security header is not employed when the network key is used for incoming APS layer frames. | No                        |
|             |   |   |               | ZigBee-PRO          | X                  |  | No                        |

| Item number | Item description   | Reference                    | ZigBee Status                 | Feature set Support |                               | Additional Constraints  | Platform Support          |
|-------------|--|------------------------------|-------------------------------|---------------------|-------------------------------|---|---------------------------|
| ASLS8       | Does the device support establish-key service using the Symmetric-Key Key Establishment (SKKE) protocol? | [R1]/4.2.3.1, 4.4.2, 4.4.9.1 | O                             | ZigBee PRO MM       | MOO1: M<br>MOO2: O            | In ZigBee and ZigBee PRO Standard Mode security, SKKE is optional for all devices. In ZigBee PRO High Security, SKKE is mandatory for all devices.                              | Click here to enter text. |
|             |  |                              |                               | ZigBee-PRO          | MOO1: M<br>MOO2: O            |   | Click here to enter text. |
| ASLS9       | Does the device support the origination of transport-key commands?                                       | [R1]/4.2.3.2, 4.4.3, 4.4.9.2 | SR1: M                        | ZigBee PRO MM       | SR1: M                        |   | No                        |
|             |  |                              |                               | ZigBee-PRO          | SR1: M                        |   | Yes                       |
| ASLS10      | Does the device support the receipt of transport-key commands?   | [R1]/4.2.3.2, 4.4.3, 4.4.9.2 | O                             | ZigBee PRO MM       | M                             | A newly joined device in ZigBee or ZigBee PRO Standard and ZigBee PRO High Security shall be capable of receiving the NWK key from the trust center via transport-key commands. | Yes                       |
|             |  |                              |                               | ZigBee-PRO          | M                             |   | Yes                       |
| ASLS11      | Does the device support the origination of update-device commands?                                       | [R1]/4.2.3.3, 4.4.4, 4.4.9.3 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |   | No                        |
|             |  |                              |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |   | Yes                       |
| ASLS12      | Does the device support the receipt of update-device commands?   | [R1]/4.2.3.3, 4.4.4, 4.4.9.3 | SR1:M                         | ZigBee PRO MM       | SR1: M                        |   | No                        |
|             |  |                              |                               | ZigBee-PRO          | SR1: M                        |   | Yes                       |

| Item number | Item description   | Reference                    | ZigBee Status                 | Feature set Support |                               | Additional Constraints  | Platform Support |
|-------------|--|------------------------------|-------------------------------|---------------------|-------------------------------|---|------------------|
| ASLS13      | Does the device support the origination of remove-device commands? | [R1]/4.2.3.4, 4.4.5, 4.4.9.4 | SR1:M                         | ZigBee PRO MM       | SR1: M                        |   | No               |
|             |  |                              |                               | ZigBee-PRO          | SR1: M                        |   | Yes              |
| ASLS14      | Does the device support the receipt of remove-device commands?     | [R1]/4.2.3.4, 4.4.5, 4.4.9.4 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X | The trust center shall be able to ask a ZigBee router or the ZigBee coordinator to request that a child device leave the network. | No               |
|             |  |                              |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |   | Yes              |
| ASLS15      | Does the device support the origination of request-key commands?   | [R1]/4.2.3.5, 4.4.6, 4.4.9.5 | O                             | ZigBee PRO MM       | O                             |   | Yes              |
|             |  |                              |                               | ZigBee-PRO          | O                             |   | Yes              |
| ASLS16      | Does the device support the receipt of request-key commands?       | [R1]/4.2.3.5, 4.4.6, 4.4.9.5 | SR1:M                         | ZigBee PRO MM       | SR1: M                        |   | No               |
|             |  |                              |                               | ZigBee-PRO          | SR1: M                        |   | Yes              |
| ASLS17      | Does the device support origination of switch-key commands?        | [R1]/4.2.3.6, 4.4.7, 4.4.9.6 | SR1:M                         | ZigBee PRO MM       | SR1: M                        |   | No               |
|             |  |                              |                               | ZigBee-PRO          | SR1: M                        |   | Yes              |
| ASLS18      | Does the device support receipt of switch-key commands?            | [R1]/4.2.3.6, 4.4.7, 4.4.9.6 | O                             | ZigBee PRO MM       | M                             |   | Yes              |

| Item number | Item description   | Reference                    | ZigBee Status | Feature set Support |  | Additional Constraints  | Platform Support |
|-------------|--|------------------------------|---------------|---------------------|--|---|------------------|
|             |  |                              |               | ZigBee-PRO          | M  |   | Yes              |
| ASLS19      | Does the device support origination of tunnel commands?                                      | [R1]/4.4.3.1, 4.4.9.8        | SR1:M         | ZigBee PRO MM       | MOO1: M<br>MOO2: O   | In ZigBee and ZigBee PRO Standard security, the ability to originate tunnel commands from the Trust Center is optional unless using link keys. In ZigBee PRO High Security, it is mandatory.      | No               |
|             |  |                              |               | ZigBee-PRO          | MOO1: M<br>MOO2: O   |   | Yes              |
| ASLS20      | Does the device support receipt of tunnel commands?  | [R1]/4.4.3.1, 4.4.9.8        | O             | ZigBee PRO MM       | MOO2: FDT1: O<br>FDT2: O<br>FDT3: X  | In ZigBee and ZigBee PRO Standard and High security, the ability for the coordinator and all routers to receive tunnel commands is mandatory.   | No               |
|             |  |                              |               | ZigBee-PRO          | MOO1: FDT1: M<br>FDT2: M<br>FDT3: X<br><br>MOO2: FDT1: O<br>FDT2: O<br>FDT3: X |   | Yes              |
| ASLS21      | Does the device support the authentication service using the entity authentication protocol? | [R1]/4.2.3.7, 4.4.8, 4.4.9.7 | O             | ZigBee PRO MM       | MOO2: FDT1: O<br>FDT2: O<br>FDT3: X  | In ZigBee and ZigBee PRO Standard security, the ability to support the authentication service using the entity authentication protocol is optional. In ZigBee PRO High Security, it is mandatory. | No               |
|             |  |                              |               | ZigBee-PRO          | MOO1: FDT1: M<br>FDT2: M<br>FDT3: X<br><br>MOO2: FDT1: O<br>FDT2: O<br>FDT3: X |   | Yes              |

## 589 10.5.7 Application layer security

| Item number | Item description  | Reference                 | ZigBee Status                 | Feature set Support |                               | Additional Constraints  | Platform Support |
|-------------|---|---------------------------|-------------------------------|---------------------|-------------------------------|---|------------------|
| ALS1        | Is this device capable of learning and maintaining knowledge of its trust center using the <i>apsTrustCenterAddress</i> attribute in the AIB? | [R1]/4.4.11, 4.6.2.2      | O                             | ZigBee PRO MM       | O                             | Trust Center must initially reside on the ZigBee coordinator but may, under application control, move to any router on the PAN as long as all devices in the PAN have their <i>apsTrustCenterAddress</i> attribute updated appropriately by the application.<br><br>Trust Center must be collocated with ZC (short address 0x0000) throughout network life (CCB 2178) | Yes              |
|             |   |                           |                               | ZigBee-PRO          | M                             |   | Yes              |
| ALS2        | Is this device capable of following the “joining a secure network procedure” in the role of a router?   | [R1]/4.6.3.1              | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |   | No               |
|             |   |                           |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |   | Yes              |
| ALS3        | Is this device capable of following the “joining a secure network procedure” in the role of a joining device?                                 | [R1]/4.6.3.1              | O                             | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |   | Yes              |
|             |   |                           |                               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |   | Yes              |
| ALS4        | Is this device capable of following the “authentication procedure” in the role of a trust center?   | [R1]/4.6.3.2, 4.6.3.2.2.1 | TCC1: O<br>TCC2: O            | ZigBee PRO MM       | SR1: M                        |   | No               |
|             |   |                           |                               | ZigBee-PRO          | SR1: M                        |   | Yes              |

| Item number | Item description   | Reference                 | ZigBee Status                 | Feature set Support |                               | Additional Constraints  | Platform Support |
|-------------|--|---------------------------|-------------------------------|---------------------|-------------------------------|---|------------------|
| ALS5        | Is this device capable of following the “authentication procedure” in the role of a router?  | [R1]/4.6.3.2, 4.6.3.2.1   | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |   | No               |
|             |  |                           |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |   | Yes              |
| ALS6        | Is this device capable of following the “authentication procedure” in the role of a joining device with a preconfigured network key?           | [R1]/4.6.3.2, 4.6.3.2.3.1 | O                             | ZigBee PRO MM       | O                             | For devices implementing ZigBee and ZigBee PRO Standard Security, following the “authentication procedure” in the role of joining device with a pre-configured network key is optional. For devices implementing ZigBee PRO High Security, it is prohibited.  | Yes              |
|             |  |                           |                               | ZigBee-PRO          | O                             |   | Yes              |
| ALS7        | Is this device capable of following the “authentication procedure” in the role of a joining device with a preconfigured trust center link key? | [R1]/4.6.3.2, 4.6.3.2.3.2 | O                             | ZigBee PRO MM       | O                             | For devices implementing ZigBee and ZigBee PRO Standard Security, following the “authentication procedure” in the role of joining device with a pre-configured trust center link key is optional. For devices implementing ZigBee PRO High Security, it is mandatory unless the ZigBee PRO High Security Trust Center policy permits in the clear delivery of the master key. | Yes              |
|             |  |                           |                               | ZigBee-PRO          | O                             |   | Yes              |
| ALS8        | Is this device capable of following the “authentication procedure” in the  | [R1]/4.6.3.2, 4.6.3.2.3.3 | O                             | ZigBee PRO MM       | O                             | For devices implementing ZigBee and ZigBee PRO Standard Security, following the   | Yes              |

| Item number | Item description  | Reference               | ZigBee Status                | Feature set Support |                               | Additional Constraints   | Platform Support          |
|-------------|---|-------------------------|------------------------------|---------------------|-------------------------------|--|---------------------------|
|             | role of a joining device without preconfigured network or trust center link keys?                         |                         |                              | ZigBee-PRO          | O                             | “authentication procedure” in the role of joining device without a pre-configured trust center link key is optional and supported by default due to the requirement to permit ZigBee Residential Security Mode devices onto PRO Standard Security networks as end devices. For devices implementing ZigBee PRO High Security, it is optional and supported only if the ZigBee PRO High Security Trust Center policy permits in the clear delivery of the master key. | Yes                       |
| ALS9        | Is this device capable of following the “network key update procedure” in the role of a trust center?     | [R1]/4.6.3.4, 4.6.3.4.1 | TCC1: O<br>TCC2: O           | ZigBee-PRO MM       | SR1: M                        |  | No                        |
|             |   |                         |                              | ZigBee-PRO          | SR1: M                        |  | Yes                       |
| ALS10       | Is this device capable of following the “network key update procedure” in the role of a network device?   | [R1]/4.6.3.4, 4.6.3.4.2 | O                            | ZigBee-PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes                       |
|             |   |                         |                              | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes                       |
| ALS11       | Is this device capable of following the “network key recovery procedure” in the role of a trust center?   |                         | TCC1:O.<br>1<br>TCC2:O.<br>1 | ZigBee-PRO MM       | X                             | This item was deprecated.  | Click here to enter text. |
|             |   |                         |                              | ZigBee-PRO          | X                             |  | Click here to enter text. |
| ALS12       | Is this device capable of following the “network key recovery procedure” in the role of a network device? |                         | O                            | ZigBee-PRO MM       | X                             | This item was deprecated.  | Click here to enter text. |
|             |   |                         |                              | ZigBee-PRO          | X                             |  | Click here to enter text. |

| Item number | Item description  | Reference                            | ZigBee Status                 | Feature set Support |                               | Additional Constraints   | Platform Support          |
|-------------|---|--------------------------------------|-------------------------------|---------------------|-------------------------------|--|---------------------------|
| ALS13       | Is this device capable of following the “end-to-end application key establishment procedure” in the role of a trust center?   | [R1]/4.6.3.5, 4.6.3.5.2              | TCC1: O<br>TCC2: O            | ZigBee PRO MM       | SR1: O                        | For ZigBee and ZigBee PRO Standard Security, it is optional for the trust center to perform the “end-to-end application key establishment” procedure. For ZigBee PRO High Security, it is mandatory. | No                        |
|             |   |                                      |                               | ZigBee-PRO          | SR1: O                        |  | Yes                       |
| ALS14       | Is this device capable of following the “end-to-end application key establishment procedure” in the role of a device receiving a master key for use with the SKKE protocol? | [R1]/4.6.3.5, 4.6.3.5.1, 4.6.3.5.1.2 | O                             | ZigBee PRO MM       | O                             | For ZigBee and ZigBee PRO Standard Security and ZigBee PRO High Security, it is optional for the network devices to perform the “end-to-end application key establishment” procedure.                | Click here to enter text. |
|             |   |                                      |                               | ZigBee-PRO          | O                             |  | Click here to enter text. |
| ALS15       | Is this device capable of following the “end-to-end application key establishment procedure” in the role of a device directly receiving a link key?                         | [R1]/4.6.3.5, 4.6.3.5.1, 4.6.3.5.1.1 | O                             | ZigBee PRO MM       | O                             | For ZigBee and ZigBee PRO Standard Security and ZigBee PRO High Security, it is optional for the network devices to perform the “end-to-end application key establishment” procedure.                | Yes                       |
|             |   |                                      |                               | ZigBee-PRO          | O                             |  | Yes                       |
| ALS16       | Is this device capable of following the “network leave procedure” in the role of a trust center?  | [R1]/4.6.3.6, 4.6.3.6.1              | TCC1: O<br>TCC2: O            | ZigBee PRO MM       | SR1: M                        |  | No                        |
|             |   |                                      |                               | ZigBee-PRO          | SR1: M                        |  | Yes                       |
| ALS17       | Is this device capable of following the “network leave procedure” in the role of a router?  | [R1]/4.6.3.6, 4.6.3.6.2              | FDT1:O,<br>FDT2:O,<br>FDT3:X  | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: X |  | No                        |
|             |   |                                      |                               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: X |  | Yes                       |
| ALS18       | Is this device capable of following the “network leave procedure” in the role of a leaving device?  | [R1]/4.6.3.6, 4.6.3.6.3              | O                             | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes                       |
|             |   |                                      |                               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes                       |
| ALS19       | Is this device capable of following the “intra-PAN  | [R1]/4.6.3.3, 4.6.3.3.1              | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |  | No                        |

| Item number | Item description  | Reference               | ZigBee Status                 | Feature set Support |                               | Additional Constraints  | Platform Support          |
|-------------|---|-------------------------|-------------------------------|---------------------|-------------------------------|---|---------------------------|
|             | portability procedure" in the role of a parent?   |                         |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |   | Yes                       |
| ALS20       | Is this device capable of following the "intra-PAN portability procedure" in the role of an end device?     | [R1]/4.6.3.3, 4.6.3.3.2 | O                             | ZigBee-PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: M |   | Yes                       |
|             |   |                         |                               | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: M |   | Yes                       |
| ALS21       | Is this device capable of following the "command tunneling procedure" in the role of a trust center device? | [R1]/4.6.3.8, 4.6.3.8.1 | TCC1: O<br>TCC2: O            | ZigBee-PRO MM       | SR1: O                        | For ZigBee PRO High Security, the command tunneling procedure in the role of a trust center device is mandatory. For ZigBee and ZigBee PRO Standard Security, it is optional. | No                        |
|             |   |                         |                               | ZigBee-PRO          | SR1: O                        |   | Yes                       |
| ALS22       | Is this device capable of following the "command tunneling procedure" in the role of a router?              | [R1]/4.6.3.8, 4.6.3.8.2 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee-PRO MM       | FDT1: O<br>FDT2: O<br>FDT3: X | For ZigBee PRO High Security, the command tunneling procedure in the role of a router device is mandatory. For ZigBee and ZigBee PRO Standard Security, it is optional.       | No                        |
|             |   |                         |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: X |   | Yes                       |
| ALS23       | Does the device support the permissions configuration table?  | [R1]/4.2.3.8, 4.6.3.8   | O                             | ZigBee-PRO MM       | O                             | The Permissions Configuration Table is optional for all devices.  | Click here to enter text. |
|             |   |                         |                               | ZigBee-PRO          | O                             |   | Click here to enter text. |

591 **10.6 Application layer PICS**592 **10.6.1 ZigBee security device types**

| Item number | Item description  | Reference         | ZigBee Status | Feature set Support |                               | Additional Constraints                    | Platform Support |
|-------------|---|-------------------|---------------|---------------------|-------------------------------|---|------------------|
| SDT1        | Is this device capable of acting as a ZigBee Trust Center?                  | [R1]/4.2.4, 4.6.2 | O.2           | ZigBee PRO MM       | FDT1: M<br>FDT2: O<br>FDT3: X | This item was deprecated in favor of SR1. | No               |
|             |   |                   |               | ZigBee-PRO          | FDT1: M<br>FDT2: O<br>FDT3: X |   | Yes              |
| SDT2        | Is this device capable of joining a secure ZigBee network only as a device? | [R1]/4.6.3        | O.2           | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |   | Yes              |
|             |   |                   |               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |   | Yes              |

593

594 **10.6.2 ZigBee APS frame format**

| Item number | Item description   | Reference      | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|--|----------------|---------------|---------------------|---|------------------------|------------------|
| AFF1        | Does the device support the general ZigBee APS frame format? | [R1]/2.2.5.1   | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |  |                |               | ZigBee-PRO          | M |                        | Yes              |
| AFF2        | Does the device support the ZigBee APS data frame format?    | [R1]/2.2.5.2.1 | M             | ZigBee PRO MM       | M |                        | Yes              |

| Item number | Item description   | Reference             | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|--|-----------------------|---------------|---------------------|---|------------------------|------------------|
|             |  |                       |               | ZigBee-PRO          | M |                        | Yes              |
| AFF3        | Does the device support the ZigBee APS command frame format?         | [R1]/2.2.5.2.2, 2.2.6 | O             | ZigBee PRO MM       | M |                        | Yes              |
|             |  |                       |               | ZigBee-PRO          | M |                        | Yes              |
| AFF4        | Does the device support the ZigBee APS acknowledgement frame format? | [R1]/2.2.5.2.3        | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |  |                       |               | ZigBee-PRO          | M |                        | Yes              |

595

### 596 10.6.3 Major capabilities of the ZigBee application layer

597 *Tables in the following subclauses detail the capabilities of the APL layer for ZigBee devices.*

#### 598 10.6.3.1 Application layer functions

##### 599 10.6.3.1.1 Application Support Sub-layer functions

| Item number | Item description  | Reference                 | ZigBee Status | Feature set Support |   | Additional Constraints                   | Platform Support          |
|-------------|---|---------------------------|---------------|---------------------|---|--|---------------------------|
| ALF1        | Does the application support sub-layer support transmission of data by the next higher layer? | [R1]/2.2.4.1.1, 2.2.4.1.2 | M             | ZigBee PRO MM       | M |  | Yes                       |
|             |   |                           |               | ZigBee-PRO          | M |  | Yes                       |
| ALF200      | Does the device support transmission of outgoing APS frames within                            | [R1]/2.2.4.1.1            | O             | ZigBee PRO MM       | X | This must be handled by the application. | Click here to enter text. |

| Item number | Item description  | Reference      | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support          |
|-------------|---|----------------|---------------|---------------------|---|------------------------|---------------------------|
|             | APSDE with the DstAddrMode set to 0x00 (indirect)   |                |               | ZigBee-PRO          | X |                        | Click here to enter text. |
| ALF201      | Does the device support transmission of outgoing APS frames within APSDE with the DstAddrMode set to 0x01 (group addressed)                                     | [R1]/2.2.4.1.1 | M             | ZigBee-PRO MM       | M |                        | Yes                       |
|             |   |                |               | ZigBee-PRO          | M |                        | Yes                       |
| ALF202      | Does the device support transmission of outgoing APS frames within APSDE with the DstAddrMode set to 0x02 (unicast using NWK address and Destination Endpoint)  | [R1]/2.2.4.1.1 | M             | ZigBee-PRO MM       | M |                        | Yes                       |
|             |   |                |               | ZigBee-PRO          | M |                        | Yes                       |
| ALF203      | Does the device support transmission of outgoing APS frames within APSDE with the DstAddrMode set to 0x03 (unicast using IEEE address and Destination Endpoint) | [R1]/2.2.4.1.1 | O             | ZigBee-PRO MM       | O |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | O |                        | Click here to enter text. |
| ALF2        | Does the application support sub-layer support reception of data by the next higher layer at the endpoint supplied by the incoming packet?                      | [R1]/2.2.4.1.3 | M             | ZigBee-PRO MM       | M |                        | Yes                       |
|             |   |                |               | ZigBee-PRO          | M |                        | Yes                       |
| ALF300      | Does the device support reception of incoming APS frames within APSDE with the DstAddrMode set to 0x00 (indirect)   | [R1]/2.2.4.1.3 | O             | ZigBee-PRO MM       | X |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | X |                        | Click here to enter text. |

| Item number | Item description  | Reference                                       | ZigBee Status | Feature set Support |   | Additional Constraints   | Platform Support |
|-------------|---|---|---------------|---------------------|---|--|------------------|
| ALF301      | Does the device support reception of incoming APS frames within APSDE with the DstAddrMode set to 0x01 (group addressed)                                    | [R1]/2.2.4.1.3                                  | M             | ZigBee PRO MM       | M |  | Yes              |
|             |   |   |               | ZigBee-PRO          | M |  | Yes              |
| ALF302      | Does the device support reception of incoming APS frames within APSDE with the DstAddrMode set to 0x02 (unicast using NWK address and Destination Endpoint) | [R1]/2.2.4.1.3                                  | M             | ZigBee PRO MM       | M |  | Yes              |
|             |   |   |               | ZigBee-PRO          | M |  | Yes              |
| ALF3        | Does the application support sub-layer support BIND and UNBIND requests and confirms?   | [R1]/2.2.4.3.1, 2.2.4.3.2, 2.2.4.3.3, 2.2.4.3.4 | O             | ZigBee PRO MM       | O | Binding support is optional for all devices, except that: <ul style="list-style-type: none"> <li>Source binding only is supported (coordinator based binding is disallowed)</li> <li>All devices shall minimally respond with NOT_IMPLEMENTED</li> </ul> | Yes              |
|             |   |   |               | ZigBee-PRO          | O | The ZigBee Coordinator shall implement the mechanism for matching end device bind requests (AZD24; FDT1: M).   | Yes              |
| ALF4        | Does the device's application support sub-layer offer the next higher layer the ability to get application information base (AIB) attributes.               | [R1]/2.2.4.4.1, 2.2.4.4.2                       | M             | ZigBee PRO MM       | M |  | Yes              |
|             |   |   |               | ZigBee-PRO          | M |  | Yes              |
| ALF5        | Does the device's application support sub-layer offer the next higher layer the   | [R1]/2.2.4.4.3, 2.2.4.4.4                       | M             | ZigBee PRO MM       | M |  | Yes              |

| Item number | Item description  | Reference                 | ZigBee Status | Feature set Support |   | Additional Constraints  | Platform Support          |
|-------------|---|---------------------------|---------------|---------------------|---|---|---------------------------|
|             | ability to set application information base (AIB) attributes.                           |                           |               | ZigBee-PRO          | M |   | Yes                       |
| ALF100      | Does the application support sub-layer support ADD GROUP requests and confirms?         | [R1]/2.2.4.5.1, 2.2.4.5.2 | M             | ZigBee PRO MM       | O | If supported, the group table in the APS shall contain a minimum of 16 group addresses. | Click here to enter text. |
|             |   |                           |               | ZigBee-PRO          | O |   | Click here to enter text. |
| ALF101      | Does the application support sub-layer support REMOVE GROUP requests and confirms?      | [R1]/2.2.4.5.3, 2.2.4.5.4 | M             | ZigBee PRO MM       | O |   | Click here to enter text. |
|             |   |                           |               | ZigBee-PRO          | O |   | Click here to enter text. |
| ALF102      | Does the application support sub-layer support REMOVE ALL GROUPS requests and confirms? | [R1]/2.2.4.5.5, 2.2.4.5.6 | M             | ZigBee PRO MM       | O |   | Click here to enter text. |
|             |   |                           |               | ZigBee-PRO          | O |   | Click here to enter text. |

600

601 **10.6.3.1.2 Application layer frames**

| Item number | Item description  | Reference                          | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|------------------------------------|---------------|---------------------|---|------------------------|------------------|
| ADF1        | Does the device support the origination of application data frames. | [R1]/2.2.5.1, 2.2.5.2.1, 2.2.8.4.1 | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |   |                                    |               | ZigBee-PRO          | M |                        | Yes              |

| Item number | Item description   | Reference   | ZigBee Status | Feature set Support |   | Additional Constraints   | Platform Support          |
|-------------|--|---|---------------|---------------------|---|--|---------------------------|
| ADF2        | Does the device support the receipt of application data frames.  | [R1]/2.2.5.1<br>2.2.5.2.1,<br>2.2.8.3.2,<br>2.2.8.3.3                   | M             | ZigBee PRO MM       | M |  | Yes                       |
|             |  |   |               | ZigBee-PRO          | M |  | Yes                       |
| ADF3        | Does the device support the origination of application data frames with the auxiliary APS security header?                 | [R1]/ 2.2.5.1,<br>2.2.5.2.1,<br>2.2.8.4.1,<br>4.4.1.1                   | O             | ZigBee PRO MM       | O | Use of the auxiliary APS security header is optional for all devices. The application profiles shall determine requirements for use of the auxiliary APS security header.  | Click here to enter text. |
|             |  |   |               | ZigBee-PRO          | O |  | Click here to enter text. |
| ADF4        | Does the device support the receipt of application data frames with the auxiliary APS security header?                     | [R1]/ 2.2.5.1<br>2.2.5.2.1,<br>2.2.8.3.2,<br>2.2.8.3.3,<br>4.4.1.2      | O             | ZigBee PRO MM       | O | Use of the auxiliary APS security header is optional for all devices. The application profiles shall determine requirements for use of the auxiliary APS security header.  | Click here to enter text. |
|             |  |   |               | ZigBee-PRO          | O |  | Click here to enter text. |
| ADF5        | Does the device support the origination of application data frames with the extended APS fragmentation/re-assembly header? | [R1]/ 2.2.5.1,<br>2.2.5.2.1,<br>2.2.8.4.1,<br>2.2.5.1.8,<br>2.2.8.4.5.1 | O             | ZigBee PRO MM       | O | Use of the extended APS fragmentation/re-assembly header is optional, but in all cases the parameters shall be set by agreement within specific application profiles.<br><br>Devices using the ZigBee and ZigBee-PRO feature sets shall set:<br><br><i>Config_Max_ZDO-Payload = 0</i> (i.e. for compatibility with the earlier ZigBee feature set, ZDO messages shall not be fragmented) | Click here to enter text. |
|             |  |   |               | ZigBee-PRO          | O |  | Click here to enter text. |

| Item number | Item description   | Reference  | ZigBee Status | Feature set Support |   | Additional Constraints   | Platform Support          |
|-------------|--|--|---------------|---------------------|---|--|---------------------------|
| ADF6        | Does the device support the receipt of application data frames with the extended APS fragmentation/re-assembly header? | [R1]/ 2.2.5.1<br>2.2.5.2.1,<br>2.2.8.3.2,<br>2.2.8.3.3,<br>2.2.5.1.8,<br>2.2.8.4.5.2 | O             | ZigBee PRO MM       | O | Use of the extended APS fragmentation/re-assembly header is optional, but in all cases the parameters shall be set by agreement within specific application profiles.<br><br>Devices using the ZigBee and ZigBee-PRO feature sets shall set:<br><br><i>Config_Max_ZDO-Payload = 0</i> (i.e. for compatibility with the earlier ZigBee feature set, ZDO messages shall not be fragmented) | Click here to enter text. |
|             |  |  |               | ZigBee-PRO          | O |  | Click here to enter text. |

602 **10.6.3.1.3 Application layer command frames**

| Item number | Item description  | Reference  | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support          |
|-------------|---|--|---------------|---------------------|---|------------------------|---------------------------|
| ACF500      | Does the device support the origination of command frames with the auxiliary APS security header? | [R1]/ 2.2.5.1,<br>2.2.5.2.2,<br>2.2.6, 4.4.1.1                 | O             | ZigBee PRO MM       | O |                        | Click here to enter text. |
|             |   |  |               | ZigBee-PRO          | O |                        | Click here to enter text. |
| ACF501      | Does the device support the receipt of command frames with the auxiliary APS security header?     | [R1]/ 2.2.5.1<br>2.2.5.2.1,<br>2.2.6,<br>2.2.8.3.3,<br>4.4.1.2 | O             | ZigBee PRO MM       | O |                        | Click here to enter text. |
|             |   |  |               | ZigBee-PRO          | O |                        | Click here to enter text. |

| Item number | Item description   | Reference   | ZigBee Status | Feature set Support |        | Additional Constraints   | Platform Support          |
|-------------|--|---|---------------|---------------------|--------|--|---------------------------|
| ACF1        | Does the device support the origination of application command frames from the Trust Center.                   | [R1]/4.4.9, 4.6.2, 4.6.3.2, 4.6.3.3, 4.6.3.4, 4.6.3.5, 4.6.3.6, 4.6.3.7 | SDT1: M       | ZigBee PRO MM       | SR1: M |  | No                        |
|             |  |   |               | ZigBee-PRO          | SR1: M |  | Yes                       |
| ACF100      | Does the device support the origination of Key Establishment application command frames from the Trust Center? | [R1]/4.4.9.1  | SDT1:M        | ZigBee PRO MM       | SR1: O | In ZigBee and ZigBee PRO Standard Security Mode, it is optional to originate Key Establishment command frames from the Trust Center. In ZigBee PRO High Security, it is mandatory.   | Click here to enter text. |
|             |  |   |               | ZigBee-PRO          | SR1: O |  | No                        |
| ACF101      | Does the device support the origination of Transport Key application command frames from the Trust Center?     | [R1]/4.4.9.2  | SDT1:M        | ZigBee PRO MM       | SR1: M | In ZigBee and ZigBee PRO Standard Security Mode, it is mandatory to originate Transport Key command frames from the Trust Center for Key Type 1 (Network Key Standard Mode). In ZigBee PRO High Security Mode, it is mandatory to originate Transport Key command frames from the Trust Center for Key Type 0 (Trust Center Master Key) and Key Type 5 (Network Key High Security Mode). It is optional in either ZigBee and ZigBee PRO Standard Security or High Security to originate Transport Key command frames for Key Types 4 (Trust Center Link Key), Key Type 2 (Application Master Key) and Key Type 3 (Application Link Key). | No                        |
|             |  |   |               | ZigBee-PRO          | SR1: M |  | Yes                       |

| Item number | Item description   | Reference   | ZigBee Status | Feature set Support |                    | Additional Constraints   | Platform Support          |
|-------------|--|---|---------------|---------------------|--------------------|--|---------------------------|
| ACF102      | Does the device support the origination of Remove Device application command frames from the Trust Center? | [R1]/4.4.9.4  | SDT1:M        | ZigBee PRO MM       | SR1: M             |  | No                        |
|             |  |   |               | ZigBee-PRO          | SR1: M             |  | Yes                       |
| ACF103      | Does the device support the origination of Switch Key application command frames from the Trust Center?    | [R1]/4.4.9.6  | SDT1:M        | ZigBee PRO MM       | SR1: M             |  | No                        |
|             |  |   |               | ZigBee-PRO          | SR1: M             |  | Yes                       |
| ACF104      | Does the device support the origination of entity authentication application command frames?               | [R1]/4.4.9.7  | SDT1:M        | ZigBee PRO MM       | SR1: O             |  | Click here to enter text. |
|             |  |   |               | ZigBee-PRO          | MOO2: O<br>MOO1: M |  | Click here to enter text. |
| ACF2        | Does the device support the receipt of application command frames at the Trust Center                      | [R1]/4.4.9, 4.6.2, 4.6.3.2, 4.6.3.3, 4.6.3.4, 4.6.3.5, 4.6.3.6, 4.6.3.7 | SDT1:M        | ZigBee PRO MM       | SR1: M             | Mandatory for the trust centre and optional for other devices.   | No                        |
|             |  |   |               | ZigBee-PRO          | SR1: M             |  | Yes                       |
| ACF200      | Does the device support the receipt of Key Establishment application command frames at the Trust Center?   | [R1]/4.4.9.1  | SDT1:M        | ZigBee PRO MM       | SR1: O             | In ZigBee and ZigBee PRO Standard Security Mode, it is optional to receive Key Establishment command frames from the Trust Center. In ZigBee PRO High Security, it is mandatory. | Click here to enter text. |
|             |  |   |               | ZigBee-PRO          | SR1: O             |  | Click here to enter text. |

| Item number | Item description   | Reference    | ZigBee Status | Feature set Support |        | Additional Constraints  | Platform Support |
|-------------|--|--------------|---------------|---------------------|--------|---|------------------|
| ACF201      | Does the device support the receipt of Transport Key application command frames at the Trust Center? | [R1]/4.4.9.2 | SDT1:M        | ZigBee PRO MM       | SR1: M | In ZigBee and ZigBee PRO Standard Security Mode, it is mandatory to receive Transport Key command frames from the Trust Center for Key Type 1 (Network Key Standard Mode). In ZigBee PRO High Security Mode, it is mandatory to receive Transport Key command frames from the Trust Center for Key Type 0 (Trust Center Master Key) and Key Type 5 (Network Key High Security Mode). It is optional in ZigBee and ZigBee PRO Standard Security to receive Transport Key command frames for Key Types 4 (Trust Center Link Key), Key Type 2 (Application Master Key) and Key Type 3 (Application Link Key). It is prohibited in ZigBee PRO High Security to receive Transport Key command frames for Key Types 4 (Trust Center Link Key) and optional to receive Transport Key command frames for Key Type 2 (Application Master Key) and Key Type 3 (Application Link Key). | Yes              |
|             |  |              |               | ZigBee-PRO          | SR1: M |   | Yes              |
| ACF202      | Does the device support the receipt of Update Device application command frames at the Trust Center? | [R1]/4.4.9.3 | SDT1:M        | ZigBee PRO MM       | SR1: M |   | No               |
|             |  |              |               | ZigBee-PRO          | SR1: M |   | Yes              |
| ACF203      | Does the device support the receipt of Request Key application command frames at the Trust Center?   | [R1]/4.4.9.5 | SDT1:M        | ZigBee PRO MM       | SR1: M |   | No               |
|             |  |              |               | ZigBee-PRO          | SR1: M |   | Yes              |

| Item number | Item description  | Reference             | ZigBee Status | Feature set Support |  | Additional Constraints  | Platform Support          |
|-------------|---|-----------------------|---------------|---------------------|--|---|---------------------------|
| ACF204      | Does the device support the receipt of entity authentication application command frames?                                | [R1]/4.4.9.7          | SDT1:M        | ZigBee PRO MM       | X  |   | Click here to enter text. |
|             |   |                       |               | ZigBee-PRO          | MOO1: M<br>MOO2: O   |   | Click here to enter text. |
| ACF3        | Does the device support the origination of application command frames from a non-Trust Center device.                   | [R1]/4.4.9, 4.6.3     | SDT2:M        | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: O  | In ZigBee and ZigBee PRO Standard Security, non Trust Center devices may optionally originate application command frames. In ZigBee PRO High Security, all non Trust Center routers and the coordinator shall originate application command frames and end devices may originate application command frames.                  | Yes                       |
|             |   |                       |               | ZigBee-PRO          | MOO1:<br>FDT1: X<br>FDT2: M<br>FDT3: M<br>MOO2:<br>FDT1: X<br>FDT2: M<br>FDT3: O |   | Yes                       |
| ACF300      | Does the device support the origination of Key Establishment application command frames from a non-Trust Center device? | [R1]/4.4.9.1, 4.6.3.5 | SDT2:M        | ZigBee PRO MM       | O  | In ZigBee and ZigBee PRO Standard Security, it is optional for all devices to support origination of Key Establishment command frames from a non Trust Center device. In ZigBee PRO High Security, it is mandatory for all devices to support origination of Key Establishment command frames from a non Trust Center device. | No                        |
|             |   |                       |               | ZigBee-PRO          | O  |   | No                        |
| ACF301      | Does the device support the origination of Transport Key application command frames from a non-Trust Center device?     | [R1]/4.4.9.2          | SDT2:M        | ZigBee PRO MM       | O  |   | No                        |
|             |   |                       |               | ZigBee-PRO          | O  |   | No                        |
| ACF302      | Does the device support the origination of Update Device application command frames from a non-Trust Center device?     | [R1]/4.4.9.3, 4.6.3.4 | SDT2:M        | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: O  | Assumes it is legal to have the Trust Center on a non-ZigBee Coordinator device for the ZigBee feature set via ZigBee-2007  | Click here to enter text. |
|             |   |                       |               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: O  |   | Yes                       |

| Item number | Item description  | Reference             | ZigBee Status  | Feature set Support |                                    | Additional Constraints   | Platform Support          |
|-------------|---|-----------------------|----------------|---------------------|------------------------------------|--|---------------------------|
| ACF303      | Does the device support the origination of Request Key application command frames from a non-Trust Center device?   | [R1]/4.4.9.5          | SDT2:M         | ZigBee PRO MM       | O                                  |  | Yes                       |
|             |   |                       |                | ZigBee-PRO          | O                                  |  | Yes                       |
| ACF304      | Does the device support the origination of Authenticate application command frames from a non-Trust Center device?  | [R1]/4.4.9.7, 4.6.3.2 | SDT2:M         | ZigBee PRO MM       | O                                  |  | Click here to enter text. |
|             |   |                       |                | ZigBee-PRO          | O                                  |  | Click here to enter text. |
| ACF4        | Does the device support the receipt of application command frames from a non-Trust Center device.                   | [R1]/4.4.9, 4.6.3     | SDT1:M, SDT2:M | ZigBee PRO MM       | SR1: FDT1: M<br>FDT2: M<br>FDT3: O | In all ZigBee and ZigBee PRO security modes, the Trust Center shall receive application command frames from non Trust Center devices. In ZigBee and ZigBee PRO Standard Security, all non Trust Center routers and the coordinator shall receive application command frames. In ZigBee PRO High Security, all non Trust Center devices shall receive application command frames. | Click here to enter text. |
|             |   |                       |                | ZigBee-PRO          | SR1: FDT1: M<br>FDT2: M<br>FDT3: O |  | Yes                       |
| ACF400      | Does the device support the receipt of Key Establishment application command frames from a non-Trust Center device? | [R1]/4.4.9.1, 4.6.3.5 | SDT1:M, SDT2:M | ZigBee PRO MM       | O                                  | For all devices in ZigBee PRO Standard Security, receipt of Key Establishment application command frames from a non Trust Center device is optional. In ZigBee PRO High Security, receipt of Key Establishment application command frames from non Trust Center devices is mandatory in all devices.   | Click here to enter text. |
|             |   |                       |                | ZigBee-PRO          | O                                  |  | Yes                       |

| Item number          | Item description  | Reference                | ZigBee Status                 | Feature set Support |                   | Additional Constraints   | Platform Support          |
|----------------------|---|--------------------------|-------------------------------|---------------------|-------------------|--|---------------------------|
| ACF401               | Does the device support the receipt of Transport Key application command frames from a non-Trust Center device?       | [R1]/4.4.9.2             | SDT1:M,<br>SDT2:M             | ZigBee PRO MM       | SR1: M<br>SDT2: M |  | Yes                       |
|                      |   |                          |                               | ZigBee-PRO          | SR1: M<br>SDT2: M |  | Yes                       |
| ACF402               | Does the device support the receipt of Update Device application command frames from a non-Trust Center device?       | [R1]/4.4.9.3,<br>4.6.3.4 | SDT1:M                        | ZigBee PRO MM       | SR1: M            |  | No                        |
|                      |   |                          |                               | ZigBee-PRO          | SR1: M            |  | Yes                       |
| ACF403               | Does the device support the receipt of Request Key application command frames from a non-Trust Center device?         | [R1]/4.4.9.5             | SDT1:M                        | ZigBee PRO MM       | SR1: M            |  | No                        |
|                      |   |                          |                               | ZigBee-PRO          | SR1: M            |  | Yes                       |
| ACF404               | Does the device support the receipt of entity authenticate application command frames from a non-Trust Center device? | [R1]/4.4.9.7,<br>4.6.3.2 | SDT1:M<br>SDT2:M              | ZigBee PRO MM       | O                 | Need a comment that this feature is optional in ZigBee and ZigBee PRO Standard Security and mandatory for all devices in ZigBee PRO High Security. | Click here to enter text. |
|                      |   |                          |                               | ZigBee-PRO          | O                 |  | Click here to enter text. |
| ACF405 <sup>11</sup> | Does the device support the receipt of a Transport Key message APS encrypted with the default TC link key?            | [R1]/4.2.1.3             | FDT1: X<br>FDT2: M<br>FDT3: M | ZigBee PRO MM       | X                 |  | Yes                       |
|                      |   |                          |                               | ZigBee-PRO          | SDT1:X<br>SDT2:M  |  | Yes                       |

603

<sup>11</sup> CCB 1039

|                      |   |              |                            |               |                  |  |     |
|----------------------|---|--------------|----------------------------|---------------|------------------|--|-----|
| ACF406 <sup>12</sup> | Does the device support the transmission of a Transport Key message APS encrypted with the default TC link key? | [R1]/4.2.1.3 | FDT1:M<br>FDT2:X<br>FDT3:X | ZigBee PRO MM | X                |  | No  |
|                      |   |              |                            | ZigBee-PRO    | SDT1:M<br>SDT2:X |  | Yes |

604 **10.6.3.1.4 Application acknowledgement frames**

| Item number | Item description   | Reference                 | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|--|---------------------------|---------------|---------------------|---|------------------------|------------------|
| AFR1        | Does the device support the origination of application acknowledgement frames. | [R1]/2.2.8.3.1, 2.2.8.3.3 | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |  |                           |               | ZigBee-PRO          | M |                        | Yes              |
| AFR2        | Does the device support the receipt of application acknowledgement frames?     | [R1]/2.2.8.3.2, 2.2.8.3.3 | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |  |                           |               | ZigBee-PRO          | M |                        | Yes              |

605 **10.6.3.1.5 ZigBee Device Objects functions**

| Item number | Item description  | Reference    | ZigBee Status | Feature set Support |              | Additional Constraints | Platform Support          |
|-------------|---|--------------|---------------|---------------------|--------------|------------------------|---------------------------|
| AZD700      | Does the device support the permissions configuration table?                | [R1]/4.6.3.8 | O             | ZigBee PRO MM       | O            |                        | Click here to enter text. |
|             |   |              |               | ZigBee-PRO          | O            |                        | Click here to enter text. |
| AZD701      | Does the device support the ModifyPermissionsCapabilityTable element of the | [R1]/4.6.3.8 | AZD700:<br>O  | ZigBee PRO MM       | AZD700:<br>O |                        | Click here to enter text. |

<sup>12</sup> CCB 1039

| Item number | Item description   | Reference    | ZigBee Status | Feature set Support |              | Additional Constraints | Platform Support          |
|-------------|--|--------------|---------------|---------------------|--------------|------------------------|---------------------------|
|             | permissions configuration table?   |              |               | ZigBee-PRO          | AZD700:<br>O |                        | Click here to enter text. |
| AZD702      | Does the device support the NetworkSettings element of the permissions configuration table?      | [R1]/4.6.3.8 | AZD700:<br>O  | ZigBee PRO MM       | AZD700:<br>O |                        | Click here to enter text. |
|             |  |              |               | ZigBee-PRO          | AZD700:<br>O |                        | Click here to enter text. |
| AZD703      | Does the device support the Application-Settings element of the permissions configuration table? | [R1]/4.6.3.8 | AZD700:<br>O  | ZigBee PRO MM       | AZD700:<br>O |                        | Click here to enter text. |
|             |  |              |               | ZigBee-PRO          | AZD700:<br>O |                        | Click here to enter text. |
| AZD704      | Does the device support the SecuritySettings element of the permissions configuration table?     | [R1]/4.6.3.8 | AZD700:<br>O  | ZigBee PRO MM       | AZD700:<br>O |                        | Click here to enter text. |
|             |  |              |               | ZigBee-PRO          | AZD700:<br>O |                        | Click here to enter text. |
| AZD705      | Does the device support the Application-Commands element of the permissions configuration table? | [R1]/4.6.3.8 | AZD700:<br>O  | ZigBee PRO MM       | AZD700:<br>O |                        | Click here to enter text. |
|             |  |              |               | ZigBee-PRO          | AZD700:<br>O |                        | Click here to enter text. |
| AZD706      | Does the device support the SKKEWith-MasterKey element of the                                    | [R1]/4.6.3.8 | AZD700:<br>O  | ZigBee PRO MM       | AZD700:<br>O |                        | Click here to enter text. |

| Item number | Item description  | Reference      | ZigBee Status                 | Feature set Support |                               | Additional Constraints  | Platform Support          |
|-------------|---|----------------|-------------------------------|---------------------|-------------------------------|---|---------------------------|
|             | permissions configuration table?                                    |                |                               | ZigBee-PRO          | AZD700:<br>O                  |   | Click here to enter text. |
| AZD707      | Does the device support the NWK rejoin procedure?                   | [R1]/3.6.1.4.2 | M                             | ZigBee PRO MM       | M                             | Support of the rejoin mechanism for recovering from a missed network update (of any kind) is mandatory ([R1] Section 2.5.5.5.4).<br><br>The length of time between hearing from its parent, or from the ZigBee coordinator, beyond which a ZigBee router shall initiate steps to rejoin the “fragment” of the network which has the ZigBee coordinator in it, is left up to the application designer. | Yes                       |
|             |   |                |                               | ZigBee-PRO          | M                             |   | Yes                       |
| AZD600      | Does the device act as a Binding Table Cache?                       | [R1]/2.5.5.5.3 | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee PRO MM       | FDT1: O<br>FDT2: O<br>FDT3: X |   | No                        |
|             |   |                |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: X |   | No                        |
| AZD601      | Does the device perform the Intra-PAN portability parent procedure? | [R1]/2.5.5.5.4 | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |   | No                        |
|             |   |                |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |   | Yes                       |
| AZD602      | Does the device perform the Intra-PAN portability child procedure?  | [R1]/2.5.5.5.4 | FDT1: X<br>FDT2: X<br>FDT3: M | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: M |   | Yes                       |
|             |   |                |                               | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: M |   | Yes                       |

| Item number | Item description  | Reference                                  | ZigBee Status | Feature set Support |         | Additional Constraints   | Platform Support          |
|-------------|---|--|---------------|---------------------|---------|--|---------------------------|
| AZD603      | Does the device support the Configuration Parameters, Startup Procedures and Additional Configuration Parameters? | [R1]/2.5.5.5.6.1, 2.5.5.5.6.2, 2.5.5.5.6.3 | O             | ZigBee PRO MM       | O       | For the ChannelMask parameter, in the 2.4 Ghz band, channel 26 shall either not be used or else a special provision for limited transmission power shall be imposed to permit U.S. FCC operations. | Yes                       |
|             |   |  |               | ZigBee-PRO          | M       |  | Yes                       |
| AZD1        | Does the device support the mandatory Device and Service Discovery Object?  | [R1]/2.5.5.6.1                             | M             | ZigBee PRO MM       | M       |  | Yes                       |
|             |   |  |               | ZigBee-PRO          | M       |  | Yes                       |
| AZD2        | Does the device support the mandatory attributes of the Device and Service Discovery Object?                      | [R1]/2.5.5.6.1                             | M             | ZigBee PRO MM       | M       |  | Yes                       |
|             |   |  |               | ZigBee-PRO          | M       |  | Yes                       |
| AZD3        | Does the device support the optional attributes of the Device and Service Discovery Object?                       | [R1]/2.5.5.6.1                             | O             | ZigBee PRO MM       | O       |  | Click here to enter text. |
|             |   |  |               | ZigBee-PRO          | O       |  | Click here to enter text. |
| AZD4        | Does the device support the optional NWK address client service of the Device and Service Discovery Object?       | [R1]/2.5.5.6.1                             | AZD3: O       | ZigBee PRO MM       | AZD3: O |  | Click here to enter text. |
|             |   |  |               | ZigBee-PRO          | AZD3: O |  | Click here to enter text. |

| Item number | Item description  | Reference      | ZigBee Status | Feature set Support |         | Additional Constraints | Platform Support          |
|-------------|---|----------------|---------------|---------------------|---------|------------------------|---------------------------|
| AZD5        | Does the device support the optional IEEE address client service of the Device and Service Discovery Object?      | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O |                        | Click here to enter text. |
| AZD6        | Does the device support the optional Node Descriptor client service of the Device and Service Discovery Object?   | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O |                        | Click here to enter text. |
| AZD7        | Does the device support the optional Power Descriptor client service of the Device and Service Discovery Object?  | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O |                        | Click here to enter text. |
| AZD8        | Does the device support the optional Simple Descriptor client service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O |                        | Click here to enter text. |
| AZD9        | Does the device support the optional Active Endpoint client service of the Device and Service Discovery Object?   | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O |                        | Click here to enter text. |

| Item number | Item description   | Reference      | ZigBee Status | Feature set Support |         | Additional Constraints | Platform Support          |
|-------------|--|----------------|---------------|---------------------|---------|------------------------|---------------------------|
| AZD10       | Does the device support the optional Match Descriptor client service of the Device and Service Discovery Object?   | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O |                        | Click here to enter text. |
|             |  |                |               | ZigBee-PRO          | AZD3: O |                        | Click here to enter text. |
| AZD11       | Does the device support the optional Complex Descriptor client service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O |                        | Click here to enter text. |
|             |  |                |               | ZigBee-PRO          | AZD3: O |                        | Click here to enter text. |
| AZD12       | Does the device support the optional Complex Descriptor server service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O |                        | Click here to enter text. |
|             |  |                |               | ZigBee-PRO          | AZD3: O |                        | Click here to enter text. |
| AZD13       | Does the device support the optional User Descriptor client service of the Device and Service Discovery Object?    | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O |                        | Click here to enter text. |
|             |  |                |               | ZigBee-PRO          | AZD3: O |                        | Click here to enter text. |
| AZD14       | Does the device support the optional User Descriptor server service of the Device and Service Discovery Object?    | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O |                        | Click here to enter text. |
|             |  |                |               | ZigBee-PRO          | AZD3: O |                        | Click here to enter text. |

| Item number | Item description  | Reference           | ZigBee Status                                | Feature set Support |         | Additional Constraints                       | Platform Support          |
|-------------|---|---------------------|--|---------------------|---------|--|---------------------------|
| AZD17       | Does the device support the mandatory Device Announce client service of the Device and Service Discovery Object?        | [R1]/2.5.5.6.1      | AZD1: M                                      | ZigBee PRO MM       | M       |  | Yes                       |
|             |   |                     |  | ZigBee-PRO          | M       |  | Yes                       |
| AZD18       | Does the device support the Device Announce server service of the Device and Service Discovery Object?                  | [R1]/2.5.5.6.1      | AZD1: M                                      | ZigBee PRO MM       | M       |  | Yes                       |
|             |   |                     |  | ZigBee-PRO          | M       |  | Yes                       |
| AZD19       | Does the device support the mandatory Security Manager Object? (CCB 2240)   | [R1]/2.1.3, 2.5.2.3 | M (for all R22 devices not on GP) (CCB 2240) | ZigBee PRO MM       | NS      | Green Power not supported on Sub GHz network | Click here to enter text. |
|             |   |                     |  | ZigBee-PRO          | M       |  | Yes                       |
| AZD100      | Does the device support the optional System Server Discovery client service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1      | AZD3: O                                      | ZigBee PRO MM       | AZD3: O |  | Click here to enter text. |
|             |   |                     |  | ZigBee-PRO          | AZD3: O |  | Click here to enter text. |
| AZD101      | Does the device support the optional System Server Discovery server service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1      | AZD3: O                                      | ZigBee PRO MM       | AZD3: O |  | Click here to enter text. |
|             |   |                     |  | ZigBee-PRO          | SR1: M  |  | Yes                       |
| AZD102      | Does the device support the optional Discovery Cache client service of the Device and                                   | [R1]/2.5.5.6.1      | AZD3: O                                      | ZigBee PRO MM       | AZD3: O |  | Click here to enter text. |

| Item number | Item description  | Reference      | ZigBee Status | Feature set Support |  | Additional Constraints | Platform Support          |
|-------------|---|----------------|---------------|---------------------|--|------------------------|---------------------------|
|             | Service Discovery Object?   |                |               | ZigBee-PRO          | AZD3: O                                |                        | Click here to enter text. |
| AZD103      | Does the device support the optional Discovery Cache server service of the Device and Service Discovery Object?       | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3:<br>FDT1: O<br>FDT2: O<br>FDT3: X |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3:<br>FDT1: O<br>FDT2: O<br>FDT3: X |                        | Click here to enter text. |
| AZD104      | Does the device support the optional Discovery Store client service of the Device and Service Discovery Object?       | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O                                |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O                                |                        | Click here to enter text. |
| AZD105      | Does the device support the optional Discovery Store server service of the Device and Service Discovery Object?       | [R1]/2.5.5.6.1 | AZD103: M     | ZigBee PRO MM       | AZD103: M                              |                        | Yes                       |
|             |   |                |               | ZigBee-PRO          | AZD103: M                              |                        | Yes                       |
| AZD106      | Does the device support the optional Node Descriptor Store client service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O                                |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O                                |                        | Click here to enter text. |
| AZD107      | Does the device support the optional Node Descriptor Store server service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1 | AZD103: M     | ZigBee PRO MM       | AZD103: M                              |                        | Yes                       |
|             |   |                |               | ZigBee-PRO          | AZD103: M                              |                        | Yes                       |

| Item number | Item description  | Reference      | ZigBee Status | Feature set Support |           | Additional Constraints | Platform Support          |
|-------------|---|----------------|---------------|---------------------|-----------|------------------------|---------------------------|
| AZD108      | Does the device support the optional Power Descriptor Store client service of the Device and Service Discovery Object?  | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O   |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O   |                        | Click here to enter text. |
| AZD109      | Does the device support the optional Power Descriptor Store server service of the Device and Service Discovery Object?  | [R1]/2.5.5.6.1 | AZD103: M     | ZigBee PRO MM       | AZD103: M |                        | Yes                       |
|             |   |                |               | ZigBee-PRO          | AZD103: M |                        | Yes                       |
| AZD110      | Does the device support the optional Active Endpoint Store client service of the Device and Service Discovery Object?   | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O   |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O   |                        | Click here to enter text. |
| AZD111      | Does the device support the optional Active Endpoint Store server service of the Device and Service Discovery Object?   | [R1]/2.5.5.6.1 | AZD103: M     | ZigBee PRO MM       | AZD103: M |                        | Yes                       |
|             |   |                |               | ZigBee-PRO          | AZD103: M |                        | Yes                       |
| AZD112      | Does the device support the optional Simple Descriptor Store client service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O   |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O   |                        | Click here to enter text. |

| Item number | Item description  | Reference      | ZigBee Status | Feature set Support |           | Additional Constraints | Platform Support          |
|-------------|---|----------------|---------------|---------------------|-----------|------------------------|---------------------------|
| AZD113      | Does the device support the optional Simple Descriptor Store server service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1 | AZD103: M     | ZigBee PRO MM       | AZD103: M |                        | Yes                       |
|             |   |                |               | ZigBee-PRO          | AZD103: M |                        | Yes                       |
| AZD114      | Does the device support the optional Remove Node Cache client service of the Device and Service Discovery Object?       | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O   |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O   |                        | Click here to enter text. |
| AZD115      | Does the device support the optional Remove Node Cache server service of the Device and Service Discovery Object?       | [R1]/2.5.5.6.1 | AZD103: M     | ZigBee PRO MM       | AZD103: M |                        | Yes                       |
|             |   |                |               | ZigBee-PRO          | AZD103: M |                        | Yes                       |
| AZD116      | Does the device support the optional Find Node Cache client service of the Device and Service Discovery Object?         | [R1]/2.5.5.6.1 | AZD3: O       | ZigBee PRO MM       | AZD3: O   |                        | Click here to enter text. |
|             |   |                |               | ZigBee-PRO          | AZD3: O   |                        | Click here to enter text. |
| AZD117      | Does the device support the optional Find Node Cache server service of the Device and Service Discovery Object?         | [R1]/2.5.5.6.1 | AZD103: M     | ZigBee PRO MM       | AZD103: M |                        | Yes                       |
|             |   |                |               | ZigBee-PRO          | AZD103: M |                        | Yes                       |

| Item number | Item description   | Reference      | ZigBee Status  | Feature set Support |           | Additional Constraints | Platform Support          |
|-------------|--|----------------|----------------|---------------------|-----------|------------------------|---------------------------|
| AZD650      | Does the device support the optional Extended Simple Descriptor client service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1 | AZD3: O        | ZigBee PRO MM       | AZD3: O   |                        | Click here to enter text. |
|             |  |                |                | ZigBee-PRO          | AZD3: O   |                        | Click here to enter text. |
| AZD651      | Does the device support the optional Extended Simple Descriptor server service of the Device and Service Discovery Object? | [R1]/2.5.5.6.1 | AZD103: M      | ZigBee PRO MM       | AZD103: M |                        | Yes                       |
|             |  |                |                | ZigBee-PRO          | AZD103: M |                        | Yes                       |
| AZD652      | Does the device support the optional Extended Active Endpoint client service of the Device and Service Discovery Object?   | [R1]/2.5.5.6.1 | AZD3: O        | ZigBee PRO MM       | AZD3: O   |                        | Click here to enter text. |
|             |  |                |                | ZigBee-PRO          | AZD3: O   |                        | Click here to enter text. |
| AZD653      | Does the device support the optional Extended Active Endpoint server service of the Device and Service Discovery Object?   | [R1]/2.5.5.6.1 | AZD103: M      | ZigBee PRO MM       | AZD103: M |                        | Yes                       |
|             |  |                |                | ZigBee-PRO          | AZD103: M |                        | Yes                       |
| AZD20       | Does the device support the mandatory attributes of the Security Manager Object with the device in a Trust Center role?    | [R1]/2.5.5.7.1 | AZD19: SDT1: M | ZigBee PRO MM       | SR1: M    |                        | No                        |
|             |  |                |                | ZigBee-PRO          | SR1: M    |                        | Yes                       |

| Item number | Item description  | Reference                        | ZigBee Status                           | Feature set Support |   | Additional Constraints   | Platform Support          |
|-------------|---|----------------------------------|---|---------------------|---|--|---------------------------|
| AZD21       | Does the device support the mandatory attributes of the Security Manager Object with the device in a non-Trust Center role? | [R1]/2.5.5.7.1                   | AZD19:<br>SDT2: M                       | ZigBee PRO MM       | SDT2: M                                 |  | Yes                       |
|             |   |                                  |   | ZigBee-PRO          | SDT2: M                                 |  | Yes                       |
| AZD22       | Does the device support the optional Binding Manager Object?  | [R1]/2.5.5.8.1                   | O                                       | ZigBee PRO MM       | FDT1: M<br>FDT2: O<br>FDT3: O           | End_Device_Bind_req server processing in the coordinator is required.<br><br>The ZigBee coordinator must process end device bind requests and supply Bind_req commands to the source of matched clusters in the paired end device bind requests. | Yes                       |
|             |   |                                  |   | ZigBee-PRO          | FDT1: M<br>FDT2: O<br>FDT3: O           |  | Yes                       |
| AZD23       | Does the device support the optional End Device Bind client service of the Binding Manager Object?                          | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.1 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |  | Yes                       |
|             |   |                                  |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |  | Yes                       |
| AZD24       | Does the device support the optional End Device Bind server service of the Binding Manager Object?                          | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.1 | AZD22:<br>FDT1: M<br>FDT2: X<br>FDT3: X | ZigBee PRO MM       | AZD22:<br>FDT1: M<br>FDT2: X<br>FDT3: X |  | Click here to enter text. |
|             |   |                                  |   | ZigBee-PRO          | AZD22:<br>FDT1: M<br>FDT2: X<br>FDT3: X |  | Yes                       |
| AZD25       | Does the device support the optional Bind client service of the Binding Manager Object?                                     | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.2 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |  | Yes                       |
|             |   |                                  |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |  | Yes                       |

| Item number | Item description   | Reference                        | ZigBee Status                           | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|--|----------------------------------|---|---------------------|---|------------------------|------------------|
| AZD26       | Does the device support the optional Bind server service of the Binding Manager Object?          | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.2 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee<br>PRO MM    | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |  |                                  |   | ZigBee-<br>PRO      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD27       | Does the device support the optional Unbind client service of the Binding Manager Object?        | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.3 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee<br>PRO MM    | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |  |                                  |   | ZigBee-<br>PRO      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD28       | Does the device support the optional Unbind server service of the Binding Manager Object?        | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.3 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee<br>PRO MM    | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |  |                                  |   | ZigBee-<br>PRO      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD200      | Does the device support the optional Bind Register client service of the Binding Manager Object? | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.4 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee<br>PRO MM    | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |  |                                  |   | ZigBee-<br>PRO      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD201      | Does the device support the optional Bind Register server service of the Binding Manager Object? | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.4 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee<br>PRO MM    | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |  |                                  |   | ZigBee-<br>PRO      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD202      | Does the device support the optional Replace Device client service of the                        | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.5 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee<br>PRO MM    | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |

| Item number | Item description  | Reference                        | ZigBee Status                           | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|----------------------------------|---|---------------------|---|------------------------|------------------|
|             | Binding Manager Object?   |                                  |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD203      | Does the device support the optional Replace Device server service of the Binding Manager Object?           | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.5 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                  |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD204      | Does the device support the optional Store Backup Bind Entry client service of the Binding Manager Object?  | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.6 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                  |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD205      | Does the device support the optional Store Backup Bind Entry server service of the Binding Manager Object?  | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.6 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                  |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD206      | Does the device support the optional Remove Backup Bind Entry client service of the Binding Manager Object? | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.7 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                  |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD207      | Does the device support the optional Remove Backup Bind Entry server  | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.7 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |

| Item number | Item description  | Reference                             | ZigBee Status                           | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|---------------------------------------|---|---------------------|---|------------------------|------------------|
|             | service of the Binding Manager Object?  |                                       |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD208      | Does the device support the optional Backup Bind Table client service of the Binding Manager Object?  | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.8      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                       |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD209      | Does the device support the optional Backup Bind Table server service of the Binding Manager Object?  | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.8      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                       |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD210      | Does the device support the optional Recover Bind Table client service of the Binding Manager Object? | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.9      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                       |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD211      | Does the device support the optional Recover Bind Table server service of the Binding Manager Object? | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.9      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                       |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD212      | Does the device support the optional Backup Source Bind client service of the Binding Manager Object? | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.1<br>0 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                       |   | ZigBee-PRO          | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |

| Item number | Item description  | Reference                             | ZigBee Status                           | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|---------------------------------------|---|---------------------|---|------------------------|------------------|
| AZD213      | Does the device support the optional Backup Source Bind server service of the Binding Manager Object?             | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.1<br>0 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee<br>PRO MM    | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                       |   | ZigBee-<br>PRO      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD214      | Does the device support the optional Recover Source Bind client service of the Binding Manager Object?            | [R1]/2.5.5.8.1<br>[R1]/2.4.3.2.1<br>1 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee<br>PRO MM    | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                       |   | ZigBee-<br>PRO      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD215      | Does the device support the optional Recover Source Bind server service of the Binding Manager Object?            | [R1]/2.5.5.8.1<br>[R1]/2.4.4.2.1<br>1 | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee<br>PRO MM    | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                                       |   | ZigBee-<br>PRO      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD29       | Does the device support the optional APSME BIND and UNBIND service of the Binding Manager Object?                 | [R1]/2.5.5.8.1                        | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO<br>MM    | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |   |                                       |   | ZigBee-<br>PRO      | AZD22:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD30       | Does the device support the mandatory NLME GET, SET and NETWORK DISCOVERY services of the Network Manager Object? | [R1]/2.5.5.9.1                        | M                                       | ZigBee<br>PRO MM    | M                                       |                        | Yes              |
|             |   |                                       |   | ZigBee-<br>PRO      | M                                       |                        | Yes              |

| Item number | Item description  | Reference      | ZigBee Status                 | Feature set Support |                               | Additional Constraints   | Platform Support          |
|-------------|---|----------------|-------------------------------|---------------------|-------------------------------|--|---------------------------|
| AZD31       | Does the device support the optional NLME NETWORK FORMATION service of the Network Manager Object?                          | [R1]/2.5.5.9.1 | FDT1: M<br>FDT2: X<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: X<br>FDT3: X |  | Click here to enter text. |
|             |   |                |                               | ZigBee-PRO          | FDT1: M<br>FDT2: X<br>FDT3: X |  | Yes                       |
| AZD299      | Does the device support the optional NLME NETWORK FORMATION service of the DistributedNetwork Service Primitive? (CCB 2137) | [R1]/3.2.2.5   | O                             | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M | Can form independent distributed network on sub-GHz network and a different distributed network on 2.4 GHz. Sub-GHz unique channel list. | Yes                       |
|             |   | [R1]/3.2.2.5   | O                             | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M | Can form a distributed network on 2.4 GHz only   | Yes                       |
| AZD32       | Does the device support the optional NLME JOIN service of the Network Manager Object?                                       | [R1]/2.5.5.9.1 | FDT1: X<br>FDT2: M<br>FDT3: M | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes                       |
|             |   |                |                               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes                       |
| AZD300      | Does the device support the optional NLME START ROUTER service of the Network Manager Object?                               | [R1]/2.5.5.9.1 | FDT1: X<br>FDT2: M<br>FDT3: X | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: X |  | Click here to enter text. |
|             |   |                |                               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: X |  | Yes                       |
| AZD33       | Does the device support the mandatory NLME LEAVE service of the Network Manager Object?                                     | [R1]/2.5.5.9.1 | FDT1: X<br>FDT2: M<br>FDT3: M | ZigBee PRO MM       | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes                       |
|             |   |                |                               | ZigBee-PRO          | FDT1: X<br>FDT2: M<br>FDT3: M |  | Yes                       |

| Item number | Item description   | Reference      | ZigBee Status                 | Feature set Support |                               | Additional Constraints   | Platform Support          |
|-------------|--|----------------|-------------------------------|---------------------|-------------------------------|--|---------------------------|
| AZD301      | Does the device support the optional NLME PERMIT JOINING service of the Network Manager Object?  | [R1]/2.5.5.9.1 | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |  | Click here to enter text. |
|             |  |                |                               | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |  | Yes                       |
| AZD34       | Does the device support the optional NLME RESET service of the Network Manager Object?           | [R1]/2.5.5.9.1 | FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | FDT1: O<br>FDT2: O<br>FDT3: O |  | Yes                       |
|             |  |                |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: O |  | Yes                       |
| AZD35       | Does the device support the optional NLME SYNC service of the Network Manager Object?            | [R1]/2.5.5.9.1 | FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | FDT1: X<br>FDT2: X<br>FDT3: M | See clause 8.4.2.1 in this document, Network layer functions, Item number NLF17. | Yes                       |
|             |  |                |                               | ZigBee-PRO          | FDT1: X<br>FDT2: X<br>FDT3: M |  | Yes                       |
| AZD302      | Does the device support the mandatory NLME NWK_STATUS service of the Network Manager Object?     | [R1]/2.5.5.9.1 | M                             | ZigBee PRO MM       | M                             |  | Yes                       |
|             |  |                |                               | ZigBee-PRO          | M                             |  | Yes                       |
| AZD303      | Does the device support the optional NLME ROUTE DISCOVERY service of the Network Manager Object? | [R1]/2.5.5.9.1 | FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | FDT1: O<br>FDT2: O<br>FDT3: O |  | Yes                       |
|             |  |                |                               | ZigBee-PRO          | FDT1: O<br>FDT2: O<br>FDT3: O |  | Yes                       |

| Item number | Item description  | Reference       | ZigBee Status                           | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|-----------------|---|---------------------|---|------------------------|------------------|
| AZD36       | Does the device support the optional Node Manager Object?                       | [R1]/2.5.5.10.1 | FDT1: O<br>FDT2: O<br>FDT3: O           | ZigBee PRO MM       | FDT1: O<br>FDT2: O<br>FDT3: O           |                        | Yes              |
|             |   |                 |   | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: O           |                        | Yes              |
| AZD37       | Does the device support the optional Node Manager NWK Discovery client service? | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD38       | Does the device support the optional Node Manager NWK Discovery server service? | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: M<br>FDT2: M<br>FDT3: O |                        | Yes              |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: M<br>FDT2: M<br>FDT3: O |                        | Yes              |
| AZD39       | Does the device support the optional Node Manager LQI client service?           | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD40       | Does the device support the optional Node Manager LQI server service?           | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: M<br>FDT2: M<br>FDT3: O |                        | Yes              |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: M<br>FDT2: M<br>FDT3: O |                        | Yes              |
| AZD41       | Does the device support the optional Node Manager RTG                           | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |

| Item number | Item description  | Reference       | ZigBee Status                           | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|-----------------|---|---------------------|---|------------------------|------------------|
|             | client service?   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD42       | Does the device support the optional Node Manager RTG server service?   | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: M<br>FDT2: M<br>FDT3: O |                        | Yes              |
| AZD43       | Does the device support the optional Node Manager Bind client service?  | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD44       | Does the device support the optional Node Manager Bind server service?  | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD45       | Does the device support the optional Node Manager Leave client service? | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD46       | Does the device support the optional Node Manager Leave                 | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: M<br>FDT2: M<br>FDT3: O |                        | Yes              |

| Item number | Item description  | Reference       | ZigBee Status                           | Feature set Support |   | Additional Constraints | Platform Support          |
|-------------|---|-----------------|---|---------------------|---|------------------------|---------------------------|
|             | server service?   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: M<br>FDT2: M<br>FDT3: O |                        | Yes                       |
| AZD47       | Does the device support the optional Node Manager Direct Join client service?     | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No                        |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No                        |
| AZD48       | Does the device support the optional Node Manager Direct Join server service?     | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | X                                       |                        | Click here to enter text. |
|             |   |                 |   | ZigBee-PRO          | X                                       |                        | Click here to enter text. |
| AZD400      | Does the device support the optional Node Manager Permit Joining client service?  | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: M<br>FDT2: M<br>FDT3: X |                        | Click here to enter text. |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes                       |
| AZD401      | Does the device support the optional Node Manager Discovery Cache client service? | [R1]/2.5.5.10.1 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No                        |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No                        |
| AZD402      | Does the device support the optional Node Manager Discovery Cache server service? | [R1]/2.5.5.10.2 | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O | ZigBee PRO MM       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No                        |
|             |   |                 |   | ZigBee-PRO          | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O |                        | No                        |

| Item number | Item description  | Reference           | ZigBee Status                           | Feature set Support |  | Additional Constraints   | Platform Support |
|-------------|---|---------------------|---|---------------------|--|--|------------------|
| AZD800      | Does the device support the optional Node Manager NWK update client service?          | [R1]/2.4.3.3.       | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee-<br>PRO MM   | AZD36:<br>FDT1: O<br>FDT2: O<br>FDT3: O  | The ability to send the Mgmt_NWK_Update_req command in order to request the target to perform an energy scan is mandatory for the Network Channel Manager, and optional for all non Network Channel Manager routers and the coordinator. Applicable to 2.4 GHz channel list. | Yes              |
| AZD801      | Does the device support the optional Node Manager NWK Enhanced update client service? | [R1]/2.4.3.3.1<br>0 | AZD36:<br>FDT1: X<br>FDT2: M<br>FDT3: O | ZigBee-<br>PRO MM   | AZD36:<br>FDT1: X<br>FDT2: M<br>FDT3: O  | The ability to send the Mgmt_NWK_Update_req command in order to request the target to perform an energy scan is mandatory for the Network Channel Manager, and optional for all non Network Channel Manager routers and the coordinator. Applicable to sub GHz channel list. | Yes              |
| AZD802      | Does the device support the optional Node Manager NWK update server service?          | [R1]/2.4.4.3.9      | AZD36:<br>FDT1: M<br>FDT2: X<br>FDT3: X | ZigBee PRO MM       | AZD36:<br>FDT1: M<br>FDT2: X<br>FDT3: X  | The ability for a non Network Channel Manager to receive and process the Mgmt_NWK_Update_req command is mandatory for the network manager and all routers and optional for end devices. Applicable to 2.4 GHz channel list.  | No               |
| AZD803      | Does the MM device support the Node Manager NWK Enhanced update server service?       | [R1]/2.4.3.3.1<br>0 | AZD36:<br>FDT1: M<br>FDT2: X<br>FDT3: X | ZigBee PRO MM       | MM Sub-GHz I/F<br>FDT1: M<br>FDT2: X<br>FDT3: X<br><br>MM 2.4 GHz I/F and<br>2.4GHz Devices<br><br>FDT1: X<br>FDT2: X<br>FDT3: X | It's MANDATORY on ALL MM Devices to support Mgmt_NWK_Enhanced Update_req on Sub-GHz interface .<br><br>All MM 2.4 GHz interface and 2.4 GHz devices SHALL NOT support Mgmt_NWK_Enhanced Update_req command.  | No               |

| Item number | Item description   | Reference           | ZigBee Status                           | Feature set Support |   | Additional Constraints  | Platform Support          |
|-------------|--|---------------------|---|---------------------|---|---|---------------------------|
| AZD804      | Does the MM device support the Mgmt_NWK_IEEE_Joining_List_client service?        | [R1]/2.4.3.3.1<br>1 | AZD36:<br>FDT1: X<br>FDT2: M<br>FDT3: X | ZigBee PRO MM       | AZD36:<br>FDT1: X<br>FDT2: M<br>FDT3: X | Mgmt_NWK_IEEE_Joining_List_req is only required on Sub-GHz devices and networks that support Sub-GHz network routers.<br><br>UK doesn't support Sub-GHz routers therefore not required in UK deployed devices.                                  | Click here to enter text. |
| AZD805      | Does the MM device support the Mgmt_NWK_IEEE_Joining_List_server service?        | [R1]/2.4.3.3.1<br>1 | AZD36:<br>FDT1: M<br>FDT2: X<br>FDT3: X | ZigBee PRO MM       | AZD36:<br>FDT1: M<br>FDT2: X<br>FDT3: X | The ability for a non Network Channel Manager to receive and process the Mgmt_NWK_IEEE_Joining_List_-req command is mandatory for the network manager, all routers and all end devices for R22. Applicable to Sub GHz and 2.4 GHz channel list. | Click here to enter text. |
| AZD806      | Does the MM device support the Channel Change Manager?                           |                     | AZD36:<br>FDT1:M<br>FDT2: X<br>FDT3:X   | ZigBee PRO MM       | AZD36:<br>FDT1:M<br>FDT2: X<br>FDT3:X   |   |                           |
| AZ807       | Does the MM device support the LINK_POWER_DELTA command on Sub-GHz interface?    |                     | AZD36:<br>FDT1:M<br>FDT2: X<br>FDT3:M   | ZigBee PRO MM       | AZD36:<br>FDT1:M<br>FDT2: X<br>FDT3:M   | LINK POWER DELTA command is only supported on MM Coordinator and Sub-GHz end devices on Sub-GHz interface.  | Yes                       |
| AZD49       | Does the device support the mandatory Configuration Attributes?                  | [R1]/2.5.6          | M                                       | ZigBee-PRO          | M                                       |   | Yes                       |
|             |  |                     |   | ZigBee PRO MM       | M                                       |   | Yes                       |
| AZD50       | Does the device support the optional Complex Descriptor configuration attribute? | [R1]/2.5.6          | O                                       | ZigBee-PRO          | O                                       |   | Yes                       |
|             |  |                     |   | ZigBee PRO MM       | O                                       |   | Yes                       |

| Item number | Item description  | Reference  | ZigBee Status                 | Feature set Support |                               | Additional Constraints | Platform Support |
|-------------|---|------------|-------------------------------|---------------------|-------------------------------|------------------------|------------------|
| AZD51       | Does the device support the optional User Descriptor configuration attribute?         | [R1]/2.5.6 | O                             | ZigBee-PRO          | O                             |                        | Yes              |
|             |   |            |                               | ZigBee-PRO MM       | O                             |                        | Yes              |
| AZD52       | Does the device support the optional Max Bind configuration attribute?                | [R1]/2.5.6 | O                             | ZigBee-PRO          | O                             |                        | No               |
|             |   |            |                               | ZigBee-PRO MM       | O                             |                        | No               |
| AZD53       | Does the device support the optional Master Key configuration attribute?              | [R1]/2.5.6 | O                             | ZigBee-PRO          | O                             |                        | No               |
|             |   |            |                               | ZigBee-PRO MM       | O                             |                        | No               |
| AZD54       | Does the device support the optional End Device Bind Timeout configuration attribute? | [R1]/2.5.6 | FDT1: M<br>FDT2: X<br>FDT3: X | ZigBee-PRO          | FDT1: M<br>FDT2: X<br>FDT3: X |                        | Yes              |
|             |   |            |                               | ZigBee-PRO MM       | FDT1: M<br>FDT2: X<br>FDT3: X |                        | No               |
| AZD55       | Does the device support the optional Permit Join Duration configuration attribute?    | [R1]/2.5.6 | FDT1: M<br>FDT2: M<br>FDT3: X | ZigBee-PRO          | FDT1: M<br>FDT2: M<br>FDT3: X |                        | Yes              |
|             |   |            |                               | ZigBee-PRO MM       | FDT1: M<br>FDT2: M<br>FDT3: X |                        | No               |
| AZD56       | Does the device support the optional NWK Security Level configuration                 | [R1]/2.5.6 | AZD19:<br>O                   | ZigBee-PRO          | AZD19: O                      |                        | No               |

| Item number | Item description   | Reference  | ZigBee Status                  | Feature set Support |                                | Additional Constraints | Platform Support |
|-------------|--|------------|--------------------------------|---------------------|--------------------------------|------------------------|------------------|
|             | attribute?   |            |                                | ZigBee PRO MM       | AZD19: O                       |                        | No               |
| AZD57       | Does the device support the optional NWK Secure All Frames configuration attribute?            | [R1]/2.5.6 | AZD19: O                       | ZigBee-PRO          | AZD19: O                       |                        | Yes              |
|             |  |            |                                | ZigBee PRO MM       | AZD19: O                       |                        | Yes              |
| AZD500      | Does the device support the optional NWK Leave Remove Children configuration attribute?        | [R1]/2.5.6 | AZD19: FDT1: M FDT2: M FDT3: X | ZigBee-PRO          | AZD19: FDT1: M FDT2: M FDT3: X |                        | Yes              |
|             |  |            |                                | ZigBee PRO MM       | AZD19: FDT1: M FDT2: M FDT3: X |                        | No               |
| AZD501      | Does the device support the optional NWK Broadcast Delivery configuration attribute?           | [R1]/2.5.6 | FDT1: O FDT2: O FDT3: X        | ZigBee-PRO          | FDT1: O FDT2: O FDT3: X        |                        | No               |
|             |  |            |                                | ZigBee PRO MM       | FDT1: O FDT2: O FDT3: X        |                        | No               |
| AZD502      | Does the device support the optional NWK Transaction Persistence Time configuration attribute? | [R1]/2.5.6 | FDT1: O FDT2: O FDT3: X        | ZigBee-PRO          | FDT1: O FDT2: O FDT3: X        |                        | No               |
|             |  |            |                                | ZigBee PRO MM       | FDT1: O FDT2: O FDT3: X        |                        | No               |
| AZD503      | Does the device support the optional NWK Indirect Poll Rate configuration                      | [R1]/2.5.6 | FDT1: X FDT2: X FDT3: M        | ZigBee-PRO          | FDT1: X FDT2: X FDT3: M        |                        | Yes              |

| Item number | Item description  | Reference                     | ZigBee Status                 | Feature set Support        |                               | Additional Constraints | Platform Support |
|-------------|---|-------------------------------|-------------------------------|----------------------------|-------------------------------|------------------------|------------------|
|             | attribute?  |                               |                               | ZigBee PRO MM              | FDT1: X<br>FDT2: X<br>FDT3: M |                        | Yes              |
| AZD504      | Does the device support the optional Max Associations configuration attribute?                                    | [R1]/2.5.6                    | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee-PRO                 | FDT1: O<br>FDT2: O<br>FDT3: X |                        | No               |
|             |   |                               |                               | ZigBee PRO MM              | FDT1: O<br>FDT2: O<br>FDT3: X |                        | No               |
| AZD505      | Does the device support the optional NWK Direct Join Addresses configuration attribute?                           | [R1]/2.5.6                    | FDT1: O<br>FDT2: O<br>FDT3: X | ZigBee-PRO                 | FDT1: O<br>FDT2: O<br>FDT3: X |                        | No               |
|             |   |                               |                               | ZigBee PRO MM              | FDT1: O<br>FDT2: O<br>FDT3: X |                        | No               |
| AZD506      | Does the device support the optional Parent Link Retry Threshold configuration attribute?                         | [R1]/2.5.6                    | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO                 | FDT1: X<br>FDT2: O<br>FDT3: O |                        | No               |
|             |   |                               |                               | ZigBee PRO MM              | FDT1: X<br>FDT2: O<br>FDT3: O |                        | No               |
| AZD507      | Does the device support the mandatory end device timeout Rejoin Interval configuration attribute?<br>(CCB 2144)   | [R1]/3.6.10.3,<br>3.6.1.4.3.1 | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO                 | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |   |                               |                               | ZigBee PRO MM              | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes              |
| AZD508      | Does the device support the optional Max end device timeout Rejoin Interval configuration attribute?<br>(CCB2144) | [R1]/3.6.10.3,<br>3.6.1.4.3.1 | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO                 | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes              |
|             |   |                               |                               | ZigBee-PRO<br>ZigBee PROMB | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes              |

| Item number | Item description  | Reference       | ZigBee Status                 | Feature set Support         |                               | Additional Constraints | Platform Support          |
|-------------|---|-----------------|-------------------------------|-----------------------------|-------------------------------|------------------------|---------------------------|
| AZD509      | When the routing procedure specifies that the NSDU is to be transmitted it is compliant to R22 per section 3.2.1.1.3? | [R1]3.2.1.1.3   | FDT1: M<br>FDT2: M<br>FDT3: M | ZigBee-PRO<br>ZigBee PROMIB | FDT1: M<br>FDT2: M<br>FDT3: M |                        | Yes                       |
| AZD510      | Does the device support Network Management Data ChannelList Structure to support one or more MAC interfaces?          | [R1]3.2.2.2.1   | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO<br>ZigBee PRO MM | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes                       |
| AZD511      | Does the device support Energy DetectChannelInfo defined in Table 3.9?  | [R1]3.2.2.2.3   | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO<br>ZigBee PRO MM | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes                       |
| AZD512      | Does the device properly support NLME-NETWORK-DISCOVERY request and Request primitive defined in Table 3.10?          | [R1]3.2.2.3.1   | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO<br>ZigBee PROMIB | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes                       |
| AZD513      | Does the device properly support NLME-NETWORK_FORMATION request and response  | [R1]3.2.2.5.3   | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO<br>ZigBee PRO MM | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Click here to enter text. |
| AZD514      | Does the device properly support NLME-ED-SCAN request and response?   | [R1] 3.2.2.12.2 | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO<br>ZigBee PRO MM | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes                       |
| AZD515      | Does the device support NLME-SET-INTERFACE command and response?  | [R1]3.2.2.36    | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO<br>ZigBee PRO MM | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Click here to enter text. |

| Item number | Item description   | Reference    | ZigBee Status                 | Feature set Support         |                               | Additional Constraints | Platform Support          |
|-------------|--|--------------|-------------------------------|-----------------------------|-------------------------------|------------------------|---------------------------|
| AZD516      | Does the device support NLME-GET-INTERFACE command and response? | [R1]3.2.2.37 | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO<br>ZigBee PRO MM | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Click here to enter text. |
| AZD517      | Does the device support Verify Link Cost Command?                | [R1]3.4.13   | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO<br>ZigBee PRO MM | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes                       |
| AZD518      | Does the device support Power Negotiation on sub GHz channels?   | [R1]3.6.11   | FDT1: X<br>FDT2: O<br>FDT3: O | ZigBee-PRO<br>ZigBee PRO MM | FDT1: X<br>FDT2: O<br>FDT3: O |                        | Yes                       |
|             |  |              |                               |                             |                               |                        |                           |

### 606 10.6.3.1.6 ZigBee Application Framework functions

| Item number | Item description  | Reference  | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|---|------------|---------------|---------------------|---|------------------------|------------------|
| AAF2        | Does the device support the mandatory ZigBee Descriptor structures? | [R1]/2.3.2 | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |   |            |               | ZigBee-PRO          | M |                        | Yes              |
| AAF3        | Does the device support the optional ZigBee Complex Descriptor      | [R1]/2.3.2 | O             | ZigBee PRO MM       | O |                        | Yes              |

| Item number | Item description   | Reference    | ZigBee Status | Feature set Support |   | Additional Constraints | Platform Support |
|-------------|--|--------------|---------------|---------------------|---|------------------------|------------------|
|             | structure?   |              |               | ZigBee-PRO          | O |                        | Yes              |
| AAF4        | Does the device support the optional ZigBee User Descriptor structure? | [R1]/2.3.2   | O             | ZigBee PRO MM       | O |                        | Yes              |
|             |  |              |               | ZigBee-PRO          | O |                        | Yes              |
| AAF5        | Does the device support the transmission of descriptors?               | [R1]/2.3.2.1 | M             | ZigBee PRO MM       | M |                        | Yes              |
|             |  |              |               | ZigBee-PRO          | M |                        | Yes              |

607