



**ZigBee**<sup>®</sup>  
Control your world

**ZigBee ZID Profile:  
PICS Proforma  
for Freescale BeeStack Consumer  
Development Kit**

ZigBee Document **docs-11-5753-02**

September 2012

Sponsored by: ZigBee Alliance

Accepted by	This document has not yet been accepted for release by the ZigBee Alliance Board of Directors
Abstract	As a part of formal conformance testing, manufacturers will be asked to submit a statement of protocol conformance with respect to the appropriate ZigBee devices required by the application profile under test. This document is intended to provide the form of that statement of conformance for the ZID profile.
Keywords	ZID, HID, PICS, Profile testing.

---

Copyright © 1996-2012 by the ZigBee Alliance.

2400 Camino Ramon, Suite 375, San Ramon, CA 94583, USA

<http://www.zigbee.org>

All rights reserved.

Permission is granted to members of the ZigBee Alliance to reproduce this document for their own use or the use of other ZigBee Alliance members only, provided this notice is included. All other rights reserved. Duplication for sale, or for commercial or for-profit use is strictly prohibited without the prior written consent of the ZigBee Alliance.

This page is intentionally blank

## Notice of use and disclosure

The ZigBee Specification is available to individuals, companies and institutions free of charge for all non-commercial purposes (including university research, technical evaluation, and development of non-commercial software, tools, or documentation). No part of this specification may be used in development of a product for sale without becoming a member of ZigBee Alliance.

Copyright © ZigBee Alliance, Inc. (2008-2011). All rights Reserved. This information within this document is the property of the ZigBee Alliance and its use and disclosure are restricted.

Elements of ZigBee Alliance specifications may be subject to third party intellectual property rights, including without limitation, patent, copyright or trademark rights (such a third party may or may not be a member of ZigBee). ZigBee is not responsible and shall not be held responsible in any manner for identifying or failing to identify any or all such third party intellectual property rights.

This document and the information contained herein are provided on an “AS IS” basis and ZigBee DISCLAIMS ALL WARRANTIES EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO (A) ANY WARRANTY THAT THE USE OF THE INFORMATION HEREIN WILL NOT INFRINGE ANY RIGHTS OF THIRD PARTIES (INCLUDING WITHOUT LIMITATION ANY INTELLECTUAL PROPERTY RIGHTS INCLUDING PATENT, COPYRIGHT OR TRADEMARK RIGHTS) OR (B) ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, TITLE OR NONINFRINGEMENT. IN NO EVENT WILL ZIGBEE BE LIABLE FOR ANY LOSS OF PROFITS, LOSS OF BUSINESS, LOSS OF USE OF DATA, INTERRUPTION OF BUSINESS, OR FOR ANY OTHER DIRECT, INDIRECT, SPECIAL OR EXEMPLARY, INCIDENTAL, PUNITIVE OR CONSEQUENTIAL DAMAGES OF ANY KIND, IN CONTRACT OR IN TORT, IN CONNECTION WITH THIS DOCUMENT OR THE INFORMATION CONTAINED HEREIN, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH LOSS OR DAMAGE. All Company, brand and product names may be trademarks that are the sole property of their respective owners.

The above notice and this paragraph must be included on all copies of this document that are made.

ZigBee Alliance, Inc.

2400 Camino Ramon, Suite 375

San Ramon, CA 94583

This page is intentionally blank

## Table of contents

1	Introduction.....	1
1.1	Scope .....	1
1.2	Purpose.....	1
1.3	Abbreviations and special symbols.....	1
1.4	Instructions for completing the PICS proforma.....	2
1.5	PICS proforma tables .....	2
2	References.....	3
3	Implementation declaration .....	4
3.1	Identification of the implementation.....	4
3.2	Identification of the protocol.....	5
3.3	Global statement of conformance .....	5
4	General.....	7
4.1	ZigBee Device Types.....	7
4.2	Boot Protocol.....	7
4.3	Fragmentation.....	7
4.4	Security.....	8
5	HID Adaptor .....	9
5.1	GDP Command Code.....	9
5.2	ZID Command Code .....	9
5.3	ZID Attributes .....	10
5.4	Transmission Model.....	10
5.5	Proxy Table .....	11
5.6	Application Specific.....	13
6	HID Class Device .....	14
6.1	GDP Command Code.....	14

6.2	ZID Command Code .....	14
6.3	ZID Attributes .....	15
6.4	Transmission Model.....	16

This page is intentionally blank





## 1 Introduction

To evaluate conformance of a particular implementation, it is necessary to have a statement of which capabilities and options have been implemented for a given standard. Such a statement is called a protocol implementation conformance statement (PICS).

### 1.1 Scope

This document provides the protocol implementation conformance statement (PICS) proforma for the ZigBee ZID profile [R3] in compliance with the relevant requirements, and in accordance with the relevant guidance.

### 1.2 Purpose

The supplier of a protocol implementation claiming to conform to the ZigBee ZID profile shall complete the following PICS proforma and accompany it with the information necessary to identify fully both the supplier and the implementation.

The PICS is in the form of answers to a set of questions in the PICS proforma. The questions in a proforma consist of a systematic list of protocol capabilities and options as well as their implementation requirements. The implementation requirement indicates whether implementation of a capability is mandatory, optional, or conditional depending on options selected. When a protocol implementer answers questions in a PICS proforma, they would indicate whether an item is implemented or not, and provide explanations if an item is not implemented.

### 1.3 Abbreviations and special symbols

Notations for requirement status:

M	Mandatory
O	Optional
O.n	Optional, but support of at least one of the group of options labeled O.n is required.
N/A	Not applicable
X	Prohibited
<i>Item Number:Status</i>	Status is conditional on support of item number

“*Item Number*”: Conditional, status dependent upon the support marked for the “*Item Number*”.

For example, FD1: O.1 indicates that the status is optional but at least one of the features described in FD1 is required to be implemented, if this implementation is to follow the standard of which this PICS Proforma is a part.

#### **1.4 Instructions for completing the PICS proforma**

If a given implementation is claimed to conform to this standard, the actual PICS proforma to be filled in by a supplier shall be technically equivalent to the text of the PICS proforma in this annex, and shall preserve the numbering and naming and the ordering of the PICS proforma.

PICS which conform to this document shall be a conforming PICS proforma completed in accordance with the instructions for completion given in this annex.

The main part of the PICS is a fixed-format questionnaire, divided into five tables. Answers to the questionnaire are to be provided in the rightmost column, either by simply marking an answer to indicate a restricted choice (such as Yes or No), or by entering a value, set, or range of values.

#### **1.5 PICS proforma tables**

The tables in clauses 4 onwards are composed of the detailed questions to be answered, which make up the PICS proforma.

## 2 References

The following standards contain provisions, which, through reference in this document, constitute provisions of this standard. All the standards listed are normative references. At the time of publication, the editions indicated were valid. All standards are subject to revision, and parties to agreements based on this standard are encouraged to investigate the possibility of applying the most recent editions of the standards indicated below.

### 2.1 ZigBee Alliance documents

- [R1] ZigBee document 11187: GDP Specification
- [R2] ZigBee document 10-5557: ZID Profile Specification
- [R3] ZigBee document 10-5933: ZigBee ZID Profile Interoperability Specification
- [R4] ZigBee document 08-0002: RF4CE Specification

## 3 Implementation declaration

### 3.1 Identification of the implementation

#### Implementation under test (IUT) identification

IUT name: ZigBee Input Device Profile and HID Adapter/Device Applications for Freescale BeeStack Consumer Development Kit

IUT version: HCS08 BeeStack Consumer Codebase 1.7

#### System under test (SUT) identification

SUT name: Freescale BeeStack Consumer Development Kit

Software Version: 1.7

Hardware Version: MC1323x

Operating system (optional): BeeStack TS

#### Product supplier

Name: Freescale

Address: 2100 E. Elliot Rd Tempe, AZ 85284 USA

Telephone number: +1-480-413-2768

Facsimile number: +1-480-413-4433

Email address: ryan.kelly@freescale.com

Additional information:

#### Client

Name: Freescale

Address: 2100 E. Elliot Rd Tempe, AZ 85284 USA

Telephone number: +1-480-413-2768

Facsimile number: +1-480-413-4433

Email address: ryan.kelly@freescale.com

Additional information:

### **PICS contact person**

Name: Ryan Kelly

Address: 2100 E. Elliot Rd Tempe, AZ 85284 USA

Telephone number: +1-480-413-2768

Facsimile number: +1-480-413-4433

Email address: ryan.kelly@freescale.com

Additional information:

## **3.2 Identification of the protocol**

This PICS proforma applies to ZigBee ZID profile specification.

## **3.3 Global statement of conformance**

The implementation described in this PICS proforma meets all of the mandatory requirements of the referenced standards:

Application Profile: ZigBee ZID – 105557

Yes

No

Note -- Answering 'No' indicates non-conformance to the specified protocol standard. Non-supported mandatory capabilities are to be identified in the following tables, with an explanation by the implementer explaining why the implementation is non-conforming.

The supplier will have fully complied with the requirements for a statement of conformance by completing the statement contained in this sub-clause. That means, by clicking the above, the statement of conformance is complete.

## 4 General

### 4.1 ZigBee Device Types

Item number	Item description	Reference	Status	Support
FDT1	Is this a ZigBee HID Adaptor?	[R1]/ Section 2	O.1	YES
FDT2	Is this a ZigBee HID Class Device?	[R1]/Section 2	O.1	YES

### 4.2 Boot Protocol

Item number	Item description	Reference	Status	Support
BPT1	Is this a ZigBee HID Adaptor handles the boot mechanism?	[R1]/ Section 5.1.4	M	YES (Not Certifiable)
BPT2	Is this a ZigBee HID Class Device support the boot protocol?	[R1]/Section 5.1.4	O	YES (Not Certifiable)

### 4.3 Fragmentation

Item number	Item description	Reference	Status	Support
BFT1	Does the ZigBee HID adaptor receives and defragment the non standard descriptor component?	[R1]/ Section 5.1.5	O	YES (Not Certifiable)
BFT2	Does the ZigBee HID Class device properly send the non standard descriptor component using the fragmentation mechanism?	[R1]/Section 5.1.5	O	YES (Not Certifiable)

#### 4.4 Security

Item number	Item description	Reference	Status	Support
ST1	Is this a ZigBee HID Adaptor that transmits the command frames security enabled?	[R1]/ Section 5.4.1	M	YES
ST2	Is this a ZigBee HID Class Device that transmits the command frames security enabled?	[R1]/ Section 5.4.1	M	YES
ST5	Is this a ZigBee HID Adaptor that transmits the Report Data command frames security enabled?	[R1]/ Section 5.4.2	M	YES
ST6	Is this a ZigBee HID Class Device that transmits the Report Data command frames security enabled?	[R1]/ Section 5.4.2	M	YES



## 5 HID Adaptor

### 5.1 GDP Command Code

Item number	Item description	Reference	Status	Support
GCCA1	Does this HID Adaptor generates and Transmits the <b>Generic response</b> command frame?	[R1]/ Section 5.1	M	YES
GCCA2	Does this HID Adaptor generates and Transmits the <b>Get Attributes</b> command frame?	[R1]/ Section 5.4	M	YES (Not Certifiable)
GCCA3	Does this HID Adaptor generates and Transmits the <b>Get Attributes Response</b> command frame?	[R1]/ Section 5.5	M	YES
GCCA4	Does this HID Adaptor support reception of the <b>Generic response</b> command frame?	[R1]/ Section 5.1	M	YES
GCCA5	Does this HID Adaptor support reception of the <b>Get Attributes</b> command frame?	[R1]/ Section 5.4	M	YES
GCCA6	Does this HID Adaptor support reception of the <b>Get Attributes response</b> command frame?	[R1]/ Section 5.5	M	YES (Not Certifiable)
GCCA7	Does this HID Adaptor support reception of the <b>Configuration complete</b> command frame?	[R1]/ Section 5.2	M	YES
GCCA8	Does this HID Adaptor support reception of the <b>Heartbeat</b> command frame?	[R1]/ Section 5.3	M	YES (Not Certifiable)
GCCA9	Does this HID Adaptor support reception of the <b>Push Attributes</b> command frame?	[R1]/ Section 5.6	M	YES

### 5.2 ZID Command Code

Item number	Item description	Reference	Status	Support
ZCCA1	Does this HID Adaptor generates and Transmits the <b>Get Report</b> command frame?	[R1]/ Section 3.2	M	YES
ZCCA2	Does this HID Adaptor generates and Transmits the <b>Report Data</b> command frame?	[R1]/ Section 3.3	M	YES (Not Certifiable)

Item number	Item description	Reference	Status	Support
ZCCA3	Does this HID Adaptor generates and Transmits the <b>Set Report</b> command frame?	[R1]/ Section 3.4	O	YES
ZCCA4	Does this HID Adaptor support reception of the <b>Report Data</b> command frame?	[R1]/ Section 3.3	M	YES

### 5.3 ZID Attributes

Item number	Item description	Reference	Status	Support
ZAA1	Does this HID Adaptor support the <b>aplKeyExchangeTransferCount</b> attribute?	[R1]/ Section 4.2.1	O	YES
ZAA2	Does this HID Adaptor support the <b>aplZIDProfileVersion</b> attribute?	[R1]/ Section 4.2.2	M	YES
ZAA3	Does this HID Adaptor support the <b>aplHIDParserVersion</b> attribute?	[R1]/ Section 4.2.5	M	YES
ZAA4	Does this HID Adaptor support the <b>aplHIDCountryCode</b> attribute?	[R1]/ Section 4.2.8	M	YES
ZAA5	Does this HID Adaptor support the <b>aplHIDDeviceReleaseNumber</b> attribute?	[R1]/ Section 4.2.9	M	YES
ZAA6	Does this HID Adaptor support the <b>aplHIDVendorId</b> attribute?	[R1]/ Section 4.2.10	M	YES
ZAA7	Does this HID Adaptor support the <b>aplHIDProductId</b> attribute?	[R1]/ Section 4.2.11	M	YES

### 5.4 Transmission Model

Item number	Item description	Reference	Status	Support
ZTA1	Does this HID Adaptor support the reception of packets over the <b>Control Pipe</b> ?	[R1]/ Section 5.1.2.1	M	YES

Item number	Item description	Reference	Status	Support
ZTA2	Does this HID Adaptor support the transmission of packets over the <b>Control Pipe</b> ?	[R1]/ Section 5.1.2.1	M	YES
ZTA3	Does this HID Adaptor support the reception of the packets from the HID Class Device in the <b>Interrupt Pipe</b> ?	[R1]/ Section 5.1.2.2	M	YES
ZTA4	Does this HID Adaptor support the transmission of low latency or asynchronous reports to the HID Class Device over the <b>Interrupt Pipe</b> ?	[R1]/ Section 5.1.2.2	O	YES (Not Certifiable)

### 5.5 Proxy Table

Item number	Item description	Reference	Status	Support
PTA1	Does this HID Adaptor store the <b>apHIDParserVersion</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA2	Does this HID Adaptor store the <b>apHIDDeviceSubclass</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA3	Does this HID Adaptor store the <b>apHIDProtocolCode</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA4	Does this HID Adaptor store the <b>apHIDCountryCode</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA5	Does this HID Adaptor store the <b>apHIDDeviceReleaseNumber</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA6	Does this HID Adaptor store the <b>apHIDVendorId</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES

Item number	Item description	Reference	Status	Support
PTA7	Does this HID Adaptor store the <b>aplHIDProductId</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA8	Does this HID Adaptor store the <b>aplHIDNumEndpoints</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA9	Does this HID Adaptor store the <b>aplHIDPollInterval</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA10	Does this HID Adaptor store the <b>aplHIDNumStdDescComps</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA12	Does this HID Adaptor store the <b>aplHIDStdDescCompsList</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA13	Does this HID Adaptor store the <b>aplHIDNumNonStdDescComps</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA14	Does this HID Adaptor store the <b>aplHIDNonStdDescCompSpec</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA15	Does this HID Adaptor store the <b>aplHIDNonStdDescCompSpec-i</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA16	Does this HID Adaptor store the <b>aplHIDNumNullReports</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA17	Does this HID Adaptor store the <b>aplDeviceIdleRate</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES
PTA18	Does this HID Adaptor store the <b>aplCurrentProtocol</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES

---

Item number	Item description	Reference	Status	Support
PTA19	Does this HID Adaptor store the <b>aplNullReportSpecList</b> attribute values in the proxy table?	[R1]/ Section 5.2.1	M	YES

## 6 HID Class Device

### 6.1 GDP Command Code

Item number	Item description	Reference	Status	Support
GCCD1	Does this HID Class Device generates and Transmits the <b>Generic response</b> command frame?	[R1]/ Section 5.1	M	YES
GCCD2	Does this HID Class Device generates and Transmits the <b>Configuration Complete</b> command frame?	[R1]/ Section 5.2	M	YES
GCCD3	Does this HID Class Device generates and Transmits the <b>Heartbeat</b> command frame?	[R1]/ Section 5.3	O	YES (Not Certifiable)
GCCD4	Does this HID Class Device generates and Transmits the <b>Get Attributes</b> command frame?	[R1]/ Section 5.4	M	YES
GCCD5	Does this HID Class Device generates and Transmits the <b>Get Attributes Response</b> command frame?	[R1]/ Section 5.5	M	YES (Not Certifiable)
GCCD6	Does this HID Class Device generates and Transmits the <b>Push Attributes</b> command frame?	[R1]/ Section 5.6	M	YES
GCCD7	Does this HID Adaptor support reception of the <b>Generic response</b> command frame?	[R1]/ Section 5.1	M	YES
GCCD8	Does this HID Adaptor support reception of the <b>Get Attributes</b> command frame?	[R1]/ Section 5.4	M	YES (Not Certifiable)
GCCD9	Does this HID Adaptor support reception of the <b>Get Attributes response</b> command frame?	[R1]/ Section 5.5	M	YES

### 6.2 ZID Command Code

Item number	Item description	Reference	Status	Support
ZCCD1	Does this HID Class Device generates and Transmits the <b>Report Data</b> command frame?	[R1]/ Section 3.3	M	YES

Item number	Item description	Reference	Status	Support
ZCCD2	Does this HID Class device support reception of the <b>Get Report</b> command frame?	[R1]/ Section 3.2	M	YES
ZCCD3	Does this HID Class device support reception of the <b>Report Data</b> command frame?	[R1]/ Section 3.3	M	YES (Not Certifiable)
ZCCD4	Does this HID Class device support reception of the <b>Set Report</b> command frame?	[R1]/ Section 3.4	O	YES

### 6.3 ZID Attributes

Item number	Item description	Reference	Status	Support
ZAD1	Does this HID Class Device support the <b>aplKeyExchangeTransferCount</b> attribute?	[R1]/ Section 4.2.1	M	YES
ZAD2	Does this HID Class Device support the <b>aplZIDProfileVersion</b> attribute?	[R1]/ Section 4.2.2	M	YES
ZAD3	Does this HID Class Device support the <b>aplIntPipeUnsafeTxWindowTime</b> attribute?	[R1]/ Section 4.2.3	M	YES
ZAD4	Does this HID Class Device support the <b>aplReportRepeatInterval</b> attribute?	[R1]/ Section 4.2.4	M	YES
ZAD5	Does this HID Class Device support the <b>aplHIDParserVersion</b> attribute?	[R1]/ Section 4.2.5	M	YES
ZAD6	Does this HID Class Device support the <b>aplHIDDeviceSubclass</b> attribute?	[R1]/ Section 4.2.6	M	YES
ZAD7	Does this HID Class Device support the <b>aplHIDProtocolCode</b> attribute?	[R1]/ Section 4.2.7	M	YES
ZAD8	Does this HID Class Device support the <b>aplHIDCountryCode</b> attribute?	[R1]/ Section 4.2.8	M	YES
ZAD9	Does this HID Class Device support the <b>aplHIDDeviceReleaseNumber</b> attribute?	[R1]/ Section 4.2.9	M	YES

Item number	Item description	Reference	Status	Support
ZAD10	Does this HID Class Device support the <b>aplHIDVendorId</b> attribute?	[R1]/ Section 4.2.10	M	YES
ZAD11	Does this HID Class Device support the <b>aplHIDProductId</b> attribute?	[R1]/ Section 4.2.11	M	YES
ZAD12	Does this HID Class Device support the <b>aplHIDNumEndpoints</b> attribute?	[R1]/ Section 4.2.12	M	YES
ZAD13	Does this HID Class Device support the <b>aplHIDPollInterval</b> attribute?	[R1]/ Section 4.2.13	M	YES
ZAD14	Does this HID Class Device support the <b>aplHIDNumStdDescComps</b> attribute?	[R1]/ Section 4.2.14	M	YES
ZAD15	Does this HID Class Device support the <b>aplHIDStdDescCompsList</b> attribute?	[R1]/ Section 4.2.15	O	YES
ZAD16	Does this HID Class Device support the <b>aplHIDNumNullReports</b> attribute?	[R1]/ Section 4.2.16	M	YES
ZAD17	Does this HID Class Device support the <b>aplHIDNumNonStdDescComps</b> attribute?	[R1]/ Section 4.2.17	M	YES
ZAD18	Does this HID Class Device support the <b>aplHIDNonStdDescCompSpec-i</b> attribute?	[R1]/ Section 4.2.11	O	YES

#### 6.4 Transmission Model

Item number	Item description	Reference	Status	Support
ZTD1	Does this HID Class Device support the transmission of application data over a <b>Control Pipe</b> ?	[R1]/ Section 5.1.2.1	M	YES
ZTD2	Does this HID Class Device support the Transmission of the information to the HID Adaptor in the <b>Interrupt Pipe</b> ?	[R1]/ Section 5.1.2.2	M	YES
ZTD3	Does this HID Class Device support the reception of low latency or asynchronous reports from the HID Adaptor over the <b>Interrupt Pipe</b> ?	[R1]/ Section 5.1.2.2	M	YES (Not Certifiable)



