

zigbee alliance

Zigbee PRO Green Power feature Protocol Implementation Conformance (PICS) Proforma Basic functionality set Version 1.1.1

Zigbee Document 15-0006-013

January 11th, 2019

Sponsored by: Zigbee Alliance

Accepted by This document has been accepted for release by the Zigbee Alliance Board of Directors

Abstract This document is a maintenance release of the Green Power Basic v1.1 PICS, containing all applicable errata.

Keywords Zigbee, Green Power, Battery-less, Energy Harvesting, Green Power stub, Green Power Cluster, Green Power Basic, generic switch, Compact Attribute Reporting, multi-sensor, setpoint

Copyright © Zigbee Alliance, Inc. (1996-2019). All rights reserved.

508 Second Street, Suite 206 Davis, CA 95616 - USA

<http://www.zigbee.org>

Permission is granted to members of the Zigbee Alliance to reproduce this document for their own use or the use of other Zigbee Alliance members only, provided this notice is included. All other rights reserved. Duplication for sale, or for commercial or for-profit use is strictly prohibited without the prior written consent of the Zigbee Alliance.

This page is intentionally blank

Notice of use and disclosure

Copyright © Zigbee Alliance, Inc. (1996-2019). All rights Reserved. This information within this document is the property of the Zigbee Alliance and its use and disclosure are restricted.

Elements of Zigbee Alliance specifications may be subject to third party intellectual property rights, including without limitation, patent, copyright or trademark rights (such a third party may or may not be a member of Zigbee). Zigbee is not responsible and shall not be held responsible in any manner for identifying or failing to identify any or all such third party intellectual property rights.

No right to use any Zigbee name, logo or trademark is conferred herein. Use of any Zigbee name, logo or trademark requires membership in the Zigbee Alliance and compliance with the Zigbee Logo and Trademark Policy and related Zigbee policies.

This document and the information contained herein are provided on an “AS IS” basis and Zigbee **DISCLAIMS ALL WARRANTIES EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO**

(A) ANY WARRANTY THAT THE USE OF THE INFORMATION HEREIN WILL NOT INFRINGE ANY RIGHTS OF THIRD PARTIES (INCLUDING WITHOUT LIMITATION ANY INTELLECTUAL PROPERTY RIGHTS INCLUDING PATENT, COPYRIGHT OR TRADEMARK RIGHTS) OR (B) ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, TITLE OR NONINFRINGEMENT. IN NO EVENT WILL ZIGBEE BE LIABLE FOR ANY LOSS OF PROFITS, LOSS OF BUSINESS, LOSS OF USE OF DATA, INTERRUPTION OF BUSINESS, OR FOR ANY OTHER DIRECT, INDIRECT, SPECIAL OR EXEMPLARY, INCIDENTAL, PUNITIVE OR CONSEQUENTIAL DAMAGES OF ANY KIND, IN CONTRACT OR IN TORT, IN CONNECTION WITH THIS DOCUMENT OR THE INFORMATION CONTAINED HEREIN, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH LOSS OR DAMAGE. All Company, brand and product names may be trademarks that are the sole property of their respective owners.

The above notice and this paragraph must be included on all copies of this document that are made.

This page is intentionally blank

Revision history

Revision	Date	Details	Editor
000	July 7 th , 2016	Baseline: clean Green Power Basic PICS (15-0006-11)	Bozena Erdmann
001	July 20 th , 2016	First draft, based on the multi-sensor baseline (16-02605)	Bozena Erdmann
002	July 29 th , 2016	Implementing comments as discussed during Green Power WG call on July 27 th and received via email from Jorgen van Parys on July 28 th	Bozena Erdmann

003	September 12 th , 2016	Implementing comments from the GP multi-sensor August PoC, Zigbee document 16-02611	Bozena Erdmann
004	October 5 th , 2016	Implementing comments from GP multi-sensor v0.7 letter ballot	Bozena Erdmann
005	October 6 th , 2016	Implementing comments from GP multi-sensor v0.7 letter ballot: comment #783	Bozena Erdmann
006	October 23 rd , 2016	Merging the GP multi-sensor v0.7 PICS with the GP generic switch v0.7 PICS (1602015-004)	Bozena Erdmann
007	November 18 th , 2016	Adding several missing references to GP multi-sensor specification	Bozena Erdmann
008	December 3 rd , 2016	Implementing resolutions to GP multi-sensor LB v0.9 comments: #973, #976. Adding several missing references.	Bozena Erdmann
009	February 10 th , 2017	Implementing resolutions to comments from GP generic switch and multi-sensor December '16 SVE: #1013, #1014, #1025.	Bozena Erdmann
010	February 13 th , 2017	Implementing resolutions to comments from GP generic switch and multi-sensor December '16 SVE: #1031. Implementing resolutions for the v0.9 TSC approval comments: #1048, #1052, #1053.	Bozena Erdmann
011	June 15 th , 2017	Integrated approved GP Basic errata from 15-02016r004. Updated list of certified/non-certified features.	Bozena Erdmann
012	January 24 th , 2018	Integrating draft errata from 15-02016r009 Implementing resolutions to CCBs against the original GP Basic PICS, as in 1502016-007: #2372, Implementing resolutions for the v1.0 WG approval comments: #1374. Implementing comment resolution from letter ballot for GP Basic errata set: Kavi comment: Kavi comment #1383. Implementing resolution for CCB #2524.	Bozena Erdmann
013	February 21 st , 2018	Adding pointers to the PIXIT items as defined in the XML PICS document [R10]. Implementing resolution for CCB #2533.	Bozena Erdmann

1 References

The following standards contain provisions, which, through reference in this document, constitute provisions of this standard. All the standards listed are normative references. At the time of publication, the editions indicated were valid. All standards are subject to revision, and parties to agreements based on this standard are encouraged to investigate the possibility of applying the most recent editions of the standards indicated below.

1.1 Zigbee Alliance documents

- [R1] Zigbee document 053474r21: Zigbee Specification 2015
- [R2] Zigbee document 08006r03: Zigbee 2007 Layer PICS and Stack Profiles
- [R3] Zigbee document 075123r04, Zigbee Cluster Library Specification
- [R4] Zigbee document 14-0563r18: Green Power Basic specification v1.1.1
- [R5] Zigbee document 15-0015r14: Green Power Basic test specification v1.1.1
- [R6] Zigbee document 064113r08: Zigbee Cluster Library PICS
- [R7] Zigbee document 15-02016, Errata for Green Power Basic PICS

[R8] Zigbee document 15-00000r004, GP Basic PICS to test case mapping

[R9] Zigbee document 13-0166r01, Master List of Green Power Device Definitions

[R10] Zigbee document 16-02615, Green Power Basic XML PICS

1.2 IEEE documents

[R11] ¹IEEE Standard for Part 15.4: Wireless Medium Access Control (MAC) and Physical Layer (PHY) specifications for Low Rate Wireless Personal Area Networks (LR-WPANs), 2011.

Table of Contents

1	References	6
1.1	Zigbee Alliance documents	6
1.2	IEEE documents	6
	Table of Contents	7
	List of Figures.....	8
2	Introduction	9
2.1	Scope	9
2.2	Purpose	9
3	Green Power certification status	10
3.1	Not certified GP functionality	10
3.2	Certified GP functionality	11
4	Abbreviations and special symbols	13
5	Instructions for completing the PICS proforma	14
6	Identification of the implementation	15
7	Identification of the protocol	17
8	Global statement of conformance	18
9	Zigbee stack profile [R2] errata	19
9.1	Modify the Table in “8.6.3.1.5 Zigbee Device Objects functions”, p.89, of 08006r03	19
9.1.1	After AZD18, add	19
9.2	Modify the Table in “8.4.2.2 Network layer frames” to include alias usage for Tx and Rx, p.47,	19
9.2.1	after NDF4, add	19
10	Green Power feature	20
10.1	Green Power Device Types	20
11	Functionality of Green Power infrastructure device	21
11.1	Green Power stub capabilities of GP infrastructure devices	21
11.2	Green Power: Support of proxy basic functionality	22
11.3	Functionality of Green Power cluster.....	25
11.3.1	Green Power cluster: items common to client and server	28
11.3.2	Server side	29
11.3.3	Client side	33
11.3.4	Support of GP functionality	37
11.4	GPS application functionality	43
11.4.1	GPS device description support	43
11.4.2	GPD command support by GPS	44
12	Green Power Device functionality	49
12.1	GPD device description support	49

¹ v0.9 TSC approval comment #1048:

https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1048

- 12.2 GPD functionality 50
 - 12.2.1 GPD Bidirectional operation 51
 - 12.2.2 GPD commissioning support 53
- 12.3 GPD application functionality 58
 - 12.3.1 GPD command support by GPD..... 58
 - 12.3.2 Zigbee attribute support by GPD sensor devices 62

2 List of Figures

Table 1	– Not certified GP functionality	10
Green Power Basic PICS v1.1.1		
Table 2	– To-date certified device types	11
Table 3	– To-date certified GP functionality	11
Table 4	– Green Power device types	20
Table 5	– Green Power cluster feature support	25
Table 6	– Green Power cluster items common to client and server	28
Table 7	– Green Power cluster server capabilities	29
Table 8	– Green Power cluster client capabilities	33
Table 9	– Support for Green Power bidirectional operation	37
Table 10	– GP Commissioning Support	38
Table 11	– GPS device description support	43
Table 12	– GPD commands support - reception	44
Table 13	– GPD device description support	49
Table 14	– GPD functionality	50
Table 15	– Support for Green Power functionality	51
Table 16	– GP Commissioning Feature Support	53
Table 17	– GPD commands support - transmission	58
Table 18	– Reported Zigbee attributes per GPD device	62
Table 19	– Readable Zigbee attributes per GPD device	62
Table 20	– Writable Zigbee attributes per GPD device	63

nal comment #1052:

[v0.9 TSC appro zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1052](https://www.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1052)

2 Introduction

To evaluate conformance of a particular implementation, it is necessary to have a statement of which capabilities and options have been implemented for a given standard. Such a statement is called a protocol implementation conformance statement (PICS).

2.1 Scope

This document provides the protocol implementation conformance statement (PICS) proforma for the Zigbee specifications cited in Reference [R4] in compliance with the relevant requirements.

This document addresses the Green Power feature of the Zigbee core stack, together with the necessary cluster-level components (Green Power cluster).

2.2 Purpose

The supplier of a protocol implementation claiming to conform to the Green Power feature shall complete the following PICS proforma and accompany it with the information necessary to identify fully both the supplier and the implementation.

The PICS is in the form of answers to a set of questions in the PICS proforma. The questions in a proforma consist of a systematic list of protocol capabilities and options as well as their implementation requirements. The implementation requirement indicates whether implementation of a capability is mandatory, optional, or conditional depending on options selected. When a protocol implementer answers questions in a PICS proforma, they would indicate whether an item is implemented or not, and provide explanations if an item is not implemented.

3 Green Power certification status

The current status of the certification and golden unit availability for Green Power functionality is listed in the tables below.

According to the current version of this specification, only the following GPI device types can be certified: GP Proxy Basic, GP Combo Basic, GP Commissioning Tool.

3.1 Not certified GP functionality

Note: this section reflects the functionality status AFTER this specification is approved.

Table 1 – Not certified GP functionality

Item number	Item description	Reference
GPPCSF5 GPPCCF5	Full unicast communication functionality	[R4] A.3.2.8
GPPCSF7 GPPCCF7 GPF9D-E GPF10A-B GPF100 GPF102 GPF108	Proximity bidirectional operation functionality	[R4] A.3.2.8
GPPCSF8 GPPCCF8 GPF9D-E GPF10A-B GPF100 GPF102 GPF108	Multi-hop bidirectional operation functionality	[R4] A.3.2.8
GPPCSF9 GPPCCF9	Proxy Table maintenance (active and passive) functionality	[R4] A.3.2.8
GPPCSF13 GPPCCF13 GPF9D-E GPF10A-B GPF100 GPCF7	Maintenance of GPD (deliver channel/key during operation) functionality	[R4] A.3.2.8
GPPCSF18	Sink Table-based groupcast forwarding functionality	[R4] A.3.2.8
GPD4 GPS4	GP Simple Sensor	[R4] A.4.3
GPD10 GPS5	GP Color Dimmer Switch	[R4] A.4.3
GPD20 GPS8	GP Door Lock Controller	[R4] A.4.3
GPD30 GPS9	GP Temperature Sensor	[R4] A.4.3
GPD31 GPS10	GP Pressure Sensor	[R4] A.4.3
GPD32 GPS11	GP Flow Sensor	[R4] A.4.3

Item number	Item description	Reference
GPD33 GPS12, GPS9, GPS6	GP Indoor Environment Sensor	[R4] A.4.3
GPS18	GP Window Covering cluster	[R4] A.4.3

3.2 Certified GP functionality

Table 2 – To-date certified device types

Item number	Item description	Reference
GPDT0	Green Power Device (GPD) functionality	[R4] A.1.6, A.1.7
GPDT2B	GP proxy functionality of Green Power Proxy Basic (GPPB) device	[R4] A.3.2.6
GPDT2CB	GP proxy functionality of Green Power Combo Basic (GPCB) device	[R4] A.3.2.7
GPDT3CB	GP sink functionality of Green Power Combo Basic (GPCB) device	[R4] A.3.2.7

Table 3 – To-date certified GP functionality

Item number	Item description	Reference
GPPCSF1 GPPCCF1	GP feature	[R4] A.3.2.8
GPPCSF2 GPPCCF2 GPF4A GPF4C	Direct communication (via GP stub) functionality	[R4] A.3.2.8
GPPCSF3 GPPCCF3	Derived groupcast communication functionality	[R4] A.3.2.8
GPPCSF4 GPPCCF4	Pre-commissioned groupcast communication functionality	[R4] A.3.2.8
GPPCSF6 GPPCCF6	Lightweight unicast communication functionality	[R4] A.3.2.8
GPPCSF10 GPPCCF10 GPCF4GPCF1 GPCF2 GPF4A-D GPF9A-C GPF10C-E GPCF10 GPCF11 GPCF12B GPCF13B	Proximity commissioning (unidirectional and bidirectional) functionality	[R4] A.3.2.8
GPPCSF11 GPPCCF11 GPCF4 GPCF1 GPCF2 GPF4A-D GPF9A-C GPF10C-E GPCF10 GPCF11 GPCF12B GPCF13B	Multi-hop commissioning (unidirectional and bidirectional) functionality	[R4] A.3.2.8

Item number	Item description	Reference
-------------	------------------	-----------

GPPCSF12 GPPCCF12 ² GPPCC151AG PPCS110	CT-based commissioning functionality	[R4] A.3.2.8
GPPCSF14 GPPCCF14 GPF8	gpdSecurityLevel = 0b00 functionality <i>Note: According to the current version of the specification, only GPD that support gpdSecurityLevel = 0b10 or higher AND support TC-LK protection (as indicated by the GPDkeyEncryption sub-field of the Extended Options field of the GPD Commissioning command) of the GPD key, if exchanged over the air, can be certified.</i>	[R4] A.3.2.8
GPPCSF15 GPPCCF15 GPF7	gpdSecurityLevel = 0b01 functionality (deprecated)	[R4] A.3.2.8
GPPCSF16 GPPCCF16 GPF6	gpdSecurityLevel = 0b10 functionality	[R4] A.3.2.8
GPPCSF17 GPPCCF17 GPF5	gpdSecurityLevel = 0b11 functionality	[R4] A.3.2.8
GPPCSF19	Translation Table functionality	[R4] A.3.2.8
GPPCSF20 GPPCCF20 GPF4D GPF4B	GPD IEEE address functionality	[R4] A.3.2.8
GPCF12B GPCF13B	TC-LK encryption of the GPD key exchanged during commissioning	[R4] A.3.9, A.1.5.9
GPD0 GPS1A	GP Simple Generic 1-state Switch	[R4] A.4.3
GPD1 GPS1B	GP Simple Generic 2-state Switch	[R4] A.4.3
GPD2 GPS2	GP On/Off switch functionality	[R4] A.4
GPD3 GPS3	GP Level Control Switch	[R4] A.4.3
GPD5 GPS14A	GP Advanced Generic 1-state Switch	[R4] A.4.3
GPD6 GPS14B	GP Advanced Generic 2-state Switch	[R4] A.4.3
GPD7 GPS17	GP Generic 8-contact Switch	
GPD11 GPS6	GP Light Sensor	[R4] A.4.3
GPD12 GPS7	GP Occupancy Sensor	[R4] A.4.3
GPD102 GPS16 GPPCSF21	Standard ZCL cluster controllable via GPD Compact Attribute Reporting	[R4] A.4.3
GPDTX10 - GPDTX1f GPDRX10 - GPDRX1f	GP Scene functionality	[R4] A.4.3

² CCB #2279 and CCB #2278; resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set: https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383

GPDTXA6 GPDRXA6	GPD ZCL Tunneling command	[R4] A.4.3
--------------------	---------------------------	------------

4 Abbreviations and special symbols

Notations for requirement status:

M	Mandatory
O	Optional
O.n	Optional, but support of at least one or only one (as indicated in the footnote to the O.n label) of the group of options labeled O.n is required. (Clarification - the number 'n' is a label for the group, not a count of the number of options within the group, or the ordinal number of the option within the group. All options in the group are indicated identically as O.n)
N/A	Not applicable
X	Prohibited
Item label: Status	Status is conditional on support of the item with the given item label.

Examples

1/ If items labeled A and B are both marked "O.n" this indicates that the status is optional for both A and B, but at least one of the two features described by items A and B is required to be implemented.

2/ If m items are each marked A: O.n, this indicates that, if item A is implemented, the status is optional for all of them, but at least one of the m features described by the items is required to be implemented.

5 Instructions for completing the PICS proforma

If a given implementation is claimed to conform to this standard, the actual PICS proforma to be filled in by a supplier shall be technically equivalent to the text of the PICS proforma in this annex, and shall preserve the numbering and naming and the ordering of the PICS proforma.

A PICS which conforms to this document shall be a conforming PICS proforma completed in accordance with the instructions for completion given in this annex.

The main part of the PICS is a fixed-format questionnaire, divided into five tables. Answers to the questionnaire are to be provided in the rightmost column, either by simply marking an answer to indicate a restricted choice (such as Yes or No), or by entering a value, set, or range of values.

6 Identification of the implementation

Implementation under test (IUT) identification

IUT name: PowerLogic Tag

IUT version: 1P+ N, 277V, EDB, 10-60A

System under test (SUT) identification

SUT name: PowerLogic Tag

Software Version: 004.000.433

Hardware Version: 001.000.000

Operating system (optional): None

Zigbee stack revision and profile (should be PRO r20 or later): NA (Green Power Device GPDT0)

Product supplier

Name: Schneider Electric Industries SAS

Address : 5 Rue Joseph Monier, Rueil-Malmaison, 92500 France

Telephone number: +33 6 73 61 10 87

Facsimile number: N/A

Email address: valentin.thomas@se.com

Additional information: N/A

Client

Name: Schneider Electric Industries SAS

Address : 5 Rue Joseph Monier, Rueil-Malmaison, 92500 France

Telephone number: +33 6 73 61 10 87

Facsimile number: N/A

Email address: valentin.thomas@se.com

Additional information: N/A

PICS contact person

Name: Elodie Chargy

Address: 38EQI, 31 Rue Pierre Mendès-France, 38320 Eybens, France

Telephone number: +337 86 35 88 84

Facsimile number: N/A

Email address: elodie.chargy@se.com

Additional information: N/A

PICS/System conformance statement

7 Identification of the protocol

This PICS proforma applies to the Green Power feature, cited in Reference [R4].

8 Global statement of conformance

The implementation described in this PICS proforma meets all of the mandatory requirements of the referenced standards:

Green Power – 14-0563r18

Yes

No

Note -- Answering 'No' indicates non-conformance to the specified protocol standard. Non-supported mandatory capabilities are to be identified in the following tables, with an explanation by the implementer explaining why the implementation is non-conforming.

The supplier will have fully complied with the requirements for a statement of conformance by completing the statement contained in this subclause. That means, by clicking the above, the statement of conformance is complete.

9 Zigbee stack profile [R2] errata

9.1 Modify the Table in “8.6.3.1.5 Zigbee Device Objects functions”, p.89, of 08006r03

9.1.1 After AZD18, add

AZD19	Does the device support conflict checking with its own short address, on reception of Device_annce with IEEE address 0xffffffffffffffff?	[R4] A.2	M	
-------	--	----------	---	--

9.2 Modify the Table in “8.4.2.2 Network layer frames” to include alias usage for Tx and Rx, p.47,

9.2.1 ³after NDF4, add

NDF5	Does the device support reception of Zigbee NWK frames with non-incremental sequence number in the NWK header Sequence Number field?			
		Zigbee	M	
NDF6	Does the device support transmission of Zigbee NWK frames with AliasSrcAddr and AliasSeqNumb, as supplied by next higher layer?			
		Zigbee-PRO	GPDT2: M GPDT3t: X GPDT3t+: X GPDT3c: X GPDT3CB: M GPDT4: M	

³ v0.9 TSC approval comment #1053:
https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1053

10 Green Power feature

The following tables are composed of the detailed questions to be answered, which make up the PICS proforma.

According to the current version of this specification, only the following GPI device types can be certified: GP Proxy Basic, GP Combo Basic, GP Commissioning Tool.

10.1 Green Power Device Types

Table 4 – Green Power device types

Item number	Item description	Reference	Status	Support
GPDT0	Does the product support GPD functionality?	[R4] A.1.6, A.1.7	O.6 ⁴	YES
GPDT1	Does the product support the functionality of GP infrastructure device?	[R4] A.3.2	O.6	NO
GPDT2	Does the product support GPP functionality?	[R4] A.3.2.3	GPDT1: O.7 ⁵	NO
GPDT2f	Is the product programmed as a GPP?	[R4] A.3.2.3	GPDT2: X	NO
GPDT2B	Is the product programmed as a GPPB?	[R4] A.3.2.6	GPDT2: O.8 ⁷	NO
GPDT2CB	Is the product programmed as a GPCB?	[R4] A.3.2.4	GPDT2: O.8	NO
GPDT3	Does the product support GPS functionality?	[R4] A.3.2	GPDT1: O.7	NO
GPDT3t	Is the product programmed as a GPT?	[R4] A.3.2.1	GPDT3: X	NO
GPDT3t+	Is the product programmed as a GPT+?	[R4] A.3.2.2	GPDT3: X	NO
GPDT3c	Is the product programmed as a GPC?	[R4] A.3.2.4	GPDT3: X	NO
GPDT3CB	Is the product programmed as a GPCB?	[R4] A.3.2.7	GPDT3: O	NO
GPDT4	Does the product support GP commissioning tool functionality?	[R4] A.3.2.5	GPDT1: O.7	NO
GPDT4ct	Is the product programmed as a GP Commissioning Tool?	[R4] A.3.2.5	GPDT1: O	NO

Please note: all PICS items applicable for all the GPP and GPS subtypes, use the generic item label: GPDT2 or GPDT3, respectively.

The sub-type specific item labels (GPDT2f, GPDT2B, GPDT2CB, GPDT2c, GPDT3t, GPDT3t+, GPDT3c, GPDT3CB) are used for sub-type specific requirements.

⁴ O.6 - Device Under Test SHALL support only one of these options.

⁵ O.7 - Device Under Test SHALL support at least one of these options.

⁷ O.8 - Device Under Test SHALL support only one of these options.

11 Functionality of Green Power infrastructure device

11.1 Green Power stub capabilities of GP infrastructure devices

This PICS table applies to GP infrastructure devices GPDT1, GPDT2, GPDT3 and GPDT4.

All PICS items applicable for all the generic GP device types, use the generic item label: GPDT1 if applicable to all devices, or GPDT2, GPDT3, and GPDT4, if applicable in general to GPP, GPS or GPCT functionality, respectively.

The sub-type specific item labels (GPDT2f, GPDT2BGPDT2CB, GPDT2c, GPDT3t, GPDT3t+, GPDT3c, and GPDT3CB) are used for sub-type specific requirements.

Since GPDT0 are not Zigbee-PRO devices, their functionality is not discussed here. Please see ZCL PICS for GPDT0 compliance requirements.

Item number	Item description	Reference	Status	Support
GPF1	Does the device implement cGP stub?	[R4] A.1	GPDT2B: M GPDT2CB: M GPDT3CB: M ⁶ GPDT4: O ⁷⁸ GPF2A: M	N/A
⁹ GPF2A	Does the device implement dGP stub?	[R4] A.1	GPDT2B: M GPDT2CB: M GPDT3CB: M ¹⁰ GPDT4: O ¹¹ GPF1: M	N/A
¹⁴ GPF2B	Does the device support gpTxQueue?	[R4] A.1	¹² GPDT2B: M GPDT2CB: M GPDT3CB: M ¹³ GPDT4: O	N/A
GPF3	Does the device support the general Green Power Device Frame format?	[R4] A.1.4	GPDT2B: M GPDT2CB: M GPDT3CB: M ¹⁴ GPDT4: O ¹⁵ GPF1 ¹⁶ GPF2A: M	N/A
GPF3A	Does the device support <i>nwkProtocolVersion</i> = 0x3?	[R4] A.1.4	GPDT2B: M GPDT2CB: M GPDT3CB: M ¹⁷ GPDT4: O ¹⁸ GPF3: M	N/A
GPF4C	Does the device support receiving GPDF frame format with <i>ApplicationID</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b000?	[R4] A.1.4	GPDT2B: M GPDT2CB: M GPDT3CB: M ¹⁹ GPDT4: O	N/A
GPF4D	Does the device support receiving GPDF frame format with <i>ApplicationID</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b010?	[R4] A.1.4	GPDT2B: M GPDT2CB: M GPDT3CB: M ²⁰ GPDT4: O	N/A

⁶ CCB #2372; Resolution added in 15-02016-007

⁷ CCB #2372; Resolution added in 15-02016-007

⁸ CCB #2524; resolution added in 15-02016-009;

⁹ CCB #2524; resolution added in 15-02016-009;

¹⁰ CCB #2372; Resolution added in 15-02016-007

¹¹ CCB #2372; Resolution added in 15-02016-007 ¹⁴

CCB #2524; resolution added in 15-02016-009;

¹² CCB #2198; Resolution added in 15-02016-002

¹³ CCB #2372; Resolution added in 15-02016-007

¹⁴ CCB #2372; Resolution added in 15-02016-007

¹⁵ CCB #2372; Resolution added in 15-02016-007

¹⁶ CCB #2524; resolution added in 15-02016-009;

¹⁷ CCB #2372; Resolution added in 15-02016-007

¹⁸ CCB #2372; Resolution added in 15-02016-007

¹⁹ CCB #2372; Resolution added in 15-02016-007

²⁰ CCB #2372; Resolution added in 15-02016-007

Item number	Item description	Reference	Status	Support
GPF5	Does the device's dGP stub support GPDF SecurityLevel=0b11?	[R4] A.1.5.4; A.3.7.2	GPDT2B: M GPDT2CB: M GPDT3CB: O.4 ²¹ GPDT4: O	N/A
GPF6	Does the device's dGP stub support GPDF SecurityLevel=0b10?	[R4] A.1.5.4; A.3.7.2	GPDT2B: M GPDT2CB: M GPDT3CB: O.4 ²² GPDT4: O	N/A
GPF7	Does the device's dGP stub support GPDF SecurityLevel=0b01? (deprecated)	[R4] A.1.5.4; A.3.7.2	GPDT1: X (deprecated)	N/A
GPF8A	Does the device's dGP stub support GPDF SecurityLevel=0b00 in commissioning?	[R4] A.1.5.4; A.3.7.2	GPDT2B: M GPDT2CB: M GPDT3CB: M ²³ GPDT4: O	N/A
GPF8B	Does the device's dGP stub support GPDF SecurityLevel=0b00 in operation?	[R4] A.1.5.4; A.3.7.2	GPDT2B: O GPDT2CB: O GPDT3CB: O ²⁴ GPDT4: O	N/A
GPF9A	Does the device support transmitting GPDF frame format with <i>ApplicationID</i> sub-field of the Extended NWK Frame Control field set to 0b000 and Frame type sub-field of the NWK Frame Control field set to 0b00 (Data frame) in commissioning, without security?	[R4] A.1	GPDT2B: M GPDT2CB: M GPDT3CB: M ²⁵ GPDT4: O	N/A
GPF9B	Does the device support transmitting GPDF frame format with <i>ApplicationID</i> sub-field of the Extended NWK Frame Control field set to 0b010 in commissioning, without security?	[R4] A.1	GPDT2B: M GPDT2CB: M GPDT3CB: M ²⁶ GPDT4: O	N/A
GPF9C	Does the device support transmitting in commissioning mode a GPDF frame format with Frame type sub-field of the NWK Frame Control field set to 0b01 (Maintenance frame)?	[R4] A.1, A.3.9	GPDT2B: M GPDT2CB: M GPDT3CB: M ²⁷ GPDT4: O	N/A
GPF9D	Does the device support transmitting GPDF frame format with <i>ApplicationID</i> sub-field of the Extended NWK Frame Control field set to 0b000 and <i>Frame type</i> sub-field of the NWK Frame Control field set to 0b00 (Data frame) in operation, with security?	[R4] A.1	GPDT2B: X GPDT2CB: X GPDT3CB: X GPDT4: O	N/A
GPF9E	Does the device support transmitting GPDF frame format with <i>ApplicationID</i> sub-field of the Extended NWK Frame Control field set to 0b010 in operation, with security?	[R4] A.1	GPDT2B: X GPDT2CB: X GPDT3CB: X GPDT4: O	N/A
²⁸ GPF11	Is the device capable of transmitting a response GPDF between <i>gpTxOffset</i> and <i>gpTxOffset+gpMaxTxOffsetVariation</i> ms after reception of the request GPDF (aka immediate response)?	[R4] A.1	GPDT2: X GPDT3: O GPF9A-E: O GPPCSF10: O GPPCSF11: O GPPCSF7: O GPPCSF8: O GPPCSF13: O	N/A

²¹ CCB #2372; Resolution added in 15-02016-007

²² CCB #2372; Resolution added in 15-02016-007

²³ CCB #2372; Resolution added in 15-02016-007

²⁴ CCB #2372; Resolution added in 15-02016-007

²⁵ CCB #2372; Resolution added in 15-02016-007

²⁶ CCB #2372; Resolution added in 15-02016-007

²⁷ CCB #2372; Resolution added in 15-02016-007

²⁸ CCB #2524; resolution added in 15-02016-009;

11.2 Green Power: Support of proxy basic functionality

This PICS table applies to GP infrastructure devices GPDT1, GPDT2, GPDT3 and GPDT4.

All PICS items applicable for all the generic GP device types use the generic item label: GPDT1 if applicable to all devices, or GPDT2, GPDT3, and GPDT4, if applicable in general to GPP, GPS or GPCT functionality, respectively. The sub-type specific item labels (GPDT2B, GPDT2CB) are used for sub-type specific requirements.

Since GPDT0 are not Zigbee-PRO devices, their functionality is not discussed here. Please see ZCL PICS for GPDT0 compliance requirements.

Item number	Item description	Reference	Status	Support
GPPC0	Does the device support the GP proxy basic functionality?	[R4] A.3.2.6	GPDT2B: M GPDT2CB: M GPDT3CB: X GPDT4: O	N/A
GPPC1	Is the Green Power cluster supported?	[R4] A.3	GPPC0: M	N/A
GPPC2	Does the device support Green Power End Point (GPEP)?	[R4] A.3.1	GPPC0: M	N/A
GPPC3	Does the device support GPEP duplicate filtering?	[R4] A.3.6.1	GPPC0: M	N/A
GPPCC1	Is the Green Power cluster supported as a client?	[R4] A.3.4	GPPC0: O.5 ²⁹ GPDT2B: M GPDT2CB: M	N/A
GPPCC2	Is the gppMaxProxyTableEntries attribute supported?	[R4] A.3.4.2.1	GPPCC1: M	N/A
GPPCC3A	Is the Proxy Table attribute supported?	[R4]A.3.4.2.2	GPPCC1: M	N/A
GPPCC3B	Is the minimum number of 5 entries in the Proxy Table attribute supported? Indicate the actual number of entries in the Proxy Table supported by this device.	[R4]A.3.4.2.2 [R10] GPPPIXIT01	GPPCC1: M	N/A
GPPCC3F	Is Proxy Table readout via ZCL Read Attributes/Read Attributes Response commands supported?	[R4] A.3.4.2.2.1	GPPCC1: M	N/A
GPPCC3G	Is Proxy Table readout via GP Proxy Table Request/Response commands supported?	[R4] A.3.4.3.1, A.3.4.4.2	GPPCC1: M	N/A
GPPCC8	Is the gppFunctionality attribute supported?	[R4]A.3.4.2.7	GPPCC1: M	N/A
GPPCC9	Is the gppActiveFunctionality attribute supported?	[R4]A.3.4.2.8	GPPCC1: M	N/A
GPPCS1	Is the Green Power cluster supported as a server?	[R4]A.3.3	GPPC0: O.5 GPDT3CB: X	N/A
GPPCS2	Is the gppMaxSinkTableEntries attribute supported?	[R4]A.3.3.2.1	GPPCS1: M	N/A
GPPCS3A	Is the Sink Table attribute supported?	[R4]A.3.3.2.2	GPPCS1: M	N/A
GPPCS3B	Is the minimum number of 5 entries in the Sink Table attribute supported?	[R4]A.3.3.2.2 [R10] GPSPIXIT01	GPPCS1: M	N/A

²⁹ O.5: Device Under Test SHALL support at least one of those options.

Item number	Item description	Reference	Status	Support
GPPCS3C	Is Sink Table readout via ZCL Read Attributes/Read Attributes Response commands supported?	[R4] A.3.3.2.2.1	GPPCS1: M	N/A
GPPCS3D	Is Sink Table readout via GP Sink Table Request/Response commands supported?	[R4] A.3.3.5.6, A.3.3.4.7	GPPCS1: M	N/A
GPPCS8	Is the gpsFunctionality attribute supported?	[R4]A.3.3.2.7	GPPCS1: M	N/A
GPPCS9	Is the gpsActiveFunctionality attribute supported?	[R4]A.3.3.2.8	GPPCS1: M	N/A
GPPC101	Is the gpSharedSecurityKeyType attribute supported?	[R4]A.3.3.3.1	GPPC0: O (GPDT2B GPDT2CB) && GPPCCF11: O GPDT3CB && (GPPCCF10 GPPCCF11): M GPPC102: M ((GPPCCF7 GPPCCF8) && (GPF5 GPF6)): M	N/A
GPPC102	Is the gpSharedSecurityKey attribute supported?	[R4]A.3.3.3.2	GPPC0: O (GPDT2B GPDT2CB) && GPPCCF11: O GPDT3CB && (GPPCCF10 GPPCCF11): M GPPC101: M ((GPPCCF7 GPPCCF8) && (GPF5 GPF6)): M	N/A
GPPC103	Is the gpLinkKey attribute supported?	[R4]A.3.3.3.3	GPDT2B: O GPDT2CB: O	N/A
GPPC104	Is the global <i>ClusterRevision</i> attribute (0xfffd) supported?	[R4]A.3.3.3	GPDT2B: M GPDT2CB: M	N/A
GPPCC101B	Is transmission of the GP Notification command in lightweight unicast supported?	[R4] A.3.3.4.1	GPDT2B: M GPDT2CB: M	N/A
GPPCC102	Is transmission of the GP Notification command in derived groupcast supported?	[R4]A.3.3.4.1	GPDT2B: M GPDT2CB: M	N/A
GPPCC103	Is transmission of the GP Notification command in commissioned groupcast supported?	[R4]A.3.3.4.1	GPDT2B: M GPDT2CB: M	N/A
³⁰ GPPCC151 A	Is reception of the GP Pairing command supported?	[R4] A.3.3.5.2	GPPCC1: M	N/A

³⁰ CCB #2279 and CCB #2278; resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:
https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383

11.3 Functionality of Green Power cluster

The GPPCCF\$ items refer ONLY to the PROXY functionality of the Device Under Test (DUT). Analogously, the GPPCSF\$ items refer ONLY to the SINK functionality of the DUT.

Thus, for a GPC, each item set covers only a part of GPC's functionality. Therefore, for the two functional parts of the GPC, both PICS items sets have to be checked independently.

Table 5 – Green Power cluster feature support

Item number	Item description	Reference	Status	Support
GPPCSF1	Is GP feature supported as a server? (GP feature sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: M ³¹ GPDT4: O	N/A
GPPCSF2	Is Direct communication (via GP stub) supported as a server? (Direct communication sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: M ³² GPDT4: O	N/A
GPPCSF3	Is Derived groupcast communication supported as a server? (Derived groupcast communication sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: O.11 GPDT4: O	N/A
GPPCSF4	Is Pre-commissioned groupcast communication supported as a server? (Pre-commissioned groupcast communication sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: O.11 (GPDT3CB & GPPCSF3: M) GPDT4: O	N/A
GPPCSF5	Is Unicast communication supported as a server? (Unicast communication sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: X GPDT4: O	N/A
GPPCSF6	Is Lightweight unicast communication supported as a server? (Lightweight unicast communication sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: O.11 GPDT4: O	N/A
GPPCSF7	Is Proximity bidirectional operation supported as a server? (Proximity bidirectional operation sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: X GPDT4: O	N/A
GPPCSF8	Is Multi-hop bidirectional operation supported as a server? (Multi-hop bidirectional operation sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: X GPDT4: O	N/A
GPPCSF9	Is Proxy Table maintenance (active and passive) supported as a server? (Proxy Table maintenance sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: X GPDT4: O	N/A
GPPCSF10	Is Proximity commissioning (unidirectional and bidirectional) supported as a server? (Proximity commissioning sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: M ³³ GPDT4: O	N/A
GPPCSF11	Is Multi-hop commissioning (unidirectional and bidirectional) supported as a server? (Multi-hop commissioning sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: M GPDT4: O	N/A
GPPCSF12	Is CT-based commissioning supported as a server? (CTbased commissioning sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: M ³⁴ GPDT4: O	N/A
GPPCSF13	Is Maintenance of GPD (deliver channel/key during operation) supported as a server? (Maintenance of GPD sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: X GPDT4: O	N/A
GPPCSF14	Is gpdSecurityLevel = 0b00 supported in operation as a server? (gpdSecurityLevel = 0b00 sub-field of the gpsFunctionality attribute set?) <i>Note: According to the current version of the specification, only GPD that support gpdSecurityLevel = 0b10 or higher AND support TC-LK protection of the GPD key, if exchanged over the air, can be certified.</i>	[R4] A.3.2.9	GPDT2: N/A GPDT3: O GPDT4: O	N/A

³¹ CCB #2372; Resolution added in 15-02016-007

³² CCB #2372; Resolution added in 15-02016-007

³³ CCB #2372; Resolution added in 15-02016-007

³⁴ CCB #2372; Resolution added in 15-02016-007

Item number	Item description	Reference	Status	Support
GPPCSF15	Is gpdSecurityLevel = 0b01 supported as a server? (gpdSecurityLevel = 0b01 sub-field of the gpsFunctionality attribute set?) (deprecated)	[R4] A.3.2.9	GPDT1: X (deprecated)	N/A
GPPCSF16	Is gpdSecurityLevel = 0b10 supported as a server? (gpdSecurityLevel = 0b10 sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3: O.12 ³⁵ GPDT4: O	N/A
GPPCSF17	Is gpdSecurityLevel = 0b11 supported as a server? (gpdSecurityLevel = 0b11 sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3: O.12 GPDT4: O	N/A
GPPCSF18	Is SinkTable-based groupcast forwarding supported as a server? (SinkTable-based groupcast forwarding sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: X GPDT4: O	N/A
GPPCSF19	Is Translation Table feature supported as a server? (Translation Table sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3: O GPDT4: O	N/A
GPPCSF20	Is GPD IEEE address feature supported as a server? (GPD IEEE address sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: M ³⁶ GPDT4: O	N/A
³⁷ GPPCSF21	Is compact attribute reporting feature supported as a server? (Compact attribute reporting sub-field of the gpsFunctionality attribute set?)	[R4] A.3.2.9	GPDT2: N/A GPDT3CB: O ³⁸ GPS6 GPS7 GPS9 GPS12: M GPDT4: O	N/A
GPPCCF1	Is GP feature supported as a client? (GP feature sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: M GPCT2CB: M GPDT3: N/A GPDT4: O	N/A
GPPCCF2	Is Direct communication (via GP stub) supported as a client? (Direct communication sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: M GPCT2CB: M GPDT3: N/A GPDT4: O	N/A
GPPCCF3	Is Derived groupcast communication supported as a client? (Derived groupcast communication sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: M GPCT2CB: M GPDT3: N/A GPDT4: O	N/A
GPPCCF4	Is Pre-commissioned groupcast communication supported as a client? (Pre-commissioned groupcast communication sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: M GPCT2CB: M GPDT3: N/A GPDT4: O	N/A
GPPCCF5	Is Full unicast communication supported as a client? (Unicast communication sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: X GPDT2CB: X GPDT3: N/A GPDT4: O	N/A
GPPCCF6	Is Lightweight unicast communication supported as a client? (Lightweight unicast communication sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: M GPCT2CB: M GPDT3: N/A GPDT4: O	N/A
GPPCCF7	Is Proximity bidirectional operation supported as a client? (Proximity bidirectional operation sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2: N/A GPDT3: N/A GPDT4: O	N/A
GPPCCF8	Is Multi-hop bidirectional operation supported as a client? (Multi-hop bidirectional operation sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: X GPDT2CB: X GPDT3: N/A GPDT4: O	N/A
GPPCCF9	Is Proxy Table maintenance (active and passive) supported as a client? (Proxy Table maintenance sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: X GPDT2CB: X GPDT3: N/A GPDT4: O	N/A

³⁵ O.12: Device Under Test SHALL support at least one of those options.

³⁶ CCB #2372; Resolution added in 15-02016-007

³⁷ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1014

³⁸ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1014

Item number	Item description	Reference	Status	Support
GPPCCF10	Is Proximity commissioning (unidirectional and bidirectional) supported as a client? (Proximity commissioning sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2: N/A GPDT3: N/A GPDT4: O	N/A
GPPCCF11	Is Multi-hop commissioning (unidirectional and bidirectional) supported as a client? (Multi-hop commissioning sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: M GPDT2CB: M GPDT3: N/A GPDT4: O	N/A
GPPCCF12	Is CT-based commissioning supported as a client? (CTbased commissioning sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: M GPDT2CB: M GPDT3: N/A GPDT4: O	N/A
GPPCCF13	Is Maintenance of GPD (deliver channel/key during operation) supported as a client? (Maintenance of GPD sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B:X GPDT2CB: X GPDT3: N/A GPDT4: O	N/A
GPPCCF14	Is gpdSecurityLevel = 0b00 supported in operation as a client? (gpdSecurityLevel = 0b00 sub-field of the gppFunctionality attribute set?) <i>Note: According to the current version of the specification, only GPD that support gpdSecurityLevel = 0b10 or higher AND support TC-LK protection of the GPD key, if exchanged over the air, can be certified.</i>	[R4] A.3.2.8	GPDT2B: O GPDT2CB: O GPDT3CB: N/A GPDT4: O	N/A
GPPCCF15	Is gpdSecurityLevel = 0b01 supported as a client? (gpdSecurityLevel = 0b01 sub-field of the gppFunctionality attribute set?) (deprecated)	[R4] A.3.2.8	GPDT1: X (deprecated)	N/A
GPPCCF16	Is gpdSecurityLevel = 0b10 supported as a client? (gpdSecurityLevel = 0b10 sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: M GPDT2CB: M GPDT3CB: N/A GPDT4: O	N/A
GPPCCF17	Is gpdSecurityLevel = 0b11 supported as a client? (gpdSecurityLevel = 0b11 sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: M GPDT2CB: M GPDT3CB: N/A GPDT4: O	N/A
GPPCCF18	Is SinkTable-based groupcast forwarding supported as a client? (SinkTable-based groupcast forwarding sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2: N/A GPDT3: N/A GPDT4: N/A	N/A
GPPCCF19	Is Translation Table feature supported as a client? (Translation Table sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2: N/A GPDT3: N/A GPDT4: N/A	N/A
GPPCCF20	Is GPD IEEE address feature supported as a client? (GPD IEEE address sub-field of the gppFunctionality attribute set?)	[R4] A.3.2.8	GPDT2B: M GPDT2CB: M GPDT3CB: N/A GPDT4: N/A	N/A

11.3.1 Green Power cluster: items common to client and server

Table 6 – Green Power cluster items common to client and server

Item number	Item description	Reference	Status	Support
GPPC1	Is the Green Power cluster supported?	[R4] A.3	GPDT1: M	N/A
GPPC2	Does the device support Green Power End Point (GPEP)?	[R4] A.3.1	GPDT1: M	N/A
GPPC3	Does the device support GPEP duplicate filtering?	[R4] A.3.6.1.2	GPDT1: M	N/A
GPPC3r	Does the device support random MAC sequence number for GPD commands' duplicate filtering?	[R4] A.3.6.1.2	GPDT1&& (GPF8A GPF8B): M	N/A
GPPC3i	Does the device support incremental MAC sequence number for GPD commands' duplicate filtering?	[R4] A.3.6.1.2	GPDT1&& (GPF8A GPF8B): M	N/A
GPPC3s	Does the device support GPD security frame counter for GPD commands' duplicate filtering?	[R4] A.3.6.1.2	GPDT1&& (GPF5 GPF6): M	N/A
GPPC4	Does the device support transmission of Device_ance for the alias?	[R4] A.3.6.3.3, A.3.6.3.4	GPDT3 && (GPPCSF3 GPPCSF4 GPPCSF6): M GPDT2: X	N/A
GPPC5	Does the device support conflict checking for the alias on reception of Device_ance?	[R4] A.3.6.3.3, A.3.6.3.4	GPDT1: M	N/A
GPPC6	Does the device support transmission of Device_ance for the alias, upon alias conflict detection?	[R4] A.3.6.3.3, A.3.6.3.4	GPDT1: M	N/A
GPPC101	Is the <i>gpSharedSecurityKeyType</i> attribute supported?	[R4] A.3.3.3.1	GPDT1: O GPPCCF11 && (GPDT2B GPDT2CB): O GPDT3CB && (GPPCSF10 GPPCSF11): M GPPC102: M GPDT1&& ((GPPCSF7 GPPCSF8 GPPCCF7 GPPCCF8) && (GPF5 GPF6): M	N/A
GPPC102	Is the <i>gpSharedSecurityKey</i> attribute supported?	[R4] A.3.3.3.2	GPDT1: O (GPDT2B GPDT2CB) && GPPCCF11: O GPDT3CB && (GPPCSF10 GPPCSF11): M GPPC102: M GPDT1&& ((GPPCSF7 GPPCSF8 GPPCCF7 GPPCCF8) && (GPF5 GPF6): M	N/A
GPPC103	Is the <i>gpLinkKey</i> attribute supported?	[R4] A.3.3.3.3	GPDT2B: O GPDT2CB: O GPDT3CB&& (GPF5 GPF6): M	N/A
GPPC104	Is the <i>ClusterRevision</i> cluster global attribute supported?	[R4] A.3.3.3	GPDT1: M	N/A

11.3.2 Server side

Table 7 – Green Power cluster server capabilities

Item number	Item description	Reference	Status	Support
GPPCS1	Is the Green Power cluster supported as a server?	[R4] A.3.3	GPDT2B: X GPDT2CB: X GPDT3CB: M ⁴² GPDT4: O GPPCSF1: M	N/A
GPPCS2	Is the <i>gpsMaxSinkTableEntries</i> attribute supported?	[R4] A.3.3.2.1	GPDT2: X GPDT3CB: M GPDT4: O	N/A
GPPCS3A	Is the Sink Table attribute supported?	[R4] A.3.3.2.2	GPDT2: X GPDT3CB: M GPDT4: O	N/A
GPPCS3B	Is the required minimum number of entries in the Sink Table attribute supported? ⁴³	[R4] A.3.3.2.2	GPDT3CB: 5 GPDT3 && GPPCSF18: 10 GPDT3 && !GPPCSF18:5	N/A
GPPCS3C	Is Sink Table readout via ZCL Read Attributes/Read Attributes Response commands supported?	[R4] A.3.3.2.2.1	GPDT3CB: M	N/A
GPPCS3D	Is Sink Table readout via GP Sink Table Request/Response commands supported?	[R4] A.3.3.5.6, .3.3.4.7	GPDT3CB: M	N/A
GPPCS4	Is the <i>gpsCommunication</i> mode attribute supported?	[R4] A.3.3.2.3	GPDT2: X GPDT3CB: M GPDT4: O	N/A
GPPCS5	Is the <i>gpsCommissioningExitMode</i> attribute supported?	[R4] A.3.3.2.4	GPDT2: X GPDT3CB: M GPDT4: O	N/A
GPPCS6	Is the <i>gpsCommissioningWindow</i> attribute supported?	[R4] A.3.3.2.5	GPDT2: X GPDT3CB: O GPDT4: O	N/A
GPPCS7	Is the <i>gpsSecurityLevel</i> attribute supported?	[R4] A.3.3.2.6	GPDT2: X GPDT3CB: M GPDT4: O	N/A
GPPCS8	Is the <i>gpsFunctionality</i> attribute supported?	[R4] A.3.3.2.7	GPDT2: X GPDT3CB: M GPDT4: O	N/A
GPPCS9	Is the <i>gpsActiveFunctionality</i> attribute supported?	[R4] A.3.3.2.8	GPDT2: X GPDT3CB: M GPDT4: O	N/A
GPPCS99	Is Translation Table supported?	[R4] A.3.5.2.2	GPDT2: X GPDT3CB: O GPDT4: O GPPCSF19: M	N/A
GPPCS100	Is reception of the GP Notification command supported?	[R4] A.3.2.10 [R4] A.3.3.3	GPDT2B: X GPDT2CB: X GPDT3CB: M GPDT4: O	N/A
GPPCS101A	Is reception of the GP Notification command in full unicast supported?	[R4] A.3.2.10 [R4] A.3.3.4.1	GPDT2: X GPDT3CB: X GPPCSF5: M GPDT4: O	N/A
GPPCS101B	Is reception of the GP Notification command in lightweight unicast supported?	[R4] A.3.2.10 [R4] A.3.3.4.1	GPDT2: X GPDT3CB: O.14 ⁴⁴ GPPCSF6: M GPDT4: O	N/A

⁴² CCB #2372; Resolution added in 15-02016-007

⁴³ 5 is the default minimum number of entries defined by the GP Proxy cluster [R4]. A particular profile adopting the cluster may mandate different value. ⁴⁴ O.14: Device Under Test SHALL support at least one of those options; only one SHALL be enabled at any given time.

Item number	Item description	Reference	Status	Support
GPPCS102	Is reception of the GP Notification command in derived groupcast supported?	[R4] A.3.2.10 [R4] A.3.3.4.1	GPDT2B: X GPDT2CB: X (GPPCCF8 GPPCCF9 GPPCCF13): M GPDT3CB: O.14 GPPCSF3: M GPDT4: O	N/A
GPPCS103	Is reception of the GP Notification command in commissioned groupcast supported?	[R4] A.3.2.10 [R4] A.3.3.4.1	GPDT2B: X GPDT2CB: X (GPPCCF8 GPPCCF9 GPPCCF13): M GPDT3CB: O.14 GPPCSF4: M GPPCS102: M GPDT4: O	N/A
GPPCS104	Is reception of the GP Notification command in broadcast supported?	[R4] A.3.2.10 [R4] A.3.3.4.1 [R4] A.5.2.1	GPDT2B: X GPDT2CB: X GPPCCF9: M GPDT3CB: X GPPCSF9: M GPDT4: O	N/A
GPPCS105	Is reception of the GP Pairing Search command supported?	[R4] A.3.2.10 [R4] A.3.3.4.2	GPDT2B: X GPDT2CB: X GPPCCF9: O GPDT3CB: X GPDT4: O GPPCSF9: M	N/A
GPPCS106	Is reception of the GP Tunneling Stop command supported?	[R4] A.3.2.10 [R4] A.3.4.4.1	GPDT2B: X GPDT2CB: X GPPCCF5: M GPDT3CB: X GPDT4: O	N/A
GPPCS107	Is reception of the GP Commissioning Notification command supported?	[R4] A.3.2.10 [R4] A.3.3.4.4	(GPDT2B GPDT2CB) && GPPCCF11: X GPPCCF11: M GPDT3CB: M GPPCSF11: M GPDT4: O	N/A
GPPCS108	Is reception of the GP Translation Table Update command supported?	[R4] A.3.2.10 [R4] A.3.3.4.6	GPDT2: X GPDT3CB: O GPDT4: O GPPCSF19: M	N/A
GPPCS109	Is reception of the GP Translation Table Request command supported?	[R4] A.3.2.10 [R4] A.3.3.4.5	GPDT2: X GPDT3CB: O GPDT4: O GPPCSF19: M	N/A
GPPCS110	Is reception of the GP Pairing Configuration command supported?	[R4] A.3.2.10 [R4] A.3.3.4.7	GPDT2: X GPDT3CB: M GPPCSF4 GPPCSF12 GPPCSF18: M	N/A
GPPCS111	Is reception of the GP Sink Table Request command supported?	[R4] A.3.3.5.6, .3.3.4.7	GPDT2B: X GPDT2CB: X GPDT3CB: M GPDT4: O	N/A
GPPCS112	Is reception of the GP Proxy Table Response command supported?	[R4] A.3.4.3.1, .3.4.4.2	GPDT2B: O GPDT2CB: O GPDT3CB: O GPDT4: O GPPCS157: M	N/A
GPPCS113	Is reception of the GP Sink Commissioning Mode command supported?	[R4] A.3.3.4.7, A.3.9.1	GPDT2: X GPDT3: O GPDT4: O	N/A
GPPCS150	Is transmission of the GP Notification Response command supported?	[R4] A.3.2.10 [R4] A.3.3.5.1	GPDT2: X GPDT3CB: X GPDT4: O GPPCSF5: M	N/A

Item number	Item description	Reference	Status	Support
GPPCS151A	Is transmission of the GP Response command with SrcID = 0x00000000 in commissioning supported?	[R4] A.3.2.10 [R4] A.3.3.5.4	GPDT2: X GPDT3CB: M GPDT4: O GPPCSF11: M GPPCSF10: O	N/A
GPPCS151B	Is transmission of the GP Response command with SrcID != 0x00000000 in commissioning supported?	[R4] A.3.2.10 [R4] A.3.3.5.4	GPDT2: X GPDT3CB: M GPDT4: O GPPCSF10 GPPCSF11: M GPPCSF10: M	N/A
GPPCS151C	Is transmission of the GP Response command with IEEE address and Endpoint in commissioning supported?	[R4] A.3.2.10 [R4] A.3.3.5.4	GPDT2: X GPDT3CB: M GPDT4: O GPPCSF10 GPPCSF11 && GPPCSF20: M	N/A
GPPCS151D	Is transmission of the GP Response command with SrcID != 0x00000000 in operation supported?	[R4] A.3.2.10 [R4] A.3.3.5.4	GPDT2: X GPDT3CB: X GPDT4: O GPPCSF8 GPPCSF13: M	N/A
GPPCS151E	Is transmission of the GP Response command with IEEE address and Endpoint in operation supported?	[R4] A.3.2.10 [R4] A.3.3.5.4	GPDT2: X GPDT3CB: X GPDT4: O (GPPCSF8 GPPCSF 13) && GPPCSF20: M	N/A
GPPCS152	Is transmission of the GP Pairing command supported?	[R4] A.3.2.10 [R4] A.3.3.5.2	GPDT2: X GPDT3CB: M ³⁹ GPDT4: O	N/A
GPPCS153	Is generation of the GP Pairing command with RemoveGPD sub-field set to 0b1 supported?	[R4] A.3.2.10 [R4] A.3.3.5.2	GPDT2: X GPDT3CB: M ⁴⁰ GPDT4: O	N/A
GPPCS153A	Is generation of the GP Pairing command with RemoveGPD sub-field set to 0b1 upon reception of Decommissioning command in commissioning mode supported?	[R4] A.3.2.10 [R4] A.3.3.5.2	GPDT2: X GPDT3CB: M ⁴¹ GPDT4: O	N/A
GPPCS153B	Is generation of the GP Pairing command with RemoveGPD sub-field set to 0b1 upon a local trigger supported?	[R4] A.3.2.10 [R4] A.3.3.5.2	GPDT2: X GPDT3CB: O ⁴² GPDT4: O	N/A
GPPCS153A	Is generation of the GP Pairing command with RemoveGPD sub-field set to 0b1 upon reception of GP Pairing Configuration command with Action sub-field of the Actions field set to 0b100 (Remove GPD) and Send GP Pairing sub-field of the Actions field set to 0b1?	[R4] A.3.2.10 [R4] A.3.3.5.2	GPDT2: X GPDT3CB: M GPPCSF12: M GPDT4: O	N/A
GPPCS154	Is transmission of the GP Proxy Commissioning Mode command supported?	[R4] A.3.2.10 [R4] A.3.3.5.3	GPDT2: X GPDT3CB: M ⁴³ GPDT4: O GPPCSF11: M	N/A
GPPCS155	Is transmission of the GP Translation Table Response command supported?	[R4] A.3.2.10 [R4] A.3.3.5.5	GPDT2: X GPDT3CB: O GPPCS109: M GPDT4: O GPPCSF19: M	N/A
GPPCS156	Is transmission of the GP Sink Table Response command supported?	[R4] A.3.3.5.6, .3.3.4.7	GPDT2B: X GPDT2CB: X GPDT3CB: M GPDT4: O	N/A
GPPCS157	Is transmission of the GP Proxy Table Request command supported?	[R4] A.3.4.3.1, .3.4.4.2	GPDT2B: O GPDT2CB: O GPDT3CB: O GPDT4: O	N/A

³⁹ CCB #2372; Resolution added in 15-02016-007⁴⁰ CCB #2372; Resolution added in 15-02016-007⁴¹ CCB #2372; Resolution added in 15-02016-007⁴² CCB #2372; Resolution added in 15-02016-007⁴³ CCB #2372; Resolution added in 15-02016-007

Item number	Item description	Reference	Status	Support
GPPCS201	Is persistent storage of Sink Table supported?	[R4] A.3.2.10 [R4] A.3.3.2.2	GPDT2: X GPDT3CB: M GPDT4: O	N/A

11.3.3 Client side

Table 8 – Green Power cluster client capabilities

Item number	Item description	Reference	Status	Support
GPPCC1	Is the Green Power cluster supported as a client?	[R4] A.3.4	GPDT2B: M GPDT2CB: M GPDT3: O GPDT4: O	N/A
GPPCC2	Is the <i>gppMaxProxyTableEntries</i> attribute supported?	[R4] A.3.4.2.1	GPDT2B: M GPDT2CB: M GPDT3: X GPDT4: O	N/A
GPPCC3A	Is the Proxy Table attribute supported?	[R4] A.3.4.2.2	GPDT2B: M GPDT2CB: M GPDT3: X GPDT4: O	N/A
GPPCC3B	Is the required minimal number of entries in the Proxy Table attribute supported? ⁵⁰ Indicate the actual number of entries in the Proxy Table attribute supported by this device.	[R4] A.3.4.2.2 [R10] GPPPIXIT01	GPDT2: 5	N/A
GPPCC3C	Is the required minimal number of entries in the <i>Lightweight sink address list</i> per Proxy Table entry supported?	[R4] A.3.4.2.2	GPDT2 && GPPCCF6: 2	N/A
GPPCC3D	Is the required minimal number of entries in the <i>Sink group list</i> per Proxy Table entry supported?	[R4] A.3.4.2.2	GPDT2 && GPPCCF4: 2	N/A
GPPCC3E	Is the required minimal number of simultaneously used entries in the <i>Lightweight sink address list/Full unicast sink address list</i> and in the <i>Sink group list</i> per Proxy Table entry supported?	[R4] A.3.4.2.2	GPDT2 && (GPPCCF5 GPPCCF6) && (GPPCCF4): 1+1	N/A
GPPCC3H	Is the required minimal number of entries in the <i>Full unicast sink address list</i> per Proxy Table entry supported?	[R4] A.3.4.2.2	GPDT2 && GPPCCF5: 2	N/A
GPPCC3F	Is Proxy Table readout via ZCL Read Attributes/Read Attributes Response commands supported?	[R4] A.3.4.2.2.1	GPPCC1: M	N/A
GPPCC3G	Is Proxy Table readout via GP Proxy Table Request/Response commands supported?	[R4] A.3.4.3.1, A.3.4.4.2	GPPCC1: M	N/A
GPPCC4	Is the <i>gppNotificationRetryNumber</i> attribute supported?	[R4] A.3.4.2.3	GPDT2B: X GPDT2CB: X GPPCCF5: M GPDT3: X GPDT4: O	N/A
GPPCC5	Is the <i>gppNotificationRetryTimer</i> attribute supported?	[R4] A.3.4.2.4	GPDT2B: X GPDT2CB: X GPPCCF5: M GPDT3: X GPDT4: O	N/A
GPPCC6	Is the <i>gppMaxSearchCounter</i> attribute supported?	[R4] A.3.4.2.5	GPDT2B: X GPDT2CB: X GPPCCF9: M GPDT3: X GPDT4: O	N/A
GPPCC7	Is the <i>gppBlockedSrcID</i> attribute supported?	[R4] A.3.4.2.6	GPDT2B: X GPDT2CB: X GPPCCF9: O GPDT3: X GPDT4: O	N/A
GPPCC8	Is the <i>gppFunctionality</i> attribute supported?	[R4] A.3.4.2.7	GPDT2B: M GPDT2CB: M GPDT3: X GPDT4: O	N/A

⁵⁰ 5 is the default minimum number of entries defined by the GP Proxy cluster [R4]. A particular profile adopting the cluster may mandate different value.

Item number	Item description	Reference	Status	Support
GPPCC9	Is the <i>gppActiveFunctionality</i> attribute supported?	[R4] A.3.4.2.8	GPDT2B: M GPDT2CB: M GPDT3: X GPDT4: O	N/A
GPPCC100	Is transmission of the GP Notification command supported?	[R4] A.3.2.10 [R4] A.3.3.4.1	GPDT2B: M GPDT2CB: M GPDT3CB: X GPDT4: O	N/A
GPPCC101A	Is transmission of the GP Notification command in full unicast supported?	[R4] A.3.2.10 [R4] A.3.3.4.1	GPDT2B: X GPDT2CB: X GPPCCF5: M GPDT3CB: X GPDT4: O	N/A
GPPCC101B	Is transmission of the GP Notification command in lightweight unicast supported?	[R4] A.3.2.10 [R4] A.3.3.4.1	GPDT2B: M GPDT2CB: M GPPCCF6: M GPDT3CB: X GPDT4: O	N/A
GPPCC102	Is transmission of the GP Notification command in derived groupcast supported?	[R4] A.3.2.10 [R4] A.3.3.4.1	GPDT2B: M GPDT2CB: M GPPCCF3: M GPDT3CB: X GPPCSF18: M GPDT4: O	N/A
GPPCC103	Is transmission of the GP Notification command in commissioned groupcast supported?	[R4] A.3.2.10 [R4] A.3.3.4.1	GPDT2: M GPDT2CB: M GPPCCF4: M GPDT3CB: X GPPCSF18: M GPDT4: O	N/A
GPPCC104	Is transmission of the GP Notification command in broadcast supported?	[R4] A.3.2.10 [R4] A.3.3.4.1	GPDT2B: X GPDT2CB: X GPDT3CB: X GPPCCF9: M GPDT4: O	N/A
GPPCC105	Is transmission of the GP Notification command in multiple communication modes supported?	[R4] A.3.2.10 [R4] A.3.5.2.1	GPDT2B: M GPDT2CB: M Any two of (GPPCCF3 GPPCCF4 GPPCCF5 GPPCCF6): M GPDT3CB: X GPPCSF18 && (GPPCCF3 GPPCCF4): M GPDT4: O	N/A
GPPCC106	Is transmission of the GP Pairing Search command supported?	[R4] A.3.2.10 [R4] A.3.4.2	GPDT2B: X GPDT2CB: X GPDT3CB: X GPPCCF9: M ⁵¹ GPDT4: O	N/A
GPPCC107	Is transmission of the GP Tunneling Stop command supported?	[R4] A.3.2.10 [R4] A.3.4.4.1	GPDT2B: X GPDT2CB: X GPPCCF5: M GPDT3CB: X GPDT4: O	N/A
GPPCC108A	Is transmission of the GP Commissioning Notification command with alias, after Dmin, supported?	[R4] A.3.2.10 [R4] A.3.3.4.4	GPDT2B: M GPDT2CB: M GPPCCF11: M GPDT3CB: X GPDT4: O	N/A

Item number	Item description	Reference	Status	Support
GPPCC108B	Is transmission of the GP Commissioning Notification command without alias, at gppTunnelingDelay supported?	[R4] A.3.2.10 [R4] A.3.3.4.4	(GPDT2B GPDT2CB) && GPPCCF11: M GPPCCF11: M GPDT3CB: X GPDT4: O	N/A
GPPCC109	Is transmission of the GP Translation Table Update command supported?	[R4] A.3.2.10 [R4] A.3.3.4.5 [R4] A.3.2.5	GPDT2: X GPDT3CB: O ⁴⁴ GPDT4: O	N/A
GPPCC110	Is transmission of the GP Translation Table Request command supported?	[R4] A.3.2.10 [R4] A.3.3.4.6 [R4] A.3.2.5	GPDT2: X GPDT3CB: O ⁴⁵ GPDT4: O	N/A
GPPCC111	Is transmission of the GP Pairing Configuration command supported?	[R4] A.3.2.10 [R4] A.3.3.4.7 [R4] A.3.2.5	GPDT2B: X GPDT2CB: X GPDT3CB: O ⁴⁶ GPDT4: O GPPCSF4 GPPCSF18: M	N/A
GPPCC112	Is transmission of the GP Proxy Table Response command supported?	[R4] A.3.3.5.6, ..3.3.4.7	GPDT2B: M GPDT2CB: M GPDT3: X GPDT4: O	N/A
GPPCC113	Is transmission of the GP Sink Table Request command supported?	[R4] A.3.4.3.1, ..3.4.4.2	GPDT2B: O GPDT2CB: O GPDT3CB: O ⁴⁷ GPDT4: O	N/A
GPPCC114	Is transmission of the GP Sink Commissioning Mode command supported?	[R4] A.3.3.4.7, A.3.9.1	GPDT2: O GPDT3: O ⁴⁸ GPDT4: O	N/A
GPPCC150	Is reception of the GP Notification Response command supported?	[R4] A.3.2.10 [R4] A.3.3.5.1	GPDT2B: X GPDT2CB: X GPPCCF5: M GPDT3: X GPDT4: O	N/A
⁴⁹ GPPCC151A	Is reception of the GP Pairing command supported?	[R4] A.3.2.10 [R4] A.3.3.5.2	GPDT2: M GPDT3: X ⁵⁰ GPDT4: O	N/A
⁵¹ GPPCC151B	Does the device support checking of the <i>CommunicationMode</i> sub-field of the <i>Options</i> field of the received GP Pairing command?	[R4] A.3.5.2.3	GPPCC151A: M	N/A
⁵² GPPCC151C	Does the device support checking if its Proxy Table is full on reception of GP Pairing command?	[R4] A.3.5.2.3	GPPCC151A: M	N/A

⁴⁴ CCB #2372; Resolution added in 15-02016-007

⁴⁵ CCB #2372; Resolution added in 15-02016-007

⁴⁶ CCB #2372; Resolution added in 15-02016-007

⁴⁷ CCB #2372; Resolution added in 15-02016-007

⁴⁸ CCB #2372; Resolution added in 15-02016-007

⁴⁹ CCB #2279 and CCB #2278; resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383

⁵⁰ CCB #2372; Resolution added in 15-02016-007

⁵¹ CCB #2278; resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383

⁵² CCB #2279; resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383

Item number	Item description	Reference	Status	Support
GPPCC152	Is reception of the GP Pairing command with <i>RemoveGPD</i> sub-field set to 0b1 supported?	[R4] A.3.2.10 [R4] A.3.3.5.2	GPDT2: M GPDT3: X ⁵³ GPDT4: O	N/A
GPPCC153	Is reception of the GP Proxy Commissioning Mode command supported?	[R4] A.3.2.10 [R4] A.3.3.5.3	GPDT2B: M GPDT2CB: M GPPCCF11: M GPDT3CB: O ⁵⁴ GPDT4: O	N/A
GPPCC154A	Is reception of the GP Response command with SrcID = 0x00000000 in commissioning mode supported?	[R4] A.3.2.10 [R4] A.3.3.5.4	GPDT2B: M GPDT2CB: M GPPCCF11: M GPDT3CB: M GPPCSF10 GPPCSF11 : M GPDT4: O	N/A
GPPCC154B	Is reception of the GP Response command with SrcID != 0x00000000 in commissioning mode supported?	[R4] A.3.2.10 [R4] A.3.3.5.4	GPDT2B: M GPDT2CB: M GPPCCF11: M GPDT3CB: M GPPCSF10 GPPCSF11: M GPDT4: O	N/A
GPPCC154C	Is reception of the GP Response command with IEEE address and Endpoint in commissioning mode supported?	[R4] A.3.2.10 [R4] A.3.3.5.4	GPDT2B: M GPDT2CB: M GPPCCF11: M GPDT3CB: M GPPCSF10 GPPCSF11: M GPDT4: O	N/A
GPPCC154B	Is reception of the GP Response command with SrcID != 0x00000000 in operation supported?	[R4] A.3.2.10 [R4] A.3.3.5.4	GPDT2B: X GPDT2CB: X (GPPCCF8 GPPCCF13): M GPDT3CB: X (GPPCSF7 GPPCSF8 GPPCCF13): M GPDT4: O	N/A
GPPCC154C	Is reception of the GP Response command with IEEE address and Endpoint in operation supported?	[R4] A.3.2.10 [R4] A.3.3.5.4	GPDT2B: X GPDT2CB: X (GPPCCF8 GPPCCF13): M GPDT3CB: X (GPPCSF7 GPPCSF8 GPPCCF13): M GPDT4: O	N/A
GPPCC155	Is reception of the GP Translation Table Response command supported?	[R4] A.3.2.10 [R4] A.3.3.5.5 [R4] A.3.2.5	GPDT2: X GPDT3CB: O GPPCC110: M ⁶³ GPDT4: O	N/A
GPPCC156	Is reception of the GP Proxy Table Request command supported?	[R4] A.3.3.5.6, .3.3.4.7	GPDT2B: M GPDT2CB: M GPDT3: X GPDT4: O	N/A
GPPCC157	Is reception of the GP Sink Table Response command supported?	[R4] A.3.4.3.1, .3.4.4.2	GPDT2: X GPDT3: O GPDT4: O GPPCC113: M	N/A
GPPCC200	Is persistent storage of Proxy Table supported?	[R4] A.3.4.2.2	GPPCC3A: M	N/A

⁵³ CCB #2372; Resolution added in 15-02016-007⁵⁴ CCB #2372; Resolution added in 15-02016-007

Item number	Item description	Reference	Status	Support
GPPCC201	Is handling of Proxy Table entries with status other than active and valid supported?	[R4] A.3.5.2.2	GPDT2B: X GPDT2CB: X GPDT3: X GPDT4: O GPPCCF9: M	N/A
GPPCC202	Is passive discovery supported?	[R4] A.3.5.2.2.3	GPDT2B: X GPDT2CB: X GPDT3: X GPDT4: O GPPCCF9: M	N/A
GPPCC2034	Is active discovery supported?	[R4] A.3.5.2.2.4	GPDT2B: X GPDT2CB: X GPDT3: X GPDT4: O GPPCCF9: M	N/A
GPPCC204	Is active re-discovery supported?	[R4] A.3.5.2.2.5	GPDT2B: X GPDT2CB: X GPDT3: X GPDT4: O GPPCCF9: M	N/A
GPPCC205	Is limiting the number of the transmitted Green Power cluster messages supported?	[R4] A.3.6.3.1, A.3.6.3.3	GPDT2B: M GPDT2CB: M GPDT3CB: X (GPPCSF18 && (GPPCSF7 GPPCSF8)): M GPDT4: O	N/A
GPPCC205A	Is quality-based gppTunnelingDelay supported?	[R4] A.3.6.3.1 [R4] A.3.2.8, [R4] A.3.2.9	(GPDT2B GPDT2CB) && GPPCCF11: M GPPCCF5 GPPCCF8 GPPCCF9 GPPCCF11 GPPCCF13: M (GPPCCF3 GPPCCF4 GPPCCF6) && !(GPPCCF5 GPPCCF8 GPPCCF9 GPPCCF11 GPPCCF13) : X GPDT3CB: X (GPPCSF18 && (GPPCSF7 GPPCSF8)): M GPDT4: O	N/A
GPPCC205B	Is dropping the scheduled Green Power cluster message on reception of equivalent message supported?	[R4] A.3.6.3.1 [R4] A.3.2.8, [R4] A.3.2.9	GPDT2B && GPPCCF11: X GPDT2CB && GPPCCF11: X GPPCCF5 GPPCCF8 GPPCCF9 GPPCCF11 GPPCCF13: M (GPPCCF3 GPPCCF4 GPPCCF6) && !(GPPCCF5 GPPCCF8 GPPCCF9 GPPCCF11 GPPCCF13) : X GPDT3CB: X (GPPCSF18 && (GPPCSF7 GPPCSF8)): M GPDT4: O	N/A
GPPCC205C	Is transmission of Green Power cluster commands with alias supported?	[R4] A.3.6.3.3 [R4] A.3.2.8, [R4] A.3.2.9	GPDT2B: M GPDT2CB: M GPPCCF3 GPPCCF4 GPPCCF5 GPPCCF11: M GPDT3CB: X GPPCSF18: M GPDT4: O	N/A
GPPCC206	Is updating <i>Lightweight sink address list</i> and <i>Full unicast sink address list</i> field of the Proxy Table attribute on reception of Device_annce supported?	[R4] A.3.5.2.1	GPDT2B: M GPDT2CB: M GPPCC3A&&(GPPCCF5 GPPCCF6): M GPDT3: N/A GPDT4: O	N/A

63

11.3.4 Support of GP functionality

11.3.4.1 Bidirectional operation

Table 9 – Support for Green Power bidirectional operation

Item number	Item description	Reference	Status	Support
GPF101	Is transmission of GPD Read Attributes command supported?	[R4] A.4.2.5 [R4] A.3.6.1.5	GPPCCF8: M.9 ⁵⁵ GPPCSF7 GPPCSF8: O	N/A
GPF102	Is reception of GPD Read Attributes command supported?	[R4] A.4.2.5 [R4] A.3.6.1.5	GPPCCF8: M.16 GPPCSF7 GPPCSF8: X	N/A
GPF103	Is transmission of GPD Read Attributes Response supported?	[R4] A.4.2.5 [R4] A.3.6.1.5	GPPCCF8: M.16 GPPCSF7 GPPCSF8: X	N/A
GPF104	Is reception of GPD Read Attributes Response command supported?	[R4] A.4.2.5 [R4] A.3.6.1.5	GPPCCF8: M.16 (GPPCSF7 GPPCSF8)&&GPF101 : M	N/A
GPF105	Is transmission of GPD Request Attributes command supported?	[R4] A.4.2.5 [R4] A.3.6.1.5	GPPCCF8: M.16 GPPCSF7 GPPCSF8: X	N/A
GPF106	Is reception of GPD Request Attributes command supported?	[R4] A.4.2.5 [R4] A.3.6.1.5	GPPCCF8: M.16 GPPCSF7 GPPCSF8: M	N/A
GPF107	Is transmission of GPD Write Attributes command supported?	[R4] A.4.2.5 [R4] A.3.6.1.5	GPPCCF8: M.16 GPPCSF7 GPPCSF8: O	N/A
GPF108	Is reception of GPD Write Attributes command supported?	[R4] A.4.2.5 [R4] A.3.6.1.5	GPPCCF8: M.16 GPPCSF7 GPPCSF8: X	N/A
GPF109	Is transmission of GPD ZCL Tunneling command (0xF6) supported?	[R4] A.4.2.3.5	GPPCCF8: M.16 (GPPCSF7 GPPCSF8)&& GPDRXA6: M	N/A
GPF110	Is reception of GPD ZCL Tunneling command (0xF6) supported?	[R4] A.4.2.3.5	GPPCCF8: M.16 GPPCSF7 GPPCSF8: X	N/A
GPF111	List the functionality accessible via GPD ZCL Tunneling command. List the ZCL generic command, with the corresponding ClusterID(s) and AttributeID(s), if any. List the cluster-specific CommandIDs per ZCL-defined Cluster, if any. Manufacturer-specific functionality doesn't have to be listed.	[R10] GPSPIXIT07 , GPSPIXIT08	GPF109: M	N/A

⁵⁵ M.16: Note: the bidirectional operation is transparent to the proxy. It just needs to act add the command received in GP Response to its gpTxQueue and send it upon reception of GPDF frame with *RxAfterTx* set; it doesn't care about the type of the command.

[CCB #2372; Resolution added in 15-02016-007](#)

11.3.4.2 Green Power Commissioning Support

Table 10 – GP Commissioning Support

Item number	Item description	Reference	Status	Support
GPCF1	Does the device support pairing with Data GPDF with Auto-Commissioning bit set to 0b1? <i>Note: According to the current version of the specification, only GPD that support <code>gpdSecurityLevel = 0b10</code> or higher AND support TC-LK protection of the GPD key, if exchanged over the air, can be certified.</i>	[R4] A.3.9	GPPCCF11: M (GPPCSF10 GPPCSF11): O GPPCSF14: M ⁵⁶ GPDT4: O	N/A
GPCF2	Does the device support pairing with Commissioning GPDF?	[R4] A.3.9	GPPCCF11: M (GPPCSF10 GPPCSF11): : M ⁵⁷ GPDT4: O	N/A
GPCF3A	Does the device support transmission of GPD Commissioning command?	[R4] A.4.2.1.1	GPDT1: X	N/A
GPCF3B	Does the device support reception of GPD Commissioning command?	[R4] A.4.2.1.1	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁵⁸ GPDT4: O	N/A
GPCF4	Does the device support bidirectional communication in commissioning mode?	[R4] A.3.9	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁵⁹ GPDT4: O	N/A
GPCF5A	Does the device support transmission of the GPD Channel Request command in commissioning mode?	[R4] A.3.9	GPDT1: X	N/A
GPCF5B	Does the device support reception of the GPD Channel Request command in commissioning mode?	[R4] A.3.9	GPPCCF11: M (GPPCSF10 GPPCSF11): M	N/A
GPCF6	Does the device support transmission of the GPD Channel Configuration command?	[R4] A.3.9	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶⁰ GPDT4: O	N/A
GPCF6A	Does the device support transmission of the GPD Channel Configuration command in commissioning mode, as a Maintenance frame?	[R4] A.3.9	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶⁰ GPDT4: O	N/A
GPCF6B	Does the device support transmission of the GPD Channel Configuration command in operational mode, as a Data frame?	[R4] A.3.9	GPPCCF8 GPPCCF13: M GPPCSF13: M GPDT4: O	N/A
GPCF7	Does the device support reception of the GPD Channel Configuration command?	[R4] A.3.9	GPDT1: X	N/A
GPCF8	Does the device support transmission of the GPD Commissioning Reply command?	[R4] A.4.2.1.2	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶¹ GPDT4: O	N/A
GPCF8A	Does the device support transmission of the GPD Commissioning Reply command in commissioning mode?	[R4] A.4.2.1.2	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶² GPDT4: O	N/A
GPCF8B	Does the device support transmission of the GPD Commissioning Reply command in operational mode?	[R4] A.4.2.1.2	GPPCCF8 GPPCCF13: M GPPCSF13: M GPDT4: O	N/A
GPCF9	Does the device support reception of the GPD Commissioning Reply command?	[R4] A.4.2.1.2	GPDT1: X	N/A
GPCF10	Is GPD removal via GPD Decommissioning command supported?	[R4] A.4.2.1.3	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶³ GPDT4: O	N/A
GPCF11	Does the device come with pre-configured GPD key?	[R4] A.3.9	GPDT1: X	N/A
GPCF12A	Does the device support GPD key exchange in GPD Commissioning command?	[R4] A.3.9	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶⁴ GPDT4: O	N/A

⁶⁰

⁵⁶ CCB #2372; Resolution added in 15-02016-007

⁵⁷ CCB #2372; Resolution added in 15-02016-007

⁵⁸ CCB #2372; Resolution added in 15-02016-007

⁵⁹ CCB #2372; Resolution added in 15-02016-007

⁶⁰ CCB #2372; Resolution added in 15-02016-007

⁶¹ CCB #2372; Resolution added in 15-02016-007

⁶² CCB #2372; Resolution added in 15-02016-007

⁶³ CCB #2372; Resolution added in 15-02016-007

⁶⁴ CCB #2372; Resolution added in 15-02016-007

Item number	Item description	Reference	Status	Support
GPCF12B	Does the device support exchange of encrypted GPD key in GPD Commissioning command?	[R4] A.3.9	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶⁵ GPDT4: O	N/A
GPCF13A	Does the device support GPD key exchange in GPD Commissioning Reply command?	[R4] A.3.9	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶⁶ GPDT4: O	N/A
GPCF13B	Does the device support exchange of encrypted GPD key in GPD Commissioning Reply command?	[R4] A.3.9	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶⁷ GPDT4: O	N/A
GPCF14	Does the device support out-of-band GPD key configuration?	[R4] A.3.9	GPDT2: O GPDT3: O GPDT4: O	N/A
GPCF15A	Does the device support transmission of GPD Success command in commissioning mode?	[R4] A.3.9	GPDT1: X	N/A
GPCF15B	Does the device support reception of GPD Success command in commissioning mode?	[R4] A.3.9	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶⁸ GPDT4: O	N/A
GPCF16	Does the device support in-band configuration of PANId (via GPD Commissioning Reply command)?	[R4] A.3.9	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁶⁹ GPDT4: O	N/A
GPCF17	Does the device support transmission of GPD Commissioning command with Application information?	[R4] A.4.2.1.1	GPDT1: X	N/A
GPCF17A	Does the device support transmission of the GPD Commissioning command with the ModelID? If YES, specify the ModelID used.	[R4] A.4.2.1.1	GPDT1: X	N/A
GPCF17B	Does the device support transmission of the GPD Commissioning command with the ManufacturerID? If YES, specify the ManufacturerID used.	[R4] A.4.2.1.1	GPDT1: X	N/A
GPCF17C	Does the device support transmission of the GPD Commissioning command with the GPD command list containing GPD-defined commands? If YES, list the GPD commands used.	[R4] A.4.2.1.1	GPDT1: X	N/A
GPCF17D	Does the device support transmission of the GPD Commissioning command with the GPD command list containing manufacturer-defined commands? If YES, list the GPD commands used.	[R4] A.4.2.1.1	GPDT1: X	N/A
GPCF17E	Does the device support transmission of the GPD Commissioning command with the Cluster list containing ZCL-defined clusters? If YES, list the ZCL clusters used.	[R4] A.4.2.1.1	GPDT1: X	N/A
GPCF17F	Does the device support transmission of the GPD Commissioning command with the Cluster list containing manufacturer-specific clusters? If YES, list the GPD commands used.	[R4] A.4.2.1.1	GPDT1: X	N/A
GPCF17G	Does the device support transmission of the GPD Commissioning command with the Switch Information?	[R4] A.4.2.1.1	GPDT1: X	N/A
GPCF18	Does the device support reception of GPD Commissioning command with Application information?	[R4] A.4.2.1.1	GPCF3B: O	N/A
GPCF18A	Does the device support reception of the GPD Commissioning command with the ModelID?	[R4] A.4.2.1.1	GPCF18: M	N/A

⁶⁵ CCB #2372; Resolution added in 15-02016-007

⁶⁶ CCB #2372; Resolution added in 15-02016-007

⁶⁷ CCB #2372; Resolution added in 15-02016-007

⁶⁸ CCB #2372; Resolution added in 15-02016-007

⁶⁹ CCB #2372; Resolution added in 15-02016-007

CCB #2372; Resolution added in 15-02016-007

Item number	Item description	Reference	Status	Support
GPCF18B	Does the device support reception of the GPD Commissioning command with the ManufacturerID? If yes, list the ManufacturerID supported.	[R4] A.4.2.1.1 [R10] GPSPIXIT02	GPCF18: M	N/A
GPCF18C	Does the device support reception of the GPD Commissioning command with the GPD command list containing GPD-defined commands? If yes, list the GPD commands supported.	[R4] A.4.2.1.1 [R10] GPSPIXIT03	GPCF18: M	N/A
GPCF18D	Does the device support reception of the GPD Commissioning command with the GPD command list containing manufacturer-defined GPD commands? If yes, list the GPD commands supported.	[R4] A.4.2.1.1 [R10] GPSPIXIT04	GPCF18: M	N/A
GPCF18E	Does the device support reception of the GPD Commissioning command with the Cluster list containing ZCL-defined clusters? If yes, list the ZCL clusters controllable via GP.	[R4] A.4.2.1.1 [R10] GPSPIXIT05	GPCF18: M	N/A
GPCF18F	Does the device support reception of the GPD Commissioning command with the Cluster list containing manufacturer-specific clusters? If yes, list the manufacturer-specific clusters controllable via GP.	[R4] A.4.2.1.1 [R10] GPSPIXIT06	GPCF18: M	N/A
GPCF18G	Does the device support reception of the GPD Commissioning command with the Switch Information?	[R4] A.4.2.1.1	GPS17: M	N/A
GPCF19	Does the device support automatic progressing between the commissioning steps?	[R4] A.3.9.1	GPDT1: X	N/A
GPCF20	Does the device support transmission of the GPD Application Description command?	[R4] A.3.9.1, A.4.2.1.6	GPDT1: X	N/A
GPCF21	Does the device support reception of the GPD Application Description command?	[R4] A.3.9.1, [R4] A.4.2.1.6	⁷⁰ GPS16: M ⁷¹ GPPCCF11: M	N/A
⁷² GPCF22	Does the GPD support subsequent commissioning?	[R4] A.3.9.1	GPDT1: X	N/A
GPCF22A	Does the GPD supporting bidirectional commissioning with OOB key implement the subsequent commissioning as full bidirectional procedure?	[R4] A.3.9.1	GPDT1: X	N/A
GPCF22B	Does the GPD supporting bidirectional commissioning with OOB key implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPDT1: X	N/A
GPCF22C	Does the GPD supporting bidirectional commissioning with shared key implement the subsequent commissioning as full bidirectional procedure?	[R4] A.3.9.1	GPDT1: X	N/A
GPCF22D	Does the GPD supporting bidirectional commissioning with shared key implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPDT1: X	N/A
GPCF22E	Does the GPD supporting unidirectional commissioning implement the subsequent commissioning as full unidirectional procedure?	[R4] A.3.9.1	GPDT1: X	N/A
GPCF22F	Does the GPD supporting unidirectional commissioning implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPDT1: X	N/A
⁷³ GPCF23	Does the device support subsequent commissioning?	[R4] A.3.9.1	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁸⁴ GPDT4: O	N/A

⁷⁰ Comment #785 from GP multi-sensor v0.7 letter ballot

⁷¹ Comment #1374 from GP multi-sensor v1.0 WG ballot;

⁷² Dec 2016 SVE comment:

https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1025

⁷³ Dec 2016 SVE comment:

https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1025 ⁸⁴

CCB #2372; Resolution added in 15-02016-007

Item number	Item description	Reference	Status	Support
GPCF23A	Does the device supporting bidirectional commissioning with OOB key implement the subsequent commissioning as full bidirectional procedure?	[R4] A.3.9.1	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁷⁴ GPDT4: O	N/A
GPCF23B	Does the device supporting bidirectional commissioning with OOB key implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁷⁵ GPDT4: O	N/A
GPCF23C	Does the device supporting bidirectional commissioning with shared key implement the subsequent commissioning as full bidirectional procedure?	[R4] A.3.9.1	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁷⁶ GPDT4: O	N/A
GPCF23D	Does the device supporting bidirectional commissioning with shared key implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁷⁷ GPDT4: O	N/A
GPCF23E	Does the device supporting unidirectional commissioning implement the subsequent commissioning as full unidirectional procedure?	[R4] A.3.9.1	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁷⁸ GPDT4: O	N/A
GPCF23F	Does the device supporting unidirectional commissioning implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPPCCF11: M GPPCSF10 GPPCSF11: M ⁷⁹ GPDT4: O	N/A
⁹¹ GPCF24A	Does the device support handling of unprotected GPDF with GPD CommandIDs from the range 0xE4 – 0xEF in commissioning mode (forwarding using GP Commissioning Notification, responding with GPDF buffered in <i>gpTxQueue</i>)?	[R4] A.3.9.1	GPPCCF11: M	N/A
⁸⁰ GPCF24B	Does the device support handling of unprotected GPDF with GPD CommandIDs from the manufacturerspecific range 0xB0 – 0xBF in commissioning mode (forwarding using GP Commissioning Notification, responding with GPDF buffered in <i>gpTxQueue</i>)?	[R4] A.3.9.1	GPPCCF11: M	N/A
⁸¹ GPCF24C	Does the device support sending of unprotected GPDF with GPD CommandIDs from the range 0xF7 – 0xFF and <i>Direction</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b1, after receiving it in a GP Response command in commissioning mode?	[R4] A.3.9.1	GPPCCF11: M	N/A
⁹⁴ GPCF24D	Does the device support sending of unprotected GPDF with GPD CommandIDs from the range 0xB0 – 0xBF and <i>Direction</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b1, after receiving it in a GP Response command in commissioning mode?	[R4] A.3.9.1	GPPCCF11: M	N/A

⁷⁴ CCB #2372; Resolution added in 15-02016-007

⁷⁵ CCB #2372; Resolution added in 15-02016-007

⁷⁶ CCB #2372; Resolution added in 15-02016-007

⁷⁷ CCB #2372; Resolution added in 15-02016-007

⁷⁸ CCB #2372; Resolution added in 15-02016-007

⁷⁹ CCB #2372; Resolution added in 15-02016-007 ⁹¹ CCB #2447; resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383

⁸⁰ CCB #2447; resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383

⁸¹ CCB #2447; resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383 ⁹⁴ CCB #2447; resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383

CCB #2372; Resolution added in 15-02016-007

Item number	Item description	Reference	Status	Support
GPCF100	Is writing into Sink Table attribute via generic ZCL command supported during commissioning mode?	[R4] A.3.3.2	GPPCCF12: N/A GPPCSF12: X GPDT4: X	N/A
GPCF101	Is writing into Sink Table attribute via generic ZCL command supported during operational mode?	[R4] A.3.3.2	GPPCCF12: N/A GPPCSF12: X GPDT4: X	N/A
GPCF102	Is writing into Proxy Table attribute via generic ZCL command supported during commissioning mode?	[R4] A.3.4.2	GPPCCF12: X GPPCSF12: N/A GPDT4: X	N/A
GPCF103	Is writing into Proxy Table attribute via generic ZCL command supported during operational mode?	[R4] A.3.4.2	GPPCCF12: X GPPCSF12: N/A GPDT4: X	N/A

11.4 GPS application functionality

11.4.1 GPS device description support

In Table 11, device descriptions for the GPS (GPDT3, i.e. GPDT3t, GPDT3t+, GPDT3c and GPDT3CB) are given.

These PICS items are not applicable to the other GP device types (i.e. GPDT0: X, GPDT1: X, GPDT2: X, GPDT4: X).

Table 11 – GPS device description support

Item number	Item description	Reference	Status	Support
GPS1A	Is the product programmed with support for GP Simple generic 1-state switch functionality?	[R4] A.4.3	GPDT3: O.17 ⁸²	N/A
GPS1B	Is the product programmed with support for GP Simple generic 2-state switch functionality?	[R4] A.4.3	GPDT3: O.17	N/A
GPS2	Is the product programmed with (GP-controllable) server-side On/Off cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS3	Is the product programmed with (GP-controllable) server-side Level Control cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS4	Is the product programmed with (GP-controllable) client-side Binary Input cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS5	Is the product programmed with (GP-controllable) server-side Color control cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS6	Is the product programmed with (GP-controllable) client-side Illuminance Measurement cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS7	Is the product programmed with (GP-controllable) client-side Occupancy Sensing cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS8	Is the product programmed with (GP-controllable) server-side Door Lock cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS9	Is the product programmed with (GP-controllable) client-side Temperature measurement cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS10	Is the product programmed with (GP-controllable) client-side Pressure Measurement cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS11	Is the product programmed with (GP-controllable) client-side Flow Measurement cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS12	Is the product programmed with (GP-controllable) client-side Relative Humidity Measurement cluster?	[R4] A.4.3	GPDT3: O.17	N/A
GPS14A	Is the product programmed with support for GP Advanced generic 1-state switch functionality?	[R4] A.4.3	GPDT3: O.17	N/A
GPS14B	Is the product programmed with support for GP Advanced generic 2-state switch functionality?	[R4] A.4.3	GPDT3: O.17	N/A
GPS15	Is the product programmed with support for other GP functionality?	[R4] A.4.3.1	GPDT3: O.17	N/A
GPS15A	What manufacturer-defined GPD commands does the product support? List ManufacturerID and GPD CommandIDs.	[R4] A.4.3.1 [R10] GPSPIXIT04	GPS15: O.35 ⁸³	N/A
Item number	Item description	Reference	Status	Support

⁸² O.17: Device Under Test SHALL support at least one of those options.

⁸³ O.35: Device Under Test SHALL support at least one of those options.

GPS15B	What additional GP-controllable clusters does the product support? List (public) ZCL ClusterIDs,	[R4] A.4.3.1 [R10] GPSPIXIT05	GPS15: O.35	N/A
GPS15C	What manufacturer-specific GP-controllable clusters does the product support? List ManufacturerID and GPD ClusterIDs.	[R4] A.4.3.1 [R10] GPSPIXIT06	GPS15: O.35	N/A
GPS16	Is the product programmed with support for any standard ZCL cluster using GPD Compact Attribute Reporting functionality? If yes, list all standard ZCL ClusterIDs supported ⁸⁴ via GPD Compact Attribute Reporting functionality:	[R4] A.4.2.3.6 [R10] GPSPIXIT09	GPDT3: O ⁸⁵ GPS6 GPS7 GPS9 GPS12: M GPPCSF21: M	N/A
⁸⁶ GPS16B	Is the product capable of buffering at least the minimum number of 1 GPD Application Description command and forwarding it as GPD Pairing Configuration commands with <i>Action</i> = 0b101 in case of <i>gpsCommunicationMode</i> = pre-commissioned group? What number of GPD Application Description commands can be buffered (<i>MultiSensorCommissioningBufferSize</i>)?	[R4] A.4.2.3.6 [R4] A.3.9.1 [R10] GPSPIXIT10	GPS16 && GPPCSF4 && GPPCSF12: M ⁸⁷ GPPCSF21: M	N/A
GPS17	Is the product programmed with support for GP Generic 8-contact switch functionality?	[R4] A.4.3.1	GPDT3: O.17 ⁸⁸ GPS1A GPS1B: M GPS2: M GPS3: M ⁸⁹ GPS14A GPS14B: M Any of GPDRX10 - GPDRX1f: M ⁹⁰ GPS18: M	N/A
GPS17A	Is the product programmed with support for other GP Generic 8-contact switch functionality indicating <i>Switch type</i> : generic in Commissioning GPDF?	[R4] A.4.2.1.1.10	GPS17: M	N/A
GPS17B	Is the product programmed with support for other GP Generic 8-contact switch functionality indicating <i>Switch type</i> : button in Commissioning GPDF?	[R4] A.4.2.1.1.10	GPS17: M	N/A
GPS17C	Is the product programmed with support for other GP Generic 8-contact switch functionality indicating <i>Switch type</i> : rocker in Commissioning GPDF?	[R4] A.4.2.1.1.10	GPS17: M	N/A
⁹¹ GPS18	Is the product programmed with (GP-controllable) server-side Window Covering cluster?	[R4] A.4.3	GPDT3: O. 17	N/A

11.4.2 GPD command support by GPS

Note: all the commands below are transparent to GPP, thus GPDT2: X. For GPDT0: X.

Table 12 – GPD commands support - reception

Item number	Item description	Reference	Status	Support
GPDRX10	Is reception of GPD Recall Scene 0 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O	N/A
GPDRX11	Is reception of GPD Recall Scene 1 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O	N/A
Item number	Item description	Reference	Status	Support
GPDRX12	Is reception of GPD Recall Scene 2 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O	N/A

⁸⁴ Comment #774 from GP multi-sensor v0.7 letter ballot

⁸⁵ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1014

⁸⁶ GP multi-sensor v0.9 LB comment #973: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=973

⁸⁷ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1014

⁸⁸ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1014

⁸⁹ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1014

⁹⁰ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

⁹¹ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

GPDRX13	Is reception of GPD Recall Scene 3 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O	N/A
GPDRX14	Is reception of GPD Recall Scene 4 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O	N/A
GPDRX15	Is reception of GPD Recall Scene 5 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O	N/A
GPDRX16	Is reception of GPD Recall Scene 6 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O	N/A
GPDRX17	Is reception of GPD Recall Scene 7 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O	N/A
GPDRX18	Is reception of GPD Store Scene 0 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O GPDRX10: O	N/A
GPDRX19	Is reception of GPD Store Scene 1 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O GPDRX11: O	N/A
GPDRX1a	Is reception of GPD Store Scene 2 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O GPDRX12: O	N/A
GPDRX1b	Is reception of GPD Store Scene 3 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O GPDRX13: O	N/A
GPDRX1c	Is reception of GPD Store Scene 4 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O GPDRX14: O	N/A
GPDRX1d	Is reception of GPD Store Scene 5 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O GPDRX15: O	N/A
GPDRX1e	Is reception of GPD Store Scene 6 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O GPDRX16: O	N/A
GPDRX1f	Is reception of GPD Store Scene 7 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT3: O GPDRX17: O	N/A
GPDRX20	Is reception of GPD Off command supported?	[R4] A.4.3 [R4] A.4.1	GPS2: O.20 ⁹²	N/A
GPDRX21	Is reception of GPD On command supported?	[R4] A.4.3 [R4] A.4.1	GPS2 && GPDRX21: M	N/A
GPDRX22	Is reception of GPD Toggle command supported?	[R4] A.4.3 [R4] A.4.1	GPS2: O.20	N/A
GPDRX23	Is reception of GPD Release command supported?	[R4] A.4.3 [R4] A.4.1	GPS2: M	N/A
⁹³ GPDRX30	Is reception of GPD Move up command supported?	[R4] A.4.3 [R4] A.4.2.4	GPS3: O.21 ⁹⁴ ⁹⁵ GPS18: O.21 GPDRX31: M	N/A
⁹⁶ GPDRX31	Is reception of GPD Move Down command supported?	[R4] A.4.3 [R4] A.4.2.4	GPS3: O.21 ⁹⁷ GPS18: O.21GPDRX30: M	N/A
⁹⁸ GPDRX32	Is reception of GPD Step Up command supported?	[R4] A.4.3 [R4] A.4.2.4	GPS3: O.21 ⁹⁹ GPS18: O.21 GPDRX33: M	N/A
¹⁰⁰ GPDRX33	Is reception of GPD Step Down command supported?	[R4] A.4.3 [R4] A.4.2.4	GPS3: O.21 ¹⁰¹ GPS18: O.21 GPDRX32: M	N/A

⁹² O.20: Device Under Test SHALL support exactly one of those options.

⁹³ CCB #2198; Resolution added in 15-02016-003;

⁹⁴ O.21: Device Under Test SHALL support at least one of those options.

⁹⁵ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

⁹⁶ CCB #2198; Resolution added in 15-02016-003;

⁹⁷ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

⁹⁸ CCB #2198; Resolution added in 15-02016-003;

⁹⁹ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

¹⁰⁰ CCB #2198; Resolution added in 15-02016-003;

¹⁰¹ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

Item number	Item description	Reference	Status	Support
¹⁰² GPDRX34	Is reception of GPD Stop command supported?	[R4] A.4.3 [R4] A.4.1	GPS3: O.21 ¹⁰³ GPS18: O.21 (GPDRX30 GPDRX31 GPDRX35 GPDRX36): M	N/A
¹⁰⁴ GPDRX35	Is reception of GPD Move Up (with On/Off) command supported?	[R4] A.4.3 [R4] A.4.2.4	GPS3: O.21 ¹⁰⁵ GPS18: O.21 GPDRX36: M	N/A
¹⁰⁶ GPDRX36	Is reception of GPD Move Down (with On/Off) command supported?	[R4] A.4.3 [R4] A.4.2.4	GPS3: O.21 ¹⁰⁷ GPS18: O.21 GPDRX35: M	N/A
¹⁰⁸ GPDRX37	Is reception of GPD Step Up (with On/Off) command supported?	[R4] A.4.3 [R4] A.4.2.4	GPS3: O.21 ¹⁰⁹ GPS18: O.21 GPDRX38: M	N/A
¹¹⁰ GPDRX38	Is reception of GPD Step Down (with On/Off) command supported?	[R4] A.4.3 [R4] A.4.2.4	GPS3: O.21 ¹¹¹ GPS18: O.21 GPDRX37: M	N/A
GPDRX40	Is reception of GPD Move Hue ¹²⁵ Stop command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22126 ¹¹² (GPDRX41 GPDRX42): M	N/A
¹¹³ GPDRX41	Is reception of GPD Move Hue Up command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22 GPDRX42: M	N/A
¹¹⁴ GPDRX42	Is reception of GPD Move Hue Down command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22 GPDRX41: M	N/A
¹¹⁵ GPDRX43	Is reception of GPD Step Hue Up command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22 GPDRX44: M	N/A
¹¹⁶ GPDRX44	Is reception of GPD Step Hue Down command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22 GPDRX43: M	N/A
¹¹⁷ GPDRX45	Is reception of GPD Move Saturation ¹¹⁸ Stop command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22 (GPDRX46 GPDRX47): M	N/A
¹¹⁹ GPDRX46	Is reception of GPD Move Saturation Up command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22 GPDRX47: M	N/A
¹²⁰ GPDRX47	Is reception of GPD Move Saturation Down command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22 GPDRX46: M	N/A

¹⁰² CCB #2198; Resolution added in 15-02016-003;

¹⁰³ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

¹⁰⁴ CCB #2198; Resolution added in 15-02016-003;

¹⁰⁵ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

¹⁰⁶ CCB #2198; Resolution added in 15-02016-003;

¹⁰⁷ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

¹⁰⁸ CCB #2198; Resolution added in 15-02016-003;

¹⁰⁹ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

¹¹⁰ CCB #2198; Resolution added in 15-02016-003;

¹¹¹ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013 ¹²⁵

https://workspace.zigbee.org/kws/groups/PRO_GP/comments?clear=1&workgroup_id=46, added in 15-02016-r004 ¹²⁶ O.22: Device Under Test SHALL support at least one of those options.

¹¹² CCB #2198; Resolution added in 15-02016-003;

¹¹³ CCB #2198; Resolution added in 15-02016-003;

¹¹⁴ CCB #2198; Resolution added in 15-02016-003;

¹¹⁵ CCB #2198; Resolution added in 15-02016-003;

¹¹⁶ CCB #2198; Resolution added in 15-02016-003;

¹¹⁷ CCB #2198; Resolution added in 15-02016-003;

¹¹⁸ https://workspace.zigbee.org/kws/groups/PRO_GP/comments?clear=1&workgroup_id=46, added in 15-02016-r004

¹¹⁹ CCB #2198; Resolution added in 15-02016-003;

¹²⁰ CCB #2198; Resolution added in 15-02016-003;

Item number	Item description	Reference	Status	Support
¹²¹ GPDRX48	Is reception of GPD Step Saturation Up command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22 GPDRX49: M	N/A
¹²² GPDRX49	Is reception of GPD Step Saturation Down command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22 GPDRX48: M	N/A
GPDRX4a	Is reception of GPD Move Color command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22	N/A
GPDRX4b	Is reception of GPD Step Color command supported?	[R4] A.4.3 [R4] A.4.2.5	GPS5: O.22	N/A
GPDRX50	Is reception of GPD Lock Door command supported?	[R4] A.4.3 [R4] A.4.1	GPS8: M	N/A
GPDRX51	Is reception of GPD Unlock Door command supported?	[R4] A.4.3 [R4] A.4.1	GPS8: M	N/A
GPDRX60	Is reception of GPD Press 1 of 1 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS1A: M GPS14A: M	N/A
GPDRX61	Is reception of GPD Release 1 of 1 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS1A: M GPS14A: M	N/A
GPDRX62	Is reception of GPD Press 1 of 2 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS1B: M GPS14B: M ¹²³ GPS18: M	N/A
GPDRX63	Is reception of GPD Release 1 of 2 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS1B: M GPS14B: M ¹²⁴ GPS18: M	N/A
GPDRX64	Is reception of GPD Press 2 of 2 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS1B: M GPS14B: M ¹²⁵ GPS18: M	N/A
GPDRX65	Is reception of GPD Release 2 of 2 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS1B: M GPS14B: M ¹²⁶ GPS18: M	N/A
GPDRX66	Is reception of GPD Short Press 1 of 1 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS14A: M	N/A
GPDRX67	Is reception of GPD Short Press 1 of 2 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS14B: M ¹²⁷ GPS18: M	N/A
GPDRX68	Is reception of GPD Short Press 2 of 2 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS14B: M ¹²⁸ GPS18: M	N/A
GPDRX69	Is reception of GPD 8-bit vector: press command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS17: M ¹²⁹ GPS18: M	N/A
GPDRX6A	Is reception of GPD 8-bit vector: release command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPS17: O ¹³⁰ GPS18: M	N/A

¹²¹ CCB #2198; Resolution added in 15-02016-003;¹²² CCB #2198; Resolution added in 15-02016-003;¹²³ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013¹²⁴ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013¹²⁵ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013¹²⁶ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013¹²⁷ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013¹²⁸ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013¹²⁹ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013¹³⁰ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013

Item number	Item description	Reference	Status	Support
GPDRXA0	Is reception of GPD Attribute Reporting command supported?	[R4] A.4.3 [R4] A.4.2.3	GPS4 GPS6 GPS7 GPS9 GPS10 GPS11 GPS12: M	N/A
GPDRXA1	Is reception of GPD Manufacturer-Specific Attribute Reporting command supported?	[R4] A.4.3 [R4] A.4.2.3	GPS4 GPS6 GPS7 GPS9 GPS10 GPS11 GPS12: M	N/A
GPDRXA2	Is reception of GPD Multi-Cluster Reporting command supported?	[R4] A.4.3 [R4] A.4.2.3	GPS4 GPS6 GPS7 GPS9 GPS10 GPS11 GPS12: M	N/A
GPDRXA3	Is reception of GPD Manufacturer-Specific Multi-Cluster Reporting command supported?	[R4] A.4.3 [R4] A.4.2.3	GPS4 GPS6 GPS7 GPS9 GPS10 GPS11 GPS12: M	N/A
GPDRXA6	Is reception of GPD ZCL Tunneling command supported?	[R4] A.4.3	GPS4 GPS6 GPS7 GPS9 GPS10 GPS11 GPS12: M GPS15C GPS15B: M	N/A
¹³¹ GPDRXA8	Is reception of GPD Compact Attribute Reporting command supported?	[R4] A.4.2.3.6	GPS6 GPS7 GPS9 GPS12 ¹³² GPS16: M ¹³³ GPPCSF21: M	N/A

¹³¹ Comment #784, #785, #783 from GP multi-sensor v0.7 letter ballot¹³² Comment #785 from GP multi-sensor v0.7 letter ballot¹³³ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1014

12 Green Power Device functionality

The PICS items in section 12 are only applicable to the GPD (GPDT0). They are not applicable to the other GP device types (i.e. GPDT1: X, GPDT2: X, GPDT3: X, GPDT4: X). If the GPD supports multiple SrcID (in case of *ApplicationID* = 0b000) or multiple Endpoints (in case of *ApplicationID* = 0b010), the SrcID/Endpoint supporting a given PICS item shall be indicated in the corresponding Support column.

12.1 GPD device description support

In Table 13, device descriptions for the GPD (GPDT0) are given.

Table 13 – GPD device description support

Item number	Item description	Reference	Status	Support
GPDT0	Is the product programmed as a GP Simple Generic 1-state Switch?	[R4] A.4.3	GPDT0: O.23 ¹³⁴	NO
GPDT1	Is the product programmed as a GP Simple Generic 2-state Switch?	[R4] A.4.3	GPDT0: O.23	NO
GPDT2	Is the product programmed as a GP On/Off Switch?	[R4] A.4.3	GPDT0: O.23	NO
GPDT3	Is the product programmed as a GP Level Control Switch?	[R4] A.4.3	GPDT0: O.23	NO
GPDT4	Is the product programmed as a GP Simple Sensor?	[R4] A.4.3	GPDT0: O.23	NO
GPDT5	Is the product programmed as a GP Advanced Generic 1-state Switch?	[R4] A.4.3	GPDT0: O.23	NO
GPDT5B	What is the value of the short press time threshold?	[R4] A.4.2.2	Implementation-specific	NO
GPDT6	Is the product programmed as a GP Advanced Generic 2-state Switch?	[R4] A.4.3	GPDT0: O.23	NO
GPDT6B	What is the value of the short press time threshold?	[R4] A.4.2.2	Implementation-specific	NO
GPDT7	Is the product programmed as a GP Generic 8-contact Switch?	[R4] A.4.3	GPDT0: O.23	NO
GPDT7B	What is the number of supported contacts?	[R4] A.4.2.1.1.10, A.4.2.2.1	GPDT7: Implementation-specific (0-8)	NO
GPDT7C	Does the GP Generic 8-contact Switch indicate <i>Switch type: generic</i> in Commissioning GPDPF?	[R4] A.4.2.1.1.10	GPDT7: O.40 ¹⁵⁰	NO
GPDT7D	Does the GP Generic 8-contact Switch indicate <i>Switch type: button</i> in Commissioning GPDPF?	[R4] A.4.2.1.1.10	GPDT7: O.40	NO
GPDT7E	Does the GP Generic 8-contact Switch indicate <i>Switch type: rocker</i> in Commissioning GPDPF?	[R4] A.4.2.1.1.10	GPDT7: O.40	NO
xGPDT10	Is the product programmed as a GP Color Dimmer Switch?	[R4] A.4.3	GPDT0: O.23	NO
GPDT11	Is the product programmed as a GP Light Sensor?	[R4] A.4.3	GPDT0: O.23	NO
GPDT12	Is the product programmed as a GP Occupancy Sensor?	[R4] A.4.3	GPDT0: O.23	NO
GPDT20	Is the product programmed as a GP Door Lock Controller?	[R4] A.4.3	GPDT0: O.23	NO
GPDT30	Is the product programmed as a GP Temperature Sensor?	[R4] A.4.3	GPDT0: O.23	NO
GPDT31	Is the product programmed as a GP Pressure Sensor?	[R4] A.4.3	GPDT0: O.23	NO
GPDT32	Is the product programmed as a GP Flow Sensor?	[R4] A.4.3	GPDT0: O.23	NO
GPDT33	Is the product programmed as a GP Indoor Environment Sensor?	[R4] A.4.3	GPDT0: O.23	NO
GPDT100	Does the product deviate from the standard GPD functionality mandatory for the product's DeviceID?	[R4] A.4.3.1	GPDT0: O	N/A

¹³⁴ O.23: Device Under Test SHALL support exactly one of those options.

¹⁵⁰ O.40: DUT shall implement exactly one of those options.

Item number	Item description	Reference	Status	Support
GPD100A	Does the standard GPD Data command set supported by the product deviate from the standard GPD Data command set mandatory for the product's DeviceID? If yes, list all standard GPD CommandIDs supported.	[R4] A.4.3.1 [R10] GPDPIXIT14	GPDT0: O.35 ¹³⁵	NO
GPD100B	Does the standard ZCL cluster set supported by the product deviate from the standard ZCL cluster set mandatory for the product's DeviceID? If yes, list all standard ZCL ClusterIDs supported,	[R4] A.4.3.1 [R10] GPDPIXIT15, [R10] GPDPIXIT16	GPDT0: O.35	NO
GPDFE	Is the product programmed as an undefined GP device (DeviceID = 0xFE)?	[R4] A.4.3	GPDT0: O.23	YES
GPD101	Is the product with DeviceID = 0xFE programmed with support for any standard functionality? Note: a GPD not supporting any standard functionality cannot be certified.	[R4] A.4.3.1	GPDFE: M	YES
GPD101A	Is the product programmed with support for any standard GPD Data command? If yes, list all standard GPD CommandIDs supported.	[R4] A.4.3.1 [R10] GPDPIXIT09	GPDT0: O.36 ¹³⁶	YES 0xA1, 0xA3, 0xA5, 0xF1, 0xF2, 0xF6
GPD101B	Is the product programmed with support for any standard ZCL cluster in a server role? If yes, list all standard ZCL ClusterIDs supported in a server role:	[R4] A.4.3.1 [R10] GPDPIXIT10	GPDT0: O.36	YES 0x0000, 0x0002, 0x0003, 0x0B04, 0x0B05, 0x0702
GPD101C	Is the product programmed with support for any standard ZCL cluster in a client role? If yes, list all standard ZCL ClusterIDs supported in a client role:	[R4] A.4.3.1 [R10] GPDPIXIT11	GPDT0: O.36	NO
GPD102	Is the product programmed with support for any standard ZCL cluster using GPD Compact Attribute Reporting functionality? If yes, list all standard ZCL ClusterIDs supported ¹³⁷ via GPD Compact Attribute Reporting functionality:	[R4] A.4.2.3.6 [R9] [R10] GPDPIXIT12	GPDT0: O.36	NO
GPD103	Is the product supporting GPD Compact Attribute Reporting ¹³⁸ functionality programmed with capability to send reports () with more than one report identifier? If yes, indicate the number of different reports:	[R4] A.4.2.3.6 [R10] GPDPIXIT13	GPDT0: O	NO

12.2 GPD functionality

Table 14 – GPD functionality

Item number	Item description	Reference	Status	Support
¹³⁵ GPF1	Does the device implement cGP stub?	[R4] A.1	GPDT0: X	NO
¹³⁹ GPF2	Does the device implement dGP stub?	[R4] A.1	GPDT0: X	NO
GPPC1	Does the device support Green Power End Point (GPEP)?	[R4] A.3.1	GPDT0: X	NO
GPF4A	Does the device support transmitting GPDF frame format with <i>ApplicationID</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b000?	[R4] A.1.4.1.3 [R10] GPDPIXIT18	GPDT0: O.22 ¹⁴⁰	YES

¹³⁵ O.35: Device Under Test MAY support at least one of those options.

¹³⁶ O.36: Device Under Test SHALL support at least one of those options.

¹³⁷ Comment #775 from GP multi-sensor v0.7 letter ballot

¹³⁸ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1013 ¹⁵⁵ CCB #2524; resolution added in 15-02016-009;

¹³⁹ CCB #2524; resolution added in 15-02016-009;

¹⁴⁰ O.22: Device Under Test SHALL support only one of those options.

Item number	Item description	Reference	Status	Support
GPF4B	Does the device support transmitting GPDF frame format with <i>ApplicationID</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b010?	[R4] A.1.4.1.3 [R10] GPDPIXIT19	GPDT0: O.22	NO
GPF4A1	Does the device support multiple SrcIDs? If yes, list the SrcIDs.	[R4] A.1.6.2.1 [R10] GPDPIXIT18	GPF4A: O GPF4B: X	NO
GPF4A2	Apart from Endpoint 0x00 and 0xFF, does the device support multiple Endpoints from the range 0x01 – 0xF0? If yes, list the Endpoints.	[R4] A.1.6.2.2 [R10] GPDPIXIT20	GPF4A: X GPF4B: O	NO
GPF5	Does the device support SecurityLevel=0b11?	[R4] A.1.5.4 [R4] A.3.7.2.1	GPDT0: O.24 ¹⁴¹	YES
GPF6	Does the device support SecurityLevel=0b10?	[R4] A.1.5.4 [R4] A.3.7.2.1	GPDT0: O.24	YES
GPF7	Does the device support SecurityLevel=0b01? (deprecated)	[R4] A.1.5.4 [R4] A.3.7.2.1	GPDT0: X (deprecated)	Deprecated
GPF8A	Does the device support SecurityLevel=0b00 in commissioning?	[R4] A.1.5.4 [R4] A.3.9.1	GPDT0: O GPDT0: && GPCF4: M	YES
GPF8B	Does the device support SecurityLevel=0b00 in operation? <i>According to the current version of the specification, only GPD that support <i>gpdSecurityLevel</i> = 0b10 or higher AND support TC-LK protection of the GPD key, if exchanged over the air, can be certified.</i>	[R4] A.1.5.4 [R4] A.3.7.2.1	GPDT0: O	YES
GPF10A	Does the device support receiving GPDF frame format with <i>ApplicationID</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b000 and <i>Frame type</i> sub-field of the <i>NWK Frame Control</i> field set to 0b00 (Data frame) in operation, with security?	[R4] A.1.4.1.3	GPDT0&&GPF4A: O (GPF4B: X)	YES
GPF10B	Does the device support receiving GPDF frame format with <i>ApplicationID</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b010 in operation, with security?	[R4] A.1.4.1.3	GPDT0&&GPF4B: O (GPF4A: X)	NO
GPF10C	Does the device support receiving in commissioning mode a GPDF frame format with <i>Frame type</i> sub-field of the <i>NWK Frame Control</i> field set to 0b01 (Maintenance frame)?	[R4] A.1, A.3.9	GPDT0 && GPCF4: M	YES
GPF10D	Does the device support receiving GPDF frame format with <i>ApplicationID</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b000 and <i>Frame type</i> sub-field of the <i>NWK Frame Control</i> field set to 0b00 (Data frame) in commissioning, without security?	[R4] A.1, A.3.9	GPDT0 && GPF4A && GPCF4: M (GPF4B: X)	YES
GPF10E	Does the device support receiving GPDF frame format with <i>ApplicationID</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b010 in commissioning, without security?	[R4] A.1, A.3.9	GPDT0 && GPF4B && GPCF4: M (GPF4A: X)	NO
GPDF2	Does the device support incremental MAC sequence number for GPD commands?	[R4] A.1.6, A.1.7	GPDT0 && (GPF4 GPF8B): O	YES
GPDF3	Is the FixedLocation flag in the Commissioning GPD command set?	[R4] A.1.6, A.1.7	GPDT0: O	YES

¹⁴¹ O.24: Device Under Test SHALL support at least one of those options.

12.2.1 GPD Bidirectional operation

Table 15 – Support for Green Power functionality

Item number	Item description	Reference	Status	Support
GPF100	Does the device support bidirectional communication in operational mode?	[R4] A.1.6.3 [R4] A.3.6.1.5	GPDT0: O	YES
GPF101	Is transmission of GPD Read Attributes command supported?	[R4] A.4.2.5	GPDT0: X	NO
GPF102	Is reception of GPD Read Attributes command supported?	[R4] A.4.2.5	GPDT0&&GPF100: M	YES
GPF103	Is transmission of GPD Read Attributes Response supported?	[R4] A.4.2.5	GPDT0&&GPF100: M	YES
GPF104	Is reception of GPD Read Attributes Response command supported?	[R4] A.4.2.5	GPDT0: X	NO
GPF105	Is transmission of GPD Request Attributes command supported?	[R4] A.4.2.5	GPDT0&&GPF100: O	NO
GPF106	Is reception of GPD Request Attributes command supported?	[R4] A.4.2.5	GPDT0: X	NO
GPF107	Is transmission of GPD Write Attributes command supported?	[R4] A.4.2.5	GPDT0: X	NO
GPF108	Is reception of GPD Write Attributes command supported?	[R4] A.4.2.5	GPDT0&&GPF100: O	YES
GPF109	Is transmission of GPD ZCL Tunneling command (0xF6) supported?	[R4] A.4.2.3.5	GPDT0: X	NO
GPF110	Is reception of GPD ZCL Tunneling command (0xF6) supported?	[R4] A.4.2.3.5	GPDT0&& GPDTXA6: M	YES
GPF111	List the functionality accessible (receivable) via GPD ZCL Tunneling command. List the ZCL generic command, with the corresponding ClusterID(s) and AttributeID(s), if any. List the cluster-specific CommandIDs per ZCL-defined Cluster, if any. Manufacturer-specific functionality doesn't have to be listed.	[R4] A.4.2.3.5 [R10] GPDPIXIT07 , GPDPIXIT08	GPDT0: X	N/A

12.2.2 GPD commissioning support

Table 16 – GP Commissioning Feature Support

Item number	Item description	Reference	Status	Support
GPCF0	Does the device support re-commissioning (to another network/channel), after it was already commissioned? <i>Note: for GPDs supporting decommissioning/reset (GPCF10A/B), it is permissible to re-commission only after reset.</i>	[R4] A.1.7.3.2	GPDT0: M	YES
GPCF1	Does the device support pairing with Data GPDF with AutoCommissioning bit set to 0b1? <i>Note: According to the current version of the specification, only GPD that support gpdSecurityLevel = 0b10 or higher AND support TC-LK protection of the GPD key, if exchanged over the air, can be certified.</i>	[R4] A.3.9 [R4] A.1.4, A.1.6	GPDT0: O.26	NO
GPCF2	Does the device support pairing with Commissioning GPDF?	[R4] A.3.9 [R4] A.4.2.1.1	GPDT0: O.26 ¹⁴² GPDT0 && (GPD4 GPD11 GPD12 GPD30 GPD31 GPD32 GPD33): M	YES
GPCF3A	Does the device support transmission of GPD Commissioning command?	[R4] A.4.2.1.1	GPDT0&&GPCF2: M	YES
GPCF3B	Does the device support reception of GPD Commissioning command?	[R4] A.4.2.1.1	GPDT0: X	NO
GPCF4	Does the device support bidirectional communication in commissioning mode?	[R4] A.3.9	GPDT0: O	YES
GPDF10	Does the device support configuration of operational channel when in commissioning mode?	[R4] A.3.9	GPDT0: O	YES
GPDF10A	Does the device support out-of-band configuration of operational channel?	[R4] A.3.9	GPDT0: O.27 ¹⁶⁰ (GPDT0 && GPCF4): X	NO
GPDF10B	Does the device support configuration of operational channel via channel toggling (GPD Commissioning command with RxAfterTx = 0b0)?	[R4] A.3.9	GPDT0: O.27 (GPDT0 && GPCF4): X	NO
GPDF10C	Does the device support in-band configuration of operational channel (via GPD Channel Request/Channel Configuration command)?	[R4] A.3.9	GPDT0: O.27 (GPDT0 && GPCF4): M	YES
GPDF10D	Does the device support the recommended channel set (11, 15, 20, 25)?	[R4] A.1.6, A.1.7	GPDT0&&GPCF16: M	YES
GPDF10E	Does the device support the full channel set (11- 25 (26))? If the device does not support a full channel set, indicate which channels are supported?	[R4] A.1.6, A.1.7 [R10] GPDPIXIT17	GPDT0: O	YES
GPCF5A	Does the device support transmission of the GPD Channel Request command in commissioning mode?	[R4] A.3.9 [R4] A.4.2.1.4 [R4] A.1.4	GPDT0: O GPDT0 &&(GPCF4 GPDF10C): M	YES
GPCF5B	Does the device support reception of the GPD Channel Request command in commissioning mode?	[R4] A.3.9 [R4] A.4.2.1.4 [R4] A.1.4	GPDT0: X	NO
GPCF6	Does the device support transmission of the GPD Channel Configuration command?	[R4] A.3.9 [R4] A.4.2.1.5 [R4] A.1.4	GPDT0: X	NO
GPCF7	Does the device support reception of the GPD Channel Configuration command?	[R4] A.3.9 [R4] A.4.2.1.5 [R4] A.1.4	GPDT0: O	YES
GPCF7A	Does the device support reception of the GPD Channel Configuration command in commissioning mode?	[R4] A.3.9 [R4] A.4.2.1.5 [R4] A.1.4	GPDT0: O GPDT0 &&(GPCF4 GPDF10C): M	YES
GPCF7B	Does the device support reception of the GPD Channel Configuration command in operational mode?	[R4] A.6 [R4] A.4.2.1.5	GPDT0: O GPDT0 && (GPF10A	YES

¹⁴² O.26: Device Under Test SHOULD support exactly one of those methods. ¹⁶⁰ O.27: Device Under Test SHALL support at least one of the methods.

Item number	Item description	Reference	Status	Support
		[R4] A.1.4	GPF10B): O	
GPCF8	Does the device support transmission of the GPD Commissioning Reply command?	[R4] A.4.2.1.2	GPDT0: X	NO
GPCF9	Does the device support reception of the GPD Commissioning Reply command?	[R4] A.4.2.1.2	GPDT0 && GPCF2: O	YES
GPCF9A	Does the device support reception of the GPD Commissioning Reply command in commissioning mode?	[R4] A.4.2.1.2	GPDT0 && GPCF4: M	YES
GPCF9B	Does the device support reception of the GPD Commissioning Reply command in operational mode?	[R4] A.6	GPDT0 && (GPF10A GPF10B): O	YES
GPCF10A	Is GPD reset/decommissioning via an explicit user action supported?	[R4] A.1.7.3.2	GPDT0: O ¹⁴³ GPCF23B GPCF23D GPCF23F: M	YES
GPCF10B	Is GPD removal via GPD Decommissioning command supported?	[R4] A.4.2.1.3	GPDT0: O GPCF10A: O	YES
GPCF11	Does the device come with pre-configured GPD key?	[R4] A.3.9	GPDT0 && (GPF5 GPF6): O.28 ¹⁶²	YES
GPCF12A	Does the device support GPD key exchange in GPD Commissioning command?	[R4] A.3.9	GPDT0 && GPCF2: O GPDT0 && GPCF11: M	YES
GPCF12B	Does the device support exchange of encrypted GPD key in GPD Commissioning command? <i>Note: According to the current version of the specification, only GPD that support gpdSecurityLevel = 0b10 or higher AND support TC-LK protection of the GPD key, if exchanged over the air, can be certified.</i>	[R4] A.3.9 [R4] A.1.5	GPDT0 && GPCF11: M	YES
GPCF13A	Does the device support GPD key exchange in GPD Commissioning Reply command?	[R4] A.3.9	GPDT0 && (GPF5 GPF6): O.28 GPDT0 && GPCF9: O	YES
GPCF13B	Does the device support exchange of encrypted GPD key in GPD Commissioning Reply command? <i>Note: According to the current version of the specification, only GPD that support gpdSecurityLevel = 0b10 or higher AND support TC-LK protection of the GPD key, if exchanged over the air, can be certified.</i>	[R4] A.3.9 [R4] A.1.5	GPDT0 && GPCF13A: M	YES
GPCF14	Does the device support out-of-band GPD key configuration?	[R4] A.3.9	GPDT0 && (GPF5 GPF6): O.28	NO
GPCF15A	Does the device support transmission of GPD Success command in commissioning mode?	[R4] A.3.9 [R4] A.4.1	GPDT0: O GPDT0 && GPCF4: M	YES
GPCF15B	Does the device support reception of GPD Success command when in commissioning mode?	[R4] A.3.9 [R4] A.4.1	GPDT0: X	NO
GPCF16	Does the device support in-band configuration of PANId (via GPD Commissioning Reply command)?	[R4] A.3.9 [R4] A.4.2.1.2	GPDT0 && GPCF4: O	NO
GPCF17	Does the device support transmission of GPD Commissioning command with Application information?	[R4] A.4.2.1.1	GPCF3A: O ¹⁴⁴ GPD7: M GPD100: M GPD102: M GPDFE: M GPCF17A GPCF17B GPCF17C GPCF17E: M	YES
GPCF17A	Does the device support transmission of the GPD Commissioning command with the ModelID? If YES, indicate the ModelID.	[R4] A.4.2.1.1 [R10] GPDPIXIT01	GPCF3A: O GPCF17: O.33 ¹⁶⁴	YES 0x433A
GPCF17B	Does the device support transmission of the GPD Commissioning command with the ManufacturerID? If YES, specify the ManufacturerID.	[R4] A.4.2.1.1 [R10] GPDPIXIT02	GPCF3A: O GPCF17: O.33 GPCF17A GPCF17D GPCF17F: M	YES 0x105E
GPCF17C	Does the device support transmission of the GPD Commissioning command with the GPD command list containing any standard GPD Data commands (0x00 –	[R4] A.4.2.1.1 [R10]	GPCF3A: O GPCF17: O.33 GPD100 GPDFE: O.34 ¹⁴⁵	YES

¹⁴³ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1025 ¹⁶² O.28: Device Under Test SHALL support at least one of those options.

¹⁴⁴ GP multi-sensor v0.9 LB comment #976: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=976 ¹⁶⁴ O.33: Device Under Test SHOULD support at least one of these options

¹⁴⁵ O.34: Device Under Test SHALL support at least one of these options

Item number	Item description	Reference	Status	Support
	0x9F, 0xF1, 0xF2, 0xF6)? If yes AND if deviating from the GPD command list mandatory for the supported DeviceID, list all the standard GPD Data commands,	GPDPXIT03	GPD100A: M GPD101A: M	--
GPCF17D	Does the device support transmission of the GPD Commissioning command with the GPD command list containing manufacturer-defined commands?	[R4] A.4.2.1.1	GPCF3A: O GPCF17: O.33	NO
GPCF17E	Does the device support transmission of the GPD Commissioning command with the Cluster list containing ZCL-defined clusters? If yes AND if deviating from the ZCL clusters mandatory for the supported DeviceID, list all the standard ZCL clusters.	[R4] A.4.2.1.1 [R10] GPDPXIT04	GPCF3A: O GPCF17: O.33 GPD100 GPDFE: O.34	YES 0x0000, 0x0002, 0x0003, 0x0B04, 0x0B05, 0x0702
GPCF17F	Does the device support transmission of the GPD Commissioning command with the Cluster list containing manufacturer-specific clusters?	[R4] A.4.2.1.1	GPCF3A: O GPCF17: O.33 GPD100B: M GPD101B: M	NO
¹⁴⁶ GPCF17G	Does the device support transmission of the GPD Commissioning command with the Switch Information?	[R4] A.4.2.1.1	GPCF3A: O GPD7: M GPDTX69: M GPDXX6A: M	NO
GPCF18	Does the device support reception of GPD Commissioning command with Application information?	[R4] A.4.2.1.1	GPDT0: X	NO
GPCF18A	Does the device support reception of the GPD Commissioning command with the ModelID?	[R4] A.4.2.1.1	GPDT0: X	NO
GPCF18B	Does the device support reception of the GPD Commissioning command with the ManufacturerID?	[R4] A.4.2.1.1	GPDT0: X	NO
GPCF18C	Does the device support reception of the GPD Commissioning command with the GPD command list containing GPD-defined commands?	[R4] A.4.2.1.1	GPDT0: X	NO
GPCF18D	Does the device support reception of the GPD Commissioning command with the GPD command list containing manufacturer-defined GPD commands?	[R4] A.4.2.1.1	GPDT0: X	NO
GPCF18E	Does the device support reception of the GPD Commissioning command with the Cluster list containing ZCL-defined clusters?	[R4] A.4.2.1.1	GPDT0: X	NO
GPCF18F	Does the device support reception of the GPD Commissioning command with the Cluster list containing manufacturer-specific clusters?	[R4] A.4.2.1.1	GPDT0: X	NO
¹⁴⁷ GPCF18G	Does the device support reception of the GPD Commissioning command with the Switch Information?	[R4] A.4.2.1.1	GPDT0: X	NO
GPCF19	Does the device support automatic progressing between the commissioning steps?	[R4] A.3.9.1	GPDT0: O GPCF4: O	YES
GPCF20	Does the device support transmission of the GPD Application Description command?	[R4] A.3.9.1, A.4.2.1.6	GPD102: M	NO
GPCF21	Does the device support reception of the GPD Application Description command?	[R4] A.3.9.1, [R4] A.4.2.1.6	GPDT0: O	NO
¹⁶⁸ GPCF22	Does the GPD support subsequent commissioning?	[R4] A.3.9.1	GPDT0: O GPD7 GPDTX69 GPDTX6A: M	N/A
GPCF22A	Does the GPD supporting bidirectional commissioning with OOB key implement the subsequent commissioning as full bidirectional procedure?	[R4] A.3.9.1	¹⁶⁹ GPCF22: O.50	NO

¹⁴⁶ GP multi-sensor v0.9 LB comment #976: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=976

¹⁴⁷ GP multi-sensor v0.9 LB comment #976: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=976 ¹⁶⁸ Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1025 ¹⁶⁹ O.50: Device Under Test SHALL support exactly one of those options.

Item number	Item description	Reference	Status	Support
GPCF22B	Does the GPD supporting bidirectional commissioning with OOB key implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPCF22: O.50	NO
GPCF22C	Does the GPD supporting bidirectional commissioning with shared key implement the subsequent commissioning as full bidirectional procedure?	[R4] A.3.9.1	¹⁷⁰ GPCF22: O.51	NO
GPCF22D	Does the GPD supporting bidirectional commissioning with shared key implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPCF22: O.51	NO
GPCF22E	Does the GPD supporting unidirectional commissioning implement the subsequent commissioning as full unidirectional procedure?	[R4] A.3.9.1	¹⁷¹ GPCF22: O.52	NO
GPCF22F	Does the GPD supporting unidirectional commissioning implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPCF22: O.52	NO
¹⁷² GPCF23	Does the device support subsequent commissioning?	[R4] A.3.9.1	GPDT0: X	NO
GPCF23A	Does the device supporting bidirectional commissioning with OOB key implement the subsequent commissioning as full bidirectional procedure?	[R4] A.3.9.1	GPDT0: X	NO
GPCF23B	Does the device supporting bidirectional commissioning with OOB key implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPDT0: X	NO
GPCF23C	Does the device supporting bidirectional commissioning with shared key implement the subsequent commissioning as full bidirectional procedure?	[R4] A.3.9.1	GPDT0: X	NO
GPCF23D	Does the device supporting bidirectional commissioning with shared key implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPDT0: X	NO
GPCF23E	Does the device supporting unidirectional commissioning implement the subsequent commissioning as full unidirectional procedure?	[R4] A.3.9.1	GPDT0: X	NO
GPCF23F	Does the device supporting unidirectional commissioning implement the subsequent commissioning as simplified unidirectional procedure?	[R4] A.3.9.1	GPDT0: X	NO
¹⁷³ GPCF24A	Does the device support handling of unprotected GPDP with GPD CommandIDs from the range 0xE4 – 0xEF in commissioning mode (forwarding using GP Commissioning Notification, responding with GPDP buffered in <i>gpTxQueue</i>)?	[R4] A.3.9.1	GPDT0: X	NO
¹⁷⁴ GPCF24B	Does the device support handling of unprotected GPDP with GPD CommandIDs from the manufacturer-specific range 0xB0 – 0xBF in commissioning mode (forwarding using GP Commissioning Notification, responding with GPDP buffered in <i>gpTxQueue</i>)?	[R4] A.3.9.1	GPDT0: X	NO
¹⁷⁵ GPCF24C	Does the device support sending of unprotected GPDP with GPD CommandIDs from the range 0xF7 – 0xFF and <i>Direction</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b1, after receiving it in a GP Response command in commissioning mode?	[R4] A.3.9.1	GPDT0: X	NO
¹⁷⁶ GPCF24D	Does the device support sending of unprotected GPDP with GPD CommandIDs from the range 0xB0 – 0xBF and <i>Direction</i> sub-field of the <i>Extended NWK Frame Control</i> field set to 0b1, after receiving it in a GP Response command in commissioning mode?	[R4] A.3.9.1	GPDT0: X	NO

¹⁷⁰ O.51: Device Under Test SHALL support exactly one of those options.

¹⁷¹ O.52: Device Under Test SHALL support exactly one of those options.

¹⁷² Dec 2016 SVE comment: https://workspace.zigbee.org/kws/groups/PRO_GP/comments/view_comment?comment_id=1025 ¹⁷³

CCB #2447; resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383 ¹⁷⁴ CCB #2447;

resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383 ¹⁷⁵ CCB #2447;

resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383 ¹⁷⁶ CCB #2447;

resolution modified in 15-02016-008 as a result of Kavi comment #1383 from letter ballot for GP Basic errata set:

https://workspace.zigbee.org/higherlogic/ws/groups/PRO_GP/comments/view_comment?comment_id=1383

Item number	Item description	Reference	Status	Support
GPCF100	Is writing into Sink Table attribute via generic ZCL command supported during commissioning mode?	[R4] A.3.3.2.2	GPDT0: X	NO
GPCF101	Is writing into Sink Table attribute via generic ZCL command supported during operational mode?	[R4] A.3.3.2.2	GPDT0: X	NO
GPCF102	Is writing into Proxy Table attribute via generic ZCL command supported during commissioning mode?	[R4] A.3.3.2.2	GPDT0: X	NO
GPCF103	Is writing into Proxy Table attribute via generic ZCL command supported during operational mode?	[R4] A.3.3.2.2	GPDT0: X	NO

12.3 GPD application functionality

12.3.1 GPD command support by GPD

Table 17 – GPD commands support - transmission

Item number	Item description	Reference	Status	Support
GPDTX10	Is transmission of GPD Recall Scene 0 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O	NO
GPDTX11	Is transmission of GPD Recall Scene 1 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O	NO
GPDTX12	Is transmission of GPD Recall Scene 2 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O	NO
GPDTX13	Is transmission of GPD Recall Scene 3 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O	NO
GPDTX14	Is transmission of GPD Recall Scene 4 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O	NO
GPDTX15	Is transmission of GPD Recall Scene 5 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O	NO
GPDTX16	Is transmission of GPD Recall Scene 6 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O	NO
GPDTX17	Is transmission of GPD Recall Scene 7 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O	NO
GPDTX18	Is transmission of GPD Store Scene 0 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O GPDTX10: O	NO
GPDTX19	Is transmission of GPD Store Scene 1 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O GPDTX11: O	NO
GPDTX1a	Is transmission of GPD Store Scene 2 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O GPDTX12: O	NO
GPDTX1b	Is transmission of GPD Store Scene 3 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O GPDTX13: O	NO
GPDTX1c	Is transmission of GPD Store Scene 4 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O GPDTX14: O	NO
GPDTX1d	Is transmission of GPD Store Scene 5 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O GPDTX15: O	NO
GPDTX1e	Is transmission of GPD Store Scene 6 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O GPDTX16: O	NO
GPDTX1f	Is transmission of GPD Store Scene 7 command supported?	[R4] A.4.3 [R4] A.4.1	GPDT1: O GPDTX17: O	NO
GPDTX20	Is transmission of GPD Off command supported?	[R4] A.4.3 [R4] A.4.1	GPD2: O.29 ¹⁴⁸	NO
GPDTX21	Is transmission of GPD On command supported?	[R4] A.4.3 [R4] A.4.1	GPD2: O.29 GPD2 && GPDTX20: O	NO
GPDTX22	Is transmission of GPD Toggle command supported?	[R4] A.4.3 [R4] A.4.1	GPD2: O.29	NO
GPDTX23	Is transmission of GPD Release command supported?	[R4] A.4.3 [R4] A.4.1	GPD2: O	NO
GPDTX30	Is transmission of GPD Move Up command supported?	[R4] A.4.3 [R4] A.4.2.4	GPD3: O.30 ¹⁴⁹	NO
GPDTX31	Is transmission of GPD Move Down command supported?	[R4] A.4.3 [R4] A.4.2.4	GPD3: O.30 GPD3 && GPDTX30: O	NO

¹⁴⁸ O.29: Device Under Test SHALL support at least one of those options.

¹⁴⁹ O.30: Device Under Test SHALL support at least one of those commands.

Item number	Item description	Reference	Status	Support
GPDTX32	Is transmission of GPD Step Up command supported?	[R4] A.4.3 [R4] A.4.2.4	GPD3: O.30	NO
GPDTX33	Is transmission of GPD Step Down command supported?	[R4] A.4.3 [R4] A.4.2.4	GPD3: O.30 GPD3 && GPDTX32: O	NO
GPDTX34	Is transmission of GPD Stop command supported?	[R4] A.4.3 [R4] A.4.1	GPD3: O.30 GPD3 && (GPDTX30 GPDTX35): O	NO
GPDTX35	Is transmission of GPD Move Up (with On/Off) command supported?	[R4] A.4.3 [R4] A.4.2.4	GPD3: O.30	NO
GPDTX36	Is transmission of GPD Move Down (with On/Off) command supported?	[R4] A.4.3 [R4] A.4.2.4	GPD3: O.30 GPD3&&GPDTX35: O	NO
GPDTX37	Is transmission of GPD Step Up (with On/Off) command supported?	[R4] A.4.3 [R4] A.4.2.4	GPD3: O.30	NO
GPDTX38	Is transmission of GPD Step Down (with On/Off) command supported?	[R4] A.4.3 [R4] A.4.2.4	GPD3: O.30 GPD3&&GPDTX37: O	NO
GPDTX40	Is transmission of GPD Move Hue ¹⁵⁰ Stop command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31 ¹⁸⁰	NO
GPDTX41	Is transmission of GPD Move Hue Up command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31	NO
GPDTX42	Is transmission of GPD Move Hue Down command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31 GPD10 && GPDTX41: O	NO
GPDTX43	Is transmission of GPD Step Hue Up command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31	NO
GPDTX44	Is transmission of GPD Step Hue Down command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31 GPD10 && GPDTX43: O	NO
GPDTX45	Is transmission of GPD Move Saturation ¹⁵¹ Stop command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31	NO
GPDTX46	Is transmission of GPD Move Saturation Up command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31	NO
GPDTX47	Is transmission of GPD Move Saturation Down command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31 GPD10 && GPDTX46: O	NO
GPDTX48	Is transmission of GPD Step Saturation Up command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31	NO
GPDTX49	Is transmission of GPD Step Saturation Down command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31 GPD10 && GPDTX48: O	NO
GPDTX4a	Is transmission of GPD Move Color command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31	NO
GPDTX4b	Is transmission of GPD Step Color command supported?	[R4] A.4.3 [R4] A.4.2.5	GPD10: O.31	NO
GPDTX50	Is transmission of GPD Lock Door command supported?	[R4] A.4.3 [R4] A.4.1	GPD20: O.37 ¹⁸²	NO
GPDTX51	Is transmission of GPD Unlock Door command supported?	[R4] A.4.3 [R4] A.4.1	GPD20: O.37	NO
GPDTX60	Is transmission of GPD Press 1 of 1 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPD0: M GPD5: M	NO
GPDTX61	Is transmission of GPD Release 1 of 1 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPD0: M GPD5: M	NO
GPDTX62	Is transmission of GPD Press 1 of 2 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPD1: M GPD6: M	NO

¹⁵⁰ CCB #2198, incl. approval ballot comment #1035; Resolution added in 15-02016-004; ¹⁸⁰ O.31: Device Under Test SHALL support at least one of those commands.

¹⁵¹ CCB #2198, incl. approval ballot comment #1035; Resolution added in 15-02016-004; ¹⁸² O.37: Device Under Test SHALL support at least one of those commands.

GPDTX63	Is transmission of GPD Release 1 of 2 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPD1: M GPD6: M	NO
GPDTX64	Is transmission of GPD Press 2 of 2 command supported?	[R4] A.4.3 [R4] A.4.1	GPD1: M GPD6: M	NO

Item number	Item description	Reference	Status	Support
		[R4] A.4.2.2		
GPDTX65	Is transmission of GPD Release 2 of 2 command supported?	[R4] A.4.3 [R4] A.4.1 [R4] A.4.2.2	GPD1: M GPD6: M	NO
GPDTX66	Is transmission of GPD Short Press 1 of 1 command supported?	[R4] Table 52	GPD5: M	NO
GPDTX67	Is transmission of GPD Short Press 1 of 2 command supported?	[R4] Table 52	GPD6: M	NO
GPDTX68	Is transmission of GPD Short Press 2 of 2 command supported?	[R4] Table 52	GPD6: M	NO
GPDTX69	Is transmission of GPD 8-bit vector: press command supported?	[R4] Table 52	GPD7: M	NO
GPDTX6A	Is transmission of GPD 8-bit vector: release command supported?	[R4] Table 52	GPD7: M	NO
GPDTXA0	Is transmission of GPD Attribute Reporting command supported?	[R4] A.4.3 [R4] A.4.2.3	GPD4 GPD11 GPD12 GPD30 GPD31 GPD32 GPD33: O.32 ¹⁵²	NO
GPDTXA1	Is transmission of GPD Manufacturer-Specific Attribute Reporting command supported?	[R4] A.4.3 [R4] A.4.2.3	GPD4 GPD11 GPD12 GPD30 GPD31 GPD32 GPD33: O.32	YES
GPDTXA2	Is transmission of GPD Multi-Cluster Reporting command supported?	[R4] A.4.3 [R4] A.4.2.3	GPD11 GPD12 GPD30 GPD31 GPD32 GPD33: O.32	NO
GPDTXA3	Is transmission of GPD Manufacturer-Specific Multi-Cluster Reporting command supported?	[R4] A.4.3 [R4] A.4.2.3	GPD11 GPD12 GPD30 GPD31 GPD32 GPD33: O.32	YES
¹⁵³ GPDTXA6	Is transmission of GPD ZCL Tunneling command (0xA6) supported?	[R4] A.4.3 [R4] A.4.2.3	GPDT0: O GPD4 GPD11 GPD12 GPD30 GPD31 GPD32 GPD33: O.32	NO
GPDTXA6.2	List the functionality accessible via GPD ZCL Tunneling command. List the ZCL generic commands, with the corresponding ClusterID(s) and AttributeID(s), if any. List the cluster-specific CommandIDs per ZCL-defined Cluster, if any. Manufacturer-specific functionality doesn't have to be listed.	[R10] GPDPIXIT05, GPDPIXIT06	GPDTXA6: M	NO
¹⁵⁴ GPDTXA8	Is transmission of GPD Compact Attribute Reporting command supported?	[R4] A.4.2.6	GPD102: M	NO

Note: all the commands below are transparent to GPP, thus GPDT2: X. For GPDT1: X.

¹⁵² O.32: Device Under Test SHALL support at least one of those commands.

¹⁵³ CCB #2533; resolution added in 15-2016-010

¹⁵⁴ Comment #783 from GP multi-sensor v0.7 letter ballot

12.3.2 Zigbee attribute support by GPD sensor devices

In Table 18 – Table 20, Zigbee attributes supported by the GPD devices are listed.

These PICS items are not applicable to the other GP device types.

Table 18 – Reported Zigbee attributes per GPD device

Item number	Item description	Reference	Status	Support
AREP1	Does the GPD support reporting of the 0x0055: PresentValue attribute from Binary Input Cluster?	[R4] A.4.3	GPD4: M	NO
AREP2	Does the GPD support reporting of the 0x0000: MeasuredValue attribute from Illuminance Measurement Cluster?	[R4] A.4.3	GPD11: M GPD33: M	NO
AREP3	Does the GPD support reporting of the 0x0000: Occupancy attribute from Occupancy Sensing Cluster?	[R4] A.4.3	GPD12: M	NO
AREP4	Does the GPD support reporting of the 0x0000: MeasuredValue attribute from Temperature Measurement Cluster?	[R4] A.4.3	GPD30: M GPD33: M	YES
AREP5	Does the GPD support reporting of the 0x0000: MeasuredValue attribute from Pressure Measurement Cluster?	[R4] A.4.3	GPD31: M	NO
AREP6	Does the GPD support reporting of the 0x0000: MeasuredValue attribute from Flow Measurement Cluster?	[R4] A.4.3	GPD32: M	NO
AREP7	Does the GPD support reporting of the 0x0000: MeasuredValue attribute from Relative Humidity Measurement Cluster?	[R4] A.4.3	GPD33: M	NO
AREPF	Does the GPD support reporting of any ZCL-defined attributes not specified above? If yes, please list all, by including ClusterID and AttributeID.	[R4] A.4.3	GPDT0: O	YES (c:0x0000/a:0x0004, c:0x0000/a:0x0005, c:0x0b04/a:0x0300, c:0x0b04/a:0x0304, c:0x0b04/a:0x0306, c:0x0b04/a:0x0401, c:0x0b04/a:0x0403, c:0x0b04/a:0x0505, c:0x0b04/a:0x0508, c:0x0b04/a:0x050B, c:0x0b04/a:0x0601, c:0x0b04/a:0x0800, c:0x0b04/a:0x0603, c:0x0b04/a:0x0905, c:0x0b04/a:0x0908, c:0x0b04/a:0x090B, c:0x0b04/a:0x0A05, c:0x0b04/a:0x0A08, c:0x0b04/a:0x0A0B, c:0x0b05/a:0x011C, c:0x0b05/a:0x011D, c:0x0702/a:0x0000, c:0x0702/a:0x0001, c:0x0702/a:0x0006, c:0x0702/a:0x0302)

Table 19 – Readable Zigbee attributes per GPD device

Item number	Item description	Reference	Status	Support
AREAD1	Does the GPD support reading of the 0x0051: OutOfService attribute from Binary Input Cluster?	[R4] A.4.3	GPD4 && GPF102: M	NO
AREAD2	Does the GPD support reading of the 0x0055: PresentValue attribute from Binary Input Cluster?	[R4] A.4.3	GPD4 && GPF102: M	NO
AREAD3	Does the GPD support reading of the 0x006F: StatusFlags attribute from Binary Input Cluster?	[R4] A.4.3	GPD4 && GPF102: M	NO
AREAD4	Does the GPD support reading of the 0x0000: MeasuredValue attribute from Illuminance Measurement Cluster?	[R4] A.4.3	GPD11 && GPF102: M GPD33 && GPF102: M	NO
AREAD5	Does the GPD support reading of the 0x0001: MinMeasuredValue attribute from Illuminance Measurement Cluster?	[R4] A.4.3	GPD11 && GPF102: M GPD33 && GPF102: M	NO
AREAD6	Does the GPD support reading of the 0x0002: MaxMeasuredValue attribute from Illuminance Measurement Cluster?	[R4] A.4.3	GPD11 && GPF102: M GPD33 && GPF102: M	NO
AREAD7	Does the GPD support reading of the 0x0000: Occupancy attribute from Occupancy Sensing Cluster?	[R4] A.4.3	GPD12 && GPF102: M	NO
AREAD8	Does the GPD support reading of the 0x0000: Occupancy Sensor Type attribute from Occupancy Sensing Cluster?	[R4] A.4.3	GPD12 && GPF102: M	NO
AREAD9	Does the GPD support reading of the 0x0000: MeasuredValue attribute from Temperature Measurement Cluster?	[R4] A.4.3	GPD30 && GPF102: M GPD33 && GPF102: M	YES
AREAD10	Does the GPD support reading of the 0x0001: MinMeasuredValue attribute from Temperature Measurement Cluster?	[R4] A.4.3	GPD30 && GPF102: M GPD33 && GPF102: M	NO
AREAD11	Does the GPD support reading of the 0x0002: MaxMeasuredValue attribute from Temperature Measurement Cluster?	[R4] A.4.3	GPD30 && GPF102: M GPD33 && GPF102: M	NO
AREAD12	Does the GPD support reading of the 0x0000: MeasuredValue attribute from Pressure Measurement Cluster?	[R4] A.4.3	GPD31 && GPF102: M	NO
AREAD13	Does the GPD support reading of the 0x0000: MeasuredValue attribute from Flow Measurement Cluster?	[R4] A.4.3	GPD32 && GPF102: M GPD33 && GPF102: M	NO
AREAD14	Does the GPD support reading of the 0x0001: MinMeasuredValue attribute from Flow Measurement Cluster?	[R4] A.4.3	GPD32 && GPF102: M GPD33 && GPF102: M	NO
AREAD15	Does the GPD support reading of the 0x0002: MaxMeasuredValue attribute from Flow Measurement Cluster?	[R4] A.4.3	GPD32 && GPF102: M GPD33 && GPF102: M	NO
AREAD16	Does the GPD support reading of the 0x0000: MeasuredValue attribute from Relative Humidity Cluster?	[R4] A.4.3	GPD33 && GPF102: M	NO
AREAD17	Does the GPD support reading of the 0x0001: MinMeasuredValue attribute from Relative Humidity Cluster?	[R4] A.4.3	GPD33 && GPF102: M	NO
AREAD18	Does the GPD support reading of the 0x0002: MaxMeasuredValue attribute from Relative Humidity Cluster?	[R4] A.4.3	GPD33 && GPF102: M	NO

Item number	Item description	Reference	Status	Support
AREADF	Does the GPD support reading of any ZCL-defined attributes not specified above? If yes, please list all, by including ClusterID and AttributeID.	[R4] A.4.3	GPDT0: O	YES (c:0x0000/a:0x0000, c:0x0000/a:0x0004, c:0x0000/a:0x0005, c:0x0000/a:0x0007, c:0x0000/a:0xFFFD, c:0x0002/a:0xFFFD, c:0x0003/a:0x0000, c:0x0003/a:0xFFFD, c:0x0b04/0x0000, c:0x0b04/a:0x0802, c:0x0b04/a:0xFFFD, c:0x0b05/a:0xFFFD, c:0x0702/a:0x0200, c:0x0702/a:0x0300, c:0x0702/a:0x0303, c:0x0702/a:0x0306, c:0x0702/a:0xFFFD;

Table 20 – Writable Zigbee attributes per GPD device

Item number	Item description	Reference	Status	Support
AWRITE1	Does the GPD support writing of the 0x0051: OutOfService attribute from Binary Input Cluster?	[R4] A.4.3	GPD4 && GPF100: M	NO
AWRITEF	Does the GPD support writing of any ZCL-defined attributes not specified above? If yes, please list all, by including ClusterID and AttributeID.	[R4] A.4.3	GPDT0: O	YES (c:0x0003/a:0x0000)